

# User manual

HX5208

## chapter one: overview

### 1. outline

### 2. button

- power button
- press and hold this button power on/off
- Volume button  
adjust the volume.when the call is coming,press this button,ringtones muted

### 3. open the back cover

nudge up from the USB interface,then can open the back cover

### 4. about the SIM/UIM card

important:For a more complete protection of SIM / UIM card, battery-top terminal lock SIM / UIM card lock design. To prevent the SIM / UIM card is damaged, you should always remove the battery before you insert or remove the card

### 5. insert SIM card/UIM card

SIM card metal contacts facing down, the card body upward gap, along SIM card slot can be pushed to the left flat

attention:Community Corrections supervision terminal SIM card is located above the top of the battery, take the SIM card is inserted before remove the battery

### 6. battery

important:Shall be in accordance with the manual instructions to insert and remove the batteries to avoid damage to the body or battery

\*swap battery

Battery-metal contact opening the battery contacts are aligned with the body, gently press down to insert the battery

Notches in the battery compartment at the top of the light outward pull, you can remove the battery

## 7. status icons

The status bar at the top of the screen displays the time, battery status, signal strength, operator name or notification icon

## chapter two: getting started

### 1. important notice

In order to avoid unnecessary harm to appear, please note the following information before using the terminal

- please do not power on the phone when ban on the use of wireless devices in place. Nearby such as aircraft, indicating non-medical use of mobile phones and medical equipment place
- Please do not power on when cause interference or dangerous places in the use of the boot device. Such as gas stations, near fuel or chemicals, near blasting areas and so on
- Please use the original accessories and batteries. Do not use incompatible products
- Please keep the terminal drying
- Please find the product manufacturer's maintenance personnel to repair the terminal
- When connecting other devices, please refer to the user manual connection method, do not arbitrarily connect incompatible devices

### 2. battery charge

- Battery upper right corner of the screen shows the battery level or charging status. You also can choose to display the percentage of battery charge. (In Settings - System - power - power style status bar, select the display style you liked)
- Use the supplied charger connected to a power outlet or connect to your computer with a USB cable to charge

### 3. Terminal connected to the computer

Connected to a computer with a USB cable, you can pop-up window or pull-down notification bar of USB data storage data storage switch open. When using the data stored, some of the SD card section of the program can not be used, such as file management

## chapter 3:basic function

### 1. use application

- To open an application, click its icon on the screen
- Return to the main screen: Press the Home key below the display
- Switch to another home screen: swipe finger left or right, or paddling bottom dot area
- Switch the applications used recently: long press the Home key

### 2. view notice

When the status bar displays notification icons have to indicate that you have new notifications, such as missed calls or new messages, etc.please pull down the notification bar, notice Support Click for details

### 3. Enter text

You can use the virtual keyboard of the screen to input Chinese, English, symbols and numbers.Some input method (such as search dogs, TouchPal, etc.) may support handwriting and pen input

# chapter four:detail function introduction

## 1. call

### ◆ dialing and answering call

Making a call is recommended to use T9 dialpad search you are looking for contacts in the terminal, you can also click on the call history to quickly call back

### ◆ dialing call

### ◆ via the T9 searching result to dialing

T9 dialpad Search Support

Enter the contact name in Chinese spelling, support initials, spelling, any part of a mixed alphabet search

Any contact search input field in English

Search Enter the contact number of any field

The search results will highlight the matching section, click the entry to Call

### ◆ direct dial

dial:enter the number direct,press the call button outgoing calls

enter symbol“+”,long press number button“0”

enter the pause symbol“ , ”: long press \* button

enter the voice mail:long press the number button “1”

### ◆ Call by call logs

- Recently dialed or connected phone is displayed in the call log, click on the list name or phone number to quickly call back or go to the contact details page, you can set the option to click through telephone dial list operations
- Call records missed calls with red logo, showing the number of rings

### ◆ via the contacts

Click the lower left corner of the address book button to jump to the Contacts screen, select a contact, then click on the "Phone" button

### ◆ answer call

- answer:press “answer”button to answer call
- refuse: press “ignore”button to refuse call

- mute call ringing: press“power”button or any”volum”button,the ringing tone is muted, but you can still choose to answer the call

### ◆ **during the call**

- During the call, you can select "hands-free", "keyboard" or "more" option
- Hands-free: Use the speakerphone loud sound.When connecting a Bluetooth device, speakerphone button changes to "Answering device", calls for switching the device to use, such as Bluetooth devices, headphones, speakers
- keyboards:Expand keyboard input digital information
- more:expand more panel, expand the "more" panel include
  - Mute: mute your line
  - Pause Call: Click on the "mute" button or answer the other call, the call will be suspended in front of an object; this time Cancel "mute" button or "Switch call" to restore the previous call
  - Contacts: Click on the "Contacts" button, jump to the Contacts screen to view the contact information
  - Add call: Skip the Contacts screen objects to add another call after phone call in front of an object turned pauses, then switch the call or choose "Merge Calls", select "Merge Calls" will enter the telephone conference status
  - Record: Click "Record" button, you can save a voice call

### ◆ **third party call**

During a call, if you receive a second call, the monitoring terminal beeps and displays the caller's information and "Answer" and "Ignore" button

[Note]dial or answer a second call may be an optional service, please contact your operator for information

### ◆ **emergency call**

In the service provider network to the extent permitted, even without SIM card terminal or not registered to monitor the local carrier's network, you can still make an emergency call. Such as input 112, point call button to make an emergency call

In the lock screen or pin code lock screen interface, click icon to enter the emergency call dial interface

## 2. message

You can view and reply to messages very easily

### ◆ write message

1. lick“write message”button

2. Add recipients

directly enter the contact's phone number

enter the contact part of the alphabet, the name or number, select fast search suggestions below the bar

click the right icon of the "Add Contacts" , select a contact to call

If you choose the wrong contact, click the contact area has been added to quickly delete the contact

3. Click on the text input box

Send button at the top there is a current surplus of words prompt messages (when there is enough space for display).When more than one text message, will use the parentheses show the current contents of the message number

4. click the send button

### ◆ check message

You receive a new message, in the message list displays the sender's name, and the time line summary. Click on the list you can view the specific content of the message. You can enter Quick reply message to the contact

### ◆ Delete message thread and which message

SMS lists and session screen, on any conversation / SMS entry lateral sliding, or press the Menu key to select "Edit", you can enter edit mode. Here the user can select and delete bulk SMS / Session

### ◆ search message

Press the Menu key, in the menu click on "Search" in the message list page to enter the search interface. Here you can search the full text of SMS-based

## 3. Limit dial whitelist

When the manager is set by the terminal management platform barring white list numbers, this terminal can only call or receive calls within the whitelist

## 4. contacts

### ◆ view contacts

- contact list
- The display includes a list head, name. In the second line shows the contact information in the fine print if there is a nickname or company. At the same time there are companies and nicknames, the first display show the company the nickname again, separated by commas
- Click the alphabetical index, magnified view of the letter and quickly navigate to the location where the letters while holding the index bar, retrieve the bar area have feedback, and there is an enlarged letter tips. In the same letter the slide list, text prompts appear surname

### ◆ search contacts

enter the contact's name first letter of alphabet, spelling, writing, nickname or company can quickly find contacts

## 5. remote upgrade

the terminal supports the new version automatically detects the system can be upgraded when the server has not found a new version of the updated information on the terminal will push upgrade notification bar message "system upgrade, found the system a new version, click install!" (as below), due to the large package file system, so when the system is upgraded, the terminal is prohibited upgraded by mobile traffic network, but by opening the WIFI networking upgrades. When prompted to upgrade when the monitoring terminal to monitor the end-user needs to turn itself on WIFI, and ensure that the link to the nearby access to the Internet WIFI hotspot network, while monitoring terminal power to meet more than 20%, before the end system to complete the installation and automatic upgrades reboot

## 6. system tools

### ◆ file management

Support by classification quick browse files, support for managing files by path. Remote management via WLAN end phone files from your computer. Network disk can also be local files quickly uploaded to the Internet, cross-platform management



- ◆ alarm clock  
the alarm time to remind you to do a good helper, support snooze, custom labels, support the shutdown alarm clock
- ◆ radio  
Radio supports automatic station search, collection your favorite radio station, putting support
- ◆ recorder  
Help you quickly save the voice recorder records support the preservation and 3gpp to amr file formats
- ◆ calendar  
in the calendar, you can view the date, holidays, support for displaying the Lunar
- ◆ compass  
Compass to help you quickly find the current location, altitude and direction

FCC Caution:

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the condition that this device does not cause harmful interference

NOTE: The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC RF Exposure Information and Statement

This smart phone meets the government's requirements for exposure to radio waves. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons regardless of age or health.

FCC RF Exposure Information and Statement The SAR limit of USA (FCC) is 1.6 W/kg averaged over one gram of tissue. Device types: HX5208 (FCC ID: 2AGY5-HX5208) has also been tested against this SAR limit. The highest SAR value reported under this standard during product certification for use at the ear is 0.310W/kg and when properly worn on the body is 0.882W/kg. This device was tested for typical body-worn operations with the back of the handset kept 1.0cm from the body. To maintain compliance with FCC RF exposure requirements, use accessories that maintain a 1.0cm separation distance between the user's body and the back of the handset. The use of belt clips, holsters and similar accessories should not contain metallic components in its assembly. The use of accessories that do not satisfy these requirements may not comply with FCC RF exposure requirements, and should be avoided.

Body-worn Operation

This device was tested for typical body-worn operations. To comply with RF exposure requirements, a minimum separation distance of 1.0 cm must be maintained between the user's body and the handset, including the antenna. Third-party belt-clips, holsters, and similar accessories used by this device should not contain any metallic components. Body-worn accessories that do not meet these requirements may not comply with RF exposure requirements and should be avoided. Use only the supplied or an approved antenna.