

SCHEMATIC DIAGRAM INDEX FOR MODEL: **SLV-M91HF**

(回路図リスト)

NO.	SCHEMATIC DIAGRAM (S NO)	NAME OF PWB	M91HF
1	S-0121-001-11	FRAME HARNESS	○
2	S-0121-002-11	SRV886UC	○
3	S-0121-003-11	MA-360 (1/9) PS	○
4	S-0121-003-21	MA-360 (2/9) SS	○
5	S-0121-003-31	MA-360 (3/9) TT	○
6	S-0121-003-41	MA-360 (4/9) VA	○
7	S-0121-003-51	MA-360 (5/9) HIFI	○
8	S-0121-003-61	MA-360 (6/9) TU	○
9	S-0121-003-71	MA-360 (7/9) RP	○
10	S-0121-003-81	MA-360 (8/9) ARC	○
11	S-0121-003-91	MA-360 (9/9) AV-BUS	○
11	S-0121-004-11	DRUM MOTOR(SDV-11B)	○
12	S-0121-004-21	DRUM MOTOR(DMVDMT04F)	○
13	S-0121-004-31	CAPSTAN MOTOR	○
14	S-0121-005-11	TUNER (BTF-MA431)	○
15	S-0121-006-11	FR-163	○
16	S-0121-007-11	DM-87	○
17	S-0121-008-11	PD-111	○
18	S-0121-009-11	LR-15	○
19			
20	S-0121-011-11	ML-18	○
21	S-0121-012-11	AN-18, AN-19	○
22	S-0121-014-11	VD-29	○
23	S-0121-015-11	JK-172	○
23	S-0121-016-11	Control Switch Block	○

AN-18 MOUNT

AN-19 MOUNT

JK-172 MOUNT

VD-29 MOUNT

ACE HEAD

FE HEAD

AUDIO CH2
AUDIO CH1
SP CH2
EP CH1
SP CH1
EP CH2

SLV-M11HF ONLY
RJ-83 MOUNT

ML-18 MOUNT

LR-15 MOUNT

PD-111 MOUNT

DM-87 MOUNT

CAPSTAN MOTOR
F2&TB29

CAM MOTOR

SDV-11 B
DRUM MOTOR
or DMVDMT04F

MA-360 MOUNT

FFM-29

FFM-28

POWER BLOCK
SRV886UC

FR-163 MOUNT

ORIGINAL MODEL SLV-M11HF
DESCRIPTION FRAME HARNESS
PART NO. 8-0121-001-11

for SLV-M11HF,
SLV-M11HF

CH270 4P
1 HF ADJ
2 PS RF
3 RF SMP
4 GND

4P CH466
1 D_GND
2 LANC OUT
3 LANC IN
4 D_SV

CH105 3P
1 CTL (Y)
2 N.C.
3 CTL (X)
CHECK

B to B
1 X DB X DB
2 SO 0 SO 0
3 SI 0 SI 0
4 SCK 0 SCK 0
5 RESET RESET
B to B
1 SW-12V SW-12V
2 D_GND D_GND
3 D_SV D_SV
4 AN_GND AN_GND

LM-116
1 DBV DBV
2 27V 27V
3 SW SV SW SV
4 AV LINK VIDEO AV LINK VIDEO
5 AN_GND AN_GND
6 AV LINK L AV LINK L
7 AU_GND AU_GND
8 AV LINK R AV LINK R
9 AU_GND AU_GND
10 SYNC ON SYNC ON

D_GND
AD1
DSV
AD0
N.C.

B to B
1 DMS 2 DMS2
2 DMS 1 DMS1
3 AD3 AD3
4 AD4 AD4
5 JDS LED JDS LED
6 AD1/AD2 AD1/AD2
7 D_SV D_SV
8 D_GND D_GND

PLAY
STOP
DMS
DMS 2
DMS 1

CH461 31P
1 POWER-LED
2 ARC-LED
3 DMS1
4 DMS2
5 PS
6 P10
7 P11
8 P12
9 P13
10 P14
11 P15
12 P16
13 BUZZER
14 B10
15 B9
16 B8
17 B7
18 B6
19 B5
20 B4
21 B3
22 B2
23 B1
24 JDS-LED
25 JDS-LED
26 B1
27 D-SV
28 D-SV
29 AD2
30 AD4
31 M-LED

CH462 15P
1 F-
2 REMON
3 AD0
4 D_GND
5 D_GND
6 D_GND
7 D_GND
8 P7
9 P6
10 P5
11 P4
12 P3
13 P2
14 P1
15 F4

CH603 15P
1 F-
2 F-
3 -50V
4 G
5 SV
6 G
7 G
8 25V
9 25V
10 25V
11 25V
12 25V
13 25V
14 25V
15 25V


CH461 10P
1 F-
2 REMON
3 AD0
4 D_GND
5 D_GND
6 D_GND
7 D_GND
8 P7
9 P6
10 P5
11 P4
12 P3
13 P2
14 P1
15 F4

CH102 3P
1 SW SV
2 CAP RVS
3 CAP FG
4 CTL-REF
5 CAP VS
6 LIMITER
7 NTR 12V
8 NTR GND
9 AN_GND

CH103 3P
1 CAM(-)
2 CAM(+)
3 CAM(+)

CH104 5P
1 NTR 12V
2 D VS
3 D PS
4 D PS
5 NTR GND

SYM.	REVISION	DATE	N



D102 PR1005 or AG01A
 D103 ERA15-02 or 11ES2
 D104 MTZJ3.0 or MA4030 or RD3.0ES
 D105 1SS119 or MA165
 D106 IN4005
 D107, D108 IN4005
 D109, D110 IN4005
 Q101 2SC4054 or 2SC4130
 Q102 2SC4040
 PC101 ON3131 or PS2501

D201 PR1003 or ERA18-02
 D202, D301 UF3DL or RL4Z or S3L20U
 D204 SB340L or RK44 or D3S4M
 D205 BZX85C51 or MA2510 or RD51F
 D206, 207 PR1003 or ERA18-02
 IC201 AN1431T or HA17431P
 D302 D2S4M
 D303 MTZJ18 or MA4180
 D305, D306 1SS119 or MA165
 Q301, Q303 2SD2394
 Q302, Q306 2SC1740
 Q304 2SC2785
 Q305 2SB1240
 Q307 2SA1015


* 調整抵抗			
symbol	min	typ	max
*R107	100/1	120/1	120/1
*R109	560	680	680
*R207	1.2K	1.5K	2.2K
*R209		2.7	


単位	抵抗	Ω/W (指示なきWは 1/4W)
	コンデンサ	μF/V (指示なきVは 50V)

SRV886UC

DWG. No.

S-0121-002-11





1000	10	14	15	34	AB	A10	A11
Q464	K18AN	A	B	C			
Q467	177001021	XX	177001021	177001021			
IC400	CXF6390-0	CXF6390-0	CXF6390-0	CXF6390-0			
R400	100	XX	100	100			
R401	100	XX	100	100			
R402	0	XX	0	0			


SLV-999HF SLV-M11HF SLV-M91HF

XX means no component mounted.

ALL resistors are in ohms. $\frac{1}{10}$ W unless otherwise noted.

ALL capacitors are in uF(p:pF) unless otherwise noted.

ORIGINAL MODEL	SLV-M91HF
DESCRIPTION	MA-360 (3/a) TT
PART NO.	S-0121-003-3/



1998-10-14 18-02 SLV-999HF SLV-M11HF SLV-M91HF

ITEM NO.	KIBAN	A	B	C
C300	0.010u 100V	0.010u 100V	0.047u 50V	0.010u 100V
C313	1000p 50V	1000p 50V	XX	1000p 50V
C332	0.01u 50V	0.01u 50V	XX	0.01u 50V
C333	47u 50V	47u 50V	XX	47u 50V
C334	0.047u 100V	0.047u 100V	XX	0.047u 100V
CN304	10P 125878711	XX	XX	10P 125878711
J3302	121650571	XX	121650571	XX
J3301	121650571	121650571	XX	121650571

1998-10-14 18-02 SLV-999HF SLV-M11HF SLV-M91HF


ITEM NO.	KIBAN	A	B	C
L331	1.0mH 3A 10A	1.0mH 3A 10A	XX	1.0mH 3A 10A
R3301	491.315	491.315	XX	491.315
G331	25C4040-TL 875301531	25C4040-TL 875301531	XX	25C4040-TL 875301531
G332	UN2115-093 875342140	UN2115-093 875342140	XX	UN2115-093 875342140
R225	0	0	XX	0
R221	5600	5600	3500	5600
R222	27k	27k	XX	27k
R223	12	12	XX	12
T301	143363811	143363811	143347911	143363811
T291	143363711	143363711	XX	143363711

XX means no component mounted.

ALL resistors are in ohms, $\frac{1}{10}$ W unless otherwise noted.

ALL capacitors are in uF(p:F) unless otherwise noted.

ORIGINAL MODEL SLV-M91HF
DESCRIPTION MA-360 (9/9) VA
PART NO. S-0121-003-41



1998-09-24 15:15
[12/017]

SLV-999HF SLV-M11HF SLV-M91HF

	KIBAN	A	B	C
C260	47u 16V	XX	XX	47u 16V
C261	47u 16V	XX	XX	47u 16V
C268	0.01u 50V B	XX	XX	0.01u 50V B
C269	47u 16V	XX	XX	47u 16V
IC261	MM1111XFBE 875843278	XX	XX	MM1111XFBE 875843278
L261	22uH ±5%	XX	XX	22uH ±5%
R261	0	XX	XX	0

Flying Erase	○	×	○
AV Lesser Link	×	×	○

XX means no component mounted.

ALL resistors are in ohms. $\frac{1}{10}W$
unless otherwise noted.

ALL capacitors are in uF(p:pF)
unless otherwise noted.

ORIGINAL MODEL	SLV-M91HF
DESCRIPTION	MA-360 (4/a) VA
PART NO.	S-0121-003-41
SHEET	2/2

SLV-M91HF
SLV-M91HF
SLV-999HF

1998-06-02 11:47
[仕向]

A10

AB FE
A11 FE


	KIBAN	A	B
C262	18p 50V CH	XX	18p 50V CH
C263	18p 50V CH	XX	18p 50V CH
C830	0.01u 50V B	XX	0.01u 50V B
C831	100p 50V CH	XX	XX
C832	100p 50V CH	XX	100p 50V CH
C833	150p 50V CH	XX	150p 50V CH
C834	55p 50V CH	XX	55p 50V CH
C835	0.1u 25V F	XX	0.1u 25V F
C836	47u 16V	XX	47u 16V
C837	0.1u 25V F	XX	0.1u 25V F
L260	10uH ±5%	XX	10uH ±5%
L264	10uH ±5%	XX	10uH ±5%
L830	6.8uH ±5%	XX	6.8uH ±5%
L831	100uH ±5%	XX	100uH ±5%
Q830	2SA812-T1M 872910271	XX	2SA812-T1M 872910271
Q831	2SA812-T1M 872910271	XX	2SA812-T1M 872910271
Q832	MJN2213T1 872902489	XX	MJN2213T1 872902489
Q833	2SB1122-ST 872962209	XX	2SB1122-ST 872962209
Q834	MJN2213T1 872902489	XX	MJN2213T1 872902489
R830	27	XX	27
R831	470	XX	470
R832	1500	XX	1500
R833	82k	XX	82k
R834	47k	XX	47k
R835	39k	XX	39k
R836	3300	XX	3300
R837	10k	XX	10k

XX means no component mounted.

ALL resistors are in ohms, $\frac{1}{10}$ W
unless otherwise noted.

ALL capacitors are in uF(p:pF)
unless otherwise noted.

ORIGINAL MODEL	SLV-M91HF
DESCRIPTION	MA-360 (2/9) RP
PART NO.	S-0121-003-71
SHEET	2/2




XX means no component mounted.

ALL resistors are in ohms, $\frac{1}{10}$ W unless otherwise noted.

ALL capacitors are in uF(p:pF) unless otherwise noted.

ORIGINAL MODEL	SLV-M9(HF)
DESCRIPTION	MA-360 (8/9) ARC
PART NO.	S-0121-003-81
SHEET	1/




XX means no component mounted.

ALL resistors are in ohms, $\frac{1}{10}$ W unless otherwise noted.

ALL capacitors are in uF(p:pF) unless otherwise noted.

ORIGINAL MODEL	SLV-M91HF
DESCRIPTION	MA-360 (9/a) AV-BUS
PART NO.	S-0121-003-91
SHEET	1/



XX means no component mounted.

ALL resistors are in ohms, 1/10W
Unless otherwise noted.

ALL capacitors are in μF
Unless otherwise noted.

ORIGINAL MODEL	SLV-M914F
DESCRIPTION	DRUM MOTOR (DMVDMT04F)
PART NO.	S-0121-004-21


Attached sheet ③

Motor circuit diagram

50
SCALE FOR MICROFILM
0

DRAWING

SONY STANDARD



-Circuit constant-

I C : M56746SP
 R 1 : 0.47Ω / 0.5W
 R 2 : 180Ω
 R 3 : 180Ω
 R 4 : $4.7k\Omega$
 C 1 : $0.047\mu F$ / 25V
 C 2 : $0.33\mu F$ / 25V
 C 3 : $0.33\mu F$ / 25V
 C 4 : $0.33\mu F$ / 25V
 C 5 : $1\mu F$ / 16V
 C 6 : $0.1\mu F$ / 25V
 C 8 : $220pF$ / 50V
 HE1 : HW101A
 HE2 : HW101A
 HE3 : HW101A

-Connector pin location-

No.	FUNCTION
1	V _{CC} (5V)
2	F/R
3	FG-OUT
4	CTL-REF
5	CTL
6	I-LIMIT
7	V _{CO} (12V)
8	GND
9	IC GND
10	N.C.

TITLE/DESCRIPTION


D. C. MOTOR

(E)

(J)

DCモータ (F2QTB29)

S-0121-004-31





XX means no component mounted.

ALL resistors are in ohms, $\frac{1}{10}$ W
unless otherwise noted.

ALL capacitors are in uF(p:pF)
unless otherwise noted.

ORIGINAL MODEL	SLV-M91HF	
DESCRIPTION	DM-87	
PART NO.	5-0121-007-11	SHEET 1/






XX means no component mounted.


ALL resistors are in ohms, $\frac{1}{10}W$
unless otherwise noted.ALL capacitors are in $\mu F(p;P)$
unless otherwise noted.

ORIGINAL DESCRIPTION	SLV-M91HF
	ML-18
PART NO.	5-0121-011-11

AN-18



AN-19




XX means no component mounted.

ALL resistors are in ohms, $\frac{1}{10}W$ unless otherwise noted.

ALL capacitors are in uF(p:pF) unless otherwise noted.

ORIGINAL MODEL	SLV-M91HF
DESCRIPTION	AN-18, AN-19
PART NO.	S-0121-012-11
SHEET	1/



TO 2/2
 >> 061 SCK 0
 >> 062 SD 0

TO 2/2
 >> 063 V SYNC
 >> 064 H SYNC

TO 2/2
 >> D_GND
 >> 065 MEDIA VIDEO
 >> 066 D 5V
 >> 067 SI 0
 >> 068 SYS RESET
 >> 069 V SET CS


XX means no component mounted.

ALL resistors are in ohms. $\frac{1}{10}W$ unless otherwise noted.

ALL capacitors are in uF(p.pF) unless otherwise noted.

ORIGINAL MODEL	SLV-M91HF
DESCRIPTION	VD-29
PART NO.	S-012/- 014-11

OSD




XX means no component mounted.

ALL resistors are in ohms, $\frac{1}{10}W$ unless otherwise noted.

ALL capacitors are in uF(p:pF) unless otherwise noted.


ORIGINAL MODEL	SLV-M91HF
DESCRIPTION	JK-172
PART NO.	S-0121-015-11
SHEET	1/



XX means no component mounted.

ALL resistors are in ohms. $\frac{1}{10}$ W
unless otherwise noted.

ALL capacitors are in uF(p:pF)
unless otherwise noted.



ORIGINAL MODEL	SLV-M91HF
DESCRIPTION	Control Switch BLOCK
PART NO.	S-0121-016-11
SHEET	1/