



FUJIFILM

FUJI PHOTO FILM CO., LTD.

26-30, NISHIAZABU 2-CHOME,

MINATO-KU, TOKYO 106, JAPAN

Telephone: (03) 3506-2934

Facsimiles: (03) 3506-9967

page 5 of 7

FCC ID: **F5GFP-30I**

Part 15 Sub.part B Class B Digital Device

6. TESTED SYSTEM DETAILS

6.1 Peripherals and Others :

<i>Description</i>	<i>Model Name</i>	<i>Serial No.</i>	<i>Manufacturer</i>	<i>FCC ID</i>
Personal Computer	12XL212	1V08FHNJE1N5	Compaq Computer Co., Ltd.	DOC
Mouse	M-BB48	LZE01271677	Logitech	DOC
PC Monitor	M2978	CY5430HF3CV	LG Electronics, Inc.	BEJCA500
Scanner	AS-1	0009	Fuji Photo Film Co., Ltd.	F5GAS-1
Head Phone Controller	-	-	Mitsumi	N/A
Head Phone Speaker	-	-	Mitsumi	N/A
AC Adapter (for PC)	LE-9702B-01	177625-001	Compaq Computer Co., Ltd.	N/A
AC Adaptor (for EUT)	AC-3V	0044	Fuji Photo Film Co., Ltd.	N/A

(for AC Adapter of EUT, Input: 120VAC, 60Hz / Output: 3VDC)

Note:

*DOC: Declaration of Conformity by Manufacturer, Compaq Computer Co., Ltd., or Logitech.

* N/A: Equipment required for the Verification.

6.2 List of Cables :

<i>Description</i>	<i>Length</i>	<i>Type of shield</i>	<i>Ferrite Core</i>
EUT / Personal Computer	1.2 m	Shielded	Add
DC Power Cord (EUT/AC adaptor)	1.9 m	Non-shielded	Add
Scanner / Personal Computer	1.5 m	Shielded	Provided
PC Monitor / Personal Computer	1.65 m	Shielded	Provided
Mouse / Personal Computer	1.9 m	Shielded	N/A
DC Power Cord (PC/AC adaptor)	1.55 m	Non-shielded	Provided
AC Power Cord (Scanner)	1.8 m	Non-shielded	N/A
AC Power Cord (PC Monitor)	1.7 m	Non-shielded	N/A
Headphone Cable	0.8 m	Shielded	N/A
Head Set Cable	1.11 m	Shielded	N/A

Note:

* Provided: The cable is an accessory for Personal Computer, Digital Camera, Scanner or PC Monitor which was attached a ferrite core.



FUJIFILM

FUJI PHOTO FILM CO., LTD.

26-30, NISHIAZABU 2-CHOME,
MINATO-KU, TOKYO 106, JAPAN

Telephone: (03) 3506-2934


Facsimiles: (03) 3506-9967

page 7 of 7

FCC ID: F5GFP-30I

Part 15 Sub.part B Class B Digital Device

Figure 6-1 System Configuration Diagram :





FUJI PHOTO FILM CO., LTD.

26-30, NISHIAZABU 2-CHOME,
MINATO-KU, TOKYO 106, JAPAN

Telephone: (03) 3506-2934

Facsimiles: (03) 3506-9967

FCC ID: F5GFP-30I

Part 15 Sub.part B Class B Digital Device

7. TEST RESULTS

7.1 Conducted Radio Noise Measurement

7.1.1 Measurement Instrumentation Used:

(Model / Serial No. / Manufacturer)

Test Receiver ----- (ESCS 30 / 825788-007 / Rohde & Schwarz)

L. I. S. N ----- (KNW-407 / 8-823-10 / Kyoritsu Electrical)

L. I. S. N ----- (KNW-407 / 8-680-7 / Kyoritsu Electrical)

Spectrum Analyzer System ----- (8568S / 2445A00924 / Hewlett Packard)

7.1.2 Measurement Procedure:

The power line conducted interference measurements were performed in a shield enclosure with peripherals placed on a table, 80cm high over a metal floor.

It was located more than required distance away from the shielded enclosure wall.

The EUT was plugged into the L.I.S.N. and the frequency range of interest scanned.

FCC ID: F5GFP-30I

Part 15 Sub.part B Class B Digital Device

7.1.3 Test Data

Table 7.1-1 Conducted Radio Noise Measurement Results:

Operating mode: Camera Mode

Date of measurement: July 31, 2001

Test Procedure: ANSI C63.4-1992

Temperature: 22 degree C

Humidity: 62 %

<i>Frequency</i> (MHz)	<i>Results</i> <i>Meter Reading.</i>		<i>Results</i> <i>Emission Level</i>	<i>Limit</i>	<i>Margin</i>
	<i>VA.</i>	<i>VB.</i>			
	(dBuV/m)	(dBuV/m)			
0.5600	40.1	32.7	40.1	47.9	7.8
1.0100	34.5	37.8	37.8	47.9	10.1
1.3900	34.5	29.4	34.5	47.9	13.4
3.2400	23.7	18.5	23.7	47.9	24.2
9.5600	13.4	11.8	13.4	47.9	34.5
18.0000	21.3	19.7	21.3	47.9	26.6

Note:

- 1) Emission Levels are higher levels of VA or VB of Meter Readings + Correction Factor.
- 2) VA: Between one end of the power cable and the grounded.
VB: Between the other end of power cable and the grounded.

7.1.4 Conducted Radio Noise Calculation

The conducted radio noise is calculated by adding the calibration factor to the measured reading. The basic equation and a sample calculation are as follows:

$$CRN = TRM + CF$$

$$Margin = Limit - CRN$$

where CRN = Conducted Radio Noise (dBuV)

TRM = Test Receiver Reading (dBuV)

CF : Correction Factor (dB/m)

The Correction factor includes cable loss and LISN factor.



FUJI PHOTO FILM CO., LTD.

26-30, NISHIAZABU 2-CHOME,

MINATO-KU, TOKYO 106, JAPAN

Telephone: (03) 3506-2934

Facsimiles: (03) 3506-9967

FCC ID: **F5GFP-30I**

Part 15 Sub.part B Class B Digital Device

7.2 Radiated Radio Noise Measurement

7.2.1 Measurement Instrumentation Used :

(Model / Serial No. / Manufacturer)

Test Receiver ----- (ESCS 30 / 834115-020 / Rohde & Schwarz)

Bi-Conical Antenna ----- (BBA9106 / D-6901 No.2 / Schwarzbeck)

Log-Periodic Antenna ----- (UHALP9107 / 424-517 / Schwarzbeck)

Spectrum Analyzer System ----- (8568S / 2445A00924 / Hewlett Packard)

7.2.2 Measurement Procedure:

The EUT was placed in a 80cm high table along with the peripherals.

The turntable was separated from the antenna at a distance of 3 meter. Cables were placed in a position to produce maximum emission as determined by experimentation, and operation mode was selected for maximum.

The frequencies and amplitudes of maximum emission were measured at varying azimuths, antenna heights and antenna polarities.



FUJIFILM

FUJI PHOTO FILM CO., LTD.

26-30, NISHIAZABU 2-CHOME,

MINATO-KU, TOKYO 106, JAPAN

Telephone: (03) 3506-2934

Facsimiles: (03) 3506-9967

FCC ID: F5GFP-301

Part 15 Sub.part B Class B Digital Device

7.2.3 Test Data

Table 7.2-1 Radiated Radio Noise Measurement Results:

Operating mode: Audio Mode

Date of measurement: July 31, 2001

Test Procedure: ANSI C63.4-1992

Temperature: 31degree C

Humidity: 48%

Frequency	Correction	Results		Results	Limit	Margin
	Factor	Meter Reading.		Emission Level		
(Mhz)	(dB)	(dBuV/m)		(dBuV/m)	(dBuV/m)	(dBuV/m)
		Hori.	Vert.			
30.000	19.9	-	28.3	28.3	40.0	11.7
52.370	11.7	-	25.5	25.5	40.0	14.5
68.890	7.9	25.9	28.5	28.5	40.0	11.5
74.890	7.7	-	25.3	25.3	40.0	14.7
178.980	18.4	-	24.1	24.1	43.5	19.4
196.360	19.2	28.9	-	28.9	43.5	14.6
220.030	20.3	33.8	-	33.8	46.0	12.2
240.040	20.7	35.3	-	35.3	46.0	10.7
304.260	19.7	35.8	-	35.8	46.0	10.2
311.420	19.8	36.5	29.6	36.5	46.0	9.5
329.320	20.2	32.0	29.5	32.0	46.0	14.0
499.740	23.6	37.8	38.2	38.2	46.0	7.8
501.130	23.6	35.0	33.0	35.0	46.0	11.0
528.030	24.2	-	31.3	31.3	46.0	14.7
540.840	24.4	-	34.9	34.9	46.0	11.1
899.110	31.8	43.6	42.1	43.6	46.0	2.4

Note: 1) Meter Readings are corrected by all Correction Factors.

2) Emission Levels are higher levels of Hori. or Vert. of Meter Readings.

3) Margin = Limit - Emission Level.



FUJIFILM

FUJI PHOTO FILM CO., LTD.

26-30, NISHIAZABU 2-CHOME,
MINATO-KU, TOKYO 106, JAPAN

Telephone: (03) 3506-2934

Facsimiles: (03) 3506-9967

FCC ID: F5GFP-30I

Part 15 Sub.part B Class B Digital Device

7.2.4 Radiated Radio Noise Calculation

The radiated radio noise is calculated by adding the correction factor to the measured reading. The basic equation and a sample of calculation are as follows;

$$\text{RRN} = \text{TRM} + \text{CF}$$

$$\text{Margin} = \text{Limit} - \text{RRN}$$

where RRN = Radiated Radio Noise (dBuV)

TRM = Test Receiver Reading (dBuV)

CF : Correction Factor (dB/m), The correction factor includes pre-amplifier gain, cable loss and antenna factor.