



## Operational Descriptions of QISMYA-LX3

### 1) Product Description

This device is a high end Tri- smart phone researched and developed independently by HUAWEI based on the chipset MT6737T produced by MediaTek Technologies Co., Ltd. It supports LTE/UMTS/GSM/GPRS frequency bands.

### 2) Intended use statements

QISMYA-LX3 is a LTE/UMTS/GPRS/GSM Smart Phone. It can only be work in the networks which supports the LTE/UMTS/GPRS/GSM technique. If there are no corresponding networks, the RF module of QISMYA-LX3 will not work and no any unwanted emission will be produced. More details about the function of this device, please refer to the document named as“10\_User Manual”

### 3) Types of Emission Designator

	Air Interface	type modulation	of bandwidth	emission designator
<input checked="" type="checkbox"/>	GSM/GPRS 850	GMSK	200K	G7D
<input checked="" type="checkbox"/>	EDGE 850	8PSK	200K	W7D
<input checked="" type="checkbox"/>	GSM/GPRS 1900	GMSK	200K	G7D
<input checked="" type="checkbox"/>	EDGE 1900	8PSK	200K	W7D
<input checked="" type="checkbox"/>	WCDMA 850	QPSK	5M	F9W
<input checked="" type="checkbox"/>	WCDMA 1700	QPSK	5M	F9W
<input checked="" type="checkbox"/>	WCDMA 1900	QPSK	5M	F9W
<input type="checkbox"/>	CDMA 800	QPSK	1.25M	F9W
<input type="checkbox"/>	CDMA 1700	QPSK	1.25M	F9W
<input type="checkbox"/>	CDMA 1900	QPSK	1.25M	F9W
<input type="checkbox"/>	CDMA 850	QPSK	1.25M	F9W
<input checked="" type="checkbox"/>	LTE Band2	QPSK	1.4M	G7D
		16QAM	1.4M	W7D
		QPSK	3M	G7D
		16QAM	3M	W7D
		QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D
		16QAM	10M	W7D
		QPSK	15M	G7D
		16QAM	15M	W7D
		QPSK	20M	G7D
		16QAM	20M	W7D
<input checked="" type="checkbox"/>	LTE Band4	QPSK	1.4M	G7D
		16QAM	1.4M	W7D

		QPSK	3M	G7D
		16QAM	3M	W7D
		QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D
		16QAM	10M	W7D
		QPSK	15M	G7D
		16QAM	15M	W7D
		QPSK	20M	G7D
		16QAM	20M	W7D
<input checked="" type="checkbox"/>	LTE Band5	QPSK	1.4M	G7D
		16QAM	1.4M	W7D
		QPSK	3M	G7D
		16QAM	3M	W7D
		QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D
		16QAM	10M	W7D
<input checked="" type="checkbox"/>	LTE Band7	QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D
		16QAM	10M	W7D
		QPSK	15M	G7D
		16QAM	15M	W7D
		QPSK	20M	G7D
		16QAM	20M	W7D
<input type="checkbox"/>	LTE Band12	QPSK	1.4M	G7D
		16QAM	1.4M	W7D
		QPSK	3M	G7D
		16QAM	3M	W7D
		QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D
		16QAM	10M	W7D
<input type="checkbox"/>	LTE Band13	QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D
		16QAM	10M	W7D
<input type="checkbox"/>	LTE Band17	QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D
		16QAM	10M	W7D
<input type="checkbox"/>	LTE Band25	QPSK	1.4M	G7D
		16QAM	1.4M	W7D
		QPSK	3M	G7D
		16QAM	3M	W7D
		QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D

		16QAM	10M	W7D
		QPSK	15M	G7D
		16QAM	15M	W7D
		QPSK	20M	G7D
		16QAM	20M	W7D
<input type="checkbox"/>	LTE Band26	QPSK	1.4M	G7D
		16QAM	1.4M	W7D
		QPSK	3M	G7D
		16QAM	3M	W7D
		QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D
		16QAM	10M	W7D
		QPSK	15M	G7D
		16QAM	15M	W7D
<input type="checkbox"/>	LTE Band30	QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D
		16QAM	10M	W7D
<input type="checkbox"/>	LTE Band38	QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D
		16QAM	10M	W7D
		QPSK	15M	G7D
		16QAM	15M	W7D
		QPSK	20M	G7D
		16QAM	20M	W7D
<input type="checkbox"/>	LTE Band41	QPSK	5M	G7D
		16QAM	5M	W7D
		QPSK	10M	G7D
		16QAM	10M	W7D
		QPSK	15M	G7D
		16QAM	15M	W7D
		QPSK	20M	G7D
		16QAM	20M	W7D

#### 4) Frequency Range

GSM/GRPS/ED GE		Frequency	Transmit MHz	Receive MHz
	<input checked="" type="checkbox"/>	850	824-849	869-894
	<input checked="" type="checkbox"/>	1900	1850-1910	1930-1990

WCDMA		Band	Transmit MHz	Receive MHz
	<input checked="" type="checkbox"/>	V	824-849	869-894
	<input checked="" type="checkbox"/>	IV	1710-1755	2110-2155

<input checked="" type="checkbox"/>	II	1850-1910	1930-1990
-------------------------------------	----	-----------	-----------

CDMA	Band		Transmit MHz	Receive MHz
	<input type="checkbox"/>	BC0 Subclass 0	824-849	869-894
	<input type="checkbox"/>	BC1	1850-1910	1930-1990
	<input type="checkbox"/>	BC10 Subclass 0,1,2,3	806-824	851-869
	<input type="checkbox"/>	BC15	1710-1755	2110-2170

LTE	Band		FDD/TDD	Transmit MHz	Receive MHz	
	<input checked="" type="checkbox"/>	2	II	FDD	1850-1910	1930-1990
	<input checked="" type="checkbox"/>	4	IV	FDD	1710-1755	2110-2170
	<input checked="" type="checkbox"/>	5	V	FDD	824-849	869-894
	<input checked="" type="checkbox"/>	7	VII	FDD	2500-2570	2620-2690
	<input type="checkbox"/>	12	XII	FDD	699-716	729-746
	<input type="checkbox"/>	13	XIII	FDD	777-787	746-756
	<input type="checkbox"/>	17	XVII	FDD	704-716	734-746
	<input type="checkbox"/>	25	XXV	FDD	1850-1915	1930-1995
	<input type="checkbox"/>	26	XXVI	FDD	814-849	859-894
	<input type="checkbox"/>	29	XXIX	FDD	NA	717-728
	<input type="checkbox"/>	30	XXX	FDD	2305-2315	2350-2360
	<input type="checkbox"/>	38	XXXVIII	TDD	2570-2620	
	<input type="checkbox"/>	41	XLI	TDD	2496-2690	

Frequency Band (MHz)	Active Scanning (the device can transmit a probe (beacon))		passive scanning (where the device is can listen only with no probes)		Ad Hoc Mode or Wi-Fi Direct capability		Access point capability	
	<input type="checkbox"/> Yes	<input type="checkbox"/> No	<input type="checkbox"/> Yes	<input type="checkbox"/> No	<input type="checkbox"/> Yes	<input type="checkbox"/> No	<input type="checkbox"/> Yes	<input type="checkbox"/> No
2412-2462	<input type="checkbox"/> Yes	<input type="checkbox"/> No	<input type="checkbox"/> Yes	<input type="checkbox"/> No	<input type="checkbox"/> Yes	<input type="checkbox"/> No	<input type="checkbox"/> Yes	<input type="checkbox"/> No
5150-5250	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No
5250-5350	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No
5470-5725	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No
5725-5825	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No
5825-5850	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No

Bluetooth: 2402MHz to 2480MHz

### 5) Range of Operating Power

Please Refer to the document “06- Tune-up Info”

## 6) Antenna description

### a) Licensed Transmitter Antenna (2G/3G/4G)

Item	Description
Frequency	824~894,1710~2155, 2500~2690(MHz)
Input impedance	50Ω ± 10Ω
VSWR	≤3
Peak gain	-5.5~2.0dB
Rated power	>Conducted power-4.5dB
Polarization	
detachable	<input type="checkbox"/> Yes <input checked="" type="checkbox"/> No

### b) Unlicensed Transmitter Antenna 2 (BT/Wi-Fi)

Item	Description
Frequency	2400~2500 (MHz)
Input impedance	50Ω ± 10Ω
VSWR	≤2
Peak gain	-0.3~1dB
Rated power	>Conducted power-4.5dB
Polarization	
detachable	<input type="checkbox"/> Yes <input checked="" type="checkbox"/> No

## 7) Applied voltages

Normal Voltage: 3.8V

Low Voltage: 3.6V

High Voltage: 4.4V

## Complete bill of material

Refer to other attachment

## Complete Circuit Diagrams

Refer to other attachment

## Instruction/Installation Manual

Refer to other attachment

## 8) Means for Frequency Stabilization

The Voltage Controlled Temperature Compensated Crystal Oscillator (VCTCXO) provides the reference frequency for all MT6169 RF parts synthesizers as well as clock generation functions within the MT6169 IC. The oscillator frequency is controlled by the MT6169.

## 9) Means for Limiting Modulation

Air Interface	Modulation
GSM	GMSK, 8PSK
WCDMA	QPSK

LTE	QPSK, 16QAM
Bluetooth	GFSK, $\pi/4$ -DQPSK, 8DPSK
Bluetooth Low Energy	GFSK
Wi-Fi	DBPSK/DQPSK/CCK(DSS), BPSK/QPSK/16QAM/64QAM(OFDM)

## 10) Description of Digital Modulation Techniques

a) **GSM** is a digital system, so speech which is inherently analog, has to be digitized. The method employed by ISDN, and by current telephone systems for multiplexing voice lines over high speed trunks and optical fiber lines, is Pulse Coded Modulation (PCM). The output stream from PCM is 64 kbps, too high a rate to be feasible over a radio link. The 64 kbps signal, although simple to implement, contains much redundancy. The GSM group studied several speech coding algorithms on the basis of subjective speech quality and complexity (which is related to cost, processing delay, and power consumption once implemented) before arriving at the choice of a Regular Pulse Excited -- Linear Predictive Coder (RPE--LPC) with a Long Term Predictor loop. Basically, information from previous samples, which does not change very quickly, is used to predict the current sample. The coefficients of the linear combination of the previous samples, plus an encoded form of the residual, the difference between the predicted and actual sample, represent the signal. Speech is divided into 20 millisecond samples, each of which is encoded as 260 bits, giving a total bit rate of 13 kbps. This is the so-called Full-Rate speech coding. Recently, an Enhanced Full-Rate (EFR) speech coding algorithm has been implemented by some North American GSM1900 operators. This is said to provide improved speech quality using the existing 13 kbps bit rate.

Because of natural and man-made electromagnetic interference, the encoded speech or data signal transmitted over the radio interface must be protected from errors. GSM uses convolutional encoding and block interleaving to achieve this protection. The exact algorithms used differ for speech and for different data rates. The method used for speech blocks will be described below.

Recall that the speech codec produces a 260 bit block for every 20 ms speech sample. From subjective testing, it was found that some bits of this block were more important for perceived speech quality than others. The bits are thus divided into three classes:

- Class Ia 50 bits - most sensitive to bit errors
- Class Ib 132 bits - moderately sensitive to bit errors
- Class II 78 bits - least sensitive to bit errors

Class Ia bits have a 3 bit Cyclic Redundancy Code added for error detection. If an error is detected, the frame is judged too damaged to be comprehensible and it is discarded. It is replaced by a slightly attenuated version of the previous correctly received frame. These 53 bits, together with the 132 Class b bits and a 4 bit tail sequence (a total of 189 bits), are input into a 1/2 rate convolutional encoder of constraint length 4. Each input bit is encoded as two output bits, based on a combination of the previous 4 input bits. The convolutional encoder thus outputs 378 bits, to which are added the 78 remaining Class II bits, which are unprotected. Thus every 20 ms speech sample is encoded as 456 bits, giving a bit rate of 22.8 kbps.

To further protect against the burst errors common to the radio interface, each sample is interleaved. The 456 bits output by the convolutional encoder are divided into 8 blocks of 57 bits, and these blocks are transmitted in eight consecutive time-slot bursts. Since each time-slot burst can carry two 57 bit blocks, each burst carries traffic from two different speech samples.

Recall that each time-slot burst is transmitted at a gross bit rate of 270.833 kbps. This digital signal is modulated onto the analog carrier frequency using Gaussian-filtered Minimum Shift Keying (GMSK). GMSK was selected over other modulation schemes as a compromise between spectral efficiency, complexity of the transmitter, and limited spurious emissions. The complexity of the transmitter is related to power consumption, which should be minimized for the mobile station. The spurious radio emissions, outside of the allotted bandwidth, must be strictly controlled so as to limit adjacent channel interference.

b) **WCDMA or UMTS** – as it is called throughout Europe – is a standard which has been developed to accommodate higher data rates to allow features like internet surfing, video telephony or video download. Even though WCDMA is focusing on high data rates it still supports simple features like a plain voice call or

sending of SMS. WCDMA is a CDMA system. CDMA stands for code division multiple access. This means that the available frequency channel is broken down by different code sequences that are multiplied by the user signals of the individual subscribers. All subscribers transmit on the same frequency and at the same time.

For WCDMA different base stations are distinguished by a different scrambling code, which makes cell planning a lot easier, since neighboring cells can re-use the same frequency! (However, the occupied "SNR" – or Signal to Noise Ratio is the limiting factor and characteristic for CDMA)

The data rate used by a terminal depends on spreading factor assigned to this particular terminal. If several terminals use the same spreading factor, the signals are distinguished through different code channels. At present the maximum data rate is 384 kbps. In the future it will be possible to combine several code channels to a multi-code link, allowing data rates up to 2 Mbps. However, when this is used the capacity of this frequency channel is used up, i.e. no other terminal can operate on this frequency channel. The reason for this is that there is no more "SNR" left for additional connections. This is the capacity issue indicated above.

In order to address higher data rates high speed downlink packet access (DC-HSDPA) has been introduced into Release 8 of the DC-HSDPA(3GPP) standard. DC-HSDPA allows data rates of up to 43.2Mbps and is based on 64-QAM modulation. As the name suggests DC-HSDPA is only available in the downlink direction, i.e. ideal for loading large Emails, surf the web or download videos.

c) **LTE**, known as Long-Term Evolution, targets more complex spectrum situations and has fewer restrictions on backwards compatibility. The radio interface is purely optimized for IP transmissions not having to support ISDN traffic: that is, there is no requirement for support of GSM circuit-switch services, a requirement that WCDMA had. For spectrum flexibility, LTE is therefore targeted to operate in spectrum allocations from roughly 1 to 20MHz. Furthermore, when going to the data rates that LTE is targeting, achieving low delay and high data rates at the cell edges are more important requirements than the peak data rate.

The multiple access scheme for the LTE physical layer is based on Orthogonal Frequency Division Multiplexing (OFDM) with a cyclic prefix (CP) in the downlink, and on Single-Carrier Frequency Division Multiple Access (SC-FDMA) with a cyclic prefix in the uplink.

The Layer 1 is defined in a bandwidth agnostic way based on resource blocks, allowing the LTE Layer 1 to adapt to various spectrum allocations. A resource block spans either 12 sub-carriers with a sub-carrier bandwidth of 15kHz or 24 sub-carriers with a sub-carrier bandwidth of 7.5kHz each over a slot duration of 0.5ms.

Frame structure type 2 is applicable to TDD. Each radio frame of length 10ms consists of two half-frames of length 5ms each. Each half-frame consists of five subframes of length 1ms. According to different UL-DL subframe configuration, the number of subframes allocated to uplink and downlink can be adjusted flexibility.

LTE has 5 terminal categories. For TDD category 4 and 20MHz bandwidth, the downlink allows data rate up to 110Mbps and is based on 64QAM modulation, the uplink allows data rate up to 8Mbps and is based on 16QAM modulation

d) **Bluetooth**, The Bluetooth SIG had completed the Bluetooth Core Specification version 4.1 . It includes Classic Bluetooth, Bluetooth high speed and Bluetooth low energy protocols. Bluetooth high speed is based on Wi-Fi, and Classic Bluetooth consists of legacy Bluetooth protocols. Bluetooth transceivers operate in the 2.4GHz ISM band. The frequency range is 2400MHz to 2483.5MHz (in most countries). The channel spacing is 1MHz, with an upper and lower guard band. Output power is also specified, Bluetooth uses GFSK (Gaussian Frequency Shift Keying),  $\pi/4$ -DQPSK and 8DPSK as its modulation. The corresponding symbol rate is 1Mbps, 2Mbps and 3Mbps. The 2.4GHz band is part of the ISM (Industrial, Scientific, and Medical) license-free radio bands. Both Bluetooth and 802.11 operate within the band. Additional frequencies of the ISM band include the 900MHz band, and 5.8GHz band. The un-licensed ISM band also means that devices need to short range so they do not interfere with other devices which may also be using the band.

e) **WLAN** transceivers operate in the 2.4GHz ISM band. The frequency range is 2400MHz to 2483.5MHz (in most countries). The channel spacing is 22MHz, with an upper and lower guard band. Output power is also specified, WLAN uses DQPSK/CCK, DQPSK, DBPSK,

OFDM/CCK and OFDM as its modulation. DQPSK/CCK corresponding symbol rate is 33 or 22 or 11 or 5.5Mbps, DQPSK corresponding symbol rate is 2Mbps, DBPSK corresponding symbol rate is 1Mbps, OFDM/CCK corresponding symbol rate is 6 or 9 or 12 or 18 or 24 or 36 or 54 Mbps, OFDM corresponding symbol rate is 6 or 9 or 12 or 18 or 24 or 36 or 48 or 54 Mbps.

The 2.4GHz band is part of the ISM (Industrial, Scientific, and Medical) license-free radio bands. Both Bluetooth and 802.11 operate with in the band.

[Home](#) ▶ [Technologies](#) ▶ [Keywords & Acronyms](#)

<http://www.3gpp.org/technologies/keywords-acronyms/104-w-cdma>

### Mobile

[Codecs](#)

[EDGE](#)

[GERAN](#)

[GPRS](#)

[GSM](#)

<http://www.etsi.org/technologies-clusters/technologies/mobile/utran>