



CFMOTO

Bluetooth Headset Manual

catalogs

1. Main Functions	3
2. List of items	3
3. Product Overview	4
4. Basic operation.....	4
5. Bluetooth intercom function.....	6
6. Network intercom function	7
7. Voice assistant function.....	8

1.Key Features

- Supports Bluetooth connection with cell phones and center screen devices
- Two-person Bluetooth intercom between the rider and the person on the back of the motorcycle or rider to rider
- Simultaneous support for 8-person Bluetooth intercom within the effective communication range
- Support voice assistant function
- Supports adjusting the volume level of connected devices
- Supports song up/down switching, play, pause
- Support for answering, hanging up, and canceling phone calls

2.List of items

serial number	module (in software)	Supplied Products
1	Bluetooth headset	Bluetooth Headset Host
2	replacement (parts)	Hard microphone, soft microphone, speaker*2, base, hard microphone sponge cover, velcro
3	synopsis (of a play or film)	Product manuals
4	outer packaging	box
5	Supporting APP	In-vehicle APP/Mobile APP

3.Product Overview



4.basic operation

functionality	keystrokes	manipulate	voice prompt	indicator light
press Ctrl-Alt-Delete	function key	Press and hold for 3s	Power on, XX%charged	Function key indicator blue light flashes at intervals, intercom

				Key on for 5s
turn off (a machine or device)	function key	Press and hold for 3s	Power off	Function key red light Long light for 2s, then
				All instructions after Lights out.
Connecting to devices	function key	Short press twice	Pairing	Function key indicator blue and red flicker
Disconnect from equipment	function key	Short press twice	Pairing cancel	Function key indicator blue light interval vague (of speech)

increase the volume	Volume +	long press	It's at maximum volume	
lower the volume	Volume-	long press	It's at minimum volume	
previous song	Volume +	Short press (music) (when played)	Du	
next song	Volume-	Short press (music) (when played)	Du	
play music	function key	short press (music pauses)	/	
Pause the music.	function key	short press	/	
		(Music playing time)		
answer the phone	function key	short press (Incoming call)	/	

hang up	function key	short press (talking on phone)	/	
Cancel call	function key	short press (de-energized)	/	
Rejection of calls	function key	Press and hold 1s (to) (Electro-medium)	/	
Call switching	function key	Press and hold 1s (three) (party on line)	/	
Turn off the microphone.	intercom button	double-click	microphone off	
Turn on the microphone.	intercom button	double-click	microphone on	

5. Bluetooth intercom function

Automatic completion of intercom pairing within the effective communication range

functionality	keystrokes	manipulate	voice prompt	indicator light
---------------	------------	------------	--------------	-----------------

Dual Intercom Pairing	function key	1. Short press twice 2. short press	1. Pairing 2. Double mode pairing	Function key indicator light blinks blue and red alternately
	intercom button	short press	Double mode pairing (do~do)	Function key indicator light blinks blue and red alternately
Disconnect two-person intercom pairing	function key	Short press twice	Double mode disconnected	Function key indicator blue and red flicker

	intercom button	short press	Double mode disconnected	
Multi- Player Intercom Pairing	intercom button	Press and hold for 3s	The intercom mode is on, pairing , and dododo	Intercom key indicator light flashes fast
Disconnectin g multiple people from pairing (math.)	intercom button	Press and hold for 3s	Intercom disconnected	Intercom Indicator Light go out (of fire)

6. Network intercom function

functionality	keystrokes	manipulate	voice prompt	indicator light
Turn on network intercom robocalls	intercom button	Short press once (network intercom connected) (pick up)	/	
Turn off network intercom rush for food	intercom button	Short press once (grab) (Mai Zhong)	/	

7.Voice assistant function

functionality	speech command (for computer speech recognition)	manipulate
Evoke the voice assistant	Chun, Chun, Chun, Chun, Chun, Chun, Chun, Chun, Chun, Chun, Chun. Hi Extreme Core/Hi ZEEHO/Customized Voice Wakeup Words	Directly say: Ah Chun Ah Chun / Ah Chun student / Hi, Extreme Core / Hi ZEEHO / Customized voice reminder word

Voice answer on incoming calls	Answer the phone (call not connected) time)	Direct: Answer the phone
Voice on call (not connected) hang up	Hang up (call not connected) time)	Straight up: hang up.
Increase the volume of your Bluetooth headset	boost	Straight up: turn up the volume
Reduce the volume of your Bluetooth headset	lower the volume	Straight up: turn down the volume
Play the previous song.	Previous song (music playing)	Straight up: the last song
Play the next song.	Next song (music playing)	Straight up: next song
Music Pause	Pause playback (music playback) (Middle)	Straight up: pause the playback
Music resume playback	Continue Playing (Music Pause) (Middle)	Straight up: keep playing

FCC Caution:

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

This device and its antenna(s) must not be co-located or operating in conjunction with any other antenna or transmitter.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction