

User's Manual of MONNY Mobile Phone

TABLE OF CONTENT

1. Basic Information

1.1. Brief Introduction

Thanks for selecting K9 MINI color screen GSM digital mobile phone. Through reading the manual, you can fully know how to use K9 MINI mobile phone, appreciate its complete function and simple operating method.

K9 MINI color screen mobile phone is designed aiming at GSM network environment; the phone is Two Card Two Standby, but you **cannot** call another SIM card when one SIM card is **on call**. Besides basic call functions **of** K9 MINI also provides many kinds of practical functions, such as name card holder, scene mode, message, audio and video player, camera and video, E-book, game, B-tooth, alarm clock, calculator, STK, time and date, auto power-on and shut-down **etc.**, **which will be** convenient for your work and leisure activities. In addition, K9 MINI adopts personalized human-computer interface design. It's complete




function can meet your different requirements.






K9 MINI color screen mobile phone accords with GSM criterion, has obtained the certification of competent authority.

The company reserves the rights to revise the contents of the manual without prior notice.

2. Before use

2.1.1. Description of the Standby Pictures

	Network signal strength Is the strength of the connection to the mobile phone with its network. The more the stripe the stronger the signal. When the SIM card is inserted in the card slot 1, standby screen will show the icon.
	Network signal strength Is the strength of the connection to the mobile phone with its network. The more the stripe the stronger the signal. When the SIM card is inserted in the card slot 2, standby screen will show the icon.
	Battery strength

	The full the fill is, the more electric quantity is. Standby screen will show the icon.
	Silent mode When the scene mode is set as the mute mode, standby screen will show the icon.
	Vibrate mode When the scene mode is set as the Vibration mode , standby screen will show the icon.
	Indoor mode When the scene mode is set as the indoor mode, standby screen will show the icon.
	Outdoor mode When the scene mode is set as the outdoor mode, standby screen will show the icon.
	Power save mode Click the icon to active the power save mode

2.1.2. Description of Keys

Keys	Function
Left soft key/ Right soft key	1. Execute functions that the left-down/right-down corner indicator

	<p>shows.</p> <p>2. In the standby mode, press Left Soft key to access Message, Right Soft key to access Contacts.</p>
Navigation key	On other interfaces, it equals to navigation key and direction key except for special functions.
Dial key	<p>1. Press this key to dial or receive an incoming call.</p> <p>2. When in the standby mode, press this key to access Dialed Calls.</p>
OK key	In the dial panel mode, press this key to show or hide the dial panel.
MP3 key	Enter into audio player.
End key	<p>1. Mainly used as power on/off.</p> <p>2. Press to return to standby screen in any interface.</p> <p>3. End calls or reject incoming calls.</p>

2.2. Installing the Memory Card

Aim at the T card slot and push the T card gently, and the card

will be inserted correctly.

Prompt: If the memory card is failed, please check whether it is correctly placed and good contact of metal point.

2.3. Security Password

■ PIN

PIN (Personal Identification Number) is used to prevent your SIM card from being used illegally. The PIN is usually provided with the SIM card together. If you input the wrong PIN for continuously three times, please input PUK to unlock it. Please contact the network operations company for more details.

■ PIN 2

You need to input PIN2 when entering some functions (such as call charge); if you input wrong PIN2 for continuous three times, you need to input PUK2 to unlock it. Please contact the network operations company for more details.

■ PUK

When changing the locked PIN, you need to input PUK (Personal Unlock Key). PUK is provided with the SIM card together. If it is not provided, please contact your service provider. If you input the wrong PUK for continuously ten times, the SIM card will be considered as permanently invalid. In that case please contact your service provider to buy a new card. You can't change

the PUK. If you lose the code, please **contact your** service provider **for assistance**.

■ **PUK2**

When changing the locked PIN2, you need to input PUK2. If you input **the** wrong PUK2 for **continuously** ten times, you can't use the functions that need PIN2. Please **contact your** service provider to buy a new card. You can't change **the** PUK 2. If you lose the code, please **contact your** service provider **for assistance**

3. Quick User Guide

3.1. Feature Functions

The phone has not only the basic functions of mobile phone, but also support rich, practical and rapid feature functions, **which we have** briefly introduced as follows:

- **Contacts:** Each name card holder record stored in the phone can be related with several telephone **numbers**. **The** phone can store 100 records at most; can send SMS in the name card holder; you can copy name card holder record between SIM card and the phone.
- **Scene mode:** Custom the ring tone (include ring tone settings,

Adjust volume, Call alert, Message alert, Alarm & calendar remind, Key tone, Battery low alert, Power on /off tone) according to different events or environment.

- Call log: The phone will automatically store the information of call log for you to check; support to call the telephone number in the call log; support to save the telephone number in the call log to name card holder and set as rejected call; support the function of sending SMS and etc. to the telephone numbers in the call log.
- Message: The phone supports storing SMS and 50 pieces at most. The phone supports the storing status of SMS in SIM card and the phone.
- Media: Your phone provides all kinds of entertainment services including player, camera, FM radio, recorder and other functions.
- Camera: The phone supports camera and video function. You can customize the camera and video.
- Tools: The phone supports various practical functions such as alarm, calculator etc etc.
- Organizer: The phone supports various practical functions such as B-tooth, Calendar, World clock etc etc.
- Settings: You can customize the phone according to your need, including call settings , phone settings, display settings,

- security settings and other settings.
- Input method: The phone supports various input modes which is convenient for you to input English letters, numbers and symbols etc.
receive the call.

Emergency Services

You can directly dial an emergency service call without the SIM card.

Different network uses different emergency numbers. Please consult your network operations company for more details.

3.2. Dialed Calls/ Received Calls/Missed Calls/ Rejected Calls

You can enter call log to check the relevant details of dialed calls, missed calls, received calls and rejected calls.

Prompt: The record of incoming call from blacklist number will be saved in Rejected Calls.

3.3. Call Divert

When you start up this function according to different divert condition settings (Unconditional transfer, Divert if busy, Divert if

no answer, Divert if unreachable, Cancel all **diverts**) you can select to switch the incoming call to voice inbox or other telephone numbers.

3.4. Call Barring

When you start up this function according to different restricted condition settings (all outgoing calls, all incoming calls, incoming calls when roaming, international calling, dial when international roaming, Cancel all barring), you can restrict the call under the corresponding conditions (need to apply to network operator for business).

4. Function Menu

4.1. Settings

- Call Settings
 - Dual-SIM
 - Network selection

This function can let you select the network manually or automatically when the phone is in the roaming state. You can use

this function only after you have made an effective roaming.

- — Call divert: When “call divert” function is start up, you can transfer the incoming call to voice inbox or other phone number according to the **task** “ call divert” conditions.

- — Call barred: All outgoing calls, incoming calls, roaming incoming calls, international outgoing calls, roaming international outgoing calls are available.

- — Call waiting: You can start up or shut down the function. When it is **selected** even when you are **on** a call, you can also receive **another call**.

- — Hide ID: This function must be supported by **the** network.

- — Select line: There are two lines can be selected: line 1 and line 2. But the function **is** just for the phone which has one SIM card and two numbers. If you **are not using that type of a phone please select** line 1, because if you choose line 2, dialing will be limited.

- — Flight mode: You can **select** the function directly or choose when power on.

- — Others

- Phone settings

- — Time & date: You can set up the date and **the** time on the phone as well as **in the** display mode.

- — Select Language: You can select phone language.

——Shortcut settings: You can set the menu when you press right softkey to enter in standby interface.

——Auto Power on/off: You can set the time and repeat mode to power-on or power-off.

——Power management: You can view the electric quantity of your battery.

——Restore factory settings: You can restore part of the phone settings as factory settings. The default code of restoring factory settings is: 1234.

■ Display settings

——Wallpaper settings: You can set as default wallpaper images or as well as other wallpaper images.

——Idle display settings

——Contrast: On the screen backlight interface you can set different brightness of your phone by pressing the left/right direction key.

——Backlight:

——Keypad backlight time

——Animation effect

■ Security settings

——PIN: You can start up shut down or modify PIN code.

The default PIN code is 1234.

——PIN2: You can review PIN2 code. For details, please

contact **the** network operator.

— — Privacy: You can review privacy protection password.

The default password of privacy protection mode is 1234.

— — Auto Keypad lock

— — Lock screen by end-key

— — Power-on password: You can start up or shut down “phone password” or revise it. The default phone password is 1234.

— — Max Sar Value:0.409W/kg

FCC Statement

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference.

(2) This device must accept any interference received, including interference that may cause undesired operation.

2. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency

energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

SAR Information Statement

Your wireless phone is a radio transmitter and receiver. It is designed and manufactured not to exceed the emission limits for exposure to radiofrequency (RF) energy set by the Federal Communications Commission of the U.S. Government. These limits are part of comprehensive guidelines and establish permitted levels of RF energy for the general population. The guidelines are based on standards that were developed by

independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons, regardless of age and health. The exposure standard for wireless mobile phones employs a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit set by the FCC is 1.6 W/kg. * Tests for SAR are conducted with the phone transmitting at its highest certified power level in all tested frequency bands. Although the SAR is determined at the highest certified power level, the actual SAR level of the phone while operating can be well below the maximum value. This is because the phone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the power output. Before a phone model is available for sale to the public, it must be tested and certified to the FCC that it does not exceed the limit established by the government adopted requirement for safe exposure. The tests are performed in positions and locations (e.g., at the ear and worn on the body) as required by the FCC for each model. The maximum scaled SAR value for this model phone when tested for use at the ear is 0.594W/Kg and when worn on the body, as described in this user guide, is 0.585W/Kg(Body-worn measurements differ among

phone models, depending upon available accessories and FCC requirements), While there may be differences between the SAR levels of various phones and at various positions, they all meet the government requirement for safe exposure. The FCC has granted an Equipment Authorization for this model phone with all reported SAR levels evaluated as in compliance with the FCC RF exposure guidelines. SAR information on this model phone is on file with the FCC and can be found under the Display Grant section of <http://www.fcc.gov/oet/fccid> after searching on FCC ID: [2AAKK-MONNY](#) Additional information on Specific Absorption Rates (SAR) can be found on the Cellular Telecommunications Industry Association (CTIA) web-site at <http://www.wow-com.com>. * In the United States and Canada, the SAR limit for mobile phones used by the public is 1.6 watts/kg (W/kg) averaged over one gram of tissue. The standard incorporates a substantial margin of safety to give additional protection for the public and to account for any variations in measurements.

Body-worn Operation

This device was tested for typical body-worn operations. To comply with RF exposure requirements, a minimum separation distance of 15mm must be maintained between the user's body

and the handset, including the antenna. Third-party belt-clips, holsters, and similar accessories used by this device should not contain any metallic components. Body-worn accessories that do not meet these requirements may not comply with RF exposure requirements and should be avoided. Use only the supplied or an approved antenna.