

Instruction



LH-101
Fm Transmitter

Features:

- 1.High fidelity, stereo.Digital PLL, transmission is stable in different environment.
- 2.LCD displays Tuning frequency more intuitive
- 3.Pure blue backlight in the middle of the machine
- 4.Full frequency range (88.1~107.9MHZ)
- 5.Memory for last frequency,It will mute the music during calls and resume playing music after calls.
- 6.Built-in lithium battery, It works more than 4 hours
- 7.**Micro USB 5V Charge Methods**(The machine comes with USB cable for charging.
- 8.Compatible with iPhone,Ipod and support all audio sources with 3.5mm Jack, such as smart phones MP3, MP4 etc.
- 9.With 3.5mm jack
- 10.Hands free talk function offer you more safety during driving

Characteristics:

- * **The unique high-grade visual design**
- * High fidelity, stereo.Digital PLL, transmission is stable in different environment.
- * Full frequency design, avoiding to conflict with radio interference

Specification:

- * Frequency range:20Hz-20KHz
- * Separation: ≥ 60 dB
- * Operating voltage:4.2V130MA(lithium battery)
- * Operating current:20mA ± 5 mA
- * Working time:More than 4 hours

- *Recharging voltage:5V500MA
- *Recharging time:Two hours
- *SNR: ≥ 60 dB
- *Audio distortion degree: $<2\%$ (mod=75KHZ。F=1KHZ)
- *Clutter or harmonic: <-35 db
- *Item size:60*26*12mm
- *Net weight:20g HS:8529906000

Instructions:

- 1.Turning on your car radio and switching it to a frequency point, which one without radio program .Such as 88.1MHZ.
- 2.Making FM transmitter insert into your phone or other audio equipment,which ones with 3.5mm audio slots .Meanwhile playing music on your phone.
- 3.After turning on the switch of the Fm transmitter ,The screen will show the transmitting frequency point,Then switch it by the "up"and "down"buttons to the frequency point as same with your car radio frequency .And then enjoy your music as your wish.
- 4.The key of "M" prestores 4 frequency points(88.1Mhz,94.1 Mhz,100.1Mhz,106.1Mhz) for quickly connecting to your lovely music.



FCC statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Caution: The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications or change to this equipment.