




OBW: 1RB-HIGH_offset





HIGH BAND EDGE BLOCK-1RB-HIGH_offset




HIGH BAND EDGE BLOCK-1RB-HIGH_offset



LOW BAND EDGE BLOCK-40MHz-100%RB

Channel power



LOW BAND EDGE BLOCK-40MHz-100%RB




HIGH BAND EDGE BLOCK-40MHz-100%RB




HIGH BAND EDGE BLOCK-40MHz-100%RB




NR n41
OBW: 1RB-LOW_offset

LOW BAND EDGE BLOCK-1RB-LOW_offset



LOW BAND EDGE BLOCK-1RB-LOW_offset




OBW: 1RB-HIGH_offset




HIGH BAND EDGE BLOCK-1RB-HIGH_offset




HIGH BAND EDGE BLOCK-1RB-HIGH_offset




LOW BAND EDGE BLOCK-100MHz-100%RB




Channel power




LOW BAND EDGE BLOCK-100MHz-100%RB




Channel power



HIGH BAND EDGE BLOCK-100MHz-100%RB




HIGH BAND EDGE BLOCK-100MHz-100%RB




NR n48


OBW: 1RB-LOW_offset




LOW BAND EDGE BLOCK-1RB-LOW_offset




LOW BAND EDGE BLOCK-1RB-LOW_offset




LOW BAND EDGE BLOCK-1RB-LOW_offset




LOW BAND EDGE BLOCK-1RB-LOW_offset




OBW: 1RB-HIGH_offset




HIGH BAND EDGE BLOCK-1RB-HIGH_offset




HIGH BAND EDGE BLOCK-1RB-HIGH_offset




HIGH BAND EDGE BLOCK-1RB-HIGH_offset




HIGH BAND EDGE BLOCK-1RB-HIGH_offset



LOW BAND EDGE BLOCK-100MHz-100%RB




LOW BAND EDGE BLOCK-100MHz-100%RB




LOW BAND EDGE BLOCK-100MHz-100%RB




LOW BAND EDGE BLOCK-100MHz-100%RB




ACLR



HIGH BAND EDGE BLOCK-100MHz-100%RB




HIGH BAND EDGE BLOCK-100MHz-100%RB



HIGH BAND EDGE BLOCK-100MHz-100%RB



HIGH BAND EDGE BLOCK-100MHz-100%RB




ACLR




NR n66


OBW: 1RB-LOW_offset




LOW BAND EDGE BLOCK-1RB-LOW_offset




OBW: 1RB-HIGH_offset



HIGH BAND EDGE BLOCK-1RB-HIGH_offset



LOW BAND EDGE BLOCK-45MHz-100%RB




HIGH BAND EDGE BLOCK-45MHz-100%RB




NR n71


LOW BAND EDGE BLOCK-1RB-LOW_offset




HIGH BAND EDGE BLOCK-1RB-HIGH_offset



LOW BAND EDGE BLOCK-35MHz-100%RB




HIGH BAND EDGE BLOCK-35MHz-100%RB




NR n78L


OBW: 1RB-LOW_offset




LOW BAND EDGE BLOCK-1RB-LOW_offset




LOW BAND EDGE BLOCK-1RB-LOW_offset




OBW: 1RB-HIGH_offset




HIGH BAND EDGE BLOCK-1RB-HIGH_offset




HIGH BAND EDGE BLOCK-1RB-HIGH_offset



LOW BAND EDGE BLOCK-100MHz-100%RB




LOW BAND EDGE BLOCK-100MHz-100%RB



HIGH BAND EDGE BLOCK-100MHz-100%RB



HIGH BAND EDGE BLOCK-100MHz-100%RB



A.7 Conducted Spurious Emission

A.7.1 Measurement Method

The following steps outline the procedure used to measure the conducted emissions from the EUT.

1. In measuring unwanted emissions, the spectrum shall be investigated from 30 MHz or the lowest radio frequency signal generated in the equipment, whichever is lower, without going below 9 kHz, up to at least the frequency given below:
 - (a) If the equipment operates below 10 GHz: to the tenth harmonic of the highest fundamental frequency or to 40 GHz, whichever is lower.
 - (b) If the equipment operates at or above 10 GHz: to the fifth harmonic of the highest fundamental frequency or to 100 GHz, whichever is lower.
2. Determine EUT transmit frequencies: below outlines the band edge frequencies pertinent to conducted emissions testing.
3. The number of sweep points of spectrum analyzer is greater than $2 \times \text{span}/\text{RBW}$.

A.7.2 Measurement Limit

Part 22.917, Part 24.238 and Part 27.53(h) specify that the power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB.

Part 27.53(m) specifies for mobile digital stations, the attenuation factor shall be not less than $40 + 10 \log(P)$ dB on all frequencies between the channel edge and 5 megahertz from the channel edge, $43 + 10 \log(P)$ dB on all frequencies between 5 megahertz and X megahertz from the channel edge, and $55 + 10 \log(P)$ dB on all frequencies more than X megahertz from the channel edge, where X is the greater of 6 megahertz or the actual emission bandwidth as defined in paragraph (m)(6) of this section. In addition, the attenuation factor shall not be less than $43 + 10 \log(P)$ dB on all frequencies between 2490.5 MHz and 2496 MHz and $55 + 10 \log(P)$ dB at or below 2490.5 MHz. Mobile Satellite Service licensees operating on frequencies below 2495 MHz may also submit a documented interference complaint against BRS licensees operating on channel BRS Channel 1 on the same terms and conditions as adjacent channel BRS or EBS licensees.

Part 27.53(g) states for operations in the 600 MHz band and the 698–746 MHz band, the power of any emission outside a licensee's frequency band(s) of operation shall be attenuated below the transmitter power (P) within the licensed band(s) of operation, measured in watts, by at least $43 + 10 \log(P)$ dB. Compliance with this provision is based on the use of measurement instrumentation employing a resolution bandwidth of 100 kilohertz or greater. However, in the 100 kilohertz bands immediately outside and adjacent to a licensee's frequency block, a resolution bandwidth of at least 30 kHz may be employed.

Part 27.53(n) states for mobile operations in the 3450-3550 MHz band, the conducted power of any emission outside the licensee's authorized bandwidth shall not exceed $-13 \text{ dBm}/\text{MHz}$. Compliance with this paragraph (n)(2) is based on the use of measurement instrumentation employing a resolution bandwidth of 1 megahertz or greater.


Part 96.41(e) states for channel and frequency assignments made by a CBSD to End User

Devices, the conducted power of any End User Device emission outside the fundamental emission (whether in or outside of the authorized band) shall not exceed -13 dBm/MHz within 0 to B megahertz (where B is the bandwidth in megahertz of the assigned channel or multiple contiguous channels of the End User Device) above the upper CBSD-assigned channel edge and within 0 to B megahertz below the lower CBSD-assigned channel edge. At all frequencies greater than B megahertz above the upper CBSD assigned channel edge and less than B megahertz below the lower CBSD-assigned channel edge, the conducted power of any End User Device emission shall not exceed -25 dBm/MHz. The conducted power of emissions below 3540 MHz or above 3710 MHz shall not exceed -25 dBm/MHz, and the conducted power of emissions below 3530 MHz or above 3720 MHz shall not exceed -40 dBm/MHz.

A.7.3 Measurement result


n2

NOTE: peak above the limit line is the carrier frequency.




n5

NOTE: peak above the limit line is the carrier frequency.




n7

NOTE: peak above the limit line is the carrier frequency.




n12

NOTE: peak above the limit line is the carrier frequency.





n41

NOTE: peak above the limit line is the carrier frequency.




n48

NOTE: peak above the limit line is the carrier frequency.




n66

NOTE: peak above the limit line is the carrier frequency.




n71

NOTE: peak above the limit line is the carrier frequency.



n78L

NOTE: peak above the limit line is the carrier frequency.



A.8 Peak-to-Average Power Ratio

The peak-to-average ratio (PAR) of the transmission may not exceed 13 dB

- Refer to instrument's analyzer instruction manual for details on how to use the power statistics/CCDF function;
- Set resolution/measurement bandwidth \geq signal's occupied bandwidth;
- Set the number of counts to a value that stabilizes the measured CCDF curve;
- Record the maximum PAPR level associated with a probability of 0.1%.

Measurement results

n2,40MHz

Frequency (MHz)	PAPR (dB)								
	DFT-s-pi/2 BPSK	DFT-s-QPSK	DFT-s-16QAM	DFT-s-64QAM	DFT-s-256QAM	CP-QPSK	CP-16QAM	CP-64QAM	CP-256QAM
1880	4.94	5.56	6.20	6.48	6.59	8.07	8.09	8.15	8.53

n7,50MHz

Frequency (MHz)	PAPR (dB)								
	DFT-s-pi/2 BPSK	DFT-s-QPSK	DFT-s-16QAM	DFT-s-64QAM	DFT-s-256QAM	CP-QPSK	CP-16QAM	CP-64QAM	CP-256QAM
2535	4.26	4.97	5.62	5.89	6.44	7.14	7.09	7.27	8.32

n12,15MHz

Frequency (MHz)	PAPR (dB)								
	DFT-s-pi/2 BPSK	DFT-s-QPSK	DFT-s-16QAM	DFT-s-64QAM	DFT-s-256QAM	CP-QPSK	CP-16QAM	CP-64QAM	CP-256QAM
707.5	4.32	5.14	6.00	6.22	6.68	7.58	7.48	7.72	8.58

n41,100MHz

Frequency (MHz)	PAPR (dB)								
	DFT-s-pi/2 BPSK	DFT-s-QPSK	DFT-s-16QAM	DFT-s-64QAM	DFT-s-256QAM	CP-QPSK	CP-16QAM	CP-64QAM	CP-256QAM
2592.99	4.43	5.06	5.84	6.08	6.62	7.41	7.38	7.56	8.43

n48,100MHz

Frequency (MHz)	PAPR (dB)								
	DFT-s-pi/2 BPSK	DFT-s-QPSK	DFT-s-16QAM	DFT-s-64QAM	DFT-s-256QAM	CP-QPSK	CP-16QAM	CP-64QAM	CP-256QAM
3624.99	5.23	5.88	6.65	6.77	6.72	8.45	8.54	8.59	8.81

n66,45MHz

Frequency (MHz)	PAPR (dB)								
	DFT-s-pi/2 BPSK	DFT-s-QPSK	DFT-s-16QAM	DFT-s-64QAM	DFT-s-256QAM	CP-QPSK	CP-16QAM	CP-64QAM	CP-256QAM
1745	4.47	5.44	6.14	6.30	6.56	8.02	8.00	8.12	8.40

n71,35MHz

Frequency (MHz)	PAPR (dB)								
	DFT-s-pi/2 BPSK	DFT-s-QPSK	DFT-s-16QAM	DFT-s-64QAM	DFT-s-256QAM	CP-QPSK	CP-16QAM	CP-64QAM	CP-256QAM
680.5	5.37	5.42	6.20	6.48	6.82	8.05	8.14	8.17	8.85

n78L,100MHz

Frequency (MHz)	PAPR (dB)								
	DFT-s-pi/2 BPSK	DFT-s-QPSK	DFT-s-16QAM	DFT-s-64QAM	DFT-s-256QAM	CP-QPSK	CP-16QAM	CP-64QAM	CP-256QAM
3500.01	5.44	5.61	6.31	6.43	6.68	8.28	8.34	8.59	8.52

Annex B: Accreditation Certificate



Accredited Laboratory

A2LA has accredited

TELECOMMUNICATION TECHNOLOGY LABS, CAICT

Beijing, People's Republic of China

for technical competence in the field of

Electrical Testing

This laboratory is accredited in accordance with the recognized International Standard ISO/IEC 17025:2017
General requirements for the competence of testing and calibration laboratories. This accreditation demonstrates
technical competence for a defined scope and the operation of a laboratory quality management system
(refer to joint ISO-ILAC-IAF Communiqué dated April 2017).



Presented this 23rd day of July 2024.



Mr. Trace McInturff, Vice President, Accreditation Services
For the Accreditation Council
Certificate Number 7049.01
Valid to July 31, 2026

For the tests to which this accreditation applies, please refer to the laboratory's Electrical Scope of Accreditation.

*****END OF REPORT*****