

Full & Default Power Mode_Main PA

n5 Ant0 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				166800	167300	167800			
Frequency (MHz)				834	836.5	839			
20	1/2 BPSK	1	1	25.29	25.29	25.29			
20	1/2 BPSK	1	53	25.31	25.28	25.24	25.7	0.0	
20	1/2 BPSK	1	104	25.11	25.13	25.14			
20	1/2 BPSK	50	0	24.69	24.70	24.63	25.2	0.5	
20	1/2 BPSK	50	28	25.28	25.32	25.26	25.7	0.0	
20	1/2 BPSK	50	56	24.62	24.72	24.63			
20	1/2 BPSK	100	0	24.82	24.77	24.82	25.2	0.5	
20	QPSK	1	1	25.29	25.33	25.27			
20	QPSK	1	53	25.32	25.32	25.24	25.7	0.0	
20	QPSK	1	104	25.13	25.09	25.09			
20	QPSK	50	0	24.23	24.27	24.26	24.7	1.0	
20	QPSK	50	28	25.20	25.23	25.21	25.7	0.0	
20	QPSK	50	56	24.15	24.08	24.08			
20	QPSK	100	0	24.26	24.29	24.28	24.7	1.0	
20	16QAM	1	1	24.16	24.15	24.20	24.7	1.0	
20	64QAM	1	1	22.63	22.62	22.60	23.2	2.5	
20	256QAM	1	1	20.49	20.51	20.56	21.2	4.5	
Channel				166300	167300	168300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				831.5	836.5	841.5			
15	QPSK	1	1	25.24	25.19	25.17	25.7	0.0	
Channel				165800	167300	168800	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				829	836.5	844			
10	QPSK	1	1	25.22	25.22	25.13	25.7	0.0	
Channel				165300	167300	169300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				826.5	836.5	846.5			
5	QPSK	1	1	25.14	25.26	25.21	25.7	0.0	

n12 Ant0 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				141300	141500	141700			
Frequency (MHz)				706.5	707.5	708.5			
15	1/2 BPSK	1	1	25.39	25.39	25.48			
15	1/2 BPSK	1	40	25.41	25.43	25.38	25.7	0.0	
15	1/2 BPSK	1	77	25.32	25.35	25.29			
15	1/2 BPSK	36	0	24.88	24.83	24.89	25.2	0.5	
15	1/2 BPSK	36	22	25.43	25.39	25.45	25.7	0.0	
15	1/2 BPSK	36	43	24.84	24.80	24.79			
15	1/2 BPSK	75	0	24.93	24.99	24.90	25.2	0.5	
15	QPSK	1	1	25.47	25.52	25.48			
15	QPSK	1	40	25.48	25.43	25.38	25.7	0.0	
15	QPSK	1	77	25.33	25.24	25.26			
15	QPSK	36	0	24.37	24.46	24.43	24.7	1.0	
15	QPSK	36	22	25.44	25.47	25.43	25.7	0.0	
15	QPSK	36	43	24.33	24.27	24.23			
15	QPSK	75	0	24.48	24.52	24.45	24.7	1.0	
15	16QAM	1	1	24.26	24.37	24.32	24.7	1.0	
15	64QAM	1	1	22.84	22.73	22.82	23.2	2.5	
15	256QAM	1	1	20.71	20.73	20.66	21.2	4.5	
Channel				140800	141500	142200	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				704	707.5	711			
10	QPSK	1	1	25.41	25.46	25.43	25.7	0.0	
Channel				140300	141500	142700	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				701.5	707.5	713.5			
5	QPSK	1	1	25.32	25.43	25.40	25.7	0.0	

n26 Ant0 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				164800	166300	167800			
Frequency (MHz)				824	831.5	839			
20	1/2 BPSK	1	1	25.34	25.35	25.33			
20	1/2 BPSK	1	53	25.25	25.30	25.28	25.7	0.0	
20	1/2 BPSK	1	104	25.19	25.11	25.09			
20	1/2 BPSK	50	0	24.74	24.66	24.76	25.2	0.5	
20	1/2 BPSK	50	28	25.29	25.27	25.36	25.7	0.0	
20	1/2 BPSK	50	56	24.68	24.74	24.73			
20	1/2 BPSK	100	0	24.78	24.79	24.79	25.2	0.5	
20	QPSK	1	1	25.35	25.39	25.37			
20	QPSK	1	53	25.36	25.33	25.27	25.7	0.0	
20	QPSK	1	104	25.14	25.14	25.09			
20	QPSK	50	0	24.32	24.28	24.22	24.7	1.0	
20	QPSK	50	28	25.29	25.34	25.31	25.7	0.0	
20	QPSK	50	56	24.05	24.09	24.09			
20	QPSK	100	0	24.35	24.36	24.29	24.7	1.0	
20	16QAM	1	1	24.15	24.19	24.11	24.7	1.0	
20	64QAM	1	1	22.59	22.59	22.58	23.2	2.5	
20	256QAM	1	1	20.48	20.46	20.53	21.2	4.5	
Channel				164300	166300	168300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				821.5	831.5	841.5			
15	QPSK	1	1	25.22	25.24	25.23	25.7	0.0	
Channel				163800	166300	168800	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				819	831.5	844			
10	QPSK	1	1	25.30	25.32	25.27	25.7	0.0	
Channel				163300	166300	169300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				816.5	831.5	846.5			
5	QPSK	1	1	25.24	25.33	25.33	25.7	0.0	

n71 Ant0 Default								
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)
Channel				136100				
Frequency (MHz)				680.5				
35	1/2 BPSK	1	1	25.24			25.7	0.0
35	1/2 BPSK	1	90	25.14				
35	1/2 BPSK	1	186	25.10				
35	1/2 BPSK	90	0	24.60			25.2	0.5
35	1/2 BPSK	90	45	25.20			25.7	0.0
35	1/2 BPSK	90	90	24.58			25.2	0.5
35	1/2 BPSK	180	0	24.70				
35	QPSK	1	1	25.25			25.7	0.0
35	QPSK	1	90	25.16				
35	QPSK	1	186	25.00				
35	QPSK	90	0	24.16			24.7	1.0
35	QPSK	90	45	25.21			25.7	0.0
35	QPSK	90	90	24.06			24.7	1.0
35	QPSK	180	0	24.23				
35	16QAM	1	1	24.04			24.7	1.0
35	64QAM	1	1	22.54			23.2	2.5
35	256QAM	1	1	20.48			21.2	4.5
Channel				135600	136100	136600	tune- up limit	MPR (dB)
Frequency (MHz)				678	680.5	683		
30	QPSK	1	1	25.14	25.19	25.10	25.7	0.0
Channel				135100	136100	137100	tune- up limit	MPR (dB)
Frequency (MHz)				675.5	680.5	685.5		
25	QPSK	1	1	25.12	25.10	25.18	25.7	0.0
Channel				134600	136100	137600	tune- up limit	MPR (dB)
Frequency (MHz)				673	680.5	688		
20	QPSK	1	1	25.18	25.13	25.15	25.7	0.0
Channel				134100	136100	138100	tune- up limit	MPR (dB)
Frequency (MHz)				670.5	680.5	690.5		
15	QPSK	1	1	25.10	25.14	25.17	25.7	0.0
Channel				133600	136100	138600	tune- up limit	MPR (dB)
Frequency (MHz)				668	680.5	693		
10	QPSK	1	1	25.14	25.15	25.14	25.7	0.0
Channel				133100	136100	139100	tune- up limit	MPR (dB)
Frequency (MHz)				665.5	680.5	695.5		
5	QPSK	1	1	25.15	25.15	25.08	25.7	0.0

n5 Ant1 Default									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				166800	167300	167800			
Frequency (MHz)				834	836.5	838			
20	1/2 BPSK	1	1	25.38	25.44	25.45	25.7	0.0	
20	1/2 BPSK	1	53	25.39	25.48	25.34			
20	1/2 BPSK	1	104	25.37	25.35	25.24			
20	1/2 BPSK	50	0	24.91	24.81	24.90	25.2	0.5	
20	1/2 BPSK	50	28	25.39	25.38	25.46	25.7	0.0	
20	1/2 BPSK	50	56	24.83	24.86	24.80	25.2	0.5	
20	1/2 BPSK	100	0	24.90	24.98	24.84	25.7	1.0	
20	QPSK	1	1	25.56	25.62	25.53			
20	QPSK	1	53	25.49	25.48	25.38			
20	QPSK	1	104	25.30	25.22	25.25	24.7	2.5	4.5
20	QPSK	50	0	24.31	24.45	24.40			
20	QPSK	50	28	25.41	25.57	25.45			
20	QPSK	50	56	24.28	24.24	24.18	24.7	1.0	
20	QPSK	100	0	24.53	24.56	24.46			
20	16QAM	1	1	24.31	24.34	24.31			
20	64QAM	1	1	22.82	22.79	22.86	23.2	2.5	
20	256QAM	1	1	20.65	20.69	20.64			
Channel				168200	167200	168200			
Frequency (MHz)				831.5	836.5	841.5			
15	QPSK	1	1	25.50	25.46	25.45	25.7	0.0	
Channel				165900	167300	168800			
Frequency (MHz)				829	836.5	844			
10	QPSK	1	1	25.51	25.50	25.44	25.7	0.0	
Channel				163200	167200	163200			
Frequency (MHz)				826.5	836.5	846.5			
5	QPSK	1	1	25.49	25.56	25.44	25.7	0.0	

n12 Ant1 Default									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch / Freq	Power Middle Ch / Freq	Power High Ch / Freq	Tune- up limit (dB)		
Channel				141300	141500	141700			
Frequency (MHz)				706.5	707.5	708.5			
15	1/2 BPSK	1	1	25.39	25.38	25.49		25.7	0.0
15	1/2 BPSK	1	40	25.47	25.40	25.39			
15	1/2 BPSK	1	77	25.27	25.39	25.30			
15	1/2 BPSK	36	0	24.89	24.82	24.86	25.2	0.5	
15	1/2 BPSK	36	22	25.38	25.43	25.41	25.7	0.0	
15	1/2 BPSK	36	43	24.89	24.85	24.80	25.2	0.5	
15	1/2 BPSK	75	0	24.89	24.94	24.93	25.2	0.0	
15	QPSK	1	1	25.54	25.63	25.57		25.7	0.0
15	QPSK	1	40	25.53	25.41	25.40			
15	QPSK	1	77	25.35	25.30	25.32			
15	QPSK	36	0	24.36	24.41	24.37	24.7	1.0	
15	QPSK	36	22	25.51	25.58	25.49	25.7	0.0	
15	QPSK	36	43	24.33	24.31	24.28	24.7	1.0	
15	QPSK	75	0	24.53	24.55	24.49	24.7	1.0	
15	16QAM	1	1	24.23	24.40	24.28	24.7	1.0	
15	64QAM	1	1	22.81	22.69	22.80	23.2	2.5	
15	256QAM	1	1	20.72	20.70	20.70	21.2	4.5	
Channel				140800	141500	142200	tune up	MPR	
Frequency (MHz)				704	707.5	711	(dB)		
10	QPSK	1	1	25.53	25.51	25.49	25.7	0.0	
Channel				140300	141500	142700	up	MPR	
Frequency (MHz)				701.5	707.5	713.5 <th>(dB)</th> <th colspan="2"></th>	(dB)		
5	QPSK	1	1	25.48	25.53	25.52	25.7	0.0	

n26 Ant1 Default									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				164800	166300	167800			
Frequency (MHz)				824	831.5	837			
20	1/2 BPSK	1	1	25.41	25.38	25.46			
20	1/2 BPSK	1	53	25.41	25.39	25.37	25.7	0.0	
20	1/2 BPSK	1	104	25.28	25.37	25.32			
20	1/2 BPSK	50	0	24.89	24.78	24.67	25.2	0.5	
20	1/2 BPSK	50	28	25.46	25.35	25.42	25.7	0.0	
20	1/2 BPSK	50	56	24.83	24.79	24.81	25.2	0.5	
20	1/2 BPSK	100	0	24.96	24.96	24.93			
20	QPSK	1	1	25.54	25.57	25.55			
20	QPSK	1	53	25.48	25.45	25.33			
20	QPSK	1	104	25.30	25.28	25.23			
20	QPSK	50	0	24.33	24.48	24.40	24.7	1.0	
20	QPSK	50	28	25.44	25.51	25.49	25.7	0.0	
20	QPSK	50	56	24.29	24.26	24.27			
20	QPSK	100	0	24.46	24.52	24.49	24.7	1.0	
20	16QAM	1	1	24.24	24.33	24.36	24.7	1.0	
20	64QAM	1	1	22.79	22.75	22.85	23.2	2.5	
20	256QAM	1	1	20.66	20.78	20.69	21.2	4.5	
Channel				164300	166300	165000			
Frequency (MHz)				821.5	831.5	841.5			
15	QPSK	1	1	25.52	25.46	25.46	25.7	0.0	
Channel				163800	166300	166800			
Frequency (MHz)				819	831.5	844			
10	QPSK	1	1	25.42	25.48	25.44	25.7	0.0	
Channel				163300	166300	163000			
Frequency (MHz)				816.5	831.5	846.5			
5	QPSK	1	1	25.43	25.51	25.45	25.7	0.0	

n71 Ant1 Default									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				136100					
Frequency (MHz)				680.5					
35	1/2 BPSK	1	1		25.24		25.7	0.0	
35	1/2 BPSK	1	90		25.18				
35	1/2 BPSK	1	186		25.18				
35	1/2 BPSK	90	0		24.69		25.2	0.5	
35	1/2 BPSK	90	45		25.19		25.7	0.0	
35	1/2 BPSK	90	90		24.55		25.2	0.5	
35	1/2 BPSK	180	0		24.82		25.2		
35	QPSK	1	1		25.32		25.7		
35	QPSK	1	90		25.24		25.7	0.0	
35	QPSK	1	186		25.10		25.7		
35	QPSK	90	0		24.25		24.7	1.0	
35	QPSK	90	45		25.28		25.7	0.0	
35	QPSK	90	90		24.10		24.7	1.0	
35	QPSK	180	0		24.24		24.7		
35	16QAM	1	1		24.18		24.7		
35	64QAM	1	1		22.47		23.2	2.5	
35	256QAM	1	1		20.55		21.2	4.5	
Channel				135600	136100	136600	118.0	MPR	
Frequency (MHz)				678	680.5	683	up	(dB)	
30	QPSK	1	1	25.21	25.16	25.23	25.7	0.0	
Channel				135100	136100	137100	118.0	MPR	
Frequency (MHz)				675.5	680.5	685.5	up	(dB)	
25	QPSK	1	1	25.17	25.19	25.22	25.7	0.0	
Channel				134600	136100	134600	118.0	MPR	
Frequency (MHz)				673	680.5	688	up	(dB)	
20	QPSK	1	1	25.21	25.19	25.19	25.7	0.0	
Channel				134100	136100	136100	118.0	MPR	
Frequency (MHz)				670.5	680.5	690.5	up	(dB)	
15	QPSK	1	1	25.19	25.25	25.19	25.7	0.0	
Channel				133600	136100	136600	118.0	MPR	
Frequency (MHz)				668	680.5	693	up	(dB)	
10	QPSK	1	1	25.22	25.26	25.25	25.7	0.0	
Channel				133100	136100	139100	118.0	MPR	
Frequency (MHz)				665.5	680.5	695.5	up	(dB)	
5	QPSK	1	1	25.18	25.17	25.26	25.7	0.0	

n2 Ant5 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376000	378000			
Frequency (MHz)				1870	1880	1890			
40	1/2 BPSK	1	1	24.14	24.27	24.14			
40	1/2 BPSK	1	108	24.21	24.33	24.21	25.0	0.0	
40	1/2 BPSK	1	214	24.29	24.42	24.38			
40	1/2 BPSK	108	0	23.83	23.87	23.74	24.5	0.5	
40	1/2 BPSK	108	54	24.31	24.36	24.27	25.0	0.0	
40	1/2 BPSK	108	108	24.03	24.05	23.93			
40	1/2 BPSK	216	0	23.91	24.03	23.91	24.5	0.5	
40	QPSK	1	1	24.57	24.62	24.54			
40	QPSK	1	108	24.36	24.45	24.33	25.0	0.0	
40	QPSK	1	214	24.44	24.52	24.41			
40	QPSK	108	0	23.32	23.43	23.32	24.0	1.0	
40	QPSK	108	54	24.43	24.54	24.45	25.0	0.0	
40	QPSK	108	108	23.52	23.57	23.48			
40	QPSK	216	0	23.54	23.64	23.58	24.0	1.0	
40	16QAM	1	1	23.20	23.29	23.17	24.0	1.0	
40	64QAM	1	1	21.62	21.72	21.67	22.5	2.5	
40	256QAM	1	1	19.58	19.57	19.61	20.5	4.5	
Channel				373000	376000	379000			
Frequency (MHz)				1887.5	1880	1892.5			
35	QPSK	1	1	24.48	24.58	24.44	25.0	0.0	
Channel				373000	376000	379000			
Frequency (MHz)				1865	1880	1895			
30	QPSK	1	1	24.50	24.58	24.49	25.0	0.0	
Channel				372000	376000	376000			
Frequency (MHz)				1862.5	1880	1897.5			
25	QPSK	1	1	24.52	24.50	24.48	25.0	0.0	
Channel				372000	376000	380000			
Frequency (MHz)				1860	1860	1860			
20	QPSK	1	1	24.44	24.58	24.41	25.0	0.0	
Channel				371500	376000	380500			
Frequency (MHz)				1857.5	1880	1902.5			
15	QPSK	1	1	24.51	24.58	24.47	25.0	0.0	
Channel				371000	376000	381000			
Frequency (MHz)				1865	1860	1865			
10	QPSK	1	1	24.55	24.59	24.42	25.0	0.0	
Channel				370500	376000	381500			
Frequency (MHz)				1862.5	1880	1907.5			
5	QPSK	1	1	24.43	24.59	24.49	25.0	0.0	

n7 Ant5 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	25.32	25.35	25.23			
50	1/2 BPSK	1	138	25.22	25.24	25.16	25.5	0.0	
50	1/2 BPSK	1	268	25.24	25.30	25.22			
50	1/2 BPSK	135	0	24.77	24.86	24.78	25.0	0.5	
50	1/2 BPSK	135	68	25.20	25.33	25.28	25.5	0.0	
50	1/2 BPSK	135	138	24.83	24.88	24.86			
50	1/2 BPSK	270	0	24.71	24.79	24.70	25.0	0.5	
50	QPSK	1	1	25.33	25.36	25.31			
50	QPSK	1	138	24.85	24.99	24.91	25.5	0.0	
50	QPSK	1	268	24.91	25.01	24.99			
50	QPSK	135	0	24.31	24.44	24.42	24.5	1.0	
50	QPSK	135	68	25.28	25.31	25.27	25.5	0.0	
50	QPSK	135	138	24.35	24.43	24.38			
50	QPSK	270	0	24.34	24.42	24.30	24.5	1.0	
50	16QAM	1	1	24.24	24.36	24.29	24.5	1.0	
50	64QAM	1	1	22.75	22.81	22.67	23.0	2.5	
50	256QAM	1	1	20.63	20.88	20.81	21.0	4.5	
Channel				504000	507000	510000			
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	25.27	25.29	25.21	25.5	0.0	
Channel				503500	507000	510500			
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	25.18	25.31	25.21	25.5	0.0	
Channel				503000	507000	511000			
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	25.19	25.34	25.24	25.5	0.0	
Channel				502500	507000	511500			
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	25.27	25.33	25.20	25.5	0.0	
Channel				502000	507000	512000			
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	25.29	25.26	25.20	25.5	0.0	
Channel				501500	507000	512500			
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	25.20	25.24	25.26	25.5	0.0	
Channel				501000	507000	513000			
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	25.26	25.28	25.20	25.5	0.0	
Channel				500500	507000	513500			
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	25.29	25.33	25.22	25.5	0.0	

n25 Ant5 Default									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376500	379000			
Frequency (MHz)				1870	1882.5	1895			
40	1/2 BPSK	1	1	24.24	24.31	24.22			
40	1/2 BPSK	1	108	24.21	24.28	24.25	25.0	0.0	
40	1/2 BPSK	1	214	24.19	24.23	24.13			
40	1/2 BPSK	108	0	23.72	23.84	23.72	24.5	0.5	
40	1/2 BPSK	108	54	24.37	24.39	24.34	25.0	0.0	
40	1/2 BPSK	108	108	24.01	24.06	23.97			
40	1/2 BPSK	216	0	24.03	24.12	24.06	24.5	0.5	
40	QPSK	1	1	24.40	24.44	24.42			
40	QPSK	1	108	24.14	24.27	24.23	25.0	0.0	
40	QPSK	1	214	24.23	24.31	24.27			
40	QPSK	108	0	23.34	23.39	23.36	24.0	1.0	
40	QPSK	108	54	24.30	24.42	24.35	25.0	0.0	
40	QPSK	108	108	23.48	23.54	23.48			
40	QPSK	216	0	23.55	23.63	23.81	24.0	1.0	
40	16QAM	1	1	23.13	23.24	23.16	24.0	1.0	
40	64QAM	1	1	21.55	21.65	21.51	22.5	2.5	
40	256QAM	1	1	19.58	19.63	19.58	20.5	4.5	
Channel				373500	376500	379500			
Frequency (MHz)				1867.5	1882.5	1897.5			
35	QPSK	1	1	24.35	24.30	24.38	25.0	0.0	
Channel				373000	376500	380000			
Frequency (MHz)				1865	1882.5	1900			
30	QPSK	1	1	24.38	24.30	24.32	25.0	0.0	
Channel				372500	376500	380500			
Frequency (MHz)				1862.5	1882.5	1902.5			
25	QPSK	1	1	24.36	24.31	24.32	25.0	0.0	
Channel				372000	376500	381000			
Frequency (MHz)				1860	1882.5	1905			
20	QPSK	1	1	24.34	24.31	24.36	25.0	0.0	
Channel				371500	376500	381500			
Frequency (MHz)				1857.5	1882.5	1907.5			
15	QPSK	1	1	24.29	24.34	24.30	25.0	0.0	
Channel				371000	376500	382000			
Frequency (MHz)				1855	1882.5	1910			
10	QPSK	1	1	24.30	24.38	24.36	25.0	0.0	
Channel				370500	376500	382500			
Frequency (MHz)				1852.5	1882.5	1912.5			
5	QPSK	1	1	24.35	24.38	24.31	25.0	0.0	

Part270 n77 PC2 Ant5 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				650000	656000	662000			
100	1/2 BPSK	1	1	27.59	27.74	27.59			
100	1/2 BPSK	1	137	27.57	27.64	27.50	28.5	0.0	
100	1/2 BPSK	1	271	27.54	27.64	27.53			
100	1/2 BPSK	135	0	27.12	27.21	27.10	28.0	0.5	
100	1/2 BPSK	135	69	27.55	27.72	27.65	28.5	0.0	
100	1/2 BPSK	135	138	27.06	27.13	27.02			
100	1/2 BPSK	270	0	27.06	27.10	27.08	28.0	0.5	
100	QPSK	1	1	27.67	27.80	27.74			
100	QPSK	1	137	27.52	27.67	27.48	28.5	0.0	
100	QPSK	1	271	27.65	27.70	27.68			
100	QPSK	135	0	26.45	26.61	26.51	27.5	1.0	
100	QPSK	135	69	27.58	27.61	27.59	28.5	0.0	
100	QPSK	135	138	26.62	26.64	26.51			
100	QPSK	270	0	26.69	26.71	26.67	27.5	1.0	
100	16QAM	1	1	26.65	26.63	26.57	27.5	1.0	
100	64QAM	1	1	25.16	25.33	25.17	26.0	2.5	
100	256QAM	1	1	23.31	23.35	23.25	24.0	4.5	
Channel				648668	650000	652334			
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	27.63	27.72	27.62	28.5	0.0	
Channel				649334	650000	652668			
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	27.57	27.74	27.65	28.5	0.0	
Channel				649200	650000	652000			
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	27.54	27.67	27.59	28.5	0.0	
Channel				648668	650000	653334			
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	27.56	27.75	27.67	28.5	0.0	
Channel				648334	650000	652668			
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	1	27.62	27.74	27.60	28.5	0.0	
Channel				648000	650000	654000			
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	27.54	27.75	27.67	28.5	0.0	
Channel				647668	650000	654334			
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	27.55	27.73	27.69	28.5	0.0	
Channel				647500	650000	654500			
Frequency (MHz)				3712.5	3840	3967.5			
25	QPSK	1	1	27.60	27.68	27.58	28.5	0.0	
Channel				647334	650000	654668			
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	1	27.55	27.73	27.64	28.5	0.0	
Channel				647168	650000	654834			
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	27.60	27.69	27.68	28.5	0.0	
Channel				647000	650000	655000			
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	27.59	27.69	27.66	28.5	0.0	

Part27Q n77 Ant5 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)		
Channel									
Frequency (MHz)				3500.01 3533.34					
100	1/2 BPSK	1	1		25.08				
100	1/2 BPSK	1	137		24.82		26.0	0.0	
100	1/2 BPSK	1	271		24.88				
100	1/2 BPSK	135	0		24.92		26.0	0.0	
100	1/2 BPSK	135	69		24.95		26.0	0.0	
100	1/2 BPSK	135	138		24.81				
100	1/2 BPSK	270	0		24.91		26.0	0.0	
100	QPSK	1	1		25.11				
100	QPSK	1	137		24.92		26.0	0.0	
100	QPSK	1	271		24.85				
100	QPSK	135	0		24.77		26.0	0.0	
100	QPSK	135	69		24.85		26.0	0.0	
100	QPSK	135	138		24.72				
100	QPSK	270	0		24.82		26.0	0.0	
100	16QAM	1	1		24.91		26.0	0.0	
100	64QAM	1	1		24.47		25.5	0.5	
100	256QAM	1	1		22.41		23.5	2.5	
Channel				633000	633334	633668			
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	24.97	25.03	25.05	26.0		
Channel				632668	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	24.98	25.03	25.05	26.0		
Channel				632334	633334	634334			
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	25.00	25.01	24.98	26.0		
Channel				632000	633334	634668			
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	24.98	24.97	25.05	26.0		
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	25.06	25.02	25.02	26.0		
Channel				631334	633334	635334			
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	25.05	24.96	25.05	26.0		
Channel				631000	633334	635668			
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	25.05	24.98	25.03	26.0		
Channel				630834	633334	635834			
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	25.04	25.06	25.06	26.0		
Channel				630668	633334	636000			
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	24.98	25.01	25.00	26.0		
Channel				630500	633334	636168			
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	25.05	24.99	25.01	26.0		
Channel				630334	633334	636334			
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	24.98	24.98	24.97	26.0		

Part27Q n77 PC2 Ant5 Default									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit [dBm]		
Channel									
Frequency [MHz]				3500.01	633334				
100	1/2 BPSK	1	1		26.97				
100	1/2 BPSK	1	137		26.74		28.5	0.0	
100	1/2 BPSK	1	271		26.93				
100	1/2 BPSK	135	0		26.35		28.0	0.5	
100	1/2 BPSK	135	69		26.84		28.5	0.0	
100	1/2 BPSK	135	138		26.28				
100	1/2 BPSK	270	0		26.20		28.0	0.5	
100	QPSK	1	1		27.06				
100	QPSK	1	137		26.79		28.5	0.0	
100	QPSK	1	271		26.82				
100	QPSK	135	0		25.85		27.5	1.0	
100	QPSK	135	69		26.75		28.5	0.0	
100	QPSK	135	138		25.78				
100	QPSK	270	0		25.81				
100	16QAM	1	1		25.89		27.5	1.0	
100	16QAM	1	1		25.42		26.0	2.5	
100	256QAM	1	1		22.48				
Channel				34900	633300	343668			
Frequency [MHz]				34390	3500.01	3505.02			
90	QPSK	1	1	27.01	26.96	27.02	28.5	0.0	
Channel				342668	633334	634000			
Frequency [MHz]				34201	3500.01	3510			
80	QPSK	1	1	27.01	26.94	26.95	28.5	0.0	
Channel				342334	633334	634334			
Frequency [MHz]				3465.01	3500.01	3515.01			
70	QPSK	1	1	26.97	27.00	26.91	28.5	0.0	
Channel				632000	633334	634668			
Frequency [MHz]				3480	3500.01	3520.02			
60	QPSK	1	1	26.92	26.96	26.91	28.5	0.0	
Channel				631668	633334	635000			
Frequency [MHz]				3475.02	3500.01	3525			
50	QPSK	1	1	26.99	26.96	26.96	28.5	0.0	
Channel				631334	633334	635334			
Frequency [MHz]				3470.01	3500.01	3530.01			
40	QPSK	1	1	26.98	26.98	26.98	28.5	0.0	
Channel				631000	633334	635668			
Frequency [MHz]				3465	3500.01	3535.02			
30	QPSK	1	1	26.90	26.96	27.00	28.5	0.0	
Channel				630834	633334	635834			
Frequency [MHz]				3462.31	3500.01	3537.31			
25	QPSK	1	1	26.97	26.94	26.90	28.5	0.0	
Channel				630668	633334	636000			
Frequency [MHz]				3460.02	3500.01	3540			
20	QPSK	1	1	27.00	26.96	26.97	28.5	0.0	
Channel				630500	633334	636168			
Frequency [MHz]				3457.3	3500.01	3542.32			
15	QPSK	1	1	26.99	26.94	26.95	28.5	0.0	
Channel				630334	633334	636334			
Frequency [MHz]				3455.01	3500.01	3545.01			
10	QPSK	1	1	26.97	26.96	26.95	28.5	0.0	

Part270 n78 PC2 Ant5 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				680000					
Frequency (MHz)				3750					
100	1/2 BPS	1	1		27.59				
100	1/2 BPS	1	137		27.57		28.5	0.0	
100	1/2 BPS	1	271		27.62				
100	1/2 BPS	135	0		27.19		28.0	0.5	
100	1/2 BPS	135	69		27.63		28.5	0.0	
100	1/2 BPS	135	138		27.15				
100	1/2 BPS	270	0		27.17		28.0	0.5	
100	QPSK	1	1		27.68				
100	QPSK	1	137		27.57		28.5	0.0	
100	QPSK	1	271		27.61				
100	QPSK	135	0		26.52		27.5	1.0	
100	QPSK	135	69		27.54		28.5	0.0	
100	QPSK	135	138		26.65		27.5	1.0	
100	QPSK	270	0		26.67				
100	16QAM	1	1		26.63		27.5	1.0	
100	64QAM	1	1		25.06		26.0	2.5	
100	256QAM	1	1		23.12		24.0	4.5	
Channel				649668	650000	650334			
Frequency (MHz)				3745.02	3750	3755.01			
90	QPSK	1	1		27.52	27.59	27.56	28.5	0.0
Channel				649334	650000	650668			
Frequency (MHz)				3740.01	3750	3760.02			
80	QPSK	1	1		27.46	27.54	27.59	28.5	0.0
Channel				649000	650000	651000			
Frequency (MHz)				3735	3750	3765			
70	QPSK	1	1		27.53	27.62	27.52	28.5	0.0
Channel				648668	650000	651334			
Frequency (MHz)				3730.02	3750	3770.01			
60	QPSK	1	1		27.45	27.56	27.59	28.5	0.0
Channel				648334	650000	651668			
Frequency (MHz)				3725.01	3750	3775.02			
50	QPSK	1	1		27.46	27.55	27.53	28.5	0.0
Channel				648000	650000	652000			
Frequency (MHz)				3720	3750	3780			
40	QPSK	1	1		27.53	27.61	27.54	28.5	0.0
Channel				647668	650000	652334			
Frequency (MHz)				3715.02	3750	3785.01			
30	QPSK	1	1		27.51	27.55	27.57	28.5	0.0
Channel				647500	650000	652500			
Frequency (MHz)				3712.5	3750	3787.5			
25	QPSK	1	1		27.54	27.59	27.56	28.5	0.0
Channel				647334	650000	652668			
Frequency (MHz)				3710.01	3750	3790.02			
20	QPSK	1	1		27.48	27.63	27.49	28.5	0.0
Channel				647168	650000	652834			
Frequency (MHz)				3707.52	3750	3792.51			
15	QPSK	1	1		27.52	27.60	27.53	28.5	0.0
Channel				647000	650000	653000			
Frequency (MHz)				3705	3750	3795			
10	QPSK	1	1		27.54	27.60	27.50	28.5	0.0

Part27Q n78 Ant5 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		25.46				
100	1/2 BPS	1	137		25.28		26.0	0.0	
100	1/2 BPS	1	271		25.31				
100	1/2 BPS	135	0		25.37		26.0	0.0	
100	1/2 BPS	135	69		25.25		26.0	0.0	
100	1/2 BPS	135	138		25.17				
100	1/2 BPS	270	0		25.27		26.0	0.0	
100	QPSK	1	1		25.55				
100	QPSK	1	137		25.23		26.0	0.0	
100	QPSK	1	271		25.37				
100	QPSK	135	0		25.21		26.0	0.0	
100	QPSK	135	69		25.24		26.0	0.0	
100	QPSK	135	138		25.23				
100	QPSK	270	0		25.43		26.0	0.0	
100	16QAM	1	1		25.45		26.0	0.0	
100	64QAM	1	1		24.92		25.5	0.5	
100	256QAM	1	1		22.90		23.5	2.5	
Channel				633000	633334	633668			
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1		25.41	25.46	25.44	26.0	0.0
Channel				632668	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1		25.44	25.45	25.43	26.0	0.0
Channel				632334	633334	634334			
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1		25.45	25.51	25.51	26.0	0.0
Channel				632000	633334	634668			
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1		25.42	25.40	25.50	26.0	0.0
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1		25.51	25.39	25.42	26.0	0.0
Channel				631334	633334	635334			
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1		25.42	25.47	25.43	26.0	0.0
Channel				631000	633334	635668			
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1		25.41	25.41	25.40	26.0	0.0
Channel				630834	633334	635834			
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1		25.45	25.49	25.42	26.0	0.0
Channel				630568	633334	636000			
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1		25.49	25.43	25.39	26.0	0.0
Channel				630500	633334	636168			
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1		25.43	25.40	25.45	26.0	0.0
Channel				630384	633334	636334			
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1		25.47	25.42	25.41	26.0	0.0

Part27Q n78 PC2 Ant5 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				3500.01					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		27.36				
100	1/2 BPS	1	137		27.10		28.5	0.0	
100	1/2 BPS	1	271		27.21				
100	1/2 BPS	135	0		26.65		28.0	0.5	
100	1/2 BPS	135	69		27.12		28.5	0.0	
100	1/2 BPS	135	138		26.64				
100	1/2 BPS	270	0		26.59		28.0	0.5	
100	QPSK	1	1		27.52				
100	QPSK	1	137		27.01		28.5	0.0	
100	QPSK	1	271		27.14				
100	QPSK	135	0		26.12		27.5	1.0	
100	QPSK	135	69		27.36		28.5	0.0	
100	QPSK	135	138		26.16		27.5	1.0	
100	QPSK	270	0		26.20				
100	16QAM	1	1		26.22		27.5	1.0	
100	64QAM	1	1		24.99		26.0	2.5	
100	256QAM	1	1		22.94		24.0	4.5	
Channel				633000	633334	633668			
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1		27.37	27.42	27.45	28.5	0.0
Channel				632668	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1		27.42	27.41	27.37	28.5	0.0
Channel				632334	633334	634334			
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1		27.40	27.42	27.45	28.5	0.0
Channel				632000	633334	634668			
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1		27.46	27.38	27.45	28.5	0.0
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1		27.46	27.42	27.46	28.5	0.0
Channel				631334	633334	635334			
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1		27.45	27.40	27.39	28.5	0.0
Channel				631000	633334	635668			
Frequency (MHz)				3465	3500.01	3536.02			
30	QPSK	1	1		27.43	27.44	27.47	28.5	0.0
Channel				630834	633334	635834			
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1		27.44	27.44	27.37	28.5	0.0
Channel				630668	633334	636000			
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1		27.37	27.38	27.39	28.5	0.0
Channel				630500	633334	636168			
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1		27.37	27.39	27.47	28.5	0.0
Channel				630334	633334	636334			
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1		27.42	27.42	27.46	28.5	0.0

Part27Q n78 Ant4 Default								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				633334		3500.01		
Frequency (MHz)						3500.01		
100	1/2 BPSK	1	1		24.49			
100	1/2 BPSK	1	137		24.32		25.1	0.0
100	1/2 BPSK	1	271		24.26			
100	1/2 BPSK	135	0		24.41		25.1	0.0
100	1/2 BPSK	135	69		24.32		25.1	0.0
100	1/2 BPSK	135	138		24.16			
100	1/2 BPSK	270	0		24.31		25.1	0.0
100	QPSK	1	1		24.55			
100	QPSK	1	137		24.19		25.1	0.0
100	QPSK	1	271		24.21			
100	QPSK	135	0		24.34		25.1	0.0
100	QPSK	135	69		24.47		25.1	0.0
100	QPSK	135	138		24.16			
100	QPSK	270	0		24.36		25.1	0.0
100	16QAM	1	1		24.41		25.1	0.0
100	64QAM	1	1		23.71		24.6	0.5
100	256QAM	1	1		21.67		22.6	2.5
Channel				633000	633334	633668	up	MPR
Frequency (MHz)				3496	3500.01	3505.02		
90	QPSK	1	1	24.45	24.48	24.43	25.1	0.0
Channel				632668	633334	634000	up	MPR
Frequency (MHz)				3490.02	3500.01	3510		
80	QPSK	1	1	24.36	24.40	24.43	25.1	0.0
Channel				632334	633334	634334	up	MPR
Frequency (MHz)				3485.01	3500.01	3515.01		
70	QPSK	1	1	24.45	24.45	24.39	25.1	0.0
Channel				632000	633334	634668	up	MPR
Frequency (MHz)				3480	3500.01	3520.02		
60	QPSK	1	1	24.35	24.44	24.43	25.1	0.0
Channel				631668	633334	635000	up	MPR
Frequency (MHz)				3475.02	3500.01	3525		
50	QPSK	1	1	24.42	24.49	24.37	25.1	0.0
Channel				631334	633334	635334	up	MPR
Frequency (MHz)				3470.01	3500.01	3530.01		
40	QPSK	1	1	24.36	24.44	24.35	25.1	0.0
Channel				631000	633334	635668	up	MPR
Frequency (MHz)				3465	3500.01	3535.02		
30	QPSK	1	1	24.35	24.49	24.39	25.1	0.0
Channel				630834	633334	635834	up	MPR
Frequency (MHz)				3462.51	3500.01	3537.51		
25	QPSK	1	1	24.42	24.41	24.37	25.1	0.0
Channel				630668	633334	636000	up	MPR
Frequency (MHz)				3460.02	3500.01	3540		
20	QPSK	1	1	24.44	24.49	24.42	25.1	0.0
Channel				630500	633334	636168	up	MPR
Frequency (MHz)				3457.5	3500.01	3542.52		
15	QPSK	1	1	24.41	24.45	24.36	25.1	0.0
Channel				630334	633334	636334	up	MPR
Frequency (MHz)				3455.01	3500.01	3545.01		
10	QPSK	1	1	24.38	24.47	24.39	25.1	0.0

Part27Q n78 PC2 Ant4 Default								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				633334		3500.01		
Frequency (MHz)						3500.01		
100	1/2 BPSK	1	1		25.88			
100	1/2 BPSK	1	137		25.89		27.2	0.0
100	1/2 BPSK	1	271		25.89			
100	1/2 BPSK	135	0		25.30		26.7	0.5
100	1/2 BPSK	135	69		25.72		27.2	0.0
100	1/2 BPSK	135	138		25.17		26.7	0.5
100	1/2 BPSK	270	0		25.37			
100	QPSK	1	1		25.95			
100	QPSK	1	137		25.93		27.2	0.0
100	QPSK	1	271		25.92			
100	QPSK	135	0		24.87		26.2	1.0
100	QPSK	135	69		25.86		27.2	0.0
100	QPSK	135	138		24.82		26.2	1.0
100	QPSK	270	0		24.89		26.2	1.0
100	16QAM	1	1		24.72		26.2	1.0
100	64QAM	1	1		23.36		24.7	2.5
100	256QAM	1	1		21.37		22.7	4.5
Channel				633000	633334	633668	up	MPR
Frequency (MHz)				3495	3500.01	3505.02		
90	QPSK	1	1	25.80	25.91	25.83	27.2	0.0
Channel				632668	633334	634000	up	MPR
Frequency (MHz)				3490.02	3500.01	3510		
80	QPSK	1	1	25.90	25.89	25.90	27.2	0.0
Channel				632334	633334	634334	up	MPR
Frequency (MHz)				3485.01	3500.01	3515.01		
70	QPSK	1	1	25.86	25.82	25.85	27.2	0.0
Channel				632000	633334	634668	up	MPR
Frequency (MHz)				3480	3500.01	3520.02		
60	QPSK	1	1	25.86	25.80	25.81	27.2	0.0
Channel				631668	633334	635000	up	MPR
Frequency (MHz)				3475.02	3500.01	3525		
50	QPSK	1	1	25.80	25.82	25.83	27.2	0.0
Channel				631334	633334	635334	up	MPR
Frequency (MHz)				3470.01	3500.01	3530.01		
40	QPSK	1	1	25.82	25.85	25.90	27.2	0.0
Channel				631000	633334	635668	up	MPR
Frequency (MHz)				3465	3500.01	3535.02		
30	QPSK	1	1	25.87	25.89	25.89	27.2	0.0
Channel				630834	633334	635834	up	MPR
Frequency (MHz)				3462.51	3500.01	3537.51		
25	QPSK	1	1	25.81	25.88	25.82	27.2	0.0
Channel				630668	633334	636000	up	MPR
Frequency (MHz)				3460.02	3500.01	3540		
20	QPSK	1	1	25.84	25.81	25.80	27.2	0.0
Channel				630500	633334	636168	up	MPR
Frequency (MHz)				3457.5	3500.01	3542.52		
15	QPSK	1	1	25.85	25.91	25.81	27.2	0.0
Channel				630334	633334	636334	up	MPR
Frequency (MHz)				3455.01	3500.01	3545.01		
10	QPSK	1	1	25.86	25.82	25.81	27.2	0.0

n2 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376000	378000			
Frequency (MHz)				1870	1890	1890			
40	1/2 BPSK	1	1	21.80	21.77	21.68			
40	1/2 BPSK	1	108	21.72	21.79	21.73	23.3	0.0	
40	1/2 BPSK	1	214	21.78	21.77	21.71			
40	1/2 BPSK	108	0	21.26	21.29	21.28	22.8	0.5	
40	1/2 BPSK	108	54	21.75	21.74	21.68	23.3	0.0	
40	1/2 BPSK	108	108	21.25	21.29	21.22			
40	1/2 BPSK	216	0	21.25	21.30	21.29			
40	QPSK	1	1	21.79	21.83	21.78			
40	QPSK	1	108	21.74	21.82	21.76	23.3	0.0	
40	QPSK	1	214	21.70	21.81	21.76			
40	QPSK	108	0	20.80	20.83	20.83	22.3	1.0	
40	QPSK	108	54	21.73	21.80	21.69	23.3	0.0	
40	QPSK	108	108	20.81	20.79	20.83			
40	QPSK	216	0	20.77	20.85	20.79			
40	16QAM	1	1	20.84	20.81	20.82	22.3	1.0	
40	64QAM	1	1	19.32	19.35	19.29	20.8	2.5	
40	256QAM	1	1	17.28	17.35	17.25	18.8	4.5	
Channel				373500	376000	376500			
Frequency (MHz)				1887.5	1880	1892.5			
35	QPSK	1	1	21.87	21.71	21.66	23.3	0.0	
Channel				373000	376000	378000			
Frequency (MHz)				1895	1880	1895			
30	QPSK	1	1	21.76	21.75	21.69	23.3	0.0	
Channel				372500	376000	376500			
Frequency (MHz)				1892.5	1880	1897.5			
25	QPSK	1	1	21.69	21.80	21.74	23.3	0.0	
Channel				372000	376000	380000			
Frequency (MHz)				1920	1920	1920			
20	QPSK	1	1	21.68	21.73	21.73	23.3	0.0	
Channel				371500	376000	380500			
Frequency (MHz)				1887.5	1880	1902.5			
15	QPSK	1	1	21.74	21.72	21.68	23.3	0.0	
Channel				371000	376000	381000			
Frequency (MHz)				1885	1850	1905			
10	QPSK	1	1	21.71	21.75	21.69	23.3	0.0	
Channel				370500	376000	381500			
Frequency (MHz)				1882.5	1880	1907.5			
5	QPSK	1	1	21.69	21.79	21.73	23.3	0.0	

n7 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	24.01	24.18	24.08			
50	1/2 BPSK	1	135	24.13	24.09	24.01	25.1	0.0	
50	1/2 BPSK	1	268	24.03	24.15	23.95			
50	1/2 BPSK	135	0	23.59	23.67	23.64	24.6	0.5	
50	1/2 BPSK	135	68	24.02	24.15	24.02	25.1	0.0	
50	1/2 BPSK	135	135	23.72	23.64	23.56			
50	1/2 BPSK	270	0	23.59	23.64	23.63			
50	QPSK	1	1	24.16	24.19	24.04			
50	QPSK	1	135	24.03	24.13	24.02	25.1	0.0	
50	QPSK	1	268	24.07	24.11	24.13			
50	QPSK	135	0	23.14	23.14	23.08	24.1	1.0	
50	QPSK	135	68	24.05	24.15	24.10	25.1	0.0	
50	QPSK	135	135	23.10	23.09	23.07			
50	QPSK	270	0	23.17	23.25	23.13	24.1	1.0	
50	16QAM	1	1	23.12	23.20	23.10	24.1	1.0	
50	64QAM	1	1	21.64	21.67	21.60	22.6	2.5	
50	256QAM	1	1	19.70	19.81	19.64	20.6	4.5	
Channel				504500	507000	510500			
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	24.08	24.14	23.90	25.1	0.0	
Channel				503500	507000	510500			
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	24.04	24.05	23.95	25.1	0.0	
Channel				503000	507000	511000			
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	24.00	24.05	23.96	25.1	0.0	
Channel				502500	507000	511500			
Frequency (MHz)				2412.5	2535	2557.5			
25	QPSK	1	1	24.03	24.10	23.90	25.1	0.0	
Channel				502000	507000	512000			
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	24.09	24.14	23.90	25.1	0.0	
Channel				501500	507000	512500			
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	24.03	24.07	23.90	25.1	0.0	
Channel				501000	507000	513000			
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	24.04	24.04	23.96	25.1	0.0	
Channel				500500	507000	513500			
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	24.10	24.14	23.89	25.1	0.0	

n25 Ant6 Default									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376500	379000			
Frequency (MHz)				1870	1892.5	1895			
40	1/2 BPSK	1	1	21.62	21.70	21.70			
40	1/2 BPSK	1	108	21.63	21.78	21.69	23.3	0.0	
40	1/2 BPSK	1	214	21.64	21.68	21.70			
40	1/2 BPSK	108	0	21.20	21.30	21.26	22.8	0.5	
40	1/2 BPSK	108	54	21.65	21.75	21.71	23.3	0.0	
40	1/2 BPSK	108	108	21.28	21.27	21.28			
40	1/2 BPSK	216	0	21.27	21.28	21.31	22.8	0.5	
40	QPSK	1	1	21.75	21.82	21.76			
40	QPSK	1	108	21.69	21.73	21.71	23.3	0.0	
40	QPSK	1	214	21.70	21.71	21.68			
40	QPSK	108	0	20.78	20.78	20.79	22.3	1.0	
40	QPSK	108	54	21.67	21.80	21.71	23.3	0.0	
40	QPSK	108	108	20.72	20.80	20.77			
40	QPSK	216	0	20.76	20.83	20.81	22.3	1.0	
40	16QAM	1	1	20.70	20.79	20.72	22.3	1.0	
40	64QAM	1	1	19.23	19.30	19.25	20.8	2.5	
40	256QAM	1	1	17.26	17.26	17.26	18.8	4.5	
Channel				373500	376500	379500			
Frequency (MHz)				1887.5	1892.5	1897.5			
35	QPSK	1	1	21.80	21.87	21.71	23.3	0.0	
Channel				373000	376500	380000			
Frequency (MHz)				1895	1882.5	1900			
30	QPSK	1	1	21.72	21.72	21.67	23.3	0.0	
Channel				372500	376500	380500			
Frequency (MHz)				1892.5	1892.5	1902.5			
25	QPSK	1	1	21.62	21.80	21.72	23.3	0.0	
Channel				372000	376500	381000			
Frequency (MHz)				1890	1892.5	1905			
20	QPSK	1	1	21.61	21.75	21.72	23.3	0.0	
Channel				371500	376500	381500			
Frequency (MHz)				1887.5	1882.5	1907.5			
15	QPSK	1	1	21.61	21.76	21.67	23.3	0.0	
Channel				371000	376500	382000			
Frequency (MHz)				1895	1892.5	1905			
10	QPSK	1	1	21.64	21.69	21.66	23.3	0.0	
Channel				370500	376500	382500			
Frequency (MHz)				1892.5	1892.5	1912.5			
5	QPSK	1	1	21.71	21.73	21.71	23.3	0.0	

Part27Q n77 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		22.27				
100	1/2 BPSK	1	137		22.17		23.7	0.0	
100	1/2 BPSK	1	271		22.19				
100	1/2 BPSK	135	0		22.20		23.7	0.0	
100	1/2 BPSK	135	69		22.20		23.7	0.0	
100	1/2 BPSK	135	138		22.23		23.7	0.0	
100	1/2 BPSK	270	0		22.22		23.7	0.0	
100	QPSK	1	1		22.36				
100	QPSK	1	137		22.16		23.7	0.0	
100	QPSK	1	271		22.35				
100	QPSK	135	0		22.22		23.7	0.0	
100	QPSK	135	69		22.25		23.7	0.0	
100	QPSK	135	138		22.23		23.7	0.0	
100	QPSK	270	0		22.12		23.7	0.0	
100	16QAM	1	1		21.78		23.7	0.0	
100	64QAM	1	1		21.78		23.2	0.5	
100	256QAM	1	1		19.34		21.2	2.5	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	22.25	22.29	22.31	23.7	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	22.30	22.20	22.21	23.7	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	22.22	22.26	22.22	23.7	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	22.32	22.29	22.29	23.7	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	22.20	22.26	22.25	23.7	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	22.26	22.30	22.29	23.7	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	22.28	22.26	22.22	23.7	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	22.27	22.29	22.27	23.7	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	22.26	22.27	22.29	23.7	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	22.21	22.32	22.31	23.7	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	22.26	22.21	22.26	23.7	0.0	

Part27Q n77 PC2 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		23.96				
100	1/2 BPSK	1	137		24.00		25.7	0.0	
100	1/2 BPSK	1	271		23.99				
100	1/2 BPSK	135	0		23.55		25.2	0.5	
100	1/2 BPSK	135	69		23.93		25.7	0.0	
100	1/2 BPSK	135	138		23.43		25.2	0.5	
100	1/2 BPSK	270	0		23.50		25.7	0.0	
100	QPSK	1	1		24.01				
100	QPSK	1	137		23.88		25.7	0.0	
100	QPSK	1	271		23.96				
100	QPSK	135	0		22.75		24.7	1.0	
100	QPSK	135	69		23.95		25.7	0.0	
100	QPSK	135	138		22.93		24.7	1.0	
100	QPSK	270	0		23.13		24.7	1.0	
100	16QAM	1	1		22.79		24.7	1.0	
100	64QAM	1	1		21.26		23.2	2.5	
100	256QAM	1	1		19.21		21.2	4.5	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	23.95	23.95	23.87	25.7	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	23.89	23.87	23.91	25.7	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	23.86	23.89	23.87	25.7	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	23.88	23.94	23.90	25.7	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	23.93	23.88	23.95	25.7	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	23.89	23.85	23.90	25.7	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	23.91	23.91	23.88	25.7	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	23.92	23.92	23.85	25.7	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	23.89	23.89	23.93	25.7	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	23.93	23.88	23.86	25.7	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	23.85	23.95	23.93	25.7	0.0	

Part270 n78 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				3750					
100	1/2 BPSK	1	1		22.41				
100	1/2 BPSK	1	137		22.47		23.7	0.0	
100	1/2 BPSK	1	271		22.40				
100	1/2 BPSK	135	0		22.35		23.7	0.0	
100	1/2 BPSK	135	69		22.33		23.7	0.0	
100	1/2 BPSK	135	138		22.39		23.7	0.0	
100	1/2 BPSK	270	0		22.41		23.7	0.0	
100	QPSK	1	1		22.48				
100	QPSK	1	137		22.36		23.7	0.0	
100	QPSK	1	271		22.46				
100	QPSK	135	0		22.39		23.7	0.0	
100	QPSK	135	69		22.42		23.7	0.0	
100	QPSK	135	138		22.36		23.7	0.0	
100	QPSK	270	0		22.32		23.7	0.0	
100	16QAM	1	1		22.37		23.7	0.0	
100	64QAM	1	1		21.86		23.2	0.5	
100	256QAM	1	1		19.92		21.2	2.5	
Channel				648668	650000	650334	MPR		
Frequency (MHz)				3745.02	3750	3755.01	up		
90	QPSK	1	1	22.30	22.38	22.32	23.7	0.0	
Channel				649334	650000	650668	MPR		
Frequency (MHz)				3740.01	3750	3760.02	up		
80	QPSK	1	1	22.22	22.32	22.18	23.7	0.0	
Channel				649000	650000	651000	MPR		
Frequency (MHz)				3735	3750	3765	up		
70	QPSK	1	1	22.23	22.36	22.26	23.7	0.0	
Channel				648668	650000	651334	MPR		
Frequency (MHz)				3730.02	3750	3770.01	up		
60	QPSK	1	1	22.28	22.26	22.30	23.7	0.0	
Channel				648334	650000	651668	MPR		
Frequency (MHz)				3725.01	3750	3775.02	up		
50	QPSK	1	1	22.19	22.35	22.22	23.7	0.0	
Channel				648000	650000	652000	MPR		
Frequency (MHz)				3720	3750	3780	up		
40	QPSK	1	1	22.25	22.31	22.26	23.7	0.0	
Channel				647668	650000	652334	MPR		
Frequency (MHz)				3715.02	3750	3785.01	up		
30	QPSK	1	1	22.19	22.31	22.25	23.7	0.0	
Channel				647500	650000	652500	MPR		
Frequency (MHz)				3712.5	3750	3787.5	up		
25	QPSK	1	1	22.27	22.36	22.20	23.7	0.0	
Channel				647334	650000	652668	MPR		
Frequency (MHz)				3710.01	3750	3790.02	up		
20	QPSK	1	1	22.23	22.27	22.28	23.7	0.0	
Channel				647168	650000	652834	MPR		
Frequency (MHz)				3707.5	3750	3792.5	up		
15	QPSK	1	1	22.27	22.39	22.28	23.7	0.0	
Channel				647000	650000	653000	MPR		
Frequency (MHz)				3705	3750	3795	up		
10	QPSK	1	1	22.28	22.26	22.26	23.7	0.0	

Part27Q n78 Ant6 Default									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334		3500.01			
Frequency (MHz)						22.17			
100	1/2 BPSK	1	1			22.17			
100	1/2 BPSK	1	137			22.10		23.7	0.0
100	1/2 BPSK	1	271			22.15			
100	1/2 BPSK	135	0			22.12		23.7	0.0
100	1/2 BPSK	135	69			22.02		23.7	0.0
100	1/2 BPSK	135	138			22.08			
100	1/2 BPSK	270	0			22.14		23.7	0.0
100	QPSK	1	1			22.23			
100	QPSK	1	137			21.98		23.7	0.0
100	QPSK	1	271			22.10			
100	QPSK	135	0			22.10		23.7	0.0
100	QPSK	135	69			22.20		23.7	0.0
100	QPSK	135	138			22.10			
100	QPSK	270	0			22.10		23.7	0.0
100	16QAM	1	1			21.77		23.7	0.0
100	64QAM	1	1			21.27		23.2	0.5
100	256QAM	1	1			21.32		21.2	2.5
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	22.19	22.09	22.18	23.7	0.0	
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	22.11	22.07	22.15	23.7	0.0	
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	22.11	22.10	22.08	23.7	0.0	
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	22.16	22.14	22.15	23.7	0.0	
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	22.18	22.13	22.09	23.7	0.0	
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	22.10	22.18	22.18	23.7	0.0	
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	22.11	22.12	22.13	23.7	0.0	
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	22.10	22.15	22.12	23.7	0.0	
Channel				630668	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	22.12	22.13	22.12	23.7	0.0	
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	22.13	22.09	22.15	23.7	0.0	
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	22.18	22.14	22.09	23.7	0.0	

Part27Q n78 PC2 Ant6 Default									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334		3500.01			
Frequency (MHz)						23.87			
100	1/2 BPSK	1	1			23.87			
100	1/2 BPSK	1	137			23.88		25.5	0.0
100	1/2 BPSK	1	271			23.98			
100	1/2 BPSK	135	0			23.06		25.0	0.5
100	1/2 BPSK	135	69			23.54		25.5	0.0
100	1/2 BPSK	135	138			23.36			
100	1/2 BPSK	270	0			23.46		25.0	0.5
100	QPSK	1	1			24.20			
100	QPSK	1	137			23.76		25.5	0.0
100	QPSK	1	271			24.05			
100	QPSK	135	0			22.71		24.5	1.0
100	QPSK	135	69			24.09		25.5	0.0
100	QPSK	135	138			22.89			
100	QPSK	270	0			23.17		24.5	1.0
100	16QAM	1	1			22.71		24.5	1.0
100	64QAM	1	1			21.44		23.0	2.5
100	256QAM	1	1			19.49		21.0	4.5
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	24.12	24.14	24.05	25.5	0.0	
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	24.04	24.14	24.05	25.5	0.0	
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	24.07	24.11	24.06	25.5	0.0	
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	24.10	24.06	24.08	25.5	0.0	
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	24.09	24.12	24.04	25.5	0.0	
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	24.07	24.11	24.04	25.5	0.0	
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	24.09	24.16	24.12	25.5	0.0	
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	24.11	24.05	24.06	25.5	0.0	
Channel				630668	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	24.15	24.16	24.11	25.5	0.0	
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	24.12	24.08	24.11	25.5	0.0	
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	24.10	24.15	24.10	25.5	0.0	

n38 Ant7 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	21.91	21.96	21.87	23.2	0.0	
40	1/2 BPSK	1	53	21.62	21.72	21.58			
40	1/2 BPSK	1	104	21.77	21.76	21.69			
40	1/2 BPSK	50	0	21.29	21.33	21.25	22.7	0.5	
40	1/2 BPSK	50	28	21.82	21.94	21.93	23.2	0.0	
40	1/2 BPSK	50	56	21.21	21.27	21.24			
40	1/2 BPSK	100	0	21.37	21.45	21.39	22.7	0.5	
40	QPSK	1	1	21.88	22.01	21.96			
40	QPSK	1	53	21.71	21.66	21.68	23.2	0.0	
40	QPSK	1	104	21.72	21.72	21.70			
40	QPSK	50	0	20.75	20.84	20.78	22.2	1.0	
40	QPSK	50	28	21.86	21.89	21.80	23.2	0.0	
40	QPSK	50	56	20.72	20.75	20.74			
40	QPSK	100	0	20.87	20.97	20.90	22.2	1.0	
40	16QAM	1	1	20.93	20.87	20.86	22.2	1.0	
40	64QAM	1	1	19.47	19.55	19.46	20.7	2.5	
40	256QAM	1	1	17.43	17.57	17.50	18.7	4.5	
Channel				517002	519000	520998	tune-up limit	MPR (dB)	
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	21.72	21.81	21.71	23.2	0.0	
Channel				516504	519000	521496	tune-up limit	MPR (dB)	
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	21.74	21.76	21.73	23.2	0.0	
Channel				516000	519000	522000	tune-up limit	MPR (dB)	
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	21.75	21.82	21.72	23.2	0.0	
Channel				515502	519000	522498	tune-up limit	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	21.68	21.75	21.69	23.2	0.0	
Channel				515004	519000	522996	tune-up limit	MPR (dB)	
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	21.66	21.72	21.73	23.2	0.0	

n41 Ant7 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	22.07	22.09	21.99			
100	1/2 BPSK	1	137	22.07	22.11	22.12	23.5	0.0	
100	1/2 BPSK	1	271	22.11	22.09	22.03			
100	1/2 BPSK	135	0	21.61	21.65	21.58	23.0	0.5	
100	1/2 BPSK	135	69	22.16	22.10	22.10	23.5	0.0	
100	1/2 BPSK	135	138	21.73	21.66	21.52			
100	1/2 BPSK	270	0	21.62	21.59	21.63	23.0	0.5	
100	QPSK	1	1	22.17	22.25	22.11			
100	QPSK	1	137	22.02	22.21	22.02	23.5	0.0	
100	QPSK	1	271	22.09	22.20	22.09			
100	QPSK	135	0	21.11	21.15	21.14	22.5	1.0	
100	QPSK	135	69	22.12	22.15	21.98	23.5	0.0	
100	QPSK	135	138	21.13	21.17	21.11			
100	QPSK	270	0	21.14	21.25	21.02	22.5	1.0	
100	16QAM	1	1	21.05	21.18	21.13	22.5	1.0	
100	64QAM	1	1	19.61	19.71	19.52	21.0	2.5	
100	256QAM	1	1	17.65	17.69	17.65	19.0	4.5	
Channel				508200	518598	528996	tune-up limit	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	21.93	22.00	21.85	23.5	0.0	
Channel				507204	518598	529998	tune-up limit	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	21.88	21.96	21.93	23.5	0.0	
Channel				506202	518598	531000	tune-up limit	MPR (dB)	
Frequency (MHz)				2531.01	2592.99	2635			
70	QPSK	1	1	21.85	21.99	21.91	23.5	0.0	
Channel				505200	518598	531996	tune-up limit	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	21.88	22.02	21.87	23.5	0.0	
Channel				504204	518598	532998	tune-up limit	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	21.88	21.93	21.94	23.5	0.0	
Channel				503700	518598	533496	tune-up limit	MPR (dB)	
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	21.88	21.91	21.90	23.5	0.0	
Channel				503202	518598	534000	tune-up limit	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	21.91	21.92	21.84	23.5	0.0	
Channel				502704	518598	534498	tune-up limit	MPR (dB)	
Frequency (MHz)				2513.52	2592.99	2672.40			
35	QPSK	1	1	21.86	21.91	21.85	23.5	0.0	
Channel				502200	518598	534996	tune-up limit	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.88			
30	QPSK	1	1	21.89	21.98	21.90	23.5	0.0	
Channel				501702	518598	535500	tune-up limit	MPR (dB)	
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	21.94	21.88	21.81	23.5	0.0	
Channel				501204	518598	535998	tune-up limit	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	21.95	21.99	21.93	23.5	0.0	
Channel				500700	518598	536496	tune-up limit	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	21.93	22.03	21.89	23.5	0.0	
Channel				500202	518598	537000	tune-up limit	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	21.87	22.00	21.88	23.5	0.0	

Part27Q n78 PC2 Ant10 Default									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune up limit (dBm)	MPR (dB)	
			Channel		633334				
			Frequency (MHz)		3500.01				
100	1/2 BPSK	1	1	27.29					
100	1/2 BPSK	1	137	27.38			29.0	0.0	
100	1/2 BPSK	1	271	27.33					
100	1/2 BPSK	135	0	27.01			28.5	0.5	
100	1/2 BPSK	135	69	27.38			29.0	0.0	
100	1/2 BPSK	135	138	27.04					
100	1/2 BPSK	270	0	26.94			28.5	0.5	
100	QPSK	1	1	27.47					
100	QPSK	1	137	27.45			29.0	0.0	
100	QPSK	1	271	27.30					
100	QPSK	135	0	26.37			28.0	1.0	
100	QPSK	135	69	27.31			29.0	0.0	
100	QPSK	135	138	26.43					
100	QPSK	270	0	26.51			28.0	1.0	
100	16QAM	1	1	26.34			28.0	1.0	
100	64QAM	1	1	24.96			26.5	2.5	
100	256QAM	1	1	24.53			24.5	4.5	
			Channel	633000	633334	633668	up	MPR	
			Frequency (MHz)	3495	3500.01	3505.02	up		
90	QPSK	1	1	27.40	27.34	27.37	29.0	0.0	
			Channel	632668	633334	634000	up	MPR	
			Frequency (MHz)	3490.02	3500.01	3510	up		
80	QPSK	1	1	27.32	27.40	27.36	29.0	0.0	
			Channel	632314	633334	634334	up	MPR	
			Frequency (MHz)	3485.01	3500.01	3515.01	up		
70	QPSK	1	1	27.32	27.43	27.36	29.0	0.0	
			Channel	632000	633334	634668	up	MPR	
			Frequency (MHz)	3480	3500.01	3520.02	up		
60	QPSK	1	1	27.33	27.42	27.33	29.0	0.0	
			Channel	631668	633334	635000	up	MPR	
			Frequency (MHz)	3475.02	3500.01	3525	up		
50	QPSK	1	1	27.40	27.36	27.41	29.0	0.0	
			Channel	631334	633334	635334	up	MPR	
			Frequency (MHz)	3470.01	3500.01	3530.01	up		
40	QPSK	1	1	27.42	27.37	27.42	29.0	0.0	
			Channel	631000	633334	635668	up	MPR	
			Frequency (MHz)	3465	3500.01	3535.02	up		
30	QPSK	1	1	27.37	27.41	27.40	29.0	0.0	
			Channel	630834	633334	635834	up	MPR	
			Frequency (MHz)	3462.51	3500.01	3537.51	up		
25	QPSK	1	1	27.38	27.37	27.37	29.0	0.0	
			Channel	630568	633334	636000	up	MPR	
			Frequency (MHz)	3460.02	3500.01	3540	up		
20	QPSK	1	1	27.32	27.40	27.35	29.0	0.0	
			Channel	630500	633334	636168	up	MPR	
			Frequency (MHz)	3457.5	3500.01	3542.52	up		
15	QPSK	1	1	27.37	27.43	27.32	29.0	0.0	
			Channel	630384	633334	636334	up	MPR	
			Frequency (MHz)	3455.01	3500.01	3545.01	up		
10	QPSK	1	1	27.37	27.38	27.43	29.0	0.0	

Reduced Power Mode for DS11_Main PA

n5 Ant0 DS11									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				166800	167300	167800			
Frequency (MHz)				834	836.5	839			
20	1/2 BPSK	1	1	25.29	25.29	25.29			
20	1/2 BPSK	1	53	25.31	25.28	25.24	25.7	0.0	
20	1/2 BPSK	1	104	25.11	25.13	25.14			
20	1/2 BPSK	50	0	24.69	24.70	24.63	25.2	0.5	
20	1/2 BPSK	50	28	25.28	25.32	25.26	25.7	0.0	
20	1/2 BPSK	50	56	24.62	24.72	24.63			
20	1/2 BPSK	100	0	24.82	24.77	24.82	25.2	0.5	
20	QPSK	1	1	25.29	25.33	25.27			
20	QPSK	1	53	25.32	25.32	25.24	25.7	0.0	
20	QPSK	1	104	25.13	25.09	25.09			
20	QPSK	50	0	24.23	24.27	24.26	24.7	1.0	
20	QPSK	50	28	25.20	25.23	25.21	25.7	0.0	
20	QPSK	50	56	24.15	24.08	24.08			
20	QPSK	100	0	24.26	24.29	24.28	24.7	1.0	
20	16QAM	1	1	24.16	24.15	24.20	24.7	1.0	
20	64QAM	1	1	22.63	22.62	22.60	23.2	2.5	
20	256QAM	1	1	20.49	20.51	20.56	21.2	4.5	
Channel				166300	167300	168300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				831.5	836.5	841.5			
15	QPSK	1	1	25.24	25.19	25.17	25.7	0.0	
Channel				165800	167300	168800	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				829	836.5	844			
10	QPSK	1	1	25.22	25.22	25.13	25.7	0.0	
Channel				165300	167300	169300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				826.5	836.5	846.5			
5	QPSK	1	1	25.14	25.26	25.21	25.7	0.0	

n12 Ant0 DS11									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				141300	141500	141700			
Frequency (MHz)				706.5	707.5	708.5			
15	1/2 BPSK	1	1	25.39	25.39	25.48			
15	1/2 BPSK	1	40	25.41	25.43	25.38	25.7	0.0	
15	1/2 BPSK	1	77	25.32	25.35	25.29			
15	1/2 BPSK	36	0	24.88	24.83	24.89	25.2	0.5	
15	1/2 BPSK	36	22	25.43	25.39	25.45	25.7	0.0	
15	1/2 BPSK	36	43	24.84	24.80	24.79			
15	1/2 BPSK	75	0	24.93	24.99	24.90	25.2	0.5	
15	QPSK	1	1	25.47	25.52	25.48			
15	QPSK	1	40	25.48	25.43	25.38	25.7	0.0	
15	QPSK	1	77	25.33	25.24	25.26			
15	QPSK	36	0	24.37	24.46	24.43	24.7	1.0	
15	QPSK	36	22	25.44	25.47	25.43	25.7	0.0	
15	QPSK	36	43	24.33	24.27	24.23			
15	QPSK	75	0	24.48	24.52	24.45	24.7	1.0	
15	16QAM	1	1	24.26	24.37	24.32	24.7	1.0	
15	64QAM	1	1	22.84	22.73	22.82	23.2	2.5	
15	256QAM	1	1	20.71	20.73	20.66	21.2	4.5	
Channel				140800	141500	142200	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				704	707.5	711			
10	QPSK	1	1	25.41	25.46	25.43	25.7	0.0	
Channel				140300	141500	142700	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				701.5	707.5	713.5			
5	QPSK	1	1	25.32	25.43	25.40	25.7	0.0	

n26 Ant0 DS11									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				164800	166300	167800			
Frequency (MHz)				824	831.5	839			
20	1/2 BPSK	1	1	25.34	25.35	25.33			
20	1/2 BPSK	1	53	25.25	25.30	25.28	25.7	0.0	
20	1/2 BPSK	1	104	25.19	25.11	25.09			
20	1/2 BPSK	50	0	24.74	24.66	24.76	25.2	0.5	
20	1/2 BPSK	50	28	25.29	25.27	25.36	25.7	0.0	
20	1/2 BPSK	50	56	24.68	24.74	24.73			
20	1/2 BPSK	100	0	24.78	24.79	24.79	25.2	0.5	
20	QPSK	1	1	25.35	25.39	25.37			
20	QPSK	1	53	25.36	25.33	25.27	25.7	0.0	
20	QPSK	1	104	25.14	25.14	25.09			
20	QPSK	50	0	24.32	24.28	24.22	24.7	1.0	
20	QPSK	50	28	25.29	25.34	25.31	25.7	0.0	
20	QPSK	50	56	24.05	24.09	24.09			
20	QPSK	100	0	24.35	24.36	24.29	24.7	1.0	
20	16QAM	1	1	24.15	24.19	24.11	24.7	1.0	
20	64QAM	1	1	22.59	22.59	22.58	23.2	2.5	
20	256QAM	1	1	20.48	20.46	20.53	21.2	4.5	
Channel				164300	166300	168300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				821.5	831.5	841.5			
15	QPSK	1	1	25.22	25.24	25.23	25.7	0.0	
Channel				163800	166300	168800	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				819	831.5	844			
10	QPSK	1	1	25.30	25.32	25.27	25.7	0.0	
Channel				163300	166300	169300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				816.5	831.5	846.5			
5	QPSK	1	1	25.24	25.33	25.33	25.7	0.0	

n71 Ant0 DSI1								
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)
Channel				136100				
Frequency (MHz)				680.5				
35	1/2 BPSK	1	1	25.24			25.7	0.0
35	1/2 BPSK	1	90	25.14				
35	1/2 BPSK	1	186	25.10				
35	1/2 BPSK	90	0	24.60			25.2	0.5
35	1/2 BPSK	90	45	25.20			25.7	0.0
35	1/2 BPSK	90	90	24.58			25.2	0.5
35	1/2 BPSK	180	0	24.70				
35	QPSK	1	1	25.25			25.7	0.0
35	QPSK	1	90	25.16				
35	QPSK	1	186	25.00				
35	QPSK	90	0	24.16			24.7	1.0
35	QPSK	90	45	25.21			25.7	0.0
35	QPSK	90	90	24.06			24.7	1.0
35	QPSK	180	0	24.23				
35	16QAM	1	1	24.04			24.7	1.0
35	64QAM	1	1	22.54			23.2	2.5
35	256QAM	1	1	20.48			21.2	4.5
Channel				135600	136100	136600	tune- up limit	MPR (dB)
Frequency (MHz)				678	680.5	683		
30	QPSK	1	1	25.14	25.19	25.10	25.7	0.0
Channel				135100	136100	137100	tune- up limit	MPR (dB)
Frequency (MHz)				675.5	680.5	685.5		
25	QPSK	1	1	25.12	25.10	25.18	25.7	0.0
Channel				134600	136100	137600	tune- up limit	MPR (dB)
Frequency (MHz)				673	680.5	688		
20	QPSK	1	1	25.18	25.13	25.15	25.7	0.0
Channel				134100	136100	138100	tune- up limit	MPR (dB)
Frequency (MHz)				670.5	680.5	690.5		
15	QPSK	1	1	25.10	25.14	25.17	25.7	0.0
Channel				133600	136100	138600	tune- up limit	MPR (dB)
Frequency (MHz)				668	680.5	693		
10	QPSK	1	1	25.14	25.15	25.14	25.7	0.0
Channel				133100	136100	139100	tune- up limit	MPR (dB)
Frequency (MHz)				665.5	680.5	695.5		
5	QPSK	1	1	25.15	25.15	25.08	25.7	0.0

n5 Ant1 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				166800	167300	167800			
Frequency (MHz)				834	836.5	839			
20	1/2 BPSK	1	1	20.91	20.93	20.94			
20	1/2 BPSK	1	53	20.91	20.91	20.86	21.2	0.0	
20	1/2 BPSK	1	104	20.97	21.02	20.93			
20	1/2 BPSK	50	0	20.93	21.03	20.93	21.2	0.0	
20	1/2 BPSK	50	28	20.89	20.98	20.87	21.2	0.0	
20	1/2 BPSK	50	56	20.92	20.94	20.87			
20	1/2 BPSK	100	0	20.97	21.02	20.87	21.2	0.0	
20	QPSK	1	1	21.00	21.05	20.98			
20	QPSK	1	53	20.94	20.98	20.86	21.2	0.0	
20	QPSK	1	104	20.93	20.91	20.94			
20	QPSK	50	0	20.88	20.95	20.85	21.2	0.0	
20	QPSK	50	28	20.87	21.01	20.93	21.2	0.0	
20	QPSK	50	56	20.96	20.96	20.85			
20	QPSK	100	0	20.88	20.98	20.85	21.2	0.0	
20	16QAM	1	1	20.91	20.93	20.87	21.2	0.0	
20	64QAM	1	1	20.90	20.94	20.95	21.2	0.0	
20	256QAM	1	1	20.89	20.95	20.90	21.2	0.0	
Channel				166300	167300	168300	↑ tune-up limit (dB)	MPR (dB)	
Frequency (MHz)				831.5	836.5	841.5			
15	QPSK	1	1	20.98	21.01	20.94	21.2	0.0	
Channel				165800	167300	168800	↑ tune-up limit (dB)	MPR (dB)	
Frequency (MHz)				829	836.5	844			
10	QPSK	1	1	20.91	20.93	20.90	21.2	0.0	
Channel				165300	167300	169300	↑ tune-up limit (dB)	MPR (dB)	
Frequency (MHz)				826.5	836.5	846.5			
5	QPSK	1	1	20.89	21.01	20.93	21.2	0.0	

n12 Ant1 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				141300	141500	141700			
Frequency (MHz)				706.5	707.5	708.5			
15	1/2 BPSK	1	1	24.54	24.60	24.52			
15	1/2 BPSK	1	40	24.48	24.55	24.55	24.7	0.0	
15	1/2 BPSK	1	77	24.58	24.59	24.56			
15	1/2 BPSK	36	0	24.52	24.65	24.57	24.7	0.0	
15	1/2 BPSK	36	22	24.54	24.64	24.47	24.7	0.0	
15	1/2 BPSK	36	43	24.51	24.59	24.55			
15	1/2 BPSK	75	0	24.56	24.57	24.51	24.7	0.0	
15	QPSK	1	1	24.62	24.68	24.60			
15	QPSK	1	40	24.50	24.57	24.55	24.7	0.0	
15	QPSK	1	77	24.56	24.61	24.56			
15	QPSK	36	0	24.58	24.64	24.52	24.7	0.0	
15	QPSK	36	22	24.50	24.65	24.57	24.7	0.0	
15	QPSK	36	43	24.52	24.58	24.49			
15	QPSK	75	0	24.54	24.63	24.54	24.7	0.0	
15	16QAM	1	1	24.54	24.60	24.47	24.7	0.0	
15	64QAM	1	1	23.10	23.15	23.16	23.2	1.5	
15	256QAM	1	1	21.16	21.12	21.05	21.2	3.5	
Channel				140800	141500	142200	↑ tune-up limit (dB)	MPR (dB)	
Frequency (MHz)				704	707.5	711			
10	QPSK	1	1	24.52	24.62	24.57	24.7	0.0	
Channel				140300	141500	142700	↑ tune-up limit (dB)	MPR (dB)	
Frequency (MHz)				701.5	707.5	713.5			
5	QPSK	1	1	24.60	24.57	24.52	24.7	0.0	

n26 Ant1 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				164800	166300	167800			
Frequency (MHz)				824	831.5	839			
20	1/2 BPSK	1	1	20.41	20.48	20.37			
20	1/2 BPSK	1	53	20.45	20.42	20.39	20.7	0.0	
20	1/2 BPSK	1	104	20.41	20.53	20.45			
20	1/2 BPSK	50	0	20.37	20.44	20.35	20.7	0.0	
20	1/2 BPSK	50	28	20.39	20.45	20.43	20.7	0.0	
20	1/2 BPSK	50	56	20.43	20.45	20.37			
20	1/2 BPSK	100	0	20.42	20.42	20.38	20.7	0.0	
20	QPSK	1	1	20.50	20.55	20.48			
20	QPSK	1	53	20.37	20.52	20.37	20.7	0.0	
20	QPSK	1	104	20.41	20.46	20.40			
20	QPSK	50	0	20.43	20.51	20.45	20.7	0.0	
20	QPSK	50	28	20.40	20.53	20.42	20.7	0.0	
20	QPSK	50	56	20.42	20.46	20.41			
20	QPSK	100	0	20.44	20.52	20.41	20.7	0.0	
20	16QAM	1	1	20.38	20.46	20.44	20.7	0.0	
20	64QAM	1	1	20.38	20.44	20.37	20.7	0.0	
20	256QAM	1	1	20.37	20.42	20.40	20.7	0.0	
Channel				164300	166300	168300	↑ tune-up limit (dB)	MPR (dB)	
Frequency (MHz)				821.5	831.5	841.5			
15	QPSK	1	1	20.45	20.44	20.44	20.7	0.0	
Channel				163800	166300	168800	↑ tune-up limit (dB)	MPR (dB)	
Frequency (MHz)				819	831.5	844			
10	QPSK	1	1	20.42	20.52	20.39	20.7	0.0	
Channel				163300	166300	169300	↑ tune-up limit (dB)	MPR (dB)	
Frequency (MHz)				816.5	831.5	846.5			
5	QPSK	1	1	20.42	20.50	20.36	20.7	0.0	

n71 Ant1 DS11								
BW [MHz]	Modulation on	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)
Channel				136100			24.2	0.0
Frequency (MHz)				680.5				
35	1/2 BPSK	1	1		23.72			
35	1/2 BPSK	1	90		23.76			
35	1/2 BPSK	1	186		23.70			
35	1/2 BPSK	90	0		23.68			24.2 0.0
35	1/2 BPSK	90	45		23.79			24.2 0.0
35	1/2 BPSK	90	90		23.76		24.2	0.0
35	1/2 BPSK	180	0		23.74			
35	QPSK	1	1		23.83			
35	QPSK	1	90		23.78		24.2	0.0
35	QPSK	1	186		23.71			
35	QPSK	90	0		23.74		24.2	0.0
35	QPSK	90	45		23.80		24.2	0.0
35	QPSK	90	90		23.79			
35	QPSK	180	0		23.77		24.2	0.0
35	16QAM	1	1		23.73		24.2	0.0
35	64QAM	1	1		22.85		23.2	1.0
35	256QAM	1	1		20.80		21.2	3.0
Channel				135600	136100	136600	24.2	0.0
Frequency (MHz)				678	680.5	683		
30	QPSK	1	1	23.72	23.78	23.76	24.2	0.0
Channel				135100	136100	137100	24.2	0.0
Frequency (MHz)				675.5	680.5	685.5		
25	QPSK	1	1	23.59	23.73	23.72	24.2	0.0
Channel				134600	136100	137600	24.2	0.0
Frequency (MHz)				673	680.5	688		
20	QPSK	1	1	23.67	23.64	23.65	24.2	0.0
Channel				134100	136100	138100	24.2	0.0
Frequency (MHz)				670.5	680.5	690.5		
15	QPSK	1	1	23.62	23.76	23.65	24.2	0.0
Channel				133600	136100	138600	24.2	0.0
Frequency (MHz)				668	680.5	693		
10	QPSK	1	1	23.70	23.72	23.63	24.2	0.0
Channel				133100	136100	139100	24.2	0.0
Frequency (MHz)				665.5	680.5	695.5		
5	QPSK	1	1	23.67	23.69	23.72	24.2	0.0

n66 Ant5 DS11									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	18.16	18.27	18.30			
45	1/2 BPSK	1	120	18.25	18.24	18.22	18.7	0.0	
45	1/2 BPSK	1	240	18.20	18.27	18.28			
45	1/2 BPSK	120	0	18.27	18.31	18.19	18.7	0.0	
45	1/2 BPSK	120	60	18.20	18.26	18.22	18.7	0.0	
45	1/2 BPSK	120	120	18.23	18.21	18.19	18.7	0.0	
45	1/2 BPSK	240	0	18.21	18.33	18.23			
45	QPSK	1	1	18.29	18.35	18.32			
45	QPSK	1	120	18.18	18.22	18.26	18.7	0.0	
45	QPSK	1	240	18.22	18.23	18.21			
45	QPSK	120	0	18.24	18.30	18.21	18.7	0.0	
45	QPSK	120	60	18.15	18.33	18.20	18.7	0.0	
45	QPSK	120	120	18.17	18.28	18.19	18.7	0.0	
45	QPSK	240	0	18.21	18.30	18.22			
45	16QAM	1	1	18.25	18.28	18.28	18.7	0.0	
45	64QAM	1	1	18.15	18.22	18.25	18.7	0.0	
45	256QAM	1	1	18.17	18.27	18.20	18.7	0.0	
Channel				346000	349000	352000	18.7	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	18.22	18.30	18.28	18.7	0.0	
Channel				345500	349000	352500	18.7	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	18.21	18.22	18.26	18.7	0.0	
Channel				345000	349000	353000	18.7	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	18.17	18.27	18.25	18.7	0.0	
Channel				344500	349000	353500	18.7	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	18.25	18.30	18.18	18.7	0.0	
Channel				344000	349000	354000	18.7	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	18.21	18.23	18.21	18.7	0.0	
Channel				343500	349000	354500	18.7	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	18.24	18.22	18.24	18.7	0.0	
Channel				343000	349000	355000	18.7	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	18.27	18.23	18.20	18.7	0.0	
Channel				342500	349000	355500	18.7	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	18.23	18.27	18.29	18.7	0.0	

Part270 n77 Ant5 DSI1										
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				650000	656000	662000				
Frequency (MHz)				3750	3840	3930				
100	1/2 BPSK	1	1	16.10	16.20	16.16				
100	1/2 BPSK	1	137	16.13	16.23	16.10	16.5	0.0		
100	1/2 BPSK	1	271	16.16	16.19	16.14				
100	1/2 BPSK	135	0	16.09	16.16	16.12	16.5	0.0		
100	1/2 BPSK	135	69	16.09	16.21		16.5	0.0		
100	1/2 BPSK	135	138	16.09	16.18	16.15	16.5	0.0		
100	1/2 BPSK	270	0	16.06	16.21	16.12				
100	QPSK	1	1	16.19	16.25	16.21				
100	QPSK	1	137	16.10	16.13	16.18	16.5	0.0		
100	QPSK	1	271	16.06	16.13	16.10				
100	QPSK	135	0	16.16	16.19	16.19	16.5	0.0		
100	QPSK	135	69	16.09	16.22	16.10	16.5	0.0		
100	QPSK	135	138	16.14	16.12	16.13	16.5	0.0		
100	QPSK	270	0	16.14	16.20	16.13				
100	16QAM	1	1	16.06	16.14	16.08	16.5	0.0		
100	64QAM	1	1	16.10	16.15	16.11	16.5	0.0		
100	256QAM	1	1	16.08	16.13	16.08	16.5	0.0		
Channel				649668	656000	662334	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3745.02	3840	3935.01				
90	QPSK	1	1	16.11	16.19	16.09	16.5	0.0		
Channel				649334	656000	662668	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3740.01	3840	3940.02				
80	QPSK	1	1	16.16	16.14	16.13	16.5	0.0		
Channel				649000	656000	663000	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3735	3840	3945				
70	QPSK	1	1	16.10	16.16	16.09	16.5	0.0		
Channel				648668	656000	663334	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3730.02	3840	3950.01				
60	QPSK	1	1	16.11	16.22	16.13	16.5	0.0		
Channel				648334	656000	663668	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3725.01	3840	3955.02				
50	QPSK	1	1	16.09	16.17	16.14	16.5	0.0		
Channel				648000	656000	664000	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3720	3840	3960				
40	QPSK	1	1	16.11	16.11	16.16	16.5	0.0		
Channel				647668	656000	664334	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3715.02	3840	3965.01				
30	QPSK	1	1	16.12	16.16	16.14	16.5	0.0		
Channel				647500	656000	664500	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3712.5	3840	3967.5				
25	QPSK	1	1	16.07	16.16	16.12	16.5	0.0		
Channel				647334	656000	664668	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3710.01	3840	3970.02				
20	QPSK	1	1	16.06	16.21	16.16	16.5	0.0		
Channel				647168	656000	664834	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3707.52	3840	3972.51				
15	QPSK	1	1	16.05	16.14	16.12	16.5	0.0		
Channel				647000	656000	665000	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3705	3840	3975				
10	QPSK	1	1	16.07	16.13	16.12	16.5	0.0		

Part270 n77 PC2 Ant5 DSI1										
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				650000	656000	662000				
Frequency (MHz)				3750	3840	3930				
100	1/2 BPSK	1	1	19.65	19.72	19.61				
100	1/2 BPSK	1	137	19.62	19.71	19.61	20.0	0.0		
100	1/2 BPSK	1	271	19.62	19.71	19.64				
100	1/2 BPSK	135	0	19.56	19.61	19.65	20.0	0.0		
100	1/2 BPSK	135	69	19.57	19.66	19.65	20.0	0.0		
100	1/2 BPSK	135	138	19.61	19.62	19.63	20.0	0.0		
100	1/2 BPSK	270	0	19.53	19.69	19.57				
100	QPSK	1	1	19.70	19.78	19.73				
100	QPSK	1	137	19.64	19.59	19.72	20.0	0.0		
100	QPSK	1	271	19.61	19.57	19.59				
100	QPSK	135	0	19.65	19.72	19.72	20.0	0.0		
100	QPSK	135	69	19.63	19.76	19.61	20.0	0.0		
100	QPSK	135	138	19.69	19.67	19.67	20.0	0.0		
100	QPSK	270	0	19.58	19.70	19.65				
100	16QAM	1	1	19.51	19.65	19.60	20.0	0.0		
100	64QAM	1	1	19.61	19.61	19.65	20.0	0.0		
100	256QAM	1	1	19.59	19.61	19.64	20.0	0.0		
Channel				649668	656000	662334	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3745.02	3840	3935.01				
90	QPSK	1	1	19.54	19.70	19.66	20.0	0.0		
Channel				649334	656000	662668	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3740.01	3840	3940.02				
80	QPSK	1	1	19.61	19.73	19.69	20.0	0.0		
Channel				649000	656000	663000	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3735	3840	3945				
70	QPSK	1	1	19.65	19.62	19.59	20.0	0.0		
Channel				648668	656000	663334	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3730.02	3840	3950.01				
60	QPSK	1	1	19.55	19.67	19.60	20.0	0.0		
Channel				648334	656000	663668	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3725.01	3840	3955.02				
50	QPSK	1	1	19.59	19.69	19.59	20.0	0.0		
Channel				648000	656000	664000	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3720	3840	3960				
40	QPSK	1	1	19.65	19.64	19.63	20.0	0.0		
Channel				647668	656000	664334	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3715.02	3840	3965.01				
30	QPSK	1	1	19.67	19.74	19.63	20.0	0.0		
Channel				647500	656000	664500	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3712.5	3840	3967.5				
25	QPSK	1	1	19.54	19.64	19.68	20.0	0.0		
Channel				647334	656000	664668	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3710.01	3840	3970.02				
20	QPSK	1	1	19.57	19.69	19.64	20.0	0.0		
Channel				647168	656000	664834	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3707.52	3840	3972.51				
15	QPSK	1	1	19.59	19.67	19.67	20.0	0.0		
Channel				647000	656000	665000	Tune-up limit (dB)	MPR (dB)		
Frequency (MHz)				3705	3840	3975				
10	QPSK	1	1	19.65	19.67	19.65	20.0	0.0		

Part27Q n77 Ant5 DSI1										
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				633334	633334					
Frequency (MHz)				3500.01						
100	1/2 BPSK	1	1	15.54	15.54		16.5	0.0		
100	1/2 BPSK	1	137	15.63						
100	1/2 BPSK	1	271	15.64						
100	1/2 BPSK	135	0	15.56	15.56		16.5	0.0		
100	1/2 BPSK	135	69	15.62	15.62		16.5	0.0		
100	1/2 BPSK	135	138	15.55	15.55		16.5	0.0		
100	1/2 BPSK	270	0	15.58						
100	QPSK	1	1	15.66	15.66					
100	QPSK	1	137	15.55	15.55		16.5	0.0		
100	QPSK	1	271	15.55	15.55					
100	QPSK	135	0	15.63	15.63		16.5	0.0		
100	QPSK	135	69	15.64	15.64		16.5	0.0		
100	QPSK	135	138	15.59	15.59		16.5	0.0		
100	QPSK	270	0	15.61	15.61					
100	16QAM	1	1	15.58	15.58		16.5	0.0		
100	64QAM	1	1	15.55	15.55		16.5	0.0		
100	256QAM	1	1	15.56	15.56		16.5	0.0		
Channel				633000	633334	633668				
Frequency (MHz)				3495	3500.01	3505.02				
90	QPSK	1	1	15.54	15.60	15.58	16.5	0.0		
Channel				632668	633334	634000				
Frequency (MHz)				3490.02	3500.01	3510				
80	QPSK	1	1	15.43	15.53	15.54	16.5	0.0		
Channel				632334	633334	634334				
Frequency (MHz)				3485.01	3500.01	3515.01				
70	QPSK	1	1	15.52	15.58	15.52	16.5	0.0		
Channel				632000	633334	634668				
Frequency (MHz)				3480	3500.01	3520.02				
60	QPSK	1	1	15.51	15.59	15.48	16.5	0.0		
Channel				631668	633334	635000				
Frequency (MHz)				3475.02	3500.01	3525				
50	QPSK	1	1	15.52	15.58	15.47	16.5	0.0		
Channel				631334	633334	635334				
Frequency (MHz)				3470.01	3500.01	3530.01				
40	QPSK	1	1	15.52	15.51	15.47	16.5	0.0		
Channel				631000	633334	635668				
Frequency (MHz)				3465	3500.01	3535.02				
30	QPSK	1	1	15.45	15.56	15.57	16.5	0.0		
Channel				630834	633334	635834				
Frequency (MHz)				3462.51	3500.01	3537.51				
25	QPSK	1	1	15.53	15.55	15.51	16.5	0.0		
Channel				630668	633334	636000				
Frequency (MHz)				3460.02	3500.01	3540				
20	QPSK	1	1	15.46	15.58	15.51	16.5	0.0		
Channel				635000	633334	636168				
Frequency (MHz)				3457.5	3500.01	3542.62				
15	QPSK	1	1	15.44	15.52	15.51	16.5	0.0		
Channel				630334	633334	636334				
Frequency (MHz)				3455.01	3500.01	3545.01				
10	QPSK	1	1	15.44	15.50	15.51	16.5	0.0		

Part27Q n78 Ant5 DSI1									
BW [MHz]	Modulat- ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334			3500.01		
Frequency (MHz)									
100	1/2 BPSK	1	1	16.10			16.5	0.0	
100	1/2 BPSK	1	137	16.09					
100	1/2 BPSK	1	271	16.06			16.5	0.0	
100	1/2 BPSK	135	0	15.94					
100	1/2 BPSK	135	69	16.07			16.5	0.0	
100	1/2 BPSK	135	138	16.04					
100	1/2 BPSK	270	0	16.06			16.5	0.0	
100	QPSK	1	1	16.16					
100	QPSK	1	137	15.86			16.5	0.0	
100	QPSK	1	271	16.04					
100	QPSK	135	0	16.04			16.5	0.0	
100	QPSK	135	69	16.11					
100	QPSK	135	138	15.93			16.5	0.0	
100	QPSK	270	0	16.00					
100	16QAM	1	1	16.04			16.5	0.0	
100	64QAM	1	1	15.94					
100	256QAM	1	1	15.99			16.5	0.0	
Channel				633000	633334	633668		MPR (dB)	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	15.95	16.06	16.00	16.5	0.0	
Channel				632668	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510	16.5	0.0	
80	QPSK	1	1	15.94	16.08	16.03		0.0	
Channel				632334	633334	634334	16.5	MPR (dB)	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	15.99	16.06	16.06	16.5	0.0	
Channel				632000	633334	634668			
Frequency (MHz)				3480	3500.01	3520.02	16.5	0.0	
60	QPSK	1	1	15.98	16.02	16.02		0.0	
Channel				631668	633334	635000	16.5	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	16.02	16.05	16.03	16.5	0.0	
Channel				631334	633334	635334			
Frequency (MHz)				3470.01	3500.01	3530.01	16.5	0.0	
40	QPSK	1	1	15.97	16.13	16.06		0.0	
Channel				631000	633334	635668	16.5	MPR (dB)	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	15.91	16.14	16.04	16.5	0.0	
Channel				630834	633334	635834			
Frequency (MHz)				3462.51	3500.01	3537.51	16.5	0.0	
25	QPSK	1	1	15.95	16.03	16.04		0.0	
Channel				630668	633334	636000	16.5	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	15.99	16.11	16.01	16.5	0.0	
Channel				630500	633334	636168			
Frequency (MHz)				3457.5	3500.01	3542.52	16.5	0.0	
15	QPSK	1	1	15.98	16.13	16.00		0.0	
Channel				630334	633334	636334	16.5	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	15.92	16.12	16.10	16.5	0.0	

Part27Q n78 PC2 Ant5 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334			3500.01		
Frequency (MHz)									
100	1/2 BPSK	1	1	19.44			20.0	0.0	
100	1/2 BPSK	1	137	19.39					
100	1/2 BPSK	1	271	19.42			20.0	0.0	
100	1/2 BPSK	135	0	19.44					
100	1/2 BPSK	135	69	19.44			20.0	0.0	
100	1/2 BPSK	135	138	19.50					
100	1/2 BPSK	270	0	19.39			20.0	0.0	
100	QPSK	1	1	19.55					
100	QPSK	1	137	19.28			20.0	0.0	
100	QPSK	1	271	19.42					
100	QPSK	135	0	19.48			20.0	0.0	
100	QPSK	135	69	19.50					
100	QPSK	135	138	19.34			20.0	0.0	
100	QPSK	270	0	19.43					
100	16QAM	1	1	19.45			20.0	0.0	
100	64QAM	1	1	19.35					
100	256QAM	1	1	19.34			20.0	0.0	
Channel				633000	633334	633668		MPR (dB)	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	19.43	19.43	19.45	20.0	0.0	
Channel				632668	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510	20.0	0.0	
80	QPSK	1	1	19.46	19.44	19.48		0.0	
Channel				632334	633334	634334	20.0	MPR (dB)	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	19.42	19.43	19.49	20.0	0.0	
Channel				632000	633334	634668			
Frequency (MHz)				3480	3500.01	3520.02	20.0	0.0	
60	QPSK	1	1	19.49	19.47	19.39		0.0	
Channel				631668	633334	635000	20.0	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	19.46	19.44	19.46	20.0	0.0	
Channel				631334	633334	635334			
Frequency (MHz)				3470.01	3500.01	3530.01	20.0	0.0	
40	QPSK	1	1	19.42	19.43	19.41		0.0	
Channel				631000	633334	635668	20.0	MPR (dB)	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	19.49	19.51	19.41	20.0	0.0	
Channel				630834	633334	635834			
Frequency (MHz)				3462.51	3500.01	3537.51	20.0	0.0	
25	QPSK	1	1	19.41	19.50	19.50		0.0	
Channel				630668	633334	636000	20.0	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	19.42	19.42	19.45	20.0	0.0	
Channel				630500	633334	636168			
Frequency (MHz)				3457.5	3500.01	3542.52	20.0	0.0	
15	QPSK	1	1	19.40	19.51	19.49		0.0	
Channel				630334	633334	636334	20.0	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	19.45	19.40	19.49	20.0	0.0	

n66 Ant4 DS11								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)
Channel				346500	349000	351500		
Frequency (MHz)				1732.5	1745	1757.5		
45	1/2 BPSK	1	1	14.18	14.29	14.13		
45	1/2 BPSK	1	120	14.19	14.20	14.14	14.9	0.0
45	1/2 BPSK	1	240	14.20	14.25	14.20		
45	1/2 BPSK	120	0	14.22	14.29	14.22	14.9	0.0
45	1/2 BPSK	120	60	14.24	14.28	14.16	14.9	0.0
45	1/2 BPSK	120	120	14.24	14.26	14.18	14.9	0.0
45	1/2 BPSK	240	0	14.16	14.30	14.20		
45	QPSK	1	1	14.28	14.34	14.25		
45	QPSK	1	120	14.15	14.20	14.18	14.9	0.0
45	QPSK	1	240	14.20	14.24	14.19		
45	QPSK	120	0	14.15	14.26	14.22	14.9	0.0
45	QPSK	120	60	14.20	14.32	14.16	14.9	0.0
45	QPSK	120	120	14.20	14.31	14.12	14.9	0.0
45	QPSK	240	0	14.25	14.29	14.14		
45	16QAM	1	1	14.24	14.22	14.22	14.9	0.0
45	64QAM	1	1	14.15	14.29	14.14	14.9	0.0
45	256QAM	1	1	14.26	14.28	14.12	14.9	0.0
Channel				346000	349000	352000	un- up limit	MPR (dB)
Frequency (MHz)				1730	1745	1760		
40	QPSK	1	1	14.14	14.26	14.20	14.9	0.0
Channel				345500	349000	352500	un- up limit	MPR (dB)
Frequency (MHz)				1727.5	1745	1762.5		
35	QPSK	1	1	14.22	14.23	14.15	14.9	0.0
Channel				345000	349000	353000	un- up limit	MPR (dB)
Frequency (MHz)				1725	1745	1765		
30	QPSK	1	1	14.19	14.20	14.19	14.9	0.0
Channel				344500	349000	353500	un- up limit	MPR (dB)
Frequency (MHz)				1722.5	1745	1767.5		
25	QPSK	1	1	14.20	14.30	14.15	14.9	0.0
Channel				344000	349000	354000	un- up limit	MPR (dB)
Frequency (MHz)				1720	1745	1770		
20	QPSK	1	1	14.25	14.21	14.16	14.9	0.0
Channel				343500	349000	354500	un- up limit	MPR (dB)
Frequency (MHz)				1717.5	1745	1772.5		
15	QPSK	1	1	14.20	14.28	14.11	14.9	0.0
Channel				343000	349000	355000	un- up limit	MPR (dB)
Frequency (MHz)				1715	1745	1775		
10	QPSK	1	1	14.23	14.27	14.13	14.9	0.0
Channel				342500	349000	355500	un- up limit	MPR (dB)
Frequency (MHz)				1712.5	1745	1777.5		
5	QPSK	1	1	14.23	14.27	14.20	14.9	0.0

n38 Ant4 DSI1										
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				518004	519000	519996				
Frequency (MHz)				2590.02	2595	2599.98				
40	1/2 BPSK	1	1	17.96	17.92	17.88				
40	1/2 BPSK	1	53	17.95	17.97	17.86	19.1	0.0		
40	1/2 BPSK	1	104	17.87	18.00	17.84				
40	1/2 BPSK	50	0	17.87	17.94	17.84	19.1	0.0		
40	1/2 BPSK	50	28	17.97	17.94	17.89	19.1	0.0		
40	1/2 BPSK	50	56	17.93	17.98	17.89				
40	1/2 BPSK	100	0	17.90	17.91	17.90	19.1	0.0		
40	QPSK	1	1	18.00	18.05	17.98				
40	QPSK	1	53	17.96	17.98	17.94	19.1	0.0		
40	QPSK	1	104	17.96	17.93	17.94				
40	QPSK	50	0	17.89	17.85	17.94	19.1	0.0		
40	QPSK	50	28	17.92	18.01	17.90	19.1	0.0		
40	QPSK	50	56	17.86	17.93	17.90				
40	QPSK	100	0	17.98	17.99	17.85	19.1	0.0		
40	16QAM	1	1	17.98	17.95	17.91	19.1	0.0		
40	64QAM	1	1	17.89	17.98	17.85	19.1	0.0		
40	256QAM	1	1	17.96	17.97	17.84	19.1	0.0		
Channel				517002	519000	520998	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2585.01	2595	2604.99				
30	QPSK	1	1	17.89	17.99	17.96	19.1	0.0		
Channel				516504	519000	521496	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2582.52	2595	2607.48				
25	QPSK	1	1	17.91	17.97	17.86	19.1	0.0		
Channel				516000	519000	522000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2580	2595	2610				
20	QPSK	1	1	17.98	18.00	17.91	19.1	0.0		
Channel				515502	519000	522498	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2577.51	2595	2612.49				
15	QPSK	1	1	17.96	17.93	17.92	19.1	0.0		
Channel				515004	519000	522996	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2575.02	2595	2614.98				
10	QPSK	1	1	17.92	17.97	17.85	19.1	0.0		

n41 Ant4 DSI1										
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				509202	518598	528000				
Frequency (MHz)				2546.01	2592.99	2640				
100	1/2 BPSK	1	1	17.05	17.20	17.02				
100	1/2 BPSK	1	137	17.13	17.16	17.06	18.3	0.0		
100	1/2 BPSK	1	271	17.11	17.13	17.03				
100	1/2 BPSK	135	0	17.06	17.17	17.11	18.3	0.0		
100	1/2 BPSK	135	69	17.14	17.16	17.13	18.3	0.0		
100	1/2 BPSK	135	138	17.13	17.12	17.10				
100	1/2 BPSK	270	0	17.07	17.15	17.08				
100	QPSK	1	1	17.19	17.23	17.15				
100	QPSK	1	137	17.12	17.17	17.02	18.3	0.0		
100	QPSK	1	271	17.11	17.15	17.07				
100	QPSK	135	0	17.10	17.15	17.07	18.3	0.0		
100	QPSK	135	69	17.16	17.20	17.09	18.3	0.0		
100	QPSK	135	138	17.06	17.14	17.12				
100	QPSK	270	0	17.15	17.19	17.06	18.3	0.0		
100	16QAM	1	1	17.12	17.15	17.11	18.3	0.0		
100	64QAM	1	1	17.17	17.17	17.05	18.3	0.0		
100	256QAM	1	1	17.11	17.10	17.05	18.3	0.0		
Channel				508200	518598	528996	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2541	2592.99	2644.98				
90	QPSK	1	1	17.12	17.19	17.02	18.3	0.0		
Channel				507204	518598	529998	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2536.02	2592.99	2649.99				
80	QPSK	1	1	17.08	17.09	17.07	18.3	0.0		
Channel				506202	518598	531000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2531.01	2592.99	2655				
70	QPSK	1	1	17.13	17.10	17.12	18.3	0.0		
Channel				505200	518598	531996	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2526	2592.99	2659.98				
60	QPSK	1	1	17.13	17.13	17.10	18.3	0.0		
Channel				504204	518598	532998	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2521.02	2592.99	2664.99				
50	QPSK	1	1	17.07	17.18	17.08	18.3	0.0		
Channel				503700	518598	533496	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2518.5	2592.99	2667.48				
45	QPSK	1	1	17.12	17.11	17.13	18.3	0.0		
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2516.01	2592.99	2670				
40	QPSK	1	1	17.06	17.13	17.02	18.3	0.0		
Channel				502704	518598	534498	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2513.52	2592.99	2672.49				
35	QPSK	1	1	17.16	17.14	17.07	18.3	0.0		
Channel				502200	518598	534996	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2511	2592.99	2674.98				
30	QPSK	1	1	17.08	17.17	17.11	18.3	0.0		
Channel				501702	518598	535500	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2508.51	2592.99	2677.5				
25	QPSK	1	1	17.15	17.10	17.11	18.3	0.0		
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2506.02	2592.99	2679.99				
20	QPSK	1	1	17.09	17.20	17.06	18.3	0.0		
Channel				500700	518598	536496	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2503.5	2592.99	2682.48				
15	QPSK	1	1	17.09	17.12	17.01	18.3	0.0		
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				2501.01	2592.99	2685				
10	QPSK	1	1	17.05	17.18	17.05	18.3	0.0		

Part270 n77 Ant4 DSI1										
BW [MHz]	Modulat on	RB Size	RB Offset	Power Low Ch. / Freq. 650000	Power Middle Ch. / Freq. 656000	Power High Ch. / Freq. 662000	Tune-up limit (dBm)	MPR (dB)		
Channel				650000	656000	662000				
Frequency (MHz)				3750	3840	3930				
100	1/2 BPSK	1	1	18.00	18.11	17.96				
100	1/2 BPSK	1	137	18.01	18.02	18.04	18.7	0.0		
100	1/2 BPSK	1	271	18.07	18.04	17.98				
100	1/2 BPSK	135	0	18.01	18.02	18.05	18.7	0.0		
100	1/2 BPSK	135	69	17.99	18.12	18.06	18.7	0.0		
100	1/2 BPSK	135	138	18.02	18.11	18.00				
100	1/2 BPSK	270	0	17.97	18.05	17.99	18.7	0.0		
100	QPSK	1	1	18.10	18.15	18.08				
100	QPSK	1	137	18.02	18.12	17.97	18.7	0.0		
100	QPSK	1	271	18.04	18.02	18.01				
100	QPSK	135	0	18.06	18.10	17.96	18.7	0.0		
100	QPSK	135	69	18.00	18.12	18.05	18.7	0.0		
100	QPSK	135	138	17.97	18.04	18.04	18.7	0.0		
100	QPSK	270	0	17.98	18.09	18.05	18.7	0.0		
100	16QAM	1	1	18.01	18.06	18.04	18.7	0.0		
100	64QAM	1	1	18.05	18.05	17.96	18.7	0.0		
100	256QAM	1	1	18.05	18.08	18.01	18.7	0.0		
Channel				649668	656000	662334	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3745.02	3840	3935.01				
90	QPSK	1	1	18.05	18.10	18.08	18.7	0.0		
Channel				649334	656000	662668	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3740.01	3840	3940.02				
80	QPSK	1	1	18.00	18.05	17.97	18.7	0.0		
Channel				649000	656000	663000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3735	3840	3945				
70	QPSK	1	1	17.95	18.01	17.97	18.7	0.0		
Channel				648668	656000	663334	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3730.01	3840	3950.01				
60	QPSK	1	1	17.94	17.98	17.97	18.7	0.0		
Channel				648334	656000	663668	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3725.01	3840	3955.02				
50	QPSK	1	1	17.96	18.01	18.05	18.7	0.0		
Channel				648000	656000	664000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3720	3840	3960				
40	QPSK	1	1	18.02	17.96	18.05	18.7	0.0		
Channel				647668	656000	664334	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3715.02	3840	3965.01				
30	QPSK	1	1	17.92	18.03	18.05	18.7	0.0		
Channel				647500	656000	664500	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3712.5	3840	3967.5				
25	QPSK	1	1	17.24	18.07	18.06	18.7	0.0		
Channel				647134	656000	664868	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3710.01	3840	3970.02				
20	QPSK	1	1	18.00	18.00	17.99	18.7	0.0		
Channel				647168	656000	664834	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3707.52	3840	3972.51				
15	QPSK	1	1	18.02	17.99	18.02	18.7	0.0		
Channel				647000	656000	665000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3705	3840	3975				
10	QPSK	1	1	17.96	17.96	17.99	18.7	0.0		

Part270 n77 PC2 Ant4 DSI1										
BW [MHz]	Modulati on	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				650000	656000	662000				
Frequency (MHz)				3750	3840	3930				
100	1/2 BPSK	1	1	20.94	21.08	20.92				
100	1/2 BPSK	1	137	20.97	21.05	21.01	21.7	0.0		
100	1/2 BPSK	1	271	21.10	21.02	21.04				
100	1/2 BPSK	135	0	20.97	21.03	21.03	21.7	0.0		
100	1/2 BPSK	135	69	21.02	21.10	21.04	21.7	0.0		
100	1/2 BPSK	135	138	21.08	21.09	21.00	21.7	0.0		
100	1/2 BPSK	270	0	21.00	21.02	20.97				
100	QPSK	1	1	21.05	21.16	21.09				
100	QPSK	1	137	21.05	21.09	20.92	21.7	0.0		
100	QPSK	1	271	21.07	21.02	21.06				
100	QPSK	135	0	21.03	21.10	20.94	21.7	0.0		
100	QPSK	135	69	20.97	21.15	21.03	21.7	0.0		
100	QPSK	135	138	20.99	21.08	21.02	21.7	0.0		
100	QPSK	270	0	20.98	21.10	21.00	21.7	0.0		
100	16QAM	1	1	21.06	21.04	21.05	21.7	0.0		
100	64QAM	1	1	21.06	21.09	20.96	21.7	0.0		
100	256QAM	1	1	20.99	21.04	21.00	21.7	0.0		
Channel				649668	656000	662334	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3745.02	3840	3935.01				
90	QPSK	1	1	20.98	21.10	20.98	21.7	0.0		
Channel				649334	656000	662668				
Frequency (MHz)				3740.01	3840	3940.02				
80	QPSK	1	1	20.92	21.11	20.96	21.7	0.0		
Channel				649000	656000	663000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3735	3840	3945				
70	QPSK	1	1	20.99	21.06	20.93	21.7	0.0		
Channel				648668	656000	663334	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3730.02	3840	3950.01				
60	QPSK	1	1	21.00	21.07	21.02	21.7	0.0		
Channel				648334	656000	663668	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3725.01	3840	3955.02				
50	QPSK	1	1	21.01	21.03	20.98	21.7	0.0		
Channel				648000	656000	664000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3720	3840	3960				
40	QPSK	1	1	21.00	21.03	20.99	21.7	0.0		
Channel				647668	656000	664334	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3715.02	3840	3965.01				
30	QPSK	1	1	20.90	21.03	21.03	21.7	0.0		
Channel				647500	656000	664500	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3712.5	3840	3967.5				
25	QPSK	1	1	20.99	21.09	21.02	21.7	0.0		
Channel				647334	656000	664668	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3710.01	3840	3970.02				
20	QPSK	1	1	20.98	21.09	21.00	21.7	0.0		
Channel				647168	656000	664834	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3707.52	3840	3972.51				
15	QPSK	1	1	20.98	21.02	20.99	21.7	0.0		
Channel				647000	656000	665000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3705	3840	3975				
10	QPSK	1	1	21.01	21.06	21.00	21.7	0.0		

Part27Q n77 Ant4 DSI1										
BW [MHz]	Modulati on	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel					633334					
Frequency (MHz)					3500.01					
100	1/2 BPSK	1	1		17.99					
100	1/2 BPSK	1	137		17.96		18.7	0.0		
100	1/2 BPSK	1	271		17.99					
100	1/2 BPSK	135	0		17.97		18.7	0.0		
100	1/2 BPSK	135	69		18.09		18.7	0.0		
100	1/2 BPSK	135	138		18.04		18.7	0.0		
100	1/2 BPSK	270	0		17.95					
100	QPSK	1	1		18.10					
100	QPSK	1	137		18.04		18.7	0.0		
100	QPSK	1	271		17.98					
100	QPSK	135	0		17.98		18.7	0.0		
100	QPSK	135	69		18.04		18.7	0.0		
100	QPSK	135	138		17.93		18.7	0.0		
100	QPSK	270	0		18.01		18.7	0.0		
100	16QAM	1	1		18.04		18.7	0.0		
100	64QAM	1	1		18.04		18.7	0.0		
100	256QAM	1	1		18.08		18.7	0.0		
Channel				633000	633334	633668	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3495	3500.01	3505.02				
90	QPSK	1	1	18.05	18.01	17.97	18.7	0.0		
Channel				632668	633334	634000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3490.02	3500.01	3510				
80	QPSK	1	1	17.95	18.01	18.02	18.7	0.0		
Channel				632334	633334	634334	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3485.01	3500.01	3515.01				
70	QPSK	1	1	17.97	18.01	18.01	18.7	0.0		
Channel				632000	633334	634668	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3480	3500.01	3520.02				
60	QPSK	1	1	18.04	18.07	17.96	18.7	0.0		
Channel				631668	633334	635000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3475.02	3500.01	3525				
50	QPSK	1	1	17.97	17.98	18.05	18.7	0.0		
Channel				631334	633334	635334	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3470.01	3500.01	3530.01				
40	QPSK	1	1	18.03	18.04	18.04	18.7	0.0		
Channel				631000	633334	635668	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3465	3500.01	3535.02				
30	QPSK	1	1	17.95	18.07	18.03	18.7	0.0		
Channel				630834	633334	635834	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3462.51	3500.01	3537.51				
25	QPSK	1	1	18.01	18.02	18.06	18.7	0.0		
Channel				630668	633334	636000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3460.02	3500.01	3540				
20	QPSK	1	1	18.00	18.00	18.01	18.7	0.0		
Channel				630500	633334	636168	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3457.5	3500.01	3542.52				
15	QPSK	1	1	18.01	18.03	18.07	18.7	0.0		
Channel				630334	633334	636334	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3455.01	3500.01	3545.01				
10	QPSK	1	1	17.97	18.00	18.02	18.7	0.0		

Part27Q n77 PC2 Ant4 DSI1										
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				633334						
Frequency (MHz)				3500.01						
100	1/2 BPSK	1	1		21.05					
100	1/2 BPSK	1	137		20.97					
100	1/2 BPSK	1	271		21.01					
100	1/2 BPSK	135	0		20.92		21.7	0.0		
100	1/2 BPSK	135	69		21.05		21.7	0.0		
100	1/2 BPSK	135	138		21.09		21.7	0.0		
100	1/2 BPSK	270	0		20.94					
100	QPSK	1	1		21.11					
100	QPSK	1	137		20.99		21.7	0.0		
100	QPSK	1	271		20.96					
100	QPSK	135	0		21.03					
100	QPSK	135	69		21.09		21.7	0.0		
100	QPSK	135	138		20.89		21.7	0.0		
100	QPSK	270	0		21.00					
100	16QAM	1	1		21.02		21.7	0.0		
100	64QAM	1	1		21.08		21.7	0.0		
100	256QAM	1	1		21.00		21.7	0.0		
Channel				633000	633334	633668				
Frequency (MHz)				3495	3500.01	3505.02				
90	QPSK	1	1	20.95	20.96	21.01	21.7	0.0		
Channel				632668	633334	634000				
Frequency (MHz)				3490.02	3500.01	3510				
80	QPSK	1	1	21.00	20.90	20.95	21.7	0.0		
Channel				632334	633334	634334				
Frequency (MHz)				3485.01	3500.01	3515.01				
70	QPSK	1	1	20.97	21.00	20.96	21.7	0.0		
Channel				632000	633334	634668				
Frequency (MHz)				3480	3500.01	3520.02				
60	QPSK	1	1	21.09	20.98	20.89	21.7	0.0		
Channel				631668	633334	635000				
Frequency (MHz)				3475.02	3500.01	3525				
50	QPSK	1	1	20.93	20.94	20.90	21.7	0.0		
Channel				631334	633334	635334				
Frequency (MHz)				3470.01	3500.01	3530.01				
40	QPSK	1	1	20.92	20.99	20.98	21.7	0.0		
Channel				631000	633334	635668				
Frequency (MHz)				3465	3500.01	3535.02				
30	QPSK	1	1	20.95	20.92	20.90	21.7	0.0		
Channel				630834	633334	635834				
Frequency (MHz)				3462.51	3500.01	3537.51				
25	QPSK	1	1	20.96	20.96	20.92	21.7	0.0		
Channel				630668	633334	636000				
Frequency (MHz)				3460.02	3500.01	3540				
20	QPSK	1	1	20.91	20.91	20.94	21.7	0.0		
Channel				630500	633334	636168				
Frequency (MHz)				3457.5	3500.01	3542.52				
15	QPSK	1	1	20.93	20.97	20.94	21.7	0.0		
Channel				630334	633334	636334				
Frequency (MHz)				3455.01	3500.01	3545.01				
10	QPSK	1	1	20.97	20.95	20.95	21.7	0.0		

Part27Q n78 PC2 Ant4 DSI1									
BW [MHz]	Modulati on	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (db)	
Channel				633334			21.6	0.0	
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1	20.90			21.6	0.0	
100	1/2 BPSK	1	137	20.97					
100	1/2 BPSK	1	271	20.96			21.6	0.0	
100	1/2 BPSK	135	0	20.91					
100	1/2 BPSK	135	69	20.98			21.6	0.0	
100	1/2 BPSK	135	138	20.99					
100	1/2 BPSK	270	0	20.96			21.6	0.0	
100	QPSK	1	1	21.11					
100	QPSK	1	137	20.89			21.6	0.0	
100	QPSK	1	271	20.96					
100	QPSK	135	0	20.89			21.6	0.0	
100	QPSK	135	69	20.99					
100	QPSK	135	138	20.93			21.6	0.0	
100	QPSK	270	0	20.98					
100	16QAM	1	1	20.78			21.6	0.0	
100	64QAM	1	1	20.94					
100	256QAM	1	1	20.82			21.6	0.0	
Channel				633000	633334	633668			
Frequency (MHz)				3495	3500.01	3505.02	21.6	0.0	
90	QPSK	1	1	21.06	21.02	21.01			
Channel				632668	633334	634000	21.6	0.0	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	20.95	21.04	20.99	21.6	0.0	
Channel				632334	633334	634334			
Frequency (MHz)				3485.01	3500.01	3515.01	21.6	0.0	
70	QPSK	1	1	20.98	20.97	21.03			
Channel				632000	633334	634668	21.6	0.0	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	21.06	21.03	20.97	21.6	0.0	
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525	21.6	0.0	
50	QPSK	1	1	20.97	21.04	21.05			
Channel				631334	633334	635334	21.6	0.0	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	21.07	20.98	20.98	21.6	0.0	
Channel				631000	633334	635668			
Frequency (MHz)				3465	3500.01	3535.02	21.6	0.0	
30	QPSK	1	1	20.96	21.04	20.95			
Channel				630834	633334	635834	21.6	0.0	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	21.06	20.96	21.00	21.6	0.0	
Channel				630668	633334	636000			
Frequency (MHz)				3460.02	3500.01	3540	21.6	0.0	
20	QPSK	1	1	21.06	21.06	21.06			
Channel				630500	633334	636168	21.6	0.0	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	20.98	21.01	21.01	21.6	0.0	
Channel				630334	633334	636334			
Frequency (MHz)				3455.01	3500.01	3545.01	21.6	0.0	
10	QPSK	1	1	21.07	21.05	20.98			

n66 Ant6 DS11									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500	23.7	0.0	
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	22.48	22.53	22.48	23.7	0.0	
45	1/2 BPSK	1	120	22.41	22.44	22.37			
45	1/2 BPSK	1	240	22.50	22.55	22.47	23.7	0.0	
45	1/2 BPSK	120	0	21.96	22.00	21.86			
45	1/2 BPSK	120	60	22.41	22.54	22.47	23.7	0.0	
45	1/2 BPSK	120	120	21.90	22.02	21.91			
45	1/2 BPSK	240	0	22.01	22.14	22.11	23.7	0.0	
45	QPSK	1	1	22.56	22.60	22.54			
45	QPSK	1	120	22.53	22.57	22.47	23.7	0.0	
45	QPSK	1	240	22.49	22.59	22.47			
45	QPSK	120	0	21.65	21.66	21.59	23.7	0.0	
45	QPSK	120	60	22.49	22.57	22.44			
45	QPSK	120	120	21.45	21.52	21.49	23.7	0.0	
45	QPSK	240	0	21.63	21.72	21.66			
45	16QAM	1	1	21.40	21.53	21.48	23.7	0.0	
45	64QAM	1	1	19.91	19.97	19.88			
45	256QAM	1	1	17.96	17.99	17.96	23.7	0.0	
Channel				346000	349000	352000			
Frequency (MHz)				1730	1745	1760	23.7	0.0	
40	QPSK	1	1	22.43	22.54	22.46			
Channel				345500	349000	352500	23.7	0.0	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	22.48	22.46	22.43	23.7	0.0	
Channel				345000	349000	353000			
Frequency (MHz)				1725	1745	1765	23.7	0.0	
30	QPSK	1	1	22.46	22.52	22.50			
Channel				344500	349000	353500	23.7	0.0	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	22.47	22.53	22.52	23.7	0.0	
Channel				344000	349000	354000			
Frequency (MHz)				1720	1745	1770	23.7	0.0	
20	QPSK	1	1	22.54	22.56	22.42			
Channel				343500	349000	354500	23.7	0.0	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	22.46	22.50	22.41	23.7	0.0	
Channel				343000	349000	355000			
Frequency (MHz)				1715	1745	1775	23.7	0.0	
10	QPSK	1	1	22.45	22.46	22.46			
Channel				342500	349000	355500	23.7	0.0	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	22.43	22.49	22.43	23.7	0.0	
Channel				342000	349000	356000			
Frequency (MHz)				1710	1745	1780			

n38 Ant7 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	17.24	17.36	17.41			
40	1/2 BPSK	1	53	17.27	17.44	17.41	18.7	0.0	
40	1/2 BPSK	1	104	17.24	17.38	17.38			
40	1/2 BPSK	50	0	17.25	17.39	17.32	18.7	0.0	
40	1/2 BPSK	50	28	17.32	17.39	17.31	18.7	0.0	
40	1/2 BPSK	50	56	17.25	17.41	17.31	18.7	0.0	
40	1/2 BPSK	100	0	17.32	17.38	17.34			
40	QPSK	1	1	17.23	17.45	17.31			
40	QPSK	1	53	17.26	17.43	17.31	18.7	0.0	
40	QPSK	1	104	17.25	17.38	17.32			
40	QPSK	50	0	17.33	17.41	17.38	18.7	0.0	
40	QPSK	50	28	17.26	17.42	17.40	18.7	0.0	
40	QPSK	50	56	17.30	17.38	17.37			
40	QPSK	100	0	17.28	17.41	17.39	18.7	0.0	
40	16QAM	1	1	17.34	17.42	17.41	18.7	0.0	
40	64QAM	1	1	17.23	17.41	17.33	18.7	0.0	
40	256QAM	1	1	17.34	17.40	17.37	18.7	0.0	
Channel				517002	519000	520998	tune-up limit	MPR (dB)	
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	17.08	17.22	17.24	18.7	0.0	
Channel				516504	519000	521496	tune-up limit	MPR (dB)	
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	17.13	17.19	17.23	18.7	0.0	
Channel				516000	519000	522000	tune-up limit	MPR (dB)	
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	17.17	17.30	17.25	18.7	0.0	
Channel				516502	519000	522498	tune-up limit	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	17.12	17.21	17.21	18.7	0.0	
Channel				515004	519000	522996	tune-up limit	MPR (dB)	
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	17.14	17.26	17.20	18.7	0.0	

n41 Ant7 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	18.45	18.51	18.43			
100	1/2 BPSK	1	137	18.51	18.59	18.37	20.0	0.0	
100	1/2 BPSK	1	271	18.49	18.60	18.37			
100	1/2 BPSK	135	0	18.49	18.58	18.46	20.0	0.0	
100	1/2 BPSK	135	69	18.50	18.51	18.46	20.0	0.0	
100	1/2 BPSK	135	138	18.47	18.58	18.47	20.0	0.0	
100	1/2 BPSK	270	0	18.52	18.53	18.41			
100	QPSK	1	1	18.53	18.68	18.46			
100	QPSK	1	137	18.50	18.55	18.38	20.0	0.0	
100	QPSK	1	271	18.47	18.58	18.46			
100	QPSK	135	0	18.48	18.53	18.41	20.0	0.0	
100	QPSK	135	69	18.50	18.55	18.37	20.0	0.0	
100	QPSK	135	138	18.50	18.59	18.40			
100	QPSK	270	0	18.52	18.53	18.42	20.0	0.0	
100	16QAM	1	1	18.51	18.55	18.38	20.0	0.0	
100	64QAM	1	1	18.46	18.56	18.39	20.0	0.0	
100	256QAM	1	1	18.51	18.60	18.46	19.0	1.0	
Channel				508200	518598	528996	tune-up limit	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	18.44	18.62	18.41	20.0	0.0	
Channel				507204	518598	529998	tune-up limit	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	18.39	18.53	18.36	20.0	0.0	
Channel				506202	518598	531000	tune-up limit	MPR (dB)	
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	18.42	18.51	18.35	20.0	0.0	
Channel				505200	518598	531996	tune-up limit	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	18.46	18.56	18.38	20.0	0.0	
Channel				504204	518598	532998	tune-up limit	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	18.45	18.60	18.30	20.0	0.0	
Channel				503700	518598	533496	tune-up limit	MPR (dB)	
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	18.43	18.59	18.38	20.0	0.0	
Channel				503202	518598	534000	tune-up limit	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	18.48	18.59	18.32	20.0	0.0	
Channel				502704	518598	534498	tune-up limit	MPR (dB)	
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	18.39	18.64	18.39	20.0	0.0	
Channel				502200	518598	534996	tune-up limit	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	18.47	18.59	18.30	20.0	0.0	
Channel				501702	518598	535500	tune-up limit	MPR (dB)	
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	18.44	18.54	18.33	20.0	0.0	
Channel				501204	518598	535998	tune-up limit	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	18.48	18.55	18.39	20.0	0.0	
Channel				500700	518598	536496	tune-up limit	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	18.45	18.59	18.30	20.0	0.0	
Channel				500202	518598	537000	tune-up limit	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	18.38	18.63	18.40	20.0	0.0	

Part27Q n78 PC2 Ant10 DSI1									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334			29.0	0.0	
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1	27.29			29.0	0.0	
100	1/2 BPSK	1	137	27.38					
100	1/2 BPSK	1	271	27.33			28.5	0.5	
100	1/2 BPSK	135	0	27.01					
100	1/2 BPSK	135	69	27.38			29.0	0.0	
100	1/2 BPSK	135	138	27.04					
100	1/2 BPSK	270	0	26.94			28.5	0.5	
100	QPSK	1	1	27.47					
100	QPSK	1	137	27.45			29.0	0.0	
100	QPSK	1	271	27.30					
100	QPSK	135	0	26.37			28.0	1.0	
100	QPSK	135	69	27.31					
100	QPSK	135	138	26.43			29.0	0.0	
100	QPSK	270	0	26.51					
100	16QAM	1	1	26.34			28.0	1.0	
100	64QAM	1	1	24.96					
100	256QAM	1	1	24.53			26.5	2.5	
Channel				633000	633334	633668			
Frequency (MHz)				3486	3500.01	3505.02	MPR up limit (dB)		
90	QPSK	1	1	27.40	27.34	27.37	29.0	0.0	
Channel				632668	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510	MPR up limit (dB)		
80	QPSK	1	1	27.32	27.40	27.36	29.0	0.0	
Channel				632314	633334	634334			
Frequency (MHz)				3485.01	3500.01	3515.01	MPR up limit (dB)		
70	QPSK	1	1	27.32	27.43	27.36	29.0	0.0	
Channel				632000	633334	634668			
Frequency (MHz)				3480	3500.01	3520.02	MPR up limit (dB)		
60	QPSK	1	1	27.33	27.42	27.33	29.0	0.0	
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525	MPR up limit (dB)		
50	QPSK	1	1	27.40	27.36	27.41	29.0	0.0	
Channel				631334	633334	635334			
Frequency (MHz)				3470.01	3500.01	3530.01	MPR up limit (dB)		
40	QPSK	1	1	27.42	27.37	27.42	29.0	0.0	
Channel				631000	633334	635668			
Frequency (MHz)				3465	3500.01	3535.02	MPR up limit (dB)		
30	QPSK	1	1	27.37	27.41	27.40	29.0	0.0	
Channel				630834	633334	635834			
Frequency (MHz)				3462.51	3500.01	3537.51	MPR up limit (dB)		
25	QPSK	1	1	27.38	27.37	27.37	29.0	0.0	
Channel				630568	633334	636000			
Frequency (MHz)				3460.02	3500.01	3540	MPR up limit (dB)		
20	QPSK	1	1	27.32	27.40	27.35	29.0	0.0	
Channel				630500	633334	636168			
Frequency (MHz)				3457.5	3500.01	3542.52	MPR up limit (dB)		
15	QPSK	1	1	27.37	27.43	27.32	29.0	0.0	
Channel				630384	633334	636342			
Frequency (MHz)				3455.01	3500.01	3545.01	MPR up limit (dB)		
10	QPSK	1	1	27.37	27.38	27.43	29.0	0.0	

Reduced Power Mode for DSI3_Main PA

n5 Ant0 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				166800	167300	167800			
Frequency (MHz)				834	836.5	839			
20	1/2 BPSK	1	1	25.29	25.29	25.29			
20	1/2 BPSK	1	53	25.31	25.28	25.24	25.7	0.0	
20	1/2 BPSK	1	104	25.11	25.13	25.14			
20	1/2 BPSK	50	0	24.69	24.70	24.63	25.2	0.5	
20	1/2 BPSK	50	28	25.28	25.32	25.26	25.7	0.0	
20	1/2 BPSK	50	56	24.62	24.72	24.63			
20	1/2 BPSK	100	0	24.82	24.77	24.82	25.2	0.5	
20	QPSK	1	1	25.29	25.33	25.27			
20	QPSK	1	53	25.32	25.32	25.24	25.7	0.0	
20	QPSK	1	104	25.13	25.09	25.09			
20	QPSK	50	0	24.23	24.27	24.26	24.7	1.0	
20	QPSK	50	28	25.20	25.23	25.21	25.7	0.0	
20	QPSK	50	56	24.15	24.08	24.08			
20	QPSK	100	0	24.26	24.29	24.28	24.7	1.0	
20	16QAM	1	1	24.16	24.15	24.20	24.7	1.0	
20	64QAM	1	1	22.63	22.62	22.60	23.2	2.5	
20	256QAM	1	1	20.49	20.51	20.56	21.2	4.5	
Channel				166300	167300	168300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				831.5	836.5	841.5			
15	QPSK	1	1	25.24	25.19	25.17	25.7	0.0	
Channel				165800	167300	168800	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				829	836.5	844			
10	QPSK	1	1	25.22	25.22	25.13	25.7	0.0	
Channel				165300	167300	169300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				826.5	836.5	846.5			
5	QPSK	1	1	25.14	25.26	25.21	25.7	0.0	

n12 Ant0 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				141300	141500	141700			
Frequency (MHz)				706.5	707.5	708.5			
15	1/2 BPSK	1	1	25.39	25.39	25.48			
15	1/2 BPSK	1	40	25.41	25.43	25.38	25.7	0.0	
15	1/2 BPSK	1	77	25.32	25.35	25.29			
15	1/2 BPSK	36	0	24.88	24.83	24.89	25.2	0.5	
15	1/2 BPSK	36	22	25.43	25.39	25.45	25.7	0.0	
15	1/2 BPSK	36	43	24.84	24.80	24.79			
15	1/2 BPSK	75	0	24.93	24.99	24.90	25.2	0.5	
15	QPSK	1	1	25.47	25.52	25.48			
15	QPSK	1	40	25.48	25.43	25.38	25.7	0.0	
15	QPSK	1	77	25.33	25.24	25.26			
15	QPSK	36	0	24.37	24.46	24.43	24.7	1.0	
15	QPSK	36	22	25.44	25.47	25.43	25.7	0.0	
15	QPSK	36	43	24.33	24.27	24.23			
15	QPSK	75	0	24.48	24.52	24.45	24.7	1.0	
15	16QAM	1	1	24.26	24.37	24.32	24.7	1.0	
15	64QAM	1	1	22.84	22.73	22.82	23.2	2.5	
15	256QAM	1	1	20.71	20.73	20.66	21.2	4.5	
Channel				140800	141500	142200	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				704	707.5	711			
10	QPSK	1	1	25.41	25.46	25.43	25.7	0.0	
Channel				140300	141500	142700	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				701.5	707.5	713.5			
5	QPSK	1	1	25.32	25.43	25.40	25.7	0.0	

n26 Ant0 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				164800	166300	167800			
Frequency (MHz)				824	831.5	839			
20	1/2 BPSK	1	1	25.34	25.35	25.33			
20	1/2 BPSK	1	53	25.25	25.30	25.28	25.7	0.0	
20	1/2 BPSK	1	104	25.19	25.11	25.09			
20	1/2 BPSK	50	0	24.74	24.66	24.76	25.2	0.5	
20	1/2 BPSK	50	28	25.29	25.27	25.36	25.7	0.0	
20	1/2 BPSK	50	56	24.68	24.74	24.73			
20	1/2 BPSK	100	0	24.78	24.79	24.79	25.2	0.5	
20	QPSK	1	1	25.35	25.39	25.37			
20	QPSK	1	53	25.36	25.33	25.27	25.7	0.0	
20	QPSK	1	104	25.14	25.14	25.09			
20	QPSK	50	0	24.32	24.28	24.22	24.7	1.0	
20	QPSK	50	28	25.29	25.34	25.31	25.7	0.0	
20	QPSK	50	56	24.05	24.09	24.09			
20	QPSK	100	0	24.35	24.36	24.29	24.7	1.0	
20	16QAM	1	1	24.15	24.19	24.11	24.7	1.0	
20	64QAM	1	1	22.59	22.59	22.58	23.2	2.5	
20	256QAM	1	1	20.48	20.46	20.53	21.2	4.5	
Channel				164300	166300	168300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				821.5	831.5	841.5			
15	QPSK	1	1	25.22	25.24	25.23	25.7	0.0	
Channel				163800	166300	168800	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				819	831.5	844			
10	QPSK	1	1	25.30	25.32	25.27	25.7	0.0	
Channel				163300	166300	169300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				816.5	831.5	846.5			
5	QPSK	1	1	25.24	25.33	25.33	25.7	0.0	

n71 Ant0 DSI3								
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)
Channel				136100			25.7	0.0
Frequency (MHz)				680.5				
35	1/2 BPSK	1	1	25.24				
35	1/2 BPSK	1	90	25.14				
35	1/2 BPSK	1	186	25.10			25.2	0.5
35	1/2 BPSK	90	0	24.60				
35	1/2 BPSK	90	45	25.20				
35	1/2 BPSK	90	90	24.58				
35	1/2 BPSK	180	0	24.70			25.7	0.0
35	QPSK	1	1	25.25				
35	QPSK	1	90	25.16				
35	QPSK	1	186	25.00				
35	QPSK	90	0	24.16			24.7	1.0
35	QPSK	90	45	25.21				
35	QPSK	90	90	24.06				
35	QPSK	180	0	24.23				
35	16QAM	1	1	24.04			24.7	1.0
35	64QAM	1	1	22.54				
35	256QAM	1	1	20.48				
Channel				135600	136100	136600	25.7	0.0
Frequency (MHz)				678	680.5	683		
30	QPSK	1	1	25.14	25.19	25.10		
Channel				135100	136100	137100	25.7	MPR (dB)
Frequency (MHz)				675.5	680.5	685.5		
25	QPSK	1	1	25.12	25.10	25.18		
Channel				134600	136100	137600	25.7	MPR (dB)
Frequency (MHz)				673	680.5	688		
20	QPSK	1	1	25.18	25.13	25.15		
Channel				134100	136100	138100	25.7	MPR (dB)
Frequency (MHz)				670.5	680.5	690.5		
15	QPSK	1	1	25.10	25.14	25.17		
Channel				133600	136100	138600	25.7	MPR (dB)
Frequency (MHz)				668	680.5	693		
10	QPSK	1	1	25.14	25.15	25.14		
Channel				133100	136100	139100	25.7	MPR (dB)
Frequency (MHz)				665.5	680.5	695.5		
5	QPSK	1	1	25.15	25.15	25.08		

n5 Ant1 DSI3									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				166800	167300	167800			
Frequency (MHz)				834	836.5	838			
20	1/2 BPSK	1	1	21.48	21.52	21.44			
20	1/2 BPSK	1	53	21.50	21.50	21.43	21.7	0.0	
20	1/2 BPSK	1	104	21.42	21.55	21.41			
20	1/2 BPSK	50	0	21.51	21.57	21.48	21.7	0.0	
20	1/2 BPSK	50	28	21.42	21.51	21.43	21.7	0.0	
20	1/2 BPSK	50	56	21.42	21.46	21.39			
20	1/2 BPSK	100	0	21.51	21.49	21.43	21.7	0.0	
20	QPSK	1	1	21.41	21.65	21.46			
20	QPSK	1	53	21.50	21.55	21.48	21.7	0.0	
20	QPSK	1	104	21.45	21.52	21.43			
20	QPSK	50	0	21.51	21.48	21.45	21.7	0.0	
20	QPSK	50	28	21.50	21.55	21.42	21.7	0.0	
20	QPSK	50	56	21.52	21.54	21.46			
20	QPSK	100	0	21.43	21.50	21.39	21.7	0.0	
20	16QAM	1	1	21.51	21.54	21.48	21.7	0.0	
20	64QAM	1	1	21.45	21.48	21.46	21.7	0.0	
20	256QAM	1	1	21.06	21.10	21.00	21.2	0.5	
Channel				168200	167200	168200			
Frequency (MHz)				831.5	836.5	841.5			
15	QPSK	1	1	21.44	21.51	21.45	21.7	0.0	
Channel				165900	167300	168800			
Frequency (MHz)				829	836.5	844			
10	QPSK	1	1	21.48	21.53	21.39	21.7	0.0	
Channel				163200	167200	168200			
Frequency (MHz)				826.5	836.5	846.5			
5	QPSK	1	1	21.39	21.46	21.45	21.7	0.0	

n12 Ant1 DSI3									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				141300	141500	141700			
Frequency (MHz)				706.5	707.5	708.5			
15	1/2 BPSK	1	1	25.39	25.38	25.49			
15	1/2 BPSK	1	40	25.47	25.40	25.39	25.7	0.0	
15	1/2 BPSK	1	77	25.27	25.39	25.30			
15	1/2 BPSK	36	0	24.89	24.82	24.86	25.2	0.5	
15	1/2 BPSK	36	22	25.38	25.43	25.41	25.7	0.0	
15	1/2 BPSK	36	43	24.89	24.85	24.80			
15	1/2 BPSK	75	0	24.89	24.94	24.93	25.2	0.5	
15	QPSK	1	1	25.54	25.63	25.57			
15	QPSK	1	40	25.53	25.41	25.40	25.7	0.0	
15	QPSK	1	77	25.35	25.30	25.32			
15	QPSK	36	0	24.36	24.41	24.37	24.7	1.0	
15	QPSK	36	22	25.51	25.58	25.49	25.7	0.0	
15	QPSK	36	43	24.33	24.31	24.28			
15	QPSK	75	0	24.53	24.55	24.49	24.7	1.0	
15	16QAM	1	1	24.23	24.40	24.28	24.7	1.0	
15	64QAM	1	1	22.81	22.69	22.80	23.2	2.5	
15	256QAM	1	1	20.72	20.70	20.70	21.2	4.5	
Channel				140800	141500	142200			
Frequency (MHz)				704	707.5	711			
10	QPSK	1	1	25.53	25.51	25.49	25.7	0.0	
Channel				140300	141500	142700			
Frequency (MHz)				701.5	707.5	713.5			
5	QPSK	1	1	25.46	25.53	25.52	25.7	0.0	

n26 Ant1 DSI3									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				164800	166300	167800			
Frequency (MHz)				824	831.5	839			
20	1/2 BPSK	1	1	22.52	22.59	22.59			
20	1/2 BPSK	1	53	22.52	22.56	22.50	22.7	0.0	
20	1/2 BPSK	1	104	22.51	22.56	22.56			
20	1/2 BPSK	50	0	22.58	22.52	22.53	22.7	0.0	
20	1/2 BPSK	50	28	22.54	22.63	22.51	22.7	0.0	
20	1/2 BPSK	50	56	22.53	22.55	22.56			
20	1/2 BPSK	100	0	22.50	22.57	22.51	22.7	0.0	
20	QPSK	1	1	22.58	22.65	22.56			
20	QPSK	1	53	22.49	22.54	22.52	22.7	0.0	
20	QPSK	1	104	22.55	22.60	22.60			
20	QPSK	50	0	22.52	22.63	22.58	22.7	0.0	
20	QPSK	50	28	22.53	22.54	22.58	22.7	0.0	
20	QPSK	50	56	22.52	22.55	22.51			
20	QPSK	100	0	22.49	22.60	22.56	22.7	0.0	
20	16QAM	1	1	22.55	22.52	22.53	22.7	0.0	
20	64QAM	1	1	22.54	22.60	22.57	22.7	0.0	
20	256QAM	1	1	21.03	21.08	21.09	21.2	1.5	
Channel				164300	166300	168300			
Frequency (MHz)				821.5	831.5	841.5			
15	QPSK	1	1	22.48	22.52	22.47	22.7	0.0	
Channel				163800	166300	168800			
Frequency (MHz)				819	831.5	844			
10	QPSK	1	1	22.50	22.43	22.51	22.7	0.0	
Channel				163300	166300	169300			
Frequency (MHz)				816.5	831.5	846.5			
5	QPSK	1	1	22.44	22.41	22.52	22.7	0.0	

n71 Ant1 DSI3									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				136100					
Frequency (MHz)				680.5					
35	1/2 BPSK	1	1		25.24				
35	1/2 BPSK	1	90		25.18		25.7	0.0	
35	1/2 BPSK	1	186		25.18				
35	1/2 BPSK	90	0		24.69		25.2	0.5	
35	1/2 BPSK	90	45		25.19		25.7	0.0	
35	1/2 BPSK	90	90		24.55				
35	1/2 BPSK	180	0		24.82		25.2	0.5	
35	QPSK	1	1		25.32				
35	QPSK	1	90		25.24		25.7	0.0	
35	QPSK	1	186		25.10				
35	QPSK	90	0		24.25		24.7	1.0	
35	QPSK	90	45		25.28		25.7	0.0	
35	QPSK	90	90		24.10				
35	QPSK	180	0		24.24		24.7	1.0	
35	16QAM	1	1		24.18		24.7	1.0	
35	64QAM	1	1		22.47		23.2	2.5	
35	256QAM	1	1		20.58		21.2	4.5	
Channel				136600	136100	136600			
Frequency (MHz)				678	680.5	683			
30	QPSK	1	1	25.21	25.16	25.23	25.7	0.0	
Channel				135100	136100	137100			
Frequency (MHz)				675.5	680.5	685.5			
25	QPSK	1	1	25.17	25.19	25.22	25.7	0.0	
Channel				134600	136100	137600			
Frequency (MHz)				673	680.5	688			
20	QPSK	1	1	25.21	25.19	25.19	25.7	0.0	
Channel				134100	136100	138100			
Frequency (MHz)				670.5	680.5	690.5			
15	QPSK	1	1	25.19	25.25	25.19	25.7	0.0	
Channel				133600	136100	138600			
Frequency (MHz)				668	680.5	693			
10	QPSK	1	1	25.22	25.26	25.25	25.7	0.0	
Channel				133100	136100	139100			
Frequency (MHz)				665.5	680.5	695.5			
5	QPSK	1	1	25.18	25.17	25.28	25.7	0.0	

n2 Ant5 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376000	378000			
Frequency (MHz)				1870	1880	1890			
40	1/2 BPSK	1	1	22.31	22.50	22.29			
40	1/2 BPSK	1	108	22.33	22.55	22.34	23.0	0.0	
40	1/2 BPSK	1	214	22.33	22.53	22.29			
40	1/2 BPSK	108	0	22.35	22.54	22.29	23.0	0.0	
40	1/2 BPSK	108	54	22.31	22.52	22.29	23.0	0.0	
40	1/2 BPSK	108	108	22.32	22.54	22.34			
40	1/2 BPSK	216	0	22.31	22.54	22.33	23.0	0.0	
40	QPSK	1	1	22.32	22.61	22.29			
40	QPSK	1	108	22.36	22.52	22.30	23.0	0.0	
40	QPSK	1	214	22.32	22.51	22.35			
40	QPSK	108	0	22.34	22.51	22.30	23.0	0.0	
40	QPSK	108	54	22.32	22.56	22.34	23.0	0.0	
40	QPSK	108	108	22.31	22.50	22.30			
40	QPSK	216	0	22.31	22.55	22.29	23.0	0.0	
40	16QAM	1	1	22.34	22.55	22.35	23.0	0.0	
40	64QAM	1	1	21.79	22.07	21.79	22.5	0.5	
40	256QAM	1	1	19.61	20.03	19.79	20.5	2.5	
Channel				373500	376000	378500			
Frequency (MHz)				1887.5	1880	1892.5			
35	QPSK	1	1	22.21	22.46	22.20	23.0	0.0	
Channel				373000	376000	379000			
Frequency (MHz)				1865	1880	1895			
30	QPSK	1	1	22.25	22.46	22.16	23.0	0.0	
Channel				372500	376000	378500			
Frequency (MHz)				1862.5	1880	1897.5			
25	QPSK	1	1	22.21	22.44	22.21	23.0	0.0	
Channel				372000	376000	380000			
Frequency (MHz)				1860	1870	1900			
20	QPSK	1	1	22.19	22.43	22.17	23.0	0.0	
Channel				371500	376000	380500			
Frequency (MHz)				1857.5	1880	1902.5			
15	QPSK	1	1	22.22	22.46	22.21	23.0	0.0	
Channel				371000	376000	381000			
Frequency (MHz)				1855	1860	1905			
10	QPSK	1	1	22.20	22.44	22.17	23.0	0.0	
Channel				370500	376000	381500			
Frequency (MHz)				1852.5	1880	1907.5			
5	QPSK	1	1	22.21	22.42	22.20	23.0	0.0	

n7 Ant5 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				50500	50700	50900			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	20.23	20.21	20.17			
50	1/2 BPSK	1	135	20.26	20.25	20.20	20.5	0.0	
50	1/2 BPSK	1	268	20.18	20.21	20.25			
50	1/2 BPSK	135	0	20.22	20.23	20.22	20.5	0.0	
50	1/2 BPSK	135	68	20.22	20.22	20.20	20.5	0.0	
50	1/2 BPSK	135	135	20.25	20.26	20.19			
50	1/2 BPSK	270	0	20.21	20.26	20.15	20.5	0.0	
50	QPSK	1	1	20.20	20.31	20.20			
50	QPSK	1	135	20.24	20.24	20.15	20.5	0.0	
50	QPSK	1	268	20.18	20.21	20.22			
50	QPSK	135	0	20.21	20.23	20.21	20.5	0.0	
50	QPSK	135	68	20.24	20.26	20.25	20.5	0.0	
50	QPSK	135	135	20.21	20.23	20.21			
50	QPSK	270	0	20.18	20.26	20.18	20.5	0.0	
50	16QAM	1	1	20.18	20.21	20.20	20.5	0.0	
50	64QAM	1	1	20.19	20.27	20.19	20.5	0.0	
50	256QAM	1	1	20.25	20.26	20.25	20.5	0.0	
Channel				504000	507000	510000			
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	20.04	20.26	20.15	20.5	0.0	
Channel				503500	507000	510500			
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	20.08	20.18	20.05	20.5	0.0	
Channel				503000	507000	511000			
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	20.08	20.23	20.15	20.5	0.0	
Channel				502500	507000	511500			
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	20.12	20.17	20.04	20.5	0.0	
Channel				502000	507000	512000			
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	20.14	20.24	20.11	20.5	0.0	
Channel				501500	507000	512500			
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	20.10	20.26	20.12	20.5	0.0	
Channel				501000	507000	513000			
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	20.06	20.22	20.04	20.5	0.0	
Channel				500500	507000	513500			
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	20.05	20.16	20.06	20.5	0.0	

n25 Ant5 DSI3									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq. (dB)	Power Middle Ch. / Freq. (dB)	Power High Ch. / Freq. (dB)	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376500	379000			
Frequency (MHz)				1870	1882.5	1895			
40	1/2 BPSK	1	1	22.92	22.96	22.89			
40	1/2 BPSK	1	108	22.88	22.95	22.92	23.5	0.0	0.0
40	1/2 BPSK	1	214	22.94	22.94	22.86			
40	1/2 BPSK	108	0	22.95	22.93	22.92	23.5	0.0	0.0
40	1/2 BPSK	108	54	22.84	22.97	22.86	23.5	0.0	0.0
40	1/2 BPSK	108	108	22.86	22.91	22.87			
40	1/2 BPSK	216	0	22.94	22.91	22.88	23.5	0.0	0.0
40	QPSK	1	1	22.87	22.98	22.90			
40	QPSK	1	108	22.90	22.94	22.88	23.5	0.0	0.0
40	QPSK	1	214	22.89	22.92	22.92			
40	QPSK	108	0	22.93	22.91	22.94	23.5	0.0	0.0
40	QPSK	108	54	22.86	22.96	22.94	23.5	0.0	0.0
40	QPSK	108	108	22.95	22.94	22.88			
40	QPSK	216	0	22.87	22.95	22.91	23.5	0.0	0.0
40	16QAM	1	1	22.88	22.91	22.92	23.5	0.0	0.0
40	64QAM	1	1	21.82	21.92	21.91	22.5	1.0	1.0
40	256QAM	1	1	19.66	19.99	19.67	20.5	3.0	3.0
Channel				373500	376500	379500			
Frequency (MHz)				1867.5	1882.5	1897.5			
35	QPSK	1	1	22.75	22.83	22.79	23.5	0.0	0.0
Channel				373000	376500	380000			
Frequency (MHz)				1865	1882.5	1900			
30	QPSK	1	1	22.77	22.88	22.75	23.5	0.0	0.0
Channel				372500	376500	380500			
Frequency (MHz)				1862.5	1882.5	1902.5			
25	QPSK	1	1	22.79	22.87	22.82	23.5	0.0	0.0
Channel				372000	376500	381000			
Frequency (MHz)				1860	1882.5	1905			
20	QPSK	1	1	22.79	22.89	22.85	23.5	0.0	0.0
Channel				371500	376500	381500			
Frequency (MHz)				1857.5	1882.5	1907.5			
15	QPSK	1	1	22.71	22.87	22.76	23.5	0.0	0.0
Channel				371000	376500	382000			
Frequency (MHz)				1855	1882.5	1910			
10	QPSK	1	1	22.72	22.98	22.80	23.5	0.0	0.0
Channel				370500	376500	382500			
Frequency (MHz)				1852.5	1882.5	1912.5			
5	QPSK	1	1	22.72	22.83	22.83	23.5	0.0	0.0

n38 Ant5 DSI3									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				516034	516000	516996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	20.83	20.90	20.90			
40	1/2 BPSK	1	53	20.85	20.93	20.82	21.2	0.0	
40	1/2 BPSK	1	104	20.86	20.92	20.83			
40	1/2 BPSK	50	0	20.80	20.84	20.83	21.2	0.0	
40	1/2 BPSK	50	25	20.86	20.91	20.87	21.2	0.0	
40	1/2 BPSK	50	56	20.81	20.86	20.80			
40	1/2 BPSK	100	0	20.81	20.85	20.81	21.2	0.0	
40	QPSK	1	1	20.81	20.84	20.79			
40	QPSK	1	53	20.80	20.88	20.87	21.2	0.0	
40	QPSK	1	104	20.88	20.83	20.82			
40	QPSK	50	0	20.84	20.91	20.88	21.2	0.0	
40	QPSK	50	25	20.90	20.93	20.82	21.2	0.0	
40	QPSK	50	56	20.83	20.84	20.80			
40	QPSK	100	0	20.89	20.93	20.88	21.2	0.0	
40	16QAM	1	1	20.86	20.89	20.79	21.2	0.0	
40	64QAM	1	1	20.85	20.90	20.85	21.2	0.0	
40	256QAM	1	1	20.84	20.83	20.85	21.2	0.0	
Channel				517002	516000	520998			
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	20.86	20.86	20.75	21.2	0.0	
Channel				516504	519000	521496			
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	20.69	20.83	20.72	21.2	0.0	
Channel				516000	519000	522000			
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	20.76	20.80	20.66	21.2	0.0	
Channel				515502	519000	522498			
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	20.70	20.85	20.72	21.2	0.0	
Channel				516000	519000	522998			
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	20.67	20.84	20.65	21.2	0.0	

n41 Ant5 DSI3									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	20.61	20.55	20.52			
100	1/2 BPSK	1	137	20.57	20.56	20.48	21.0	0.0	
100	1/2 BPSK	1	271	20.53	20.54	20.52			
100	1/2 BPSK	135	0	20.51	20.57	20.50	21.0	0.0	
100	1/2 BPSK	135	69	20.56	20.57	20.50	21.0	0.0	
100	1/2 BPSK	135	138	20.55	20.61	20.52			
100	1/2 BPSK	270	0	20.50	20.62	20.59	21.0	0.0	
100	QPSK	1	1	20.53	20.70	20.52			
100	QPSK	1	137	20.51	20.62	20.53	21.0	0.0	
100	QPSK	1	271	20.52	20.55	20.50			
100	QPSK	135	0	20.57	20.62	20.53	21.0	0.0	
100	QPSK	135	69	20.61	20.66	20.52	21.0	0.0	
100	QPSK	135	138	20.57	20.62	20.51			
100	QPSK	270	0	20.53	20.63	20.58	21.0	0.0	
100	16QAM	1	1	20.58	20.60	20.58	21.0	0.0	
100	64QAM	1	1	20.52	20.62	20.52	21.0	0.0	
100	256QAM	1	1	20.58	20.60	20.45	21.0	0.0	
Channel				520000	518598	523998			
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	20.46	20.72	20.44	21.0	0.0	
Channel				507204	518598	529998			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	20.45	20.69	20.37	21.0	0.0	
Channel				520000	518598	523000			
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	20.44	20.66	20.39	21.0	0.0	
Channel				505200	518598	531998			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	20.43	20.69	20.41	21.0	0.0	
Channel				520000	518598	529998			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	20.44	20.72	20.45	21.0	0.0	
Channel				503700	518598	533498			
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	20.46	20.68	20.46	21.0	0.0	
Channel				520000	518598	530000			
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	20.41	20.64	20.43	21.0	0.0	
Channel				502704	518598	534498			
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	20.47	20.64	20.46	21.0	0.0	
Channel				520000	518598	530998			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	20.46	20.69	20.39	21.0	0.0	
Channel				501702	518598	535500			
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	20.37	20.73	20.41	21.0	0.0	
Channel				520000	518598	530998			
Frequency (MHz)				2506.52	2592.99	2679.99			
20	QPSK	1	1	20.41	20.72	20.44	21.0	0.0	
Channel				500700	518598	536498			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	20.39	20.67	20.40	21.0	0.0	
Channel				500202	518598	537000			
Frequency (MHz)				2501.51	2592.99	2685			
10	QPSK	1	1	20.45	20.73	20.39	21.0	0.0	

n48 Ant5 DSI3									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				638000	641666	645332			
Frequency (MHz)				3570	3624.99	3679.98			
40	1/2 BPSK	1	1	17.83	17.82	17.81			
40	1/2 BPSK	1	53	17.87	17.91	17.85	19.0		0.0
40	1/2 BPSK	1	104	17.81	17.82	17.81			
40	1/2 BPSK	50	0	17.85	17.92	17.79	19.0		0.0
40	1/2 BPSK	50	25	17.82	17.90	17.79	19.0		0.0
40	1/2 BPSK	50	56	17.85	17.91	17.78			
40	1/2 BPSK	100	0	17.84	17.91	17.74	19.0		0.0
40	QPSK	1	1	17.83	17.94	17.77			
40	QPSK	1	53	17.86	17.84	17.80	19.0		0.0
40	QPSK	1	104	17.76	17.89	17.80			
40	QPSK	50	0	17.86	17.85	17.81	19.0		0.0
40	QPSK	50	25	17.80	17.91	17.84	19.0		0.0
40	QPSK	50	56	17.76	17.89	17.74			
40	QPSK	100	0	17.88	17.89	17.75	19.0		0.0
40	16QAM	1	1	17.76	17.80	17.76	19.0		0.0
40	64QAM	1	1	17.77	17.86	17.79	19.0		0.0
40	256QAM	1	1	17.82	17.82	17.51	19.0		0.0
Channel				637668	641666	645666			
Frequency (MHz)				3565.02	3624.99	3684.99			
30	QPSK	1	1	17.72	17.82	17.63	19.0		0.0
Channel				637334	641666	646000			
Frequency (MHz)				3560.01	3624.99	3690			
20	QPSK	1	1	17.74	17.83	17.72	19.0		0.0
Channel				637168	641666	645166			
Frequency (MHz)				3558.01	3624.99	367166			
15	QPSK	1	1	17.71	17.83	17.65	19.0		0.0
Channel				637020	641666	645332			
Frequency (MHz)				3555	3624.99	3664.98			
10	QPSK	1	1	17.72	17.83	17.71	19.0		0.0

Part270 n77 PC2 Ant5 DS13									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3760	3840	3920			
100	1/2 BPSK	1	1	21.29	21.34	21.35			
100	1/2 BPSK	1	137	21.36	21.42	21.19	21.5	0.0	
100	1/2 BPSK	1	271	21.26	21.37	21.26			
100	1/2 BPSK	135	0	21.33	21.29	21.31	21.5	0.0	
100	1/2 BPSK	135	69	21.27	21.42	21.26	21.5	0.0	
100	1/2 BPSK	135	138	21.24	21.30	21.26		21.5	0.0
100	1/2 BPSK	270	0	21.32	21.46	21.17	21.5		
100	QPSK	1	1	21.28	21.46	21.17			
100	QPSK	1	137	21.38	21.34	21.29	21.5		
100	QPSK	1	271	21.33	21.31	21.23			
100	QPSK	135	0	21.27	21.26	21.31	21.5	0.0	
100	QPSK	135	69	21.33	21.41	21.33	21.5	0.0	
100	QPSK	135	138	21.35	21.39	21.34		21.5	0.0
100	QPSK	270	0	21.29	21.38	21.31	21.5		
100	16QAM	1	1	21.32	21.40	21.29	21.5		
100	64QAM	1	1	21.41	21.34	21.32	21.5	0.0	
100	256QAM	1	1	21.34	21.34	21.29	21.5	0.0	
Channel				648668	650000	663334	MPR up (dB)		
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	21.39	21.42	21.37	21.5	0.0	
Channel				649334	650000	662668	MPR up (dB)		
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	21.41	21.35	21.36	21.5	0.0	
Channel				649000	650000	663000	MPR up (dB)		
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	21.42	21.34	21.31	21.5	0.0	
Channel				648668	650000	663334	MPR up (dB)		
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	21.39	21.40	21.40	21.5	0.0	
Channel				648334	650000	663668	MPR up (dB)		
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	1	21.32	21.35	21.34	21.5	0.0	
Channel				648000	650000	664000	MPR up (dB)		
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	21.34	21.42	21.34	21.5	0.0	
Channel				647668	650000	664334	MPR up (dB)		
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	21.31	21.30	21.40	21.5	0.0	
Channel				647500	650000	664500	MPR up (dB)		
Frequency (MHz)				3712.5	3840	3967.5			
25	QPSK	1	1	21.35	21.35	21.35	21.5	0.0	
Channel				647334	650000	664834	MPR up (dB)		
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	1	21.32	21.32	21.39	21.5	0.0	
Channel				647168	650000	664834	MPR up (dB)		
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	21.38	21.31	21.41	21.5	0.0	
Channel				647000	650000	665000	MPR up (dB)		
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	21.41	21.32	21.39	21.5	0.0	

Part27Q n77 Ant5 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		17.14				
100	1/2 BPSK	1	137		17.10		18.0	0.0	
100	1/2 BPSK	1	271		17.08				
100	1/2 BPSK	135	0		17.14		18.0	0.0	
100	1/2 BPSK	135	69		17.15		18.0	0.0	
100	1/2 BPSK	135	138		17.06				
100	1/2 BPSK	270	0		17.14		18.0	0.0	
100	QPSK	1	1		17.18				
100	QPSK	1	137		17.16		18.0	0.0	
100	QPSK	1	271		17.08				
100	QPSK	135	0		17.15		18.0	0.0	
100	QPSK	135	69		17.15		18.0	0.0	
100	QPSK	135	138		17.12				
100	QPSK	270	0		17.14		18.0	0.0	
100	16QAM	1	1		17.12		18.0	0.0	
100	64QAM	1	1		17.14		18.0	0.0	
100	256QAM	1	1		17.07		18.0	0.0	
Channel				633000	633334	633668	MPR up (dB)		
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	17.04	17.08	17.10	18.0	0.0	
Channel				632668	633334	634000	MPR up (dB)		
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	17.11	17.00	17.11	18.0	0.0	
Channel				632334	633334	634334	MPR up (dB)		
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	17.03	17.06	17.01	18.0	0.0	
Channel				632000	633334	634668	MPR up (dB)		
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	17.05	17.06	17.11	18.0	0.0	
Channel				631668	633334	635000	MPR up (dB)		
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	17.10	17.01	17.02	18.0	0.0	
Channel				631334	633334	635334	MPR up (dB)		
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	17.06	17.08	17.03	18.0	0.0	
Channel				631000	633334	635668	MPR up (dB)		
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	17.09	17.03	17.06	18.0	0.0	
Channel				630634	633334	635834	MPR up (dB)		
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	17.08	17.06	17.00	18.0	0.0	
Channel				630500	633334	635900	MPR up (dB)		
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	17.01	17.04	17.00	18.0	0.0	
Channel				630500	633334	636168	MPR up (dB)		
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	17.11	17.09	17.00	18.0	0.0	
Channel				630334	633334	636334	MPR up (dB)		
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	17.11	17.10	17.07	18.0	0.0	

Part27Q n77 PC2 Ant5 DSI3									
BW	Modulat	RB Size	RB Offset	Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		20.67				
100	1/2 BPSK	1	137		20.59		21.5	0.0	
100	1/2 BPSK	1	271		20.56				
100	1/2 BPSK	135	0		20.65		21.5	0.0	
100	1/2 BPSK	135	69		20.70		21.5	0.0	
100	1/2 BPSK	135	138		20.58				
100	1/2 BPSK	270	0		20.62		21.5	0.0	
100	QPSK	1	1		20.71				
100	QPSK	1	137		20.67		21.5	0.0	
100	QPSK	1	271		20.62				
100	QPSK	135	0		20.60		21.5	0.0	
100	QPSK	135	69		20.65		21.5	0.0	
100	QPSK	135	138		20.63				
100	QPSK	270	0		20.67		21.5	0.0	
100	16QAM	1	1		20.66		21.5	0.0	
100	64QAM	1	1		20.65		21.5	0.0	
100	256QAM	1	1		20.62		21.5	0.0	
Channel									
90	QPSK	1	1	3495	3500.01	3505.02			
Channel				3495	3500.01 <th>3505.02<th><th><th></th></th></th></th>	3505.02 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
Frequency (MHz)				3490.02	3500.01	3510	<th><th></th></th>	<th></th>	
80	QPSK	1	1	20.63	20.55	20.61	21.5	0.0	
Channel				342668	343334	344000 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
Frequency (MHz)				3490.02	3500.01	3510	<th><th></th></th>	<th></th>	
70	QPSK	1	1	20.66	20.65	20.63	21.5	0.0	
Channel				343235	343334	343433 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
Frequency (MHz)				3468.01	3500.01 <th>3515.01<th><th><th></th></th></th></th>	3515.01 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
60	QPSK	1	1	20.64	20.64	20.65	21.5	0.0	
Channel				343000	343334	344668 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
Frequency (MHz)				3480	3500.01	3520.02 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
50	QPSK	1	1	20.74	20.60	20.59	21.5	0.0	
Channel				341666	343334	345000 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
Frequency (MHz)				3474.02 <th>3500.01</th> <th>3525<th><th><th></th></th></th></th>	3500.01	3525 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
40	QPSK	1	1	20.63	20.65	20.64	21.5	0.0	
Channel				341334	343334	345334 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
Frequency (MHz)				3470.01 <th>3500.01</th> <th>3530.01<th><th><th></th></th></th></th>	3500.01	3530.01 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
30	QPSK	1	1	20.59	20.62	20.61	21.5	0.0	
Channel				343100	343334	345662 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
Frequency (MHz)				3465	3500.01	3535.02 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
20	QPSK	1	1	20.66	20.66	20.62	21.5	0.0	
Channel				346384	343334	345834 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
Frequency (MHz)				3462.51	3500.01	3537.51 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
15	QPSK	1	1	20.57	20.66	20.63	21.5	0.0	
Channel				343464	343334	345262 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
Frequency (MHz)				3460.02 <th>3500.01</th> <th>3540<th><th><th></th></th></th></th>	3500.01	3540 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
10	QPSK	1	1	20.59	20.62	20.60	21.5	0.0	
Channel				349500	343334	346168 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
Frequency (MHz)				3437.5	3500.01	3542.52 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
5	QPSK	1	1	20.59	20.68	20.61	21.5	0.0	
Channel				343033	343334	345334 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
Frequency (MHz)				3455.01	3500.01	3545.01 <th><th><th></th></th></th>	<th><th></th></th>	<th></th>	
10	QPSK	1	1	20.60	20.59	20.59	21.5	0.0	

Part270 n78 PC2 Ant5 DSI3									
BW MHz	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	1/2 BPS	1	1		21.02			21.5	0.0
100	1/2 BPS	1	137		20.97				
100	1/2 BPS	1	271		21.00			21.5	0.0
100	1/2 BPS	135	0		20.90				
100	1/2 BPS	135	69		20.99			21.5	0.0
100	1/2 BPS	135	138		20.93				
100	1/2 BPS	270	0		21.03			21.5	0.0
100	QPSK	1	1		21.11				
100	QPSK	1	137		21.09			21.5	0.0
100	QPSK	1	271		20.96				
100	QPSK	135	0		21.00			21.5	0.0
100	QPSK	135	69		21.02				
100	QPSK	135	138		20.96			21.5	0.0
100	QPSK	270	0		20.90				
100	16QAM	1	1		20.91			21.5	0.0
100	64QAM	1	1		20.90				
100	256QAM	1	1		21.06			21.5	0.0
Channel				648668	650000	650334	up		
Frequency (MHz)				3745.02	3750	3755.01	up	MPR (dB)	
90	QPSK	1	1	20.98	21.05	20.95	21.5	0.0	0.0
Channel				649334	650000	650668	up		
Frequency (MHz)				3740.01	3750	3760.02	up	MPR (dB)	
80	QPSK	1	1	21.04	20.99	20.98	21.5	0.0	0.0
Channel				649000	650000	651000	up		
Frequency (MHz)				3735	3750	3765	up	MPR (dB)	
70	QPSK	1	1	21.01	21.01	20.95	21.5	0.0	0.0
Channel				648668	650000	651334	up		
Frequency (MHz)				3730.02	3750	3770.01	up	MPR (dB)	
60	QPSK	1	1	21.06	21.06	21.06	21.5	0.0	0.0
Channel				648334	650000	651668	up		
Frequency (MHz)				3725.01	3750	3775.02	up	MPR (dB)	
50	QPSK	1	1	20.97	21.06	21.02	21.5	0.0	0.0
Channel				648000	650000	652000	up		
Frequency (MHz)				3720	3750	3780	up	MPR (dB)	
40	QPSK	1	1	20.99	21.01	21.01	21.5	0.0	0.0
Channel				647668	650000	652334	up		
Frequency (MHz)				3715.02	3750	3785.01	up	MPR (dB)	
30	QPSK	1	1	21.00	20.96	21.05	21.5	0.0	0.0
Channel				647500	650000	652500	up		
Frequency (MHz)				3712.5	3750	3787.5	up	MPR (dB)	
25	QPSK	1	1	21.02	21.02	21.02	21.5	0.0	0.0
Channel				647334	650000	652668	up		
Frequency (MHz)				3710.01	3750	3790.02	up	MPR (dB)	
20	QPSK	1	1	21.03	21.06	20.96	21.5	0.0	0.0
Channel				647168	650000	652834	up		
Frequency (MHz)				3707.52	3750	3792.51	up	MPR (dB)	
15	QPSK	1	1	21.04	20.96	21.01	21.5	0.0	0.0
Channel				647000	650000	653000	up		
Frequency (MHz)				3705	3750	3795	up	MPR (dB)	
10	QPSK	1	1	20.96	21.05	20.96	21.5	0.0	0.0
Channel									

Part27Q n78 Ant5 DSI3									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		17.38		18.0	0.0	
100	1/2 BPS	1	137		17.33				
100	1/2 BPS	1	271		17.34		18.0	0.0	
100	1/2 BPS	135	0		17.31				
100	1/2 BPS	135	69		17.38		18.0	0.0	
100	1/2 BPS	135	138		17.33				
100	1/2 BPS	270	0		17.47		18.0	0.0	
100	QPSK	1	1		17.50				
100	QPSK	1	137		17.40		18.0	0.0	
100	QPSK	1	271		17.44				
100	QPSK	135	0		17.37		18.0	0.0	
100	QPSK	135	69		17.42				
100	QPSK	135	138		17.36		18.0	0.0	
100	QPSK	270	0		17.39				
100	16QAM	1	1		17.29		18.0	0.0	
100	64QAM	1	1		17.38				
100	256QAM	1	1		17.43		18.0	0.0	
Channel				633000	633334	633668			
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	17.42	17.46	17.44	18.0		
Channel				632668	633334	634000	up		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	17.39	17.37	17.39	18.0		
Channel				632334	633334	634334	up		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	17.41	17.40	17.40	18.0		
Channel				632000	633334	634668	up		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	17.35	17.35	17.44	18.0		
Channel				631668	633334	635000	up		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	17.38	17.42	17.46	18.0		
Channel				631334	633334	635334	up		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	17.35	17.39	17.39	18.0		
Channel				631000	633334	635668	up		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	17.40	17.42	17.44	18.0		
Channel				630834	633334	635834	up		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	17.40	17.34	17.38	18.0		
Channel				630668	633334	636000	up		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	17.44	17.38	17.45	18.0		
Channel				630500	633334	636168	up		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	17.39	17.41	17.43	18.0		
Channel				630334	633334	636334	up		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	17.37	17.43	17.35	18.0		
Channel									

Part27Q n78 PC2 Ant5 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		20.89		21.5	0.0	
100	1/2 BPS	1	137		20.82				
100	1/2 BPS	1	271		20.85		21.5	0.0	
100	1/2 BPS	135	0		20.75				
100	1/2 BPS	135	69		20.83		21.5	0.0	
100	1/2 BPS	135	138		20.87				
100	1/2 BPS	270	0		20.87		21.5	0.0	
100	QPSK	1	1		21.03				
100	QPSK	1	137		20.94		21.5	0.0	
100	QPSK	1	271		20.82				
100	QPSK	135	0		20.92		21.5	0.0	
100	QPSK	135	69		20.96				
100	QPSK	135	138		20.83		21.5	0.0	
100	QPSK	270	0		20.81				
100	16QAM	1	1		20.80		21.5	0.0	
100	64QAM	1	1		20.83				
100	256QAM	1	1		20.95		21.5	0.0	
Channel				633500		633534			
Frequency (MHz)				3486		3500.01		3500.01	
90	QPSK	1	1	20.89	20.97	20.94	21.5	0.0	
Channel				632668		633334		634000	
Frequency (MHz)				3460.02		3500.01		3510	
80	QPSK	1	1	20.89	20.93	20.92	21.5	0.0	
Channel				632328		632994		633658	
Frequency (MHz)				3485.01		3500.01		3515.01	
70	QPSK	1	1	20.94	20.96	20.93	21.5	0.0	
Channel				632000		633334		634668	
Frequency (MHz)				3480		3500.01		3520.02	
60	QPSK	1	1	20.92	20.99	20.95	21.5	0.0	
Channel				631668		632994		635000	
Frequency (MHz)				3475.02		3500.01		3505	
50	QPSK	1	1	20.97	20.99	20.94	21.5	0.0	
Channel				631334		633334		635334	
Frequency (MHz)				3470.01		3500.01		3530.01	
40	QPSK	1	1	20.88	20.98	20.98	21.5	0.0	
Channel				631000		632994		635000	
Frequency (MHz)				3465		3500.01		3535.02	
30	QPSK	1	1	20.90	20.98	20.92	21.5	0.0	
Channel				630834		633334		635834	
Frequency (MHz)				3462.51		3500.01		3537.51	
25	QPSK	1	1	20.88	20.95	20.92	21.5	0.0	
Channel				630500		632994		635000	
Frequency (MHz)				3460.02		3500.01		3540	
20	QPSK	1	1	20.96	20.97	20.93	21.5	0.0	
Channel				630500		633334		636168	
Frequency (MHz)				3457.5		3500.01		3542.52	
15	QPSK	1	1	20.90	20.89	20.93	21.5	0.0	
Channel				630334		633334		636334	
Frequency (MHz)				3455.01		3500.01		3545.01	
10	QPSK	1	1	20.92	20.94	20.98	21.5	0.0	

n2 Ant4 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376000	378000			
Frequency (MHz)				1870	1880	1890			
40	1/2 BPSK	1	1	19.60	19.68	19.61			
40	1/2 BPSK	1	108	19.66	19.66	19.57	20.9	0.0	
40	1/2 BPSK	1	214	19.65	19.62	19.64			
40	1/2 BPSK	108	0	19.67	19.62	19.57	20.9	0.0	
40	1/2 BPSK	108	54	19.67	19.70	19.60	20.9	0.0	
40	1/2 BPSK	108	108	19.66	19.69	19.58			
40	1/2 BPSK	216	0	19.59	19.62	19.63	20.9	0.0	
40	QPSK	1	1	19.61	19.75	19.60			
40	QPSK	1	108	19.61	19.66	19.66	20.9	0.0	
40	QPSK	1	214	19.59	19.60	19.66			
40	QPSK	108	0	19.68	19.61	19.59	20.9	0.0	
40	QPSK	108	54	19.63	19.69	19.56	20.9	0.0	
40	QPSK	108	108	19.63	19.67	19.59			
40	QPSK	216	0	19.65	19.68	19.58	20.9	0.0	
40	16QAM	1	1	19.59	19.67	19.61	20.9	0.0	
40	64QAM	1	1	18.61	18.78	18.58	19.9	1.0	
40	256QAM	1	1	16.67	16.70	16.55	17.9	3.0	
Channel				373500	376000	378500			
Frequency (MHz)				1887.5	1880	1892.5			
35	QPSK	1	1	19.52	19.62	19.52	20.9	0.0	
Channel				373000	376000	378000			
Frequency (MHz)				1865	1880	1895			
30	QPSK	1	1	19.49	19.67	19.48	20.9	0.0	
Channel				372500	376000	378500			
Frequency (MHz)				1862.5	1880	1897.5			
25	QPSK	1	1	19.49	19.59	19.47	20.9	0.0	
Channel				372000	376000	380000			
Frequency (MHz)				1870	1870	1900			
20	QPSK	1	1	19.48	19.63	19.53	20.9	0.0	
Channel				371500	376000	380500			
Frequency (MHz)				1857.5	1880	1902.5			
15	QPSK	1	1	19.45	19.65	19.52	20.9	0.0	
Channel				371000	376000	381000			
Frequency (MHz)				1865	1870	1905			
10	QPSK	1	1	19.50	19.67	19.45	20.9	0.0	
Channel				370500	376000	381500			
Frequency (MHz)				1852.5	1880	1907.5			
5	QPSK	1	1	19.54	19.59	19.46	20.9	0.0	

n7 Ant4 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	18.71	18.83	18.71			
50	1/2 BPSK	1	135	18.75	18.85	18.65	19.8	0.0	
50	1/2 BPSK	1	268	18.77	18.76	18.69			
50	1/2 BPSK	135	0	18.78	18.75	18.64	19.8	0.0	
50	1/2 BPSK	135	68	18.80	18.79	18.68	19.8	0.0	
50	1/2 BPSK	135	135	18.72	18.78	18.65			
50	1/2 BPSK	270	0	18.75	18.80	18.73	19.8	0.0	
50	QPSK	1	1	18.78	18.90	18.65			
50	QPSK	1	135	18.73	18.82	18.67	19.8	0.0	
50	QPSK	1	268	18.78	18.85	18.67			
50	QPSK	135	0	18.71	18.79	18.70	19.8	0.0	
50	QPSK	135	68	18.71	18.85	18.69	19.8	0.0	
50	QPSK	135	135	18.70	18.84	18.68			
50	QPSK	270	0	18.75	18.79	18.66	19.8	0.0	
50	16QAM	1	1	18.79	18.81	18.71	19.8	0.0	
50	64QAM	1	1	18.74	18.81	18.71	19.8	0.0	
50	256QAM	1	1	16.72	16.81	16.65	19.8	0.0	
Channel				504000	507000	510000			
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	18.72	18.84	18.55	19.8	0.0	
Channel				503500	507000	510500			
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	18.71	18.86	18.50	19.8	0.0	
Channel				503000	507000	511000			
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	18.65	18.89	18.51	19.8	0.0	
Channel				502500	507000	511500			
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	18.67	18.89	18.50	19.8	0.0	
Channel				502000	507000	512000			
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	18.65	18.91	18.52	19.8	0.0	
Channel				501500	507000	512500			
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	18.64	18.94	18.50	19.8	0.0	
Channel				501000	507000	513000			
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	18.63	18.94	18.56	19.8	0.0	
Channel				500500	507000	513500			
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	18.63	18.84	18.59	19.8	0.0	

n25 Ant4 DSI3									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376500	379000			
Frequency (MHz)				1870	1882.5	1895			
40	1/2 BPSK	1	1	19.76	19.78	19.82			
40	1/2 BPSK	1	108	19.76	19.81	19.74	20.9	0.0	
40	1/2 BPSK	1	214	19.73	19.82	19.78			
40	1/2 BPSK	108	0	19.71	19.76	19.72	20.9	0.0	
40	1/2 BPSK	108	54	19.79	19.77	19.80	20.9	0.0	
40	1/2 BPSK	108	108	19.70	19.81	19.75	20.9	0.0	
40	1/2 BPSK	216	0	19.73	19.75	19.78			
40	QPSK	1	1	19.68	19.83	19.80			
40	QPSK	1	108	19.70	19.75	19.78	20.9	0.0	
40	QPSK	1	214	19.77	19.78	19.72			
40	QPSK	108	0	19.70	19.75	19.78	20.9	0.0	
40	QPSK	108	54	19.70	19.81	19.80	20.9	0.0	
40	QPSK	108	108	19.69	19.80	19.72			
40	QPSK	216	0	19.70	19.79	19.74	20.9	0.0	
40	16QAM	1	1	19.69	19.76	19.73	20.9	0.0	
40	64QAM	1	1	18.66	18.89	18.77	19.9	1.0	
40	256QAM	1	1	16.64	16.85	16.64	17.9	3.0	
Channel				373500	376500	379500			
Frequency (MHz)				1867.5	1882.5	1897.5			
35	QPSK	1	1	19.63	19.68	19.66	20.9	0.0	
Channel				373000	376500	380000			
Frequency (MHz)				1865	1882.5	1900			
30	QPSK	1	1	19.55	19.76	19.66	20.9	0.0	
Channel				372500	376500	380500			
Frequency (MHz)				1862.5	1882.5	1902.5			
25	QPSK	1	1	19.60	19.68	19.71	20.9	0.0	
Channel				372000	376500	381000			
Frequency (MHz)				1860	1882.5	1905			
20	QPSK	1	1	19.58	19.74	19.65	20.9	0.0	
Channel				371500	376500	381500			
Frequency (MHz)				1857.5	1882.5	1907.5			
15	QPSK	1	1	19.56	19.68	19.70	20.9	0.0	
Channel				371000	376500	382000			
Frequency (MHz)				1855	1882.5	1910			
10	QPSK	1	1	19.54	19.74	19.65	20.9	0.0	
Channel				370500	376500	382500			
Frequency (MHz)				1852.5	1882.5	1912.5			
5	QPSK	1	1	19.53	19.76	19.70	20.9	0.0	

n38 Ant4 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2580.02	2598	2599.98			
40	1/2 BPSK	1	1	19.52	19.60	19.46			
40	1/2 BPSK	1	53	19.59	19.64	19.55	20.6	0.0	
40	1/2 BPSK	1	104	19.59	19.61	19.45			
40	1/2 BPSK	50	0	19.60	19.58	19.57	20.6	0.0	
40	1/2 BPSK	50	26	19.52	19.55	19.54	20.6	0.0	
40	1/2 BPSK	50	56	19.57	19.59	19.54	20.6	0.0	
40	1/2 BPSK	100	0	19.52	19.60	19.47			
40	QPSK	1	1	19.52	19.60	19.47			
40	QPSK	1	53	19.59	19.61	19.57	20.6	0.0	
40	QPSK	1	104	19.57	19.62	19.45			
40	QPSK	50	0	19.59	19.56	19.49	20.6	0.0	
40	QPSK	50	26	19.54	19.64	19.47	20.6	0.0	
40	QPSK	50	56	19.58	19.63	19.54	20.6	0.0	
40	QPSK	100	0	19.56	19.57	19.52	20.6	0.0	
40	16QAM	1	1	19.60	19.58	19.47	20.6	0.0	
40	64QAM	1	1	19.54	19.63	19.47	20.6	0.0	
40	256QAM	1	1	19.50	19.59	19.53	20.1	0.5	
Channel				517002	518000	520998			
Frequency (MHz)				2585.01	2599	2604.99			
30	QPSK	1	1	19.41	19.51	19.33	20.6	0.0	
Channel				516504	519000	521496			
Frequency (MHz)				2582.52	2599	2607.48			
25	QPSK	1	1	19.44	19.51	19.39	20.6	0.0	
Channel				515000	519000	522000			
Frequency (MHz)				2580	2599	2610			
20	QPSK	1	1	19.48	19.52	19.38	20.6	0.0	
Channel				515502	519000	522498			
Frequency (MHz)				2577.51	2599	2612.49			
15	QPSK	1	1	19.47	19.50	19.36	20.6	0.0	
Channel				515004	519000	522500			
Frequency (MHz)				2575.02	2599	2614.98			
10	QPSK	1	1	19.47	19.41	19.40	20.6	0.0	

n41 Ant4 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				509002	516598	520000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	19.05	19.10	18.95			
100	1/2 BPSK	1	137	18.95	19.08	19.00	20.3	0.0	
100	1/2 BPSK	1	271	18.95	19.06	18.97			
100	1/2 BPSK	135	0	19.02	19.09	19.03	20.3	0.0	
100	1/2 BPSK	135	69	18.98	19.11	19.02	20.3	0.0	
100	1/2 BPSK	135	138	19.01	19.07	19.04	20.3	0.0	
100	1/2 BPSK	270	0	19.03	19.11	18.97			
100	QPSK	1	1	19.05	19.14	18.96			
100	QPSK	1	137	18.98	19.09	19.02	20.3	0.0	
100	QPSK	1	271	18.96	19.03	18.94			
100	QPSK	135	0	19.04	19.07	18.95	20.3	0.0	
100	QPSK	135	69	18.95	19.09	18.96	20.3	0.0	
100	QPSK	135	138	19.01	19.08	19.05	20.3	0.0	
100	QPSK	270	0	19.05	19.12	18.97			
100	16QAM	1	1	19.01	19.09	19.00	20.3	0.0	
100	64QAM	1	1	18.98	19.07	18.94	20.3	0.0	
100	256QAM	1	1	18.94	19.07	18.99	20.3	0.0	
Channel				505000	518598	520998			
Frequency (MHz)				2541	2592.99	2644.99			
90	QPSK	1	1	18.95	19.03	18.85	20.3	0.0	
Channel				507204	518598	520998			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	18.52	19.08	18.90	20.3	0.0	
Channel				505002	518598	521000			
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	18.94	19.07	18.89	20.3	0.0	
Channel				505000	518598	521000			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	18.51	18.99	18.85	20.3	0.0	
Channel				504204	518598	520998			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	18.90	18.99	18.84	20.3	0.0	
Channel				503700	518598	520496			
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	18.59	19.02	18.63	20.3	0.0	
Channel				503002	518598	520998			
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	18.97	19.05	18.87	20.3	0.0	
Channel				502704	518598	520496			
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	18.62	19.09	18.83	20.3	0.0	
Channel				502200	518598	520998			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	18.95	19.04	18.83	20.3	0.0	
Channel				501702	518598	520500			
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	19.00	19.06	18.91	20.3	0.0	
Channel				501204	518598	520500			
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	18.96	19.01	18.92	20.3	0.0	
Channel				500700	518598	520496			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	18.97	18.99	18.90	20.3	0.0	
Channel				500202	518598	520500			
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	18.93	19.01	18.91	20.3	0.0	

Part270 n77 Ant4 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				650000	660000	662000			
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	18.57	18.59	18.52			
100	1/2 BPSK	1	137	18.54	18.60	18.50	19.2	0.0	
100	1/2 BPSK	1	271	18.63	18.58	18.55			
100	1/2 BPSK	135	0	18.63	18.56	18.53	19.2	0.0	
100	1/2 BPSK	135	69	18.57	18.54	18.56	19.2	0.0	
100	1/2 BPSK	135	138	18.59	18.59	18.57	19.2	0.0	
100	1/2 BPSK	270	0	18.53	18.58	18.57			
100	QPSK	1	1	18.59	18.66	18.58			
100	QPSK	1	137	18.61	18.64	18.51	19.2	0.0	
100	QPSK	1	271	18.55	18.64	18.57			
100	QPSK	135	0	18.54	18.59	18.56	19.2	0.0	
100	QPSK	135	69	18.58	18.61	18.57	19.2	0.0	
100	QPSK	135	138	18.57	18.54	18.51	19.2	0.0	
100	QPSK	270	0	18.54	18.55	18.51			
100	16QAM	1	1	18.57	18.55	18.58	19.2	0.0	
100	64QAM	1	1	18.58	18.53	18.52	19.2	0.0	
100	256QAM	1	1	18.59	18.63	18.50	19.2	0.0	
Channel				646668	656000	662334			
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	18.49	18.52	18.49	19.2	0.0	
Channel				649334	656000	662668			
Frequency (MHz)				3750	3840	3940.02			
80	QPSK	1	1	18.54	18.47	18.40	19.2	0.0	
Channel				647000	656000	663000			
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	18.52	18.50	18.48	19.2	0.0	
Channel				646668	656000	663334			
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	18.44	18.45	18.52	19.2	0.0	
Channel				647000	656000	663000			
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	1	18.50	18.47	18.51	19.2	0.0	
Channel				648000	656000	664000			
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	18.47	18.52	18.47	19.2	0.0	
Channel				647000	656000	663000			
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	18.53	18.53	18.47	19.2	0.0	
Channel				647500	656000	664500			
Frequency (MHz)				3712.5	3840	3967.5			
25	QPSK	1	1	18.48	18.51	18.46	19.2	0.0	
Channel				647000	656000	663000			
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	1	18.55	18.48	18.52	19.2	0.0	
Channel				647168	656000	664834			
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	18.46	18.52	18.50	19.2	0.0	
Channel				647000	656000	663000			
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	18.52	18.51	18.47	19.2	0.0	

Part27Q n77 Ant4 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		18.46				
100	1/2 BPSK	1	137		18.44		19.2	0.0	
100	1/2 BPSK	1	271		18.43				
100	1/2 BPSK	135	0		18.51		19.2	0.0	
100	1/2 BPSK	135	69		18.39		19.2	0.0	
100	1/2 BPSK	135	138		18.50				
100	1/2 BPSK	270	0		18.49		19.2	0.0	
100	QPSK	1	1		18.60				
100	QPSK	1	137		18.49		19.2	0.0	
100	QPSK	1	271		18.59				
100	QPSK	135	0		18.44		19.2	0.0	
100	QPSK	135	69		18.54		19.2	0.0	
100	QPSK	135	138		18.50				
100	QPSK	270	0		18.40		19.2	0.0	
100	16QAM	1	1		18.42		19.2	0.0	
100	64QAM	1	1		18.49		19.2	0.0	
100	256QAM	1	1		18.55		19.2	0.0	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02	(dB)	(dB)	
90	QPSK	1	1	18.51	18.52	18.49	19.2	0.0	
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	(dB)	(dB)	
80	QPSK	1	1	18.50	18.46	18.46	19.2	0.0	
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	(dB)	(dB)	
70	QPSK	1	1	18.50	18.45	18.46	19.2	0.0	
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	(dB)	(dB)	
60	QPSK	1	1	18.48	18.50	18.52	19.2	0.0	
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525	(dB)	(dB)	
50	QPSK	1	1	18.55	18.52	18.51	19.2	0.0	
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	(dB)	(dB)	
40	QPSK	1	1	18.51	18.47	18.48	19.2	0.0	
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	(dB)	(dB)	
30	QPSK	1	1	18.54	18.55	18.51	19.2	0.0	
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	(dB)	(dB)	
25	QPSK	1	1	18.45	18.49	18.46	19.2	0.0	
Channel				630500	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dB)	(dB)	
20	QPSK	1	1	18.46	18.51	18.52	19.2	0.0	
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	(dB)	(dB)	
15	QPSK	1	1	18.48	18.48	18.48	19.2	0.0	
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	(dB)	(dB)	
10	QPSK	1	1	18.54	18.56	18.51	19.2	0.0	

Part27Q n77 PC2 Ant4 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		21.43				
100	1/2 BPSK	1	137		21.42		22.2	0.0	
100	1/2 BPSK	1	271		21.52				
100	1/2 BPSK	135	0		21.52		22.2	0.0	
100	1/2 BPSK	135	69		21.47		22.2	0.0	
100	1/2 BPSK	135	138		21.53		22.2	0.0	
100	1/2 BPSK	270	0		21.53				
100	QPSK	1	1		21.63				
100	QPSK	1	137		21.47		22.2	0.0	
100	QPSK	1	271		21.55				
100	QPSK	135	0		21.52		22.2	0.0	
100	QPSK	135	69		21.56		22.2	0.0	
100	QPSK	135	138		21.49		22.2	0.0	
100	QPSK	270	0		21.53				
100	16QAM	1	1		21.53		22.2	0.0	
100	64QAM	1	1		21.52		22.2	0.0	
100	256QAM	1	1		21.59		22.2	0.0	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02	up	(dB)	
90	QPSK	1	1	21.51	21.50	21.57	22.2	0.0	
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up	(dB)	
80	QPSK	1	1	21.52	21.52	21.47	22.2	0.0	
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up	(dB)	
70	QPSK	1	1	21.57	21.50	21.51	22.2	0.0	
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up	(dB)	
60	QPSK	1	1	21.58	21.58	21.55	22.2	0.0	
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525	up	(dB)	
50	QPSK	1	1	21.58	21.49	21.53	22.2	0.0	
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up	(dB)	
40	QPSK	1	1	21.52	21.59	21.53	22.2	0.0	
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	up	(dB)	
30	QPSK	1	1	21.51	21.49	21.47	22.2	0.0	
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up	(dB)	
25	QPSK	1	1	21.49	21.57	21.53	22.2	0.0	
Channel				630500	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up	(dB)	
20	QPSK	1	1	21.58	21.50	21.59	22.2	0.0	
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up	(dB)	
15	QPSK	1	1	21.52	21.56	21.47	22.2	0.0	
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up	(dB)	
10	QPSK	1	1	21.53	21.51	21.49	22.2	0.0	

Part27O n78 Ant4 DS13									
BW	Modulat	RB Size	RB Offset	Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.	Tune-up limit	MPR	
				Channel		650000			
				Frequency (MHz)		3750			
100	1/2 BPSK	1	1		17.69				
100	1/2 BPSK	1	137		17.72		18.6	0.0	
100	1/2 BPSK	1	271		17.77				
100	1/2 BPSK	135	0		17.71		18.6	0.0	
100	1/2 BPSK	135	69		17.74		18.6	0.0	
100	1/2 BPSK	135	138		17.78				
100	1/2 BPSK	270	0		17.74		18.6	0.0	
100	QPSK	1	1		17.84				
100	QPSK	1	137		17.77		18.6	0.0	
100	QPSK	1	271		17.70				
100	QPSK	135	0		17.78		18.6	0.0	
100	QPSK	135	69		17.80		18.6	0.0	
100	QPSK	135	138		17.77				
100	QPSK	270	0		17.78		18.6	0.0	
100	16QAM	1	1		17.67		18.6	0.0	
100	64QAM	1	1		17.74		18.6	0.0	
100	256QAM	1	1		17.69		18.6	0.0	
				Channel		649668	650000	650334	
				Frequency (MHz)		3745.02	3750	3755.01	
90	QPSK	1	1	17.72	17.78	17.75	18.6	0.0	
				Channel		649334	650000	650668	
				Frequency (MHz)		3740.01	3750	3760.02	
80	QPSK	1	1	17.6	17.72	17.72	18.6	0.0	
				Channel		649000	650000	651000	
				Frequency (MHz)		3735	3750	3765	
70	QPSK	1	1	17.61	17.70	17.71	18.6	0.0	
				Channel		648668	650000	651334	
				Frequency (MHz)		3730.02	3750	3770.01	
60	QPSK	1	1	17.62	17.68	17.67	18.6	0.0	
				Channel		648334	650000	651668	
				Frequency (MHz)		3725.01	3750	3775.02	
50	QPSK	1	1	17.63	17.67	17.63	18.6	0.0	
				Channel		648000	650000	652000	
				Frequency (MHz)		3720	3750	3760	
40	QPSK	1	1	17.65	17.66	17.65	18.6	0.0	
				Channel		647668	650000	652334	
				Frequency (MHz)		3715.02	3750	3785.01	
30	QPSK	1	1	17.65	17.67	17.70	18.6	0.0	
				Channel		647500	650000	652500	
				Frequency (MHz)		3712.5	3750	3787.5	
25	QPSK	1	1	17.63	17.73	17.66	18.6	0.0	
				Channel		647334	650000	652668	
				Frequency (MHz)		6470.01	3750	3790.02	
20	QPSK	1	1	17.60	17.74	17.70	18.6	0.0	
				Channel		647168	650000	652834	
				Frequency (MHz)		64707.52	3750	3792.51	
15	QPSK	1	1	17.70	17.64	17.63	18.6	0.0	
				Channel		647000	650000	653000	
				Frequency (MHz)		3705	3750	3795	
10	QPSK	1	1	17.67	17.69	17.65	18.6	0.0	

Part27Q n78 Ant4 DSI3								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				633334	3500.01			
Frequency (MHz)					17.94			
100	1/2 BPSK	1	1		17.94			
100	1/2 BPSK	1	137		17.96		18.6	0.0
100	1/2 BPSK	1	271		17.91			
100	1/2 BPSK	135	0		17.86		18.6	0.0
100	1/2 BPSK	135	69		17.94		18.6	0.0
100	1/2 BPSK	135	138		17.93		18.6	0.0
100	1/2 BPSK	270	0		17.90			
100	QPSK	1	1		18.09			
100	QPSK	1	137		17.94		18.6	0.0
100	QPSK	1	271		17.92			
100	QPSK	135	0		17.92		18.6	0.0
100	QPSK	135	69		18.00		18.6	0.0
100	QPSK	135	138		17.91		18.6	0.0
100	QPSK	270	0		18.03			
100	16QAM	1	1		17.83		18.6	0.0
100	64QAM	1	1		17.97		18.6	0.0
100	256QAM	1	1		17.88		18.6	0.0
Channel				633000	633334	633668	tune up	MPR (dB)
Frequency (MHz)				3498	3500.01	3505.02		
90	QPSK	1	1	17.88	17.86	17.92	18.6	0.0
Channel				632668	633334	634000	tune up	MPR (dB)
Frequency (MHz)				3490.02	3500.01	3510		
80	QPSK	1	1	17.88	17.87	17.89	18.6	0.0
Channel				632334	633334	634334	tune up	MPR (dB)
Frequency (MHz)				3485.01	3500.01	3515.01		
70	QPSK	1	1	17.81	17.86	17.91	18.6	0.0
Channel				632000	633334	634668	tune up	MPR (dB)
Frequency (MHz)				3480	3500.01	3520.02		
60	QPSK	1	1	17.82	17.87	17.84	18.6	0.0
Channel				631668	633334	635000	tune up	MPR (dB)
Frequency (MHz)				3475.02	3500.01	3525		
50	QPSK	1	1	17.88	17.91	17.83	18.6	0.0
Channel				631334	633334	635334	tune up	MPR (dB)
Frequency (MHz)				3470.01	3500.01	3530.01		
40	QPSK	1	1	17.82	17.86	17.86	18.6	0.0
Channel				631000	633334	635668	tune up	MPR (dB)
Frequency (MHz)				3465	3500.01	3535.02		
30	QPSK	1	1	17.84	17.86	17.89	18.6	0.0
Channel				630834	633334	635834	tune up	MPR (dB)
Frequency (MHz)				3462.51	3500.01	3537.51		
25	QPSK	1	1	17.82	17.91	17.83	18.6	0.0
Channel				630568	633334	636000	tune up	MPR (dB)
Frequency (MHz)				3460.02	3500.01	3540		
20	QPSK	1	1	17.79	17.93	17.86	18.6	0.0
Channel				630500	633334	636168	tune up	MPR (dB)
Frequency (MHz)				3457.5	3500.01	3542.52		
15	QPSK	1	1	17.87	17.93	17.81	18.6	0.0
Channel				630334	633334	636334	tune up	MPR (dB)
Frequency (MHz)				3455.01	3500.01	3545.01		
10	QPSK	1	1	17.83	17.94	17.83	18.6	0.0

Part27Q n78 PC2 Ant4 DSI3								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				633334	3500.01			
Frequency (MHz)					20.94			
100	1/2 BPSK	1	1		20.94			
100	1/2 BPSK	1	137		21.01		21.6	0.0
100	1/2 BPSK	1	271		20.87			
100	1/2 BPSK	135	0		20.81		21.6	0.0
100	1/2 BPSK	135	69		21.00		21.6	0.0
100	1/2 BPSK	135	138		20.90		21.6	0.0
100	1/2 BPSK	270	0		20.91			
100	QPSK	1	1		21.15			
100	QPSK	1	137		20.93		21.6	0.0
100	QPSK	1	271		20.90			
100	QPSK	135	0		20.97		21.6	0.0
100	QPSK	135	69		21.04		21.6	0.0
100	QPSK	135	138		20.90		21.6	0.0
100	QPSK	270	0		20.98			
100	16QAM	1	1		20.84		21.6	0.0
100	64QAM	1	1		20.98		21.6	0.0
100	256QAM	1	1		20.92		21.6	0.0
Channel				633000	633334	633668	tune up	MPR (dB)
Frequency (MHz)				3495	3500.01	3505.02		
90	QPSK	1	1	21.01	20.86	20.69	21.6	0.0
Channel				632668	633334	634000	tune up	MPR (dB)
Frequency (MHz)				3490.02	3500.01	3510		
80	QPSK	1	1	21.09	20.65	20.70	21.6	0.0
Channel				632334	633334	634334	tune up	MPR (dB)
Frequency (MHz)				3485.01	3500.01	3515.01		
70	QPSK	1	1	21.05	20.64	20.69	21.6	0.0
Channel				632000	633334	634668	tune up	MPR (dB)
Frequency (MHz)				3480	3500.01	3520.02		
60	QPSK	1	1	21.07	20.69	20.72	21.6	0.0
Channel				631668	633334	635000	tune up	MPR (dB)
Frequency (MHz)				3475.02	3500.01	3525		
50	QPSK	1	1	21.10	20.73	20.70	21.6	0.0
Channel				631334	633334	635334	tune up	MPR (dB)
Frequency (MHz)				3470.01	3500.01	3530.01		
40	QPSK	1	1	21.02	20.68	20.67	21.6	0.0
Channel				631000	633334	635668	tune up	MPR (dB)
Frequency (MHz)				3465	3500.01	3535.02		
30	QPSK	1	1	21.06	20.65	20.66	21.6	0.0
Channel				630834	633334	635834	tune up	MPR (dB)
Frequency (MHz)				3462.51	3500.01	3537.51		
25	QPSK	1	1	21.07	20.65	20.66	21.6	0.0
Channel				630568	633334	636000	tune up	MPR (dB)
Frequency (MHz)				3460.02	3500.01	3540		
20	QPSK	1	1	21.05	20.66	20.72	21.6	0.0
Channel				630500	633334	636168	tune up	MPR (dB)
Frequency (MHz)				3457.5	3500.01	3542.52		
15	QPSK	1	1	21.07	20.69	20.74	21.6	0.0
Channel				630334	633334	636334	tune up	MPR (dB)
Frequency (MHz)				3455.01	3500.01	3545.01		
10	QPSK	1	1	21.01	20.65	20.74	21.6	0.0

n38 Ant7 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	18.80	18.95	19.02		20.2	0.0
40	1/2 BPSK	1	53	18.93	19.00	18.92			
40	1/2 BPSK	1	104	18.90	19.04	19.02			
40	1/2 BPSK	50	0	18.91	19.00	18.98		20.2	0.0
40	1/2 BPSK	50	28	18.91	19.01	18.99		20.2	0.0
40	1/2 BPSK	50	56	18.83	19.05	19.01		20.2	0.0
40	1/2 BPSK	100	0	18.87	19.03	19.02			
40	QPSK	1	1	18.89	19.10	18.92			
40	QPSK	1	53	18.92	18.97	18.96		20.2	0.0
40	QPSK	1	104	18.86	19.00	18.93			
40	QPSK	50	0	18.90	18.95	18.92		20.2	0.0
40	QPSK	50	28	18.86	18.99	18.93		20.2	0.0
40	QPSK	50	56	18.92	18.90	18.92			
40	QPSK	100	0	18.85	18.97	18.96		20.2	0.0
40	16QAM	1	1	18.80	18.89	18.88		20.2	0.0
40	64QAM	1	1	18.90	18.94	18.96		20.2	0.0
40	256QAM	1	1	17.36	17.31	17.39		18.7	1.5
Channel				517002	519000	520998	tune-up limit	MPR (dB)	
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	18.78	19.01	18.82		20.2	0.0
Channel				516504	519000	521496	tune-up limit	MPR (dB)	
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	18.77	18.97	18.83		20.2	0.0
Channel				516000	519000	522000	tune-up limit	MPR (dB)	
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	18.81	18.98	18.79		20.2	0.0
Channel				515502	519000	522498	tune-up limit	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	18.76	19.01	18.79		20.2	0.0
Channel				515004	519000	522996	tune-up limit	MPR (dB)	
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	18.77	18.99	18.84		20.2	0.0

n41 Ant7 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	18.45	18.51	18.43		20.0	0.0
100	1/2 BPSK	1	137	18.51	18.59	18.37			
100	1/2 BPSK	1	271	18.49	18.60	18.37			
100	1/2 BPSK	135	0	18.49	18.58	18.46		20.0	0.0
100	1/2 BPSK	135	69	18.50	18.51	18.46		20.0	0.0
100	1/2 BPSK	135	138	18.47	18.58	18.47		20.0	0.0
100	1/2 BPSK	270	0	18.52	18.53	18.41			
100	QPSK	1	1	18.53	18.68	18.46			
100	QPSK	1	137	18.50	18.55	18.38		20.0	0.0
100	QPSK	1	271	18.47	18.56	18.46			
100	QPSK	135	0	18.48	18.53	18.41		20.0	0.0
100	QPSK	135	69	18.50	18.55	18.37		20.0	0.0
100	QPSK	135	138	18.50	18.59	18.40			
100	QPSK	270	0	18.52	18.53	18.42		20.0	0.0
100	16QAM	1	1	18.51	18.55	18.38		20.0	0.0
100	64QAM	1	1	18.46	18.56	18.39		20.0	0.0
100	256QAM	1	1	18.51	18.60	18.46		19.0	1.0
Channel				508200	518598	528996	tune-up limit	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	18.44	18.62	18.41		20.0	0.0
Channel				507204	518598	529998	tune-up limit	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	18.39	18.53	18.36		20.0	0.0
Channel				506202	518598	531000	tune-up limit	MPR (dB)	
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	18.42	18.51	18.36		20.0	0.0
Channel				505200	518598	531996	tune-up limit	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	18.46	18.56	18.38		20.0	0.0
Channel				504204	518598	532998	tune-up limit	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	18.45	18.60	18.30		20.0	0.0
Channel				503700	518598	533496	tune-up limit	MPR (dB)	
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	18.43	18.59	18.38		20.0	0.0
Channel				503202	518598	534000	tune-up limit	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	18.48	18.59	18.32		20.0	0.0
Channel				502704	518598	534498	tune-up limit	MPR (dB)	
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	18.39	18.64	18.39		20.0	0.0
Channel				502200	518598	534996	tune-up limit	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	18.47	18.58	18.30		20.0	0.0
Channel				501702	518598	535500	tune-up limit	MPR (dB)	
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	18.44	18.54	18.33		20.0	0.0
Channel				501204	518598	535998	tune-up limit	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	18.48	18.55	18.39		20.0	0.0
Channel				500700	518598	536496	tune-up limit	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	18.45	18.59	18.30		20.0	0.0
Channel				500202	518598	537000	tune-up limit	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	18.38	18.63	18.40		20.0	0.0

Part27Q n78 PC2 Ant10 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune up limit (dBm)	MPR (dB)	
Channel				633334			27.0	0.0	
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1	26.39			27.0	0.0	
100	1/2 BPSK	1	137	26.40					
100	1/2 BPSK	1	271	26.48			27.0	0.0	
100	1/2 BPSK	135	0	26.32					
100	1/2 BPSK	135	69	26.46			27.0	0.0	
100	1/2 BPSK	135	138	26.41					
100	1/2 BPSK	270	0	26.40			27.0	0.0	
100	QPSK	1	1	26.50					
100	QPSK	1	137	26.52			27.0	0.0	
100	QPSK	1	271	26.43					
100	QPSK	135	0	26.48			27.0	0.0	
100	QPSK	135	69	26.36					
100	QPSK	135	138	26.52			27.0	0.0	
100	QPSK	270	0	26.51					
100	16QAM	1	1	26.40			27.0	0.0	
100	64QAM	1	1	26.10					
100	256QAM	1	1	24.01			24.5	2.5	
Channel				633000	633334	633668	Tune up limit	MPR	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	26.52	26.50	26.53	27.0	0.0	
Channel				632668	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510	Tune up limit	MPR	
80	QPSK	1	1	26.48	26.52	26.54		27.0	
Channel				632314	633334	634334	Tune up limit		
Frequency (MHz)				3485.01	3500.01	3515.01	MPR		
70	QPSK	1	1	26.49	26.47	26.47	Tune up limit	27.0	
Channel				632000	633334	634668			
Frequency (MHz)				3480	3500.01	3520.02	Tune up limit	MPR	
60	QPSK	1	1	26.54	26.53	26.49		27.0	
Channel				631668	633334	635000	Tune up limit		
Frequency (MHz)				3475.02	3500.01	3525	MPR		
50	QPSK	1	1	26.54	26.46	26.52	Tune up limit	27.0	
Channel				631334	633334	635334			
Frequency (MHz)				3470.01	3500.01	3530.01	Tune up limit	MPR	
40	QPSK	1	1	26.54	26.48	26.47		27.0	
Channel				631000	633334	635668	Tune up limit		
Frequency (MHz)				3465	3500.01	3535.02	MPR		
30	QPSK	1	1	26.46	26.52	26.45	Tune up limit	27.0	
Channel				630834	633334	635834			
Frequency (MHz)				3462.51	3500.01	3537.51	Tune up limit	MPR	
25	QPSK	1	1	26.55	26.53	26.48		27.0	
Channel				630500	633334	636000	Tune up limit		
Frequency (MHz)				3460.02	3500.01	3540	MPR		
20	QPSK	1	1	26.45	26.48	26.49	Tune up limit	27.0	
Channel				630500	633334	636168			
Frequency (MHz)				3457.5	3500.01	3542.52	Tune up limit	MPR	
15	QPSK	1	1	26.52	26.48	26.53		27.0	
Channel				630334	633334	636334	Tune up limit		
Frequency (MHz)				3455.01	3500.01	3545.01	MPR		
10	QPSK	1	1	26.47	26.54	26.46	Tune up limit	27.0	

Reduced Power Mode for DS14 Main PA

n5 Ant0 DS14									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				166800	167300	167800			
Frequency (MHz)				834	836.5	839			
20	1/2 BPSK	1	1	25.29	25.29	25.29			
20	1/2 BPSK	1	53	25.31	25.28	25.24	25.7	0.0	
20	1/2 BPSK	1	104	25.11	25.13	25.14			
20	1/2 BPSK	50	0	24.69	24.70	24.63	25.2	0.5	
20	1/2 BPSK	50	28	25.28	25.32	25.26	25.7	0.0	
20	1/2 BPSK	50	56	24.62	24.72	24.63			
20	1/2 BPSK	100	0	24.82	24.77	24.82	25.2	0.5	
20	QPSK	1	1	25.29	25.33	25.27			
20	QPSK	1	53	25.32	25.32	25.24	25.7	0.0	
20	QPSK	1	104	25.13	25.09	25.09			
20	QPSK	50	0	24.23	24.27	24.26	24.7	1.0	
20	QPSK	50	28	25.20	25.23	25.21	25.7	0.0	
20	QPSK	50	56	24.15	24.08	24.08			
20	QPSK	100	0	24.26	24.29	24.28	24.7	1.0	
20	16QAM	1	1	24.16	24.15	24.20	24.7	1.0	
20	64QAM	1	1	22.63	22.62	22.60	23.2	2.5	
20	256QAM	1	1	20.49	20.51	20.56	21.2	4.5	
Channel				166300	167300	168300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				831.5	836.5	841.5			
15	QPSK	1	1	25.24	25.19	25.17	25.7	0.0	
Channel				165800	167300	168800	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				829	836.5	844			
10	QPSK	1	1	25.22	25.22	25.13	25.7	0.0	
Channel				165300	167300	169300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				826.5	836.5	846.5			
5	QPSK	1	1	25.14	25.26	25.21	25.7	0.0	

n12 Ant0 DS14									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				141300	141500	141700			
Frequency (MHz)				706.5	707.5	708.5			
15	1/2 BPSK	1	1	25.39	25.39	25.48			
15	1/2 BPSK	1	40	25.41	25.43	25.38	25.7	0.0	
15	1/2 BPSK	1	77	25.32	25.35	25.29			
15	1/2 BPSK	36	0	24.88	24.83	24.89	25.2	0.5	
15	1/2 BPSK	36	22	25.43	25.39	25.45	25.7	0.0	
15	1/2 BPSK	36	43	24.84	24.80	24.79			
15	1/2 BPSK	75	0	24.93	24.99	24.90	25.2	0.5	
15	QPSK	1	1	25.47	25.52	25.48			
15	QPSK	1	40	25.48	25.43	25.38	25.7	0.0	
15	QPSK	1	77	25.33	25.24	25.26			
15	QPSK	36	0	24.37	24.46	24.43	24.7	1.0	
15	QPSK	36	22	25.44	25.47	25.43	25.7	0.0	
15	QPSK	36	43	24.33	24.27	24.23			
15	QPSK	75	0	24.48	24.52	24.45	24.7	1.0	
15	16QAM	1	1	24.26	24.37	24.32	24.7	1.0	
15	64QAM	1	1	22.84	22.73	22.82	23.2	2.5	
15	256QAM	1	1	20.71	20.73	20.66	21.2	4.5	
Channel				140800	141500	142200	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				704	707.5	711			
10	QPSK	1	1	25.41	25.46	25.43	25.7	0.0	
Channel				140300	141500	142700	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				701.5	707.5	713.5			
5	QPSK	1	1	25.32	25.43	25.40	25.7	0.0	

n26 Ant0 DS14									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				164800	166300	167800			
Frequency (MHz)				824	831.5	839			
20	1/2 BPSK	1	1	25.34	25.35	25.33			
20	1/2 BPSK	1	53	25.25	25.30	25.28	25.7	0.0	
20	1/2 BPSK	1	104	25.19	25.11	25.09			
20	1/2 BPSK	50	0	24.74	24.66	24.76	25.2	0.5	
20	1/2 BPSK	50	28	25.29	25.27	25.36	25.7	0.0	
20	1/2 BPSK	50	56	24.68	24.74	24.73			
20	1/2 BPSK	100	0	24.78	24.79	24.79	25.2	0.5	
20	QPSK	1	1	25.35	25.39	25.37			
20	QPSK	1	53	25.36	25.33	25.27	25.7	0.0	
20	QPSK	1	104	25.14	25.14	25.09			
20	QPSK	50	0	24.32	24.28	24.22	24.7	1.0	
20	QPSK	50	28	25.29	25.34	25.31	25.7	0.0	
20	QPSK	50	56	24.05	24.09	24.09			
20	QPSK	100	0	24.35	24.36	24.29	24.7	1.0	
20	16QAM	1	1	24.15	24.19	24.11	24.7	1.0	
20	64QAM	1	1	22.59	22.59	22.58	23.2	2.5	
20	256QAM	1	1	20.48	20.46	20.53	21.2	4.5	
Channel				164300	166300	168300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				821.5	831.5	841.5			
15	QPSK	1	1	25.22	25.24	25.23	25.7	0.0	
Channel				163800	166300	168800	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				819	831.5	844			
10	QPSK	1	1	25.30	25.32	25.27	25.7	0.0	
Channel				163300	166300	169300	↑ tune-up limit	MPR (dB)	
Frequency (MHz)				816.5	831.5	846.5			
5	QPSK	1	1	25.24	25.33	25.33	25.7	0.0	

n71 Ant0 DSI4								
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)
Channel				136100			25.7	0.0
Frequency (MHz)				680.5				
35	1/2 BPSK	1	1	25.24				
35	1/2 BPSK	1	90	25.14				
35	1/2 BPSK	1	186	25.10			25.2	0.5
35	1/2 BPSK	90	0	24.60				
35	1/2 BPSK	90	45	25.20				
35	1/2 BPSK	90	90	24.58				
35	1/2 BPSK	180	0	24.70			25.7	0.0
35	QPSK	1	1	25.25				
35	QPSK	1	90	25.16				
35	QPSK	1	186	25.00				
35	QPSK	90	0	24.16			24.7	1.0
35	QPSK	90	45	25.21				
35	QPSK	90	90	24.06				
35	QPSK	180	0	24.23				
35	16QAM	1	1	24.04			24.7	1.0
35	64QAM	1	1	22.54				
35	256QAM	1	1	20.48				
Channel				135600	136100	136600	25.7	0.0
Frequency (MHz)				678	680.5	683		
30	QPSK	1	1	25.14	25.19	25.10		
Channel				135100	136100	137100	25.7	MPR (dB)
Frequency (MHz)				675.5	680.5	685.5		
25	QPSK	1	1	25.12	25.10	25.18		
Channel				134600	136100	137600	25.7	MPR (dB)
Frequency (MHz)				673	680.5	688		
20	QPSK	1	1	25.18	25.13	25.15		
Channel				134100	136100	138100	25.7	MPR (dB)
Frequency (MHz)				670.5	680.5	690.5		
15	QPSK	1	1	25.10	25.14	25.17		
Channel				133600	136100	138600	25.7	MPR (dB)
Frequency (MHz)				668	680.5	693		
10	QPSK	1	1	25.14	25.15	25.14		
Channel				133100	136100	139100	25.7	MPR (dB)
Frequency (MHz)				665.5	680.5	695.5		
5	QPSK	1	1	25.15	25.15	25.08		

Part27Q n78 Ant4 DSI4								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				633334	3500.01			
Frequency (MHz)					3500.01			
100	1/2 BPSK	1	1		17.94			
100	1/2 BPSK	1	137		17.96		18.6	0.0
100	1/2 BPSK	1	271		17.91			
100	1/2 BPSK	135	0		17.86		18.6	0.0
100	1/2 BPSK	135	69		17.94		18.6	0.0
100	1/2 BPSK	135	138		17.93		18.6	0.0
100	1/2 BPSK	270	0		17.90			
100	QPSK	1	1		18.09			
100	QPSK	1	137		17.94		18.6	0.0
100	QPSK	1	271		17.92			
100	QPSK	135	0		17.92		18.6	0.0
100	QPSK	135	69		18.00		18.6	0.0
100	QPSK	135	138		17.91		18.6	0.0
100	QPSK	270	0		18.03			
100	16QAM	1	1		17.83		18.6	0.0
100	64QAM	1	1		17.97		18.6	0.0
100	256QAM	1	1		17.88		18.6	0.0
Channel				633000	633334	633668	tune up	MPR
Frequency (MHz)				3498	3500.01	3505.02		
90	QPSK	1	1	17.88	17.86	17.92	18.6	0.0
Channel				632668	633334	634000	tune up	MPR
Frequency (MHz)				3490.02	3500.01	3510		
80	QPSK	1	1	17.88	17.87	17.89	18.6	0.0
Channel				632334	633334	634334	tune up	MPR
Frequency (MHz)				3485.01	3500.01	3515.01		
70	QPSK	1	1	17.81	17.86	17.91	18.6	0.0
Channel				632000	633334	634668	tune up	MPR
Frequency (MHz)				3480	3500.01	3520.02		
60	QPSK	1	1	17.82	17.87	17.84	18.6	0.0
Channel				631668	633334	635000	tune up	MPR
Frequency (MHz)				3475.02	3500.01	3525		
50	QPSK	1	1	17.88	17.91	17.83	18.6	0.0
Channel				631334	633334	635334	tune up	MPR
Frequency (MHz)				3470.01	3500.01	3530.01		
40	QPSK	1	1	17.82	17.86	17.86	18.6	0.0
Channel				631000	633334	635668	tune up	MPR
Frequency (MHz)				3465	3500.01	3535.02		
30	QPSK	1	1	17.84	17.86	17.89	18.6	0.0
Channel				630834	633334	635834	tune up	MPR
Frequency (MHz)				3462.51	3500.01	3537.51		
25	QPSK	1	1	17.82	17.91	17.83	18.6	0.0
Channel				630568	633334	636000	tune up	MPR
Frequency (MHz)				3460.02	3500.01	3540		
20	QPSK	1	1	17.79	17.93	17.86	18.6	0.0
Channel				630500	633334	636168	tune up	MPR
Frequency (MHz)				3457.5	3500.01	3542.52		
15	QPSK	1	1	17.87	17.93	17.81	18.6	0.0
Channel				630334	633334	636334	tune up	MPR
Frequency (MHz)				3455.01	3500.01	3545.01		
10	QPSK	1	1	17.83	17.94	17.83	18.6	0.0

Part27Q n78 PC2 Ant4 DSI4								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				633334	3500.01			
Frequency (MHz)					3500.01			
100	1/2 BPSK	1	1		20.94			
100	1/2 BPSK	1	137		21.01		21.6	0.0
100	1/2 BPSK	1	271		20.87			
100	1/2 BPSK	135	0		20.81		21.6	0.0
100	1/2 BPSK	135	69		21.00		21.6	0.0
100	1/2 BPSK	135	138		20.90		21.6	0.0
100	1/2 BPSK	270	0		20.91			
100	QPSK	1	1		21.15			
100	QPSK	1	137		20.93		21.6	0.0
100	QPSK	1	271		20.90			
100	QPSK	135	0		20.97		21.6	0.0
100	QPSK	135	69		21.04		21.6	0.0
100	QPSK	135	138		20.90		21.6	0.0
100	QPSK	270	0		20.98			
100	16QAM	1	1		20.84		21.6	0.0
100	64QAM	1	1		20.98		21.6	0.0
100	256QAM	1	1		20.92		21.6	0.0
Channel				633000	633334	633668	tune up	MPR
Frequency (MHz)				3495	3500.01	3505.02		
90	QPSK	1	1	21.01	20.86	20.69	21.6	0.0
Channel				632668	633334	634000	tune up	MPR
Frequency (MHz)				3490.02	3500.01	3510		
80	QPSK	1	1	21.09	20.65	20.70	21.6	0.0
Channel				632334	633334	634334	tune up	MPR
Frequency (MHz)				3485.01	3500.01	3515.01		
70	QPSK	1	1	21.05	20.64	20.69	21.6	0.0
Channel				632000	633334	634668	tune up	MPR
Frequency (MHz)				3480	3500.01	3520.02		
60	QPSK	1	1	21.07	20.69	20.72	21.6	0.0
Channel				631668	633334	635000	tune up	MPR
Frequency (MHz)				3475.02	3500.01	3525		
50	QPSK	1	1	21.10	20.73	20.70	21.6	0.0
Channel				631334	633334	635334	tune up	MPR
Frequency (MHz)				3470.01	3500.01	3530.01		
40	QPSK	1	1	21.02	20.68	20.67	21.6	0.0
Channel				631000	633334	635668	tune up	MPR
Frequency (MHz)				3465	3500.01	3535.02		
30	QPSK	1	1	21.06	20.65	20.66	21.6	0.0
Channel				630834	633334	635834	tune up	MPR
Frequency (MHz)				3462.51	3500.01	3537.51		
25	QPSK	1	1	21.07	20.65	20.66	21.6	0.0
Channel				630568	633334	636000	tune up	MPR
Frequency (MHz)				3460.02	3500.01	3540		
20	QPSK	1	1	21.05	20.66	20.72	21.6	0.0
Channel				630500	633334	636168	tune up	MPR
Frequency (MHz)				3457.5	3500.01	3542.52		
15	QPSK	1	1	21.07	20.69	20.74	21.6	0.0
Channel				630334	633334	636334	tune up	MPR
Frequency (MHz)				3455.01	3500.01	3545.01		
10	QPSK	1	1	21.01	20.65	20.74	21.6	0.0

Part27Q n78 Ant6 DSI4									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334		3500.01			
Frequency (MHz)						22.17			
100	1/2 BPSK	1	1			22.17			
100	1/2 BPSK	1	137			22.10		23.7	0.0
100	1/2 BPSK	1	271			22.15			
100	1/2 BPSK	135	0			22.12		23.7	0.0
100	1/2 BPSK	135	69			22.02		23.7	0.0
100	1/2 BPSK	135	138			22.08			
100	1/2 BPSK	270	0			22.14		23.7	0.0
100	QPSK	1	1			22.23			
100	QPSK	1	137			21.98		23.7	0.0
100	QPSK	1	271			22.10			
100	QPSK	135	0			22.10		23.7	0.0
100	QPSK	135	69			22.20		23.7	0.0
100	QPSK	135	138			22.10			
100	QPSK	270	0			22.10		23.7	0.0
100	16QAM	1	1			21.77		23.7	0.0
100	64QAM	1	1			21.27		23.2	0.5
100	256QAM	1	1			21.32		21.2	2.5
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	22.19	22.09	22.18	23.7	0.0	
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	22.11	22.07	22.15	23.7	0.0	
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	22.11	22.10	22.08	23.7	0.0	
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	22.16	22.14	22.15	23.7	0.0	
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	22.18	22.13	22.09	23.7	0.0	
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	22.10	22.18	22.18	23.7	0.0	
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	22.11	22.12	22.13	23.7	0.0	
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	22.10	22.15	22.12	23.7	0.0	
Channel				630668	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	22.12	22.13	22.12	23.7	0.0	
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	22.13	22.09	22.15	23.7	0.0	
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	22.18	22.14	22.09	23.7	0.0	

Part27Q n78 PC2 Ant6 DSI4									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334		3500.01			
Frequency (MHz)						23.87			
100	1/2 BPSK	1	1			23.87			
100	1/2 BPSK	1	137			23.88		25.5	0.0
100	1/2 BPSK	1	271			23.98			
100	1/2 BPSK	135	0			23.06		25.0	0.5
100	1/2 BPSK	135	69			23.54		25.5	0.0
100	1/2 BPSK	135	138			23.36			
100	1/2 BPSK	270	0			23.46		25.0	0.5
100	QPSK	1	1			24.20			
100	QPSK	1	137			23.76		25.5	0.0
100	QPSK	1	271			24.05			
100	QPSK	135	0			22.71		24.5	1.0
100	QPSK	135	69			24.09		25.5	0.0
100	QPSK	135	138			22.89			
100	QPSK	270	0			23.17		24.5	1.0
100	16QAM	1	1			22.71		24.5	1.0
100	64QAM	1	1			21.44		23.0	2.5
100	256QAM	1	1			19.49		21.0	4.5
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	24.12	24.14	24.05	25.5	0.0	
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	24.04	24.14	24.05	25.5	0.0	
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	24.07	24.11	24.06	25.5	0.0	
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	24.10	24.06	24.08	25.5	0.0	
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	24.09	24.12	24.04	25.5	0.0	
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	24.07	24.11	24.04	25.5	0.0	
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	24.09	24.16	24.12	25.5	0.0	
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	24.11	24.05	24.06	25.5	0.0	
Channel				630668	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	24.15	24.16	24.11	25.5	0.0	
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	24.12	24.08	24.11	25.5	0.0	
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	24.10	24.15	24.10	25.5	0.0	

n38 Ant7 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	18.80	18.95	19.02	20.2	0.0	
40	1/2 BPSK	1	53	18.93	19.00	18.92			
40	1/2 BPSK	1	104	18.90	19.04	19.02			
40	1/2 BPSK	50	0	18.91	19.00	18.98	20.2	0.0	
40	1/2 BPSK	50	28	18.91	19.01	18.99	20.2	0.0	
40	1/2 BPSK	50	56	18.83	19.05	19.01	20.2	0.0	
40	1/2 BPSK	100	0	18.87	19.03	19.02			
40	QPSK	1	1	18.89	19.10	18.92	20.2	0.0	
40	QPSK	1	53	18.92	18.97	18.96			
40	QPSK	1	104	18.86	19.00	18.93			
40	QPSK	50	0	18.90	18.95	18.92	20.2	0.0	
40	QPSK	50	28	18.86	18.99	18.93	20.2	0.0	
40	QPSK	50	56	18.92	18.90	18.92	20.2	0.0	
40	QPSK	100	0	18.85	18.97	18.96			
40	16QAM	1	1	18.80	18.89	18.88	20.2	0.0	
40	64QAM	1	1	18.90	18.94	18.96	20.2	0.0	
40	256QAM	1	1	17.36	17.31	17.39	18.7	1.5	
Channel				517002	519000	520998	tune-up limit	MPR (dB)	
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	18.78	19.01	18.82	20.2	0.0	
Channel				516504	519000	521496	tune-up limit	MPR (dB)	
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	18.77	18.97	18.83	20.2	0.0	
Channel				516000	519000	522000	tune-up limit	MPR (dB)	
Frequency (MHz)				2560	2595	2610			
20	QPSK	1	1	18.81	18.98	18.79	20.2	0.0	
Channel				515502	519000	522498	tune-up limit	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	18.76	19.01	18.79	20.2	0.0	
Channel				515004	519000	522996	tune-up limit	MPR (dB)	
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	18.77	18.99	18.84	20.2	0.0	

n41 Ant7 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	18.45	18.51	18.43	20.0	0.0	
100	1/2 BPSK	1	137	18.51	18.59	18.37			
100	1/2 BPSK	1	271	18.49	18.60	18.37			
100	1/2 BPSK	135	0	18.49	18.58	18.46	20.0	0.0	
100	1/2 BPSK	135	69	18.50	18.51	18.46	20.0	0.0	
100	1/2 BPSK	135	138	18.47	18.58	18.47	20.0	0.0	
100	1/2 BPSK	270	0	18.52	18.53	18.41			
100	QPSK	1	1	18.53	18.68	18.46	20.0	0.0	
100	QPSK	1	137	18.50	18.55	18.38			
100	QPSK	1	271	18.47	18.56	18.46			
100	QPSK	135	0	18.48	18.53	18.41	20.0	0.0	
100	QPSK	135	69	18.50	18.55	18.37	20.0	0.0	
100	QPSK	135	138	18.50	18.59	18.40	20.0	0.0	
100	QPSK	270	0	18.52	18.53	18.42	20.0	0.0	
100	16QAM	1	1	18.51	18.55	18.38	20.0	0.0	
100	64QAM	1	1	18.46	18.56	18.39	20.0	0.0	
100	256QAM	1	1	18.51	18.60	18.46	19.0	1.0	
Channel				508200	518598	528996	tune-up limit	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	18.44	18.62	18.41	20.0	0.0	
Channel				507204	518598	529998	tune-up limit	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	18.39	18.53	18.36	20.0	0.0	
Channel				506202	518598	531000	tune-up limit	MPR (dB)	
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	18.42	18.61	18.36	20.0	0.0	
Channel				505200	518598	531996	tune-up limit	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	18.46	18.56	18.38	20.0	0.0	
Channel				504204	518598	532998	tune-up limit	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	18.45	18.60	18.30	20.0	0.0	
Channel				503700	518598	533496	tune-up limit	MPR (dB)	
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	18.43	18.59	18.38	20.0	0.0	
Channel				503202	518598	534000	tune-up limit	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	18.48	18.59	18.32	20.0	0.0	
Channel				502704	518598	534498	tune-up limit	MPR (dB)	
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	18.39	18.64	18.39	20.0	0.0	
Channel				502200	518598	534996	tune-up limit	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	18.47	18.59	18.30	20.0	0.0	
Channel				501702	518598	535500	tune-up limit	MPR (dB)	
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	18.44	18.54	18.33	20.0	0.0	
Channel				501204	518598	535998	tune-up limit	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	18.48	18.55	18.39	20.0	0.0	
Channel				500700	518598	536496	tune-up limit	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	18.45	18.59	18.30	20.0	0.0	
Channel				500202	518598	537000	tune-up limit	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	18.38	18.63	18.40	20.0	0.0	

Part27Q n78 PC2 Ant10 DSI4									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334			29.0	0.0	
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1	27.29			29.0	0.0	
100	1/2 BPSK	1	137	27.38					
100	1/2 BPSK	1	271	27.33			28.5	0.5	
100	1/2 BPSK	135	0	27.01					
100	1/2 BPSK	135	69	27.38			29.0	0.0	
100	1/2 BPSK	135	138	27.04					
100	1/2 BPSK	270	0	26.94			28.5	0.5	
100	QPSK	1	1	27.47					
100	QPSK	1	137	27.45			29.0	0.0	
100	QPSK	1	271	27.30					
100	QPSK	135	0	26.37			28.0	1.0	
100	QPSK	135	69	27.31					
100	QPSK	135	138	26.43			28.0	1.0	
100	QPSK	270	0	26.51					
100	16QAM	1	1	26.34			28.0	1.0	
100	64QAM	1	1	24.96					
100	256QAM	1	1	24.53			24.5	4.5	
Channel				633000	633334	633668			
Frequency (MHz)				3486	3500.01	3505.02	29.0	0.0	
90	QPSK	1	1	27.40	27.34	27.37			
Channel				632668	633334	634000	29.0	0.0	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	27.32	27.40	27.36	29.0	0.0	
Channel				632314	633334	634334			
Frequency (MHz)				3485.01	3500.01	3515.01	29.0	0.0	
70	QPSK	1	1	27.32	27.43	27.36			
Channel				632000	633334	634668	29.0	0.0	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	27.33	27.42	27.33	29.0	0.0	
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525	29.0	0.0	
50	QPSK	1	1	27.40	27.36	27.41			
Channel				631334	633334	635334	29.0	0.0	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	27.42	27.37	27.42	29.0	0.0	
Channel				631000	633334	635668			
Frequency (MHz)				3465	3500.01	3535.02	29.0	0.0	
30	QPSK	1	1	27.37	27.41	27.40			
Channel				630834	633334	635834	29.0	0.0	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	27.38	27.37	27.37	29.0	0.0	
Channel				630568	633334	636000			
Frequency (MHz)				3460.02	3500.01	3540	29.0	0.0	
20	QPSK	1	1	27.32	27.40	27.35			
Channel				630500	633334	636168	29.0	0.0	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	27.37	27.43	27.32	29.0	0.0	
Channel				630384	633334	636342			
Frequency (MHz)				3455.01	3500.01	3545.01	29.0	0.0	
10	QPSK	1	1	27.37	27.38	27.43			

Reduced Power Mode for DSI5_Main PA

n5 Ant0 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				166800	167300	167800			
Frequency (MHz)				834	836.5	839			
20	1/2 BPSK	1	1	25.29	25.29	25.29			
20	1/2 BPSK	1	53	25.31	25.28	25.24	25.7	0.0	
20	1/2 BPSK	1	104	25.11	25.13	25.14			
20	1/2 BPSK	50	0	24.69	24.70	24.63	25.2	0.5	
20	1/2 BPSK	50	28	25.28	25.32	25.26	25.7	0.0	
20	1/2 BPSK	50	56	24.62	24.72	24.63			
20	1/2 BPSK	100	0	24.82	24.77	24.82	25.2	0.5	
20	QPSK	1	1	25.29	25.33	25.27			
20	QPSK	1	53	25.32	25.32	25.24	25.7	0.0	
20	QPSK	1	104	25.13	25.09	25.09			
20	QPSK	50	0	24.23	24.27	24.26	24.7	1.0	
20	QPSK	50	28	25.20	25.23	25.21	25.7	0.0	
20	QPSK	50	56	24.15	24.08	24.08			
20	QPSK	100	0	24.26	24.29	24.28	24.7	1.0	
20	16QAM	1	1	24.16	24.15	24.20	24.7	1.0	
20	64QAM	1	1	22.63	22.62	22.60	23.2	2.5	
20	256QAM	1	1	20.49	20.51	20.56	21.2	4.5	
Channel				166300	167300	168300	Turn-up limit	MPR	
Frequency (MHz)				831.5	836.5	841.5	(dB)		
15	QPSK	1	1	25.24	25.19	25.17	25.7	0.0	
Channel				165800	167300	168800	Turn-up limit	MPR	
Frequency (MHz)				829	836.5	844	(dB)		
10	QPSK	1	1	25.22	25.22	25.13	25.7	0.0	
Channel				165300	167300	169300	Turn-up limit	MPR	
Frequency (MHz)				826.5	836.5	846.5	(dB)		
5	QPSK	1	1	25.14	25.26	25.21	25.7	0.0	

n12 Ant0 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				141300	141500	141700			
Frequency (MHz)				706.5	707.5	708.5			
15	1/2 BPSK	1	1	25.39	25.39	25.48			
15	1/2 BPSK	1	40	25.41	25.43	25.38	25.7	0.0	
15	1/2 BPSK	1	77	25.32	25.35	25.29			
15	1/2 BPSK	36	0	24.88	24.83	24.89	25.2	0.5	
15	1/2 BPSK	36	22	25.43	25.39	25.45	25.7	0.0	
15	1/2 BPSK	36	43	24.84	24.80	24.79			
15	1/2 BPSK	75	0	24.93	24.99	24.90	25.2	0.5	
15	QPSK	1	1	25.47	25.52	25.48			
15	QPSK	1	40	25.48	25.43	25.38	25.7	0.0	
15	QPSK	1	77	25.33	25.24	25.26			
15	QPSK	36	0	24.37	24.46	24.43	24.7	1.0	
15	QPSK	36	22	25.44	25.47	25.43	25.7	0.0	
15	QPSK	36	43	24.33	24.27	24.23			
15	QPSK	75	0	24.48	24.52	24.45	24.7	1.0	
15	16QAM	1	1	24.26	24.37	24.32	24.7	1.0	
15	64QAM	1	1	22.84	22.73	22.82	23.2	2.5	
15	256QAM	1	1	20.71	20.73	20.66	21.2	4.5	
Channel				140800	141500	142200	Turn-up limit	MPR	
Frequency (MHz)				704	707.5	711	(dB)		
10	QPSK	1	1	25.41	25.46	25.43	25.7	0.0	
Channel				140300	141500	142700	Turn-up limit	MPR	
Frequency (MHz)				701.5	707.5	713.5	(dB)		
5	QPSK	1	1	25.32	25.43	25.40	25.7	0.0	

n26 Ant0 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				164800	166300	167800			
Frequency (MHz)				824	831.5	839			
20	1/2 BPSK	1	1	25.34	25.35	25.33			
20	1/2 BPSK	1	53	25.25	25.30	25.28	25.7	0.0	
20	1/2 BPSK	1	104	25.19	25.11	25.09			
20	1/2 BPSK	50	0	24.74	24.66	24.76	25.2	0.5	
20	1/2 BPSK	50	28	25.29	25.27	25.36	25.7	0.0	
20	1/2 BPSK	50	56	24.68	24.74	24.73			
20	1/2 BPSK	100	0	24.78	24.79	24.79	25.2	0.5	
20	QPSK	1	1	25.35	25.39	25.37			
20	QPSK	1	53	25.36	25.33	25.27	25.7	0.0	
20	QPSK	1	104	25.14	25.14	25.09			
20	QPSK	50	0	24.32	24.28	24.22	24.7	1.0	
20	QPSK	50	28	25.29	25.34	25.31	25.7	0.0	
20	QPSK	50	56	24.05	24.09	24.09			
20	QPSK	100	0	24.35	24.36	24.29	24.7	1.0	
20	16QAM	1	1	24.15	24.19	24.11	24.7	1.0	
20	64QAM	1	1	22.59	22.59	22.58	23.2	2.5	
20	256QAM	1	1	20.48	20.46	20.53	21.2	4.5	
Channel				164300	166300	168300	Turn-up limit	MPR	
Frequency (MHz)				821.5	831.5	841.5	(dB)		
15	QPSK	1	1	25.22	25.24	25.23	25.7	0.0	
Channel				163800	166300	168800	Turn-up limit	MPR	
Frequency (MHz)				819	831.5	844	(dB)		
10	QPSK	1	1	25.30	25.32	25.27	25.7	0.0	
Channel				163300	166300	169300	Turn-up limit	MPR	
Frequency (MHz)				816.5	831.5	846.5	(dB)		
5	QPSK	1	1	25.24	25.33	25.33	25.7	0.0	

n71 Ant0 DSI5								
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)
Channel				136100			25.7	0.0
Frequency (MHz)				680.5				
35	1/2 BPSK	1	1	25.24				
35	1/2 BPSK	1	90	25.14				
35	1/2 BPSK	1	186	25.10			25.2	0.5
35	1/2 BPSK	90	0	24.60				
35	1/2 BPSK	90	45	25.20				
35	1/2 BPSK	90	90	24.58				
35	1/2 BPSK	180	0	24.70			25.7	0.0
35	QPSK	1	1	25.25				
35	QPSK	1	90	25.16				
35	QPSK	1	186	25.00				
35	QPSK	90	0	24.16			24.7	1.0
35	QPSK	90	45	25.21				
35	QPSK	90	90	24.06				
35	QPSK	180	0	24.23				
35	16QAM	1	1	24.04			24.7	1.0
35	64QAM	1	1	22.54				
35	256QAM	1	1	20.48				
Channel				135600	136100	136600	25.7	0.0
Frequency (MHz)				678	680.5	683		
30	QPSK	1	1	25.14	25.19	25.10		
Channel				135100	136100	137100	25.7	MPR (dB)
Frequency (MHz)				675.5	680.5	685.5		
25	QPSK	1	1	25.12	25.10	25.18		
Channel				134600	136100	137600	25.7	MPR (dB)
Frequency (MHz)				673	680.5	688		
20	QPSK	1	1	25.18	25.13	25.15		
Channel				134100	136100	138100	25.7	MPR (dB)
Frequency (MHz)				670.5	680.5	690.5		
15	QPSK	1	1	25.10	25.14	25.17		
Channel				133600	136100	138600	25.7	MPR (dB)
Frequency (MHz)				668	680.5	693		
10	QPSK	1	1	25.14	25.15	25.14		
Channel				133100	136100	139100	25.7	MPR (dB)
Frequency (MHz)				665.5	680.5	695.5		
5	QPSK	1	1	25.15	25.15	25.08		

n5 Ant1 DSI5											
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)			
Channel				166800	167300	167800					
Frequency (MHz)				834	836.5	839					
20	1/2 BPSK	1	1	20.91	20.93	20.94	21.2	0.0			
20	1/2 BPSK	1	53	20.91	20.91	20.86					
20	1/2 BPSK	1	104	20.97	21.02	20.93					
20	1/2 BPSK	50	0	20.93	21.03	20.93	21.2	0.0			
20	1/2 BPSK	50	28	20.89	20.96	20.87	21.2	0.0			
20	1/2 BPSK	50	56	20.92	20.94	20.87	21.2	0.0			
20	1/2 BPSK	100	0	20.97	21.02	20.87	21.2	0.0			
20	QPSK	1	1	21.00	21.05	20.98					
20	QPSK	1	53	20.94	20.98	20.86					
20	QPSK	1	104	20.93	20.91	20.94	21.2	0.0			
20	QPSK	50	0	20.88	20.95	20.85					
20	QPSK	50	28	20.97	21.01	20.93					
20	QPSK	50	56	20.96	20.96	20.85	21.2	0.0			
20	QPSK	100	0	20.88	20.98	20.85					
20	16QAM	1	1	20.91	20.93	20.87	21.2	0.0			
20	64QAM	1	1	20.90	20.94	20.95	21.2	0.0			
20	256QAM	1	1	20.89	20.95	20.90	21.2	0.0			
Channel				168300	167300	168300					
Frequency (MHz)				831.5	836.5	841.5					
15	QPSK	1	1	20.98	21.01	20.94	21.2	0.0			
Channel				165900	167300	168800					
Frequency (MHz)				829	836.5	844					
10	QPSK	1	1	20.91	20.93	20.90	21.2	0.0			
Channel				163500	167300	165200					
Frequency (MHz)				826.5	836.5	846.5					
5	QPSK	1	1	20.89	21.01	20.93	21.2	0.0			

n12 Ant1 DSI5									
BW [MHz]	Modulat- ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit [dBm]		
Channel				141300	141500	141700			
Frequency (MHz)				706.5	707.5	708.5			
15	1/2 BPSK	1	1	24.54	24.60	24.52	24.7	0.0	
15	1/2 BPSK	1	40	24.48	24.54	24.55			
15	1/2 BPSK	1	77	24.58	24.59	24.56			
15	1/2 BPSK	36	0	24.52	24.65	24.57	24.7	0.0	
15	1/2 BPSK	36	22	24.54	24.64	24.47	24.7	0.0	
15	1/2 BPSK	36	43	24.51	24.59	24.55	24.7	0.0	
15	1/2 BPSK	75	0	24.56	24.57	24.51	24.7	0.0	
15	QPSK	1	1	24.62	24.68	24.60			
15	QPSK	1	40	24.50	24.57	24.55			
15	QPSK	1	77	24.56	24.61	24.56	24.7	0.0	
15	QPSK	36	0	24.58	24.64	24.52			
15	QPSK	36	22	24.50	24.65	24.57			
15	QPSK	36	43	24.52	24.58	24.49	24.7	0.0	
15	QPSK	75	0	24.54	24.63	24.54	24.7	0.0	
15	16QAM	1	1	24.54	24.60	24.47			
15	64QAM	1	1	23.10	23.15	23.16	23.2	1.5	
15	256QAM	1	1	21.16	21.12	21.05	21.2	3.5	
Channel				140800	141500	142200			
Frequency (MHz)				704	707.5	711			
10	QPSK	1	1	24.52	24.62	24.57	24.7	0.0	
Channel				140300	141500	142700			
Frequency (MHz)				701.5	707.5	713.5			
5	QPSK	1	1	24.60	24.57	24.52	24.7	0.0	

n26 Ant1 DSI5											
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.	Tune- up limit [dBm]	MPR			
Channel				164800	166300	167800					
Frequency [MHz]				824	831.5	839					
20	1/2 BPSK	1	1	20.41	20.48	20.37	20.7	0.0			
20	1/2 BPSK	1	53	20.45	20.42	20.39					
20	1/2 BPSK	1	104	20.41	20.53	20.45					
20	1/2 BPSK	50	0	20.37	20.44	20.35	20.7	0.0			
20	1/2 BPSK	50	28	20.39	20.45	20.43	20.7	0.0			
20	1/2 BPSK	50	56	20.43	20.45	20.37	20.7	0.0			
20	1/2 BPSK	100	0	20.42	20.42	20.39	20.7	0.0			
20	QPSK	1	1	20.50	20.55	20.48					
20	QPSK	1	53	20.37	20.52	20.37					
20	QPSK	1	104	20.41	20.46	20.40	20.7	0.0			
20	QPSK	50	0	20.43	20.51	20.45					
20	QPSK	50	28	20.40	20.53	20.42					
20	QPSK	50	56	20.42	20.46	20.41	20.7	0.0			
20	QPSK	100	0	20.44	20.52	20.41					
20	16QAM	1	1	20.36	20.46	20.44	20.7	0.0			
20	64QAM	1	1	20.38	20.44	20.37	20.7	0.0			
20	256QAM	1	1	20.37	20.42	20.40	20.7	0.0			
Channel				164300	166300	165900					
Frequency [MHz]				821.5	831.5	841.5					
15	QPSK	1	1	20.45	20.44	20.44	20.7	0.0			
Channel				163800	166300	168800					
Frequency [MHz]				819	831.5	844					
10	QPSK	1	1	20.42	20.52	20.39	20.7	0.0			
Channel				163300	166300	165200					
Frequency [MHz]				816.5	831.5	846.5					
5	QPSK	1	1	20.42	20.50	20.36	20.7	0.0			

n71 Ant1 DSI5											
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)			
Channel				136100							
Frequency (MHz)				680.5							
35	1/2 BPSK	1	1		23.72		24.2	0.0			
35	1/2 BPSK	1	90		23.78						
35	1/2 BPSK	1	186		23.70						
35	1/2 BPSK	90	0		23.68		24.2	0.0			
35	1/2 BPSK	90	45		23.79		24.2	0.0			
35	1/2 BPSK	90	90		23.76		24.2	0.0			
35	1/2 BPSK	180	0		23.74		24.2	0.0			
35	QPSK	1	1		23.83						
35	QPSK	1	90		23.78						
35	QPSK	1	186		23.71		24.2	0.0			
35	QPSK	90	0		23.74						
35	QPSK	90	45		23.80						
35	QPSK	90	90		23.79		24.2	0.0			
35	QPSK	180	0		23.77		24.2	0.0			
35	16QAM	1	1		23.73						
35	64QAM	1	1		22.85		23.2	1.0			
35	256QAM	1	1		20.80		21.2	3.0			
Channel				135600	136100	136600					
Frequency (MHz)				676	680.5	683					
30	QPSK	1	1	23.67	23.73	23.76	24.2	0.0			
Channel				135100	136100	137100					
Frequency (MHz)				675.5	680.5	685.5					
25	QPSK	1	1	23.59	23.73	23.72	24.2	0.0			
Channel				134600	136100	137000					
Frequency (MHz)				673	680.5	688					
20	QPSK	1	1	23.67	23.64	23.65	24.2	0.0			
Channel				134100	136100	138100					
Frequency (MHz)				670.5	680.5	690.5					
15	QPSK	1	1	23.62	23.76	23.65	24.2	0.0			
Channel				133600	136100	136900					
Frequency (MHz)				668	680.5	693					
10	QPSK	1	1	23.70	23.72	23.63	24.2	0.0			
Channel				133100	136100	139100					
Frequency (MHz)				665.5	680.5	695.5					
5	QPSK	1	1	23.67	23.69	23.72	24.2	0.0			

n2 Ant5 DSI5										
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				374000	376000	378000				
Frequency (MHz)				1870	1880	1890				
40	1/2 BPSK	1	1	18.36	18.27	18.31				
40	1/2 BPSK	1	108	18.33	18.38	18.27	19.0	0.0		
40	1/2 BPSK	1	214	18.26	18.37	18.22				
40	1/2 BPSK	108	0	18.34	18.29	18.23	19.0	0.0		
40	1/2 BPSK	108	54	18.36	18.33	18.32	19.0	0.0		
40	1/2 BPSK	108	108	18.29	18.32	18.26				
40	1/2 BPSK	216	0	18.24	18.28	18.23	19.0	0.0		
40	QPSK	1	1	18.38	18.41	18.35				
40	QPSK	1	108	18.33	18.33	18.21	19.0	0.0		
40	QPSK	1	214	18.29	18.30	18.32				
40	QPSK	108	0	18.26	18.27	18.32	19.0	0.0		
40	QPSK	108	54	18.26	18.38	18.22	19.0	0.0		
40	QPSK	108	108	18.24	18.31	18.25				
40	QPSK	216	0	18.31	18.35	18.32	19.0	0.0		
40	16QAM	1	1	18.34	18.29	18.30	19.0	0.0		
40	64QAM	1	1	18.25	18.30	18.21	19.0	0.0		
40	256QAM	1	1	18.27	18.32	18.32	19.0	0.0		
Channel				373500	376000	378500				
Frequency (MHz)				1887.5	1880	1892.5				
35	QPSK	1	1	18.35	18.35	18.30	19.0	0.0		
Channel				373000	376000	378000				
Frequency (MHz)				1895	1880	1895				
30	QPSK	1	1	18.26	18.33	18.32	19.0	0.0		
Channel				372500	376000	378500				
Frequency (MHz)				1892.5	1880	1897.5				
25	QPSK	1	1	18.25	18.30	18.32	19.0	0.0		
Channel				372000	376000	380000				
Frequency (MHz)				1900	1900	1900				
20	QPSK	1	1	18.31	18.30	18.30	19.0	0.0		
Channel				371500	376000	380500				
Frequency (MHz)				1897.5	1880	1902.5				
15	QPSK	1	1	18.31	18.38	18.21	19.0	0.0		
Channel				371000	376000	381000				
Frequency (MHz)				1895	1890	1905				
10	QPSK	1	1	18.27	18.31	18.24	19.0	0.0		
Channel				370500	376000	381500				
Frequency (MHz)				1892.5	1880	1907.5				
5	QPSK	1	1	18.36	18.29	18.28	19.0	0.0		

n7 Ant5 DSI5										
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				505000	507000	509000				
Frequency (MHz)				2525	2535	2545				
50	1/2 BPSK	1	1	17.74	17.77	17.64				
50	1/2 BPSK	1	135	17.75	17.79	17.67	18.0	0.0		
50	1/2 BPSK	1	268	17.71	17.78	17.64				
50	1/2 BPSK	135	0	17.68	17.72	17.63	18.0	0.0		
50	1/2 BPSK	135	68	17.65	17.70	17.70	18.0	0.0		
50	1/2 BPSK	135	135	17.74	17.78	17.62				
50	1/2 BPSK	270	0	17.75	17.72	17.71	18.0	0.0		
50	QPSK	1	1	17.78	17.83	17.75				
50	QPSK	1	135	17.72	17.74	17.68	18.0	0.0		
50	QPSK	1	268	17.70	17.81	17.65				
50	QPSK	135	0	17.74	17.70	17.66	18.0	0.0		
50	QPSK	135	68	17.65	17.68	17.64	18.0	0.0		
50	QPSK	135	135	17.75	17.73	17.73				
50	QPSK	270	0	17.72	17.77	17.61	18.0	0.0		
50	16QAM	1	1	17.75	17.75	17.68	18.0	0.0		
50	64QAM	1	1	17.73	17.73	17.66	18.0	0.0		
50	256QAM	1	1	17.67	17.74	17.65	18.0	0.0		
Channel				504000	507000	510000				
Frequency (MHz)				2520	2535	2550				
40	QPSK	1	1	17.66	17.73	17.71	18.0	0.0		
Channel				503500	507000	510500				
Frequency (MHz)				2517.5	2535	2552.5				
35	QPSK	1	1	17.67	17.71	17.69	18.0	0.0		
Channel				503000	507000	511000				
Frequency (MHz)				2515	2535	2555				
30	QPSK	1	1	17.76	17.70	17.64	18.0	0.0		
Channel				502500	507000	511500				
Frequency (MHz)				2512.5	2535	2557.5				
25	QPSK	1	1	17.70	17.72	17.64	18.0	0.0		
Channel				502000	507000	512000				
Frequency (MHz)				2510	2535	2560				
20	1/2 BPSK	1	1	17.74	17.75	17.71	18.0	0.0		
Channel				501500	507000	512500				
Frequency (MHz)				2507.5	2535	2562.5				
15	QPSK	1	1	17.64	17.80	17.61	18.0	0.0		
Channel				501000	507000	513000				
Frequency (MHz)				2505	2535	2565				
10	QPSK	1	1	17.70	17.80	17.71	18.0	0.0		
Channel				500500	507000	513500				
Frequency (MHz)				2502.5	2535	2567.5				
5	QPSK	1	1	17.64	17.72	17.67	18.0	0.0		

n25 Ant5 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq. (kHz)	Power Middle Ch. / Freq. (kHz)	Power High Ch. / Freq. (kHz)	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376500	379000			
Frequency (MHz)				1870	1892.5	1895			
40	1/2 BPSK	1	1	19.44	19.54	19.39			
40	1/2 BPSK	1	108	19.45	19.52	19.35	20.0	0.0	
40	1/2 BPSK	1	214	19.37	19.52	19.46			
40	1/2 BPSK	108	0	19.49	19.48	19.37	20.0	0.0	
40	1/2 BPSK	108	54	19.46	19.49	19.37	20.0	0.0	
40	1/2 BPSK	108	108	19.44	19.52	19.40			
40	1/2 BPSK	216	0	19.47	19.50	19.38	20.0	0.0	
40	QPSK	1	1	19.51	19.56	19.48			
40	QPSK	1	108	19.43	19.49	19.41	20.0	0.0	
40	QPSK	1	214	19.39	19.45	19.37			
40	QPSK	108	0	19.41	19.50	19.35	20.0	0.0	
40	QPSK	108	54	19.40	19.53	19.42	20.0	0.0	
40	QPSK	108	108	19.47	19.49	19.39			
40	QPSK	216	0	19.48	19.49	19.44	20.0	0.0	
40	16QAM	1	1	19.37	19.44	19.40	20.0	0.0	
40	64QAM	1	1	19.43	19.43	19.34	20.0	0.0	
40	256QAM	1	1	19.39	19.45	19.42	20.0	0.0	
Channel				373500	376500	379500			
Frequency (MHz)				1887.5	1892.5	1897.5			
35	QPSK	1	1	19.41	19.44	19.45	20.0	0.0	
Channel				373000	376500	380000			
Frequency (MHz)				1895	1892.5	1900			
30	QPSK	1	1	19.40	19.45	19.42	20.0	0.0	
Channel				372500	376500	380500			
Frequency (MHz)				1892.5	1892.5	1902.5			
25	QPSK	1	1	19.51	19.51	19.36	20.0	0.0	
Channel				372000	376500	381000			
Frequency (MHz)				1890	1892.5	1905			
20	QPSK	1	1	19.42	19.52	19.38	20.0	0.0	
Channel				371500	376500	381500			
Frequency (MHz)				1887.5	1892.5	1907.5			
15	QPSK	1	1	19.49	19.53	19.39	20.0	0.0	
Channel				371000	376500	382000			
Frequency (MHz)				1895	1892.5	1910			
10	QPSK	1	1	19.45	19.44	19.41	20.0	0.0	
Channel				370500	376500	382500			
Frequency (MHz)				1892.5	1892.5	1912.5			
5	QPSK	1	1	19.41	19.52	19.35	20.0	0.0	

n38 Ant5 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				516034	516000	516996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	17.33	17.36	17.32			
40	1/2 BPSK	1	53	17.34	17.31	17.31	17.7	0.0	
40	1/2 BPSK	1	104	17.26	17.32	17.22			
40	1/2 BPSK	50	0	17.25	17.32	17.32	17.7	0.0	
40	1/2 BPSK	50	28	17.33	17.40	17.32	17.7	0.0	
40	1/2 BPSK	50	56	17.26	17.29	17.30			
40	1/2 BPSK	100	0	17.35	17.33	17.29	17.7	0.0	
40	QPSK	1	1	17.38	17.42	17.35			
40	QPSK	1	53	17.29	17.39	17.31	17.7	0.0	
40	QPSK	1	104	17.28	17.37	17.28			
40	QPSK	50	0	17.35	17.31	17.23	17.7	0.0	
40	QPSK	50	28	17.24	17.39	17.22	17.7	0.0	
40	QPSK	50	56	17.25	17.31	17.30			
40	QPSK	100	0	17.26	17.37	17.22	17.7	0.0	
40	16QAM	1	1	17.34	17.30	17.32	17.7	0.0	
40	64QAM	1	1	17.35	17.33	17.23	17.7	0.0	
40	256QAM	1	1	17.31	17.29	17.32	17.7	0.0	
Channel				517002	516000	520998			
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	17.27	17.35	17.24	17.7	0.0	
Channel				516504	519000	521496			
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	17.36	17.36	17.28	17.7	0.0	
Channel				516000	516000	522000			
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	17.26	17.39	17.26	17.7	0.0	
Channel				515502	519000	522498			
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	17.27	17.33	17.22	17.7	0.0	
Channel				516034	516000	522996			
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	17.26	17.33	17.29	17.7	0.0	

n41 Ant5 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	520000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	17.03	17.00	17.04			
100	1/2 BPSK	1	137	16.98	17.03	17.03	17.5	0.0	
100	1/2 BPSK	1	271	17.04	17.05	16.92			
100	1/2 BPSK	135	0	17.01	17.01	16.99	17.5	0.0	
100	1/2 BPSK	135	69	16.98	17.04	16.97	17.5	0.0	
100	1/2 BPSK	135	138	17.06	17.07	17.03			
100	1/2 BPSK	270	0	16.95	17.01	16.99	17.5	0.0	
100	QPSK	1	1	17.08	17.11	17.06			
100	QPSK	1	137	16.94	17.01	17.00	17.5	0.0	
100	QPSK	1	271	17.03	17.01	16.95			
100	QPSK	135	0	17.03	16.99	17.04	17.5	0.0	
100	QPSK	135	69	16.96	17.06	16.99	17.5	0.0	
100	QPSK	135	138	17.04	16.98	17.04			
100	QPSK	270	0	17.02	17.04	17.03	17.5	0.0	
100	16QAM	1	1	16.95	16.98	16.99	17.5	0.0	
100	64QAM	1	1	16.96	16.99	16.95	17.5	0.0	
100	256QAM	1	1	16.97	17.02	17.00	17.5	0.0	
Channel				520200	518598	520998			
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	16.96	17.01	16.97	17.5	0.0	
Channel				507204	518598	520998			
Frequency (MHz)				2536.02	2592.99	2640.99			
80	QPSK	1	1	17.03	16.98	16.93	17.5	0.0	
Channel				520200	518598	520998			
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	17.00	17.07	17.02	17.5	0.0	
Channel				505200	518598	521996			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	17.02	17.02	17.00	17.5	0.0	
Channel				520200	518598	520998			
Frequency (MHz)				2521.02	2592.99	2664.98			
50	QPSK	1	1	17.05	16.97	17.03	17.5	0.0	
Channel				503700	518598	523496			
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	16.97	17.08	16.95	17.5	0.0	
Channel				5216.01	2592.99	2670			
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	17.00	17.08	16.93	17.5	0.0	
Channel				502704	518598	524496			
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	16.95	17.01	17.03	17.5	0.0	
Channel				502200	518598	523996			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	17.03	17.04	17.01	17.5	0.0	
Channel				501702	518598	523500			
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	17.03	16.99	16.94	17.5	0.0	
Channel				501204	518598	523996			
Frequency (MHz)				2506.52	2592.99	2679.99			
20	QPSK	1	1	16.95	17.05	16.96	17.5	0.0	
Channel				500700	518598	526496			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	17.03	17.01	17.02	17.5	0.0	
Channel				500202	518598	527000			
Frequency (MHz)				2501.51	2592.99	2684			
10	QPSK	1	1	16.99	17.06	16.94	17.5	0.0	

n48 Ant5 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				638000	641666	645332			
Frequency (MHz)				3570	3624.99	3679.98			
40	1/2 BPSK	1	1	16.88	17.00	16.83			
40	1/2 BPSK	1	53	16.93	17.02	16.89	18.0	0.0	
40	1/2 BPSK	1	104	16.90	17.01	16.86			
40	1/2 BPSK	50	0	16.93	16.96	16.92	18.0	0.0	
40	1/2 BPSK	50	28	16.95	16.99	16.94	18.0	0.0	
40	1/2 BPSK	50	56	16.96	17.03	16.90			
40	1/2 BPSK	100	0	16.92	16.99	16.88	18.0	0.0	
40	QPSK	1	1	16.98	17.05	16.96			
40	QPSK	1	53	16.88	16.97	16.91	18.0	0.0	
40	QPSK	1	104	16.91	16.97	16.84			
40	QPSK	50	0	16.95	16.94	16.87	18.0	0.0	
40	QPSK	50	28	16.93	17.02	16.88	18.0	0.0	
40	QPSK	50	56	16.86	16.96	16.87			
40	QPSK	100	0	16.89	16.98	16.87	18.0	0.0	
40	16QAM	1	1	16.88	16.97	16.89	18.0	0.0	
40	64QAM	1	1	16.89	16.92	16.86	18.0	0.0	
40	256QAM	1	1	16.87	16.96	16.91	18.0	0.0	
Channel				637696	641666	645566			
Frequency (MHz)				3565.02	3624.99	3684.99			
30	QPSK	1	1	16.84	17.02	16.91	18.0	0.0	
Channel				637334	641666	646000			
Frequency (MHz)				3560.01	3624.99	3690			
20	QPSK	1	1	16.89	16.94	16.87	18.0	0.0	
Channel				637168	641666	645166			
Frequency (MHz)				3567.00	3624.99	3674.99			
15	QPSK	1	1	16.89	17.00	16.91	18.0	0.0	
Channel				637000	641666	645332			
Frequency (MHz)				3565	3624.99	3684.98			
10	QPSK	1	1	16.90	16.91	16.94	18.0	0.0	

Part270 n77 PC2 Ant5 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				65000	65000	66200			
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	19.65	19.72	19.61			
100	1/2 BPSK	1	137	19.62	19.71	19.61	20.0	0.0	
100	1/2 BPSK	1	271	19.62	19.71	19.64			
100	1/2 BPSK	135	0	19.56	19.61	19.65	20.0	0.0	
100	1/2 BPSK	135	69	19.57	19.66	19.65	20.0	0.0	
100	1/2 BPSK	135	138	19.61	19.62	19.63	20.0	0.0	
100	1/2 BPSK	270	0	19.53	19.69	19.57			
100	QPSK	1	1	19.70	19.78	19.73			
100	QPSK	1	137	19.64	19.59	19.72	20.0	0.0	
100	QPSK	1	271	19.61	19.57	19.59			
100	QPSK	135	0	19.65	19.72	19.72	20.0	0.0	
100	QPSK	135	69	19.63	19.76	19.61	20.0	0.0	
100	QPSK	135	138	19.69	19.67	19.67			
100	QPSK	270	0	19.58	19.70	19.65	20.0	0.0	
100	16QAM	1	1	19.51	19.65	19.60	20.0	0.0	
100	64QAM	1	1	19.61	19.61	19.65	20.0	0.0	
100	256QAM	1	1	19.59	19.61	19.64	20.0	0.0	
Channel				64666	65000	66234			
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	19.54	19.70	19.66	20.0	0.0	
Channel				649334	650000	662668			
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	19.61	19.73	19.69	20.0	0.0	
Channel				649200	650200	663000			
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	19.65	19.62	19.58	20.0	0.0	
Channel				648668	650000	663334			
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	19.55	19.67	19.60	20.0	0.0	
Channel				648334	650200	663668			
Frequency (MHz)				3725.01	3840	3965.02			
50	QPSK	1	1	19.59	19.69	19.59	20.0	0.0	
Channel				648000	650000	664000			
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	19.65	19.64	19.63	20.0	0.0	
Channel				647668	650000	664334			
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	19.57	19.74	19.63	20.0	0.0	
Channel				647500	650000	664500			
Frequency (MHz)				3712.5	3840	3967.5			
25	QPSK	1	1	19.54	19.64	19.68	20.0	0.0	
Channel				647334	650000	664834			
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	1	19.57	19.68	19.64	20.0	0.0	
Channel				647168	650000	664834			
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	19.59	19.67	19.67	20.0	0.0	
Channel				647000	650000	665000			
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	19.65	19.67	19.65	20.0	0.0	

Part27Q n77 Ant5 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				63300	63334	63500			
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		15.64				
100	1/2 BPSK	1	137		15.63		16.5	0.0	
100	1/2 BPSK	1	271		15.64				
100	1/2 BPSK	135	0		15.56		16.5	0.0	
100	1/2 BPSK	135	69		15.62		16.5	0.0	
100	1/2 BPSK	135	138		15.55		16.5	0.0	
100	1/2 BPSK	270	0		15.58		16.5	0.0	
100	QPSK	1	1		15.66				
100	QPSK	1	137		15.55		16.5	0.0	
100	QPSK	1	271		15.55				
100	QPSK	135	0		15.63		16.5	0.0	
100	QPSK	135	69		15.61		16.5	0.0	
100	QPSK	135	138		15.59		16.5	0.0	
100	QPSK	270	0		15.61		16.5	0.0	
100	16QAM	1	1		15.58		16.5	0.0	
100	64QAM	1	1		15.55		16.5	0.0	
100	256QAM	1	1		15.56		16.5	0.0	
Channel				633000	633334	633668			
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	15.54	15.60	15.58	16.5	0.0	
Channel				632668	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	15.43	15.53	15.54	16.5	0.0	
Channel				632334	633334	634334			
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	15.52	15.58	15.52	16.5	0.0	
Channel				632000	633334	634668			
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	15.51	15.50	15.43	16.5	0.0	
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	15.52	15.58	15.47	16.5	0.0	
Channel				631334	633334	635334			
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	15.52	15.51	15.47	16.5	0.0	
Channel				631000	633334	635668			
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	15.45	15.56	15.57	16.5	0.0	
Channel				630634	633334	635834			
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	15.53	15.55	15.51	16.5	0.0	
Channel				630334	633334	636000			
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	15.46	15.58	15.51	16.5	0.0	
Channel				630500	633334	636168			
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	15.44	15.52	15.51	16.5	0.0	
Channel				630334	633334	636334			
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	15.44	15.59	15.51	16.5	0.0	

Part27Q n77 PC2 Ant5 DSI5									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.	Tune- up limit [dBm]	MPR (dB)	
Channel				633000	633334				
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		19.17			20.0	0.0
100	1/2 BPSK	1	137		19.07			20.0	0.0
100	1/2 BPSK	1	271		19.16			20.0	0.0
100	1/2 BPSK	135	0		19.10			20.0	0.0
100	1/2 BPSK	135	69		19.18			20.0	0.0
100	1/2 BPSK	135	138		19.00			20.0	0.0
100	1/2 BPSK	270	0		19.07			20.0	0.0
100	QPSK	1	1		19.24				
100	QPSK	1	137		19.06			20.0	0.0
100	QPSK	1	271		19.15				
100	QPSK	135	0		19.17			20.0	0.0
100	QPSK	135	69		19.21			20.0	0.0
100	QPSK	135	138		19.20			20.0	0.0
100	QPSK	270	0		19.17			20.0	0.0
100	16QAM	1	1		19.08			20.0	0.0
100	64QAM	1	1		19.09			20.0	0.0
100	256QAM	1	1		19.08			20.0	0.0
Channel				633000	633334	633668			
Frequency (MHz)				3499.31	3500.31	3501.31			
90	QPSK	1	1	19.20	19.16	19.10			
Channel				632668	633334	634000		Tune- up limit	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	19.19	19.14	19.14		20.0	0.0
Channel				632334	633334	634334		Tune- up limit	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	19.11	19.09	19.11		20.0	0.0
Channel				632000	633334	634668		Tune- up limit	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	19.18	19.16	19.20		20.0	0.0
Channel				631668	633334	635000		Tune- up limit	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	19.17	19.17	19.14		20.0	0.0
Channel				631334	633334	635334		Tune- up limit	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	19.14	19.17	19.11		20.0	0.0
Channel				631000	633334	635668		Tune- up limit	
Frequency (MHz)				3465	3500.01	3536.02			
30	QPSK	1	1	19.17	19.13	19.11		20.0	0.0
Channel				630634	633334	635834		Tune- up limit	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	19.11	19.09	19.12		20.0	0.0
Channel				630268	633334	636168		Tune- up limit	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	19.13	19.14	19.18		20.0	0.0
Channel				630500	633334	636168		Tune- up limit	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	19.09	19.12	19.14		20.0	0.0
Channel				630134	633334	636334		Tune- up limit	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	19.20	19.10	19.16		20.0	0.0

Part270 n78 PC2 Ant5 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	1/2 BPS	1	1		19.62				
100	1/2 BPS	1	137		19.63		20.0	0.0	
100	1/2 BPS	1	271		19.68				
100	1/2 BPS	135	0		19.64		20.0	0.0	
100	1/2 BPS	135	69		19.57		20.0	0.0	
100	1/2 BPS	135	138		19.66				
100	1/2 BPS	270	0		19.67		20.0	0.0	
100	QPSK	1	1		19.78				
100	QPSK	1	137		19.57		20.0	0.0	
100	QPSK	1	271		19.62				
100	QPSK	135	0		19.68		20.0	0.0	
100	QPSK	135	69		19.70		20.0	0.0	
100	QPSK	135	138		19.52				
100	QPSK	270	0		19.65		20.0	0.0	
100	16QAM	1	1		19.57		20.0	0.0	
100	64QAM	1	1		19.56		20.0	0.0	
100	256QAM	1	1		19.56		20.0	0.0	
Channel				648668	650000	650334	MPR		
Frequency (MHz)				3745.02	3750	3755.01	up		
90	QPSK	1	1	19.68	19.63	19.65	20.0	0.0	
Channel				649334	650000	650668	MPR		
Frequency (MHz)				3740.01	3750	3760.02	up		
80	QPSK	1	1	19.70	19.63	19.65	20.0	0.0	
Channel				649000	650000	651000	MPR		
Frequency (MHz)				3735	3750	3765	up		
70	QPSK	1	1	19.65	19.71	19.65	20.0	0.0	
Channel				648668	650000	651334	MPR		
Frequency (MHz)				3730.02	3750	3770.01	up		
60	QPSK	1	1	19.67	19.71	19.71	20.0	0.0	
Channel				649334	650000	651668	MPR		
Frequency (MHz)				3725.01	3750	3775.02	up		
50	QPSK	1	1	19.68	19.73	19.63	20.0	0.0	
Channel				648000	650000	652000	MPR		
Frequency (MHz)				3720	3750	3780	up		
40	QPSK	1	1	19.62	19.72	19.64	20.0	0.0	
Channel				647668	650000	652334	MPR		
Frequency (MHz)				3715.02	3750	3785.01	up		
30	QPSK	1	1	19.67	19.66	19.65	20.0	0.0	
Channel				647500	650000	652500	MPR		
Frequency (MHz)				3712.5	3750	3787.5	up		
25	QPSK	1	1	19.64	19.64	19.66	20.0	0.0	
Channel				647334	650000	652668	MPR		
Frequency (MHz)				3710.01	3750	3790.02	up		
20	QPSK	1	1	19.67	19.63	19.64	20.0	0.0	
Channel				647168	650000	652834	MPR		
Frequency (MHz)				3707.52	3750	3792.51	up		
15	QPSK	1	1	19.70	19.63	19.71	20.0	0.0	
Channel				647000	650000	653000	MPR		
Frequency (MHz)				3705	3750	3795	up		
10	QPSK	1	1	19.65	19.74	19.67	20.0	0.0	

Part27Q n78 Ant5 DSI5									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		16.10				
100	1/2 BPS	1	137		16.09		16.5	0.0	
100	1/2 BPS	1	271		16.06				
100	1/2 BPS	135	0		15.94		16.5	0.0	
100	1/2 BPS	135	69		16.07		16.5	0.0	
100	1/2 BPS	138	138		16.04				
100	1/2 BPS	270	0		16.06		16.5	0.0	
100	QPSK	1	1		16.16				
100	QPSK	1	137		15.86		16.5	0.0	
100	QPSK	1	271		16.04				
100	QPSK	135	0		16.04		16.5	0.0	
100	QPSK	135	69		16.11		16.5	0.0	
100	QPSK	138	138		15.93				
100	QPSK	270	0		16.00		16.5	0.0	
100	16QAM	1	1		16.04		16.5	0.0	
100	64QAM	1	1		15.94		16.5	0.0	
100	256QAM	1	1		15.99		16.5	0.0	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	15.95	16.06	16.00	16.5	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	15.94	16.08	16.03	16.5	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	15.99	16.06	16.06	16.5	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	15.98	16.02	16.02	16.5	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	16.02	16.05	16.03	16.5	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	15.97	16.13	16.06	16.5	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	15.91	16.14	16.04	16.5	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	15.95	16.03	16.04	16.5	0.0	
Channel				630568	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	15.99	16.11	16.01	16.5	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	15.98	16.13	16.00	16.5	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	15.92	16.12	16.10	16.5	0.0	

Part27Q n78 PC2 Ant5 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		19.44				
100	1/2 BPS	1	137		19.39		20.0	0.0	
100	1/2 BPS	1	271		19.42				
100	1/2 BPS	135	0		19.44		20.0	0.0	
100	1/2 BPS	135	69		19.44		20.0	0.0	
100	1/2 BPS	135	138		19.50				
100	1/2 BPS	270	0		19.39		20.0	0.0	
100	QPSK	1	1		19.55				
100	QPSK	1	137		19.28		20.0	0.0	
100	QPSK	1	271		19.42				
100	QPSK	135	0		19.48		20.0	0.0	
100	QPSK	135	69		19.50		20.0	0.0	
100	QPSK	135	138		19.34				
100	QPSK	270	0		19.43		20.0	0.0	
100	16QAM	1	1		19.45		20.0	0.0	
100	64QAM	1	1		19.35		20.0	0.0	
100	256QAM	1	1		19.34		20.0	0.0	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	19.43	19.43	19.45	20.0	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	19.46	19.44	19.48	20.0	0.0	
Channel				633235	633571	633907	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	19.42	19.43	19.49	20.0	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	19.49	19.47	19.39	20.0	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525.01	up		
50	QPSK	1	1	19.46	19.44	19.46	20.0	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	19.42	19.43	19.41	20.0	0.0	
Channel				631000	633334	635000	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	19.49	19.51	19.41	20.0	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	19.41	19.50	19.50	20.0	0.0	
Channel				630668	633334	635668	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	19.42	19.42	19.45	20.0	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	19.40	19.51	19.49	20.0	0.0	
Channel				630335	633334	635335	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	19.45	19.40	19.49	20.0	0.0	

n2 Ant4 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376000	378000			
Frequency (MHz)				1870	1890	1890			
40	1/2 BPSK	1	1	17.26	17.24	17.26			
40	1/2 BPSK	1	108	17.20	17.30	17.24	18.4	0.0	
40	1/2 BPSK	1	214	17.23	17.25	17.28			
40	1/2 BPSK	108	0	17.24	17.25	17.28	18.4	0.0	
40	1/2 BPSK	108	54	17.23	17.24	17.28	18.4	0.0	
40	1/2 BPSK	108	108	17.26	17.32	17.25			
40	1/2 BPSK	216	0	17.22	17.31	17.21	18.4	0.0	
40	QPSK	1	1	17.31	17.38	17.33			
40	QPSK	1	108	17.21	17.34	17.19	18.4	0.0	
40	QPSK	1	214	17.23	17.30	17.26			
40	QPSK	108	0	17.28	17.31	17.24	18.4	0.0	
40	QPSK	108	54	17.27	17.35	17.22	18.4	0.0	
40	QPSK	108	108	17.26	17.28	17.30			
40	QPSK	216	0	17.21	17.31	17.22	18.4	0.0	
40	16QAM	1	1	17.20	17.30	17.23	18.4	0.0	
40	64QAM	1	1	17.22	17.24	17.29	18.4	0.0	
40	256QAM	1	1	16.78	16.85	16.80	17.8	0.5	
Channel				373500	376000	376500			
Frequency (MHz)				1887.5	1880	1892.5			
35	QPSK	1	1	17.28	17.35	17.28	18.4	0.0	
Channel				373000	376000	378000			
Frequency (MHz)				1865	1880	1895			
30	QPSK	1	1	17.22	17.35	17.30	18.4	0.0	
Channel				372500	376000	376500			
Frequency (MHz)				1862.5	1880	1897.5			
25	QPSK	1	1	17.23	17.27	17.24	18.4	0.0	
Channel				372000	376000	380000			
Frequency (MHz)				1850	1850	1900			
20	QPSK	1	1	17.22	17.26	17.31	18.4	0.0	
Channel				371500	376000	380500			
Frequency (MHz)				1857.5	1880	1902.5			
15	QPSK	1	1	17.26	17.30	17.23	18.4	0.0	
Channel				371000	376000	381000			
Frequency (MHz)				1855	1850	1905			
10	QPSK	1	1	17.28	17.34	17.25	18.4	0.0	
Channel				370500	376000	381500			
Frequency (MHz)				1852.5	1880	1907.5			
5	QPSK	1	1	17.22	17.28	17.22	18.4	0.0	

n7 Ant4 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	16.89	16.88	16.89			
50	1/2 BPSK	1	135	16.81	16.88	16.89	17.8	0.0	
50	1/2 BPSK	1	268	16.89	16.95	16.84			
50	1/2 BPSK	135	0	16.80	16.97	16.89	17.8	0.0	
50	1/2 BPSK	135	68	16.82	16.90	16.94	17.8	0.0	
50	1/2 BPSK	135	135	16.89	16.92	16.94			
50	1/2 BPSK	270	0	16.87	16.94	16.91	17.8	0.0	
50	QPSK	1	1	16.92	17.00	16.96			
50	QPSK	1	135	16.80	16.88	16.92	17.8	0.0	
50	QPSK	1	268	16.88	16.87	16.85			
50	QPSK	135	0	16.89	16.86	16.94	17.8	0.0	
50	QPSK	135	68	16.79	16.98	16.94	17.8	0.0	
50	QPSK	135	135	16.83	16.91	16.89			
50	QPSK	270	0	16.79	16.94	16.89	17.8	0.0	
50	16QAM	1	1	16.86	16.90	16.86	17.8	0.0	
50	64QAM	1	1	16.79	16.92	16.85	17.8	0.0	
50	256QAM	1	1	16.76	16.91	16.85	17.8	0.0	
Channel				504500	507000	510500			
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	16.86	16.97	16.92	17.8	0.0	
Channel				503500	507000	510500			
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	16.90	16.88	16.91	17.8	0.0	
Channel				503000	507000	511000			
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	16.83	16.90	16.83	17.8	0.0	
Channel				502500	507000	511500			
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	16.89	16.91	16.91	17.8	0.0	
Channel				502000	507000	512000			
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	16.87	16.87	16.92	17.8	0.0	
Channel				501500	507000	512500			
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	16.86	16.86	16.92	17.8	0.0	
Channel				501000	507000	513000			
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	16.81	16.93	16.89	17.8	0.0	
Channel				500500	507000	513500			
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	16.80	16.94	16.92	17.8	0.0	

n25 Ant4 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq. (dBm)	Power Middle Ch. / Freq. (dBm)	Power High Ch. / Freq. (dBm)	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376500	379000			
Frequency (MHz)				1870	1892.5	1895			
40	1/2 BPSK	1	1	15.77	15.82	15.89			
40	1/2 BPSK	1	108	15.74	15.75	15.74	16.9	0.0	0.0
40	1/2 BPSK	1	214	15.73	15.77	15.78			
40	1/2 BPSK	108	0	15.80	15.74	15.75	16.9	0.0	0.0
40	1/2 BPSK	108	54	15.79	15.74	15.74	16.9	0.0	0.0
40	1/2 BPSK	108	108	15.75	15.84	15.69			
40	1/2 BPSK	216	0	15.71	15.74	15.75	16.9	0.0	0.0
40	QPSK	1	1	15.83	15.86	15.81			
40	QPSK	1	108	15.73	15.73	15.77	16.9	0.0	0.0
40	QPSK	1	214	15.71	15.76	15.78			
40	QPSK	108	0	15.72	15.75	15.78	16.9	0.0	0.0
40	QPSK	108	54	15.70	15.83	15.79	16.9	0.0	0.0
40	QPSK	108	108	15.81	15.78	15.70			
40	QPSK	216	0	15.71	15.81	15.87	16.9	0.0	0.0
40	16QAM	1	1	15.79	15.77	15.72	16.9	0.0	0.0
40	64QAM	1	1	15.77	15.75	15.79	16.9	0.0	0.0
40	256QAM	1	1	15.76	15.78	15.78	16.9	0.0	0.0
Channel				373500	376500	379500			
Frequency (MHz)				1867.5	1892.5	1897.5			
35	QPSK	1	1	15.70	15.79	15.70	16.9	0.0	0.0
Channel				373000	376500	380000			
Frequency (MHz)				1865	1882.5	1900			
30	QPSK	1	1	15.81	15.76	15.68	16.9	0.0	0.0
Channel				372500	376500	380500			
Frequency (MHz)				1862.5	1882.5	1902.5			
25	QPSK	1	1	15.69	15.72	15.78	16.9	0.0	0.0
Channel				372000	376500	381000			
Frequency (MHz)				1860	1872.5	1905			
20	QPSK	1	1	15.72	15.82	15.70	16.9	0.0	0.0
Channel				371500	376500	381500			
Frequency (MHz)				1857.5	1882.5	1907.5			
15	QPSK	1	1	15.77	15.73	15.71	16.9	0.0	0.0
Channel				371000	376500	382000			
Frequency (MHz)				1855	1882.5	1910			
10	QPSK	1	1	15.70	15.81	15.69	16.9	0.0	0.0
Channel				370500	376500	382500			
Frequency (MHz)				1852.5	1882.5	1912.5			
5	QPSK	1	1	15.69	15.72	15.71	16.9	0.0	0.0

n38 Ant4 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				518004	519000	519996			
Channel				2580.02	2595	2599.98			
40	1/2 BPSK	1	1	17.96	17.92	17.88			
40	1/2 BPSK	1	53	17.95	17.97	17.86	19.1	0.0	
40	1/2 BPSK	1	104	17.87	18.00	17.84			
40	1/2 BPSK	50	0	17.87	17.94	17.84	19.1	0.0	
40	1/2 BPSK	50	26	17.97	17.94	17.89	19.1	0.0	
40	1/2 BPSK	50	56	17.93	17.96	17.89			
40	1/2 BPSK	100	0	17.90	17.91	17.90	19.1	0.0	
40	QPSK	1	1	18.00	18.05	17.98			
40	QPSK	1	53	17.86	17.98	17.94	19.1	0.0	
40	QPSK	1	104	17.96	17.93	17.94			
40	QPSK	50	0	17.89	17.95	17.94	19.1	0.0	
40	QPSK	50	26	17.92	18.01	17.90	19.1	0.0	
40	QPSK	50	56	17.86	17.93	17.90			
40	QPSK	100	0	17.98	17.99	17.85	19.1	0.0	
40	16QAM	1	1	17.98	17.95	17.91	19.1	0.0	
40	64QAM	1	1	17.89	17.96	17.85	19.1	0.0	
40	256QAM	1	1	17.86	17.97	17.84	19.1	0.0	
Channel				517002	516000	520998			
Frequency (MHz)				2585.01	2599	2604.99			
30	QPSK	1	1	17.89	17.99	17.96	19.1	0.0	
Channel				516504	519000	521496			
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	17.91	17.97	17.85	19.1	0.0	
Channel				513000	516000	522000			
Frequency (MHz)				2580	2599	2610			
20	QPSK	1	1	17.98	18.00	17.91	19.1	0.0	
Channel				515502	519000	522498			
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	17.96	17.93	17.92	19.1	0.0	
Channel				515004	519000	522996			
Frequency (MHz)				2575.02	2599	2614.98			
10	QPSK	1	1	17.92	17.97	17.85	19.1	0.0	

n41 Ant4 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				509002	516598	530000			
Channel				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	17.05	17.20	17.02			
100	1/2 BPSK	1	137	17.13	17.16	17.06	18.3	0.0	
100	1/2 BPSK	1	271	17.11	17.13	17.03			
100	1/2 BPSK	135	0	17.06	17.17	17.11	18.3	0.0	
100	1/2 BPSK	135	69	17.14	17.16	17.15	18.3	0.0	
100	1/2 BPSK	135	138	17.13	17.12	17.10	18.3	0.0	
100	1/2 BPSK	270	0	17.07	17.15	17.08			
100	QPSK	1	1	17.19	17.23	17.15			
100	QPSK	1	137	17.12	17.17	17.02	18.3	0.0	
100	QPSK	1	271	17.11	17.15	17.07			
100	QPSK	135	0	17.10	17.15	17.07	18.3	0.0	
100	QPSK	135	69	17.16	17.20	17.09	18.3	0.0	
100	QPSK	135	138	17.06	17.14	17.12	18.3	0.0	
100	QPSK	270	0	17.15	17.19	17.06	18.3	0.0	
100	16QAM	1	1	17.12	17.15	17.11	18.3	0.0	
100	64QAM	1	1	17.17	17.17	17.05	18.3	0.0	
100	256QAM	1	1	17.11	17.10	17.05	18.3	0.0	
Channel				505000	518598	530998			
Frequency (MHz)				2541	2592.99	2644.99			
90	QPSK	1	1	17.12	17.19	17.02	18.3	0.0	
Channel				507204	518598	529998			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	17.03	17.09	17.07	18.3	0.0	
Channel				505002	518598	531000			
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	17.13	17.16	17.12	18.3	0.0	
Channel				505200	518598	531996			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	17.13	17.13	17.10	18.3	0.0	
Channel				504204	518598	532998			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	17.07	17.18	17.08	18.3	0.0	
Channel				503700	518598	533496			
Frequency (MHz)				2516.5	2592.99	2667.48			
45	QPSK	1	1	17.12	17.11	17.13	18.3	0.0	
Channel				503601	518598	533000			
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	17.06	17.13	17.02	18.3	0.0	
Channel				502704	518598	534498			
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	17.16	17.14	17.07	18.3	0.0	
Channel				502200	518598	533998			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	17.06	17.17	17.11	18.3	0.0	
Channel				501702	518598	535500			
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	17.15	17.10	17.11	18.3	0.0	
Channel				501204	518598	535998			
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	17.09	17.20	17.06	18.3	0.0	
Channel				500700	518598	536496			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	17.09	17.12	17.01	18.3	0.0	
Channel				500202	518598	537000			
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	17.05	17.18	17.05	18.3	0.0	

Part270 n77 Ant4 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				650000	656000	662000			
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	18.00	18.11	17.96			
100	1/2 BPSK	1	137	18.01	18.02	18.04	18.7	0.0	
100	1/2 BPSK	1	271	18.07	18.04	17.98			
100	1/2 BPSK	135	0	18.01	18.02	18.05	18.7	0.0	
100	1/2 BPSK	135	69	17.99	18.12	18.06	18.7	0.0	
100	1/2 BPSK	135	138	18.02	18.11	18.00	18.7	0.0	
100	1/2 BPSK	270	0	17.97	18.05	17.99			
100	QPSK	1	1	18.10	18.15	18.08			
100	QPSK	1	137	18.02	18.12	17.97	18.7	0.0	
100	QPSK	1	271	18.04	18.12	18.01			
100	QPSK	135	0	18.06	18.10	17.96	18.7	0.0	
100	QPSK	135	69	18.00	18.12	18.05	18.7	0.0	
100	QPSK	135	138	17.97	18.04	18.04	18.7	0.0	
100	QPSK	270	0	17.98	18.06	18.05	18.7	0.0	
100	16QAM	1	1	18.01	18.06	18.04	18.7	0.0	
100	64QAM	1	1	18.05	18.05	17.96	18.7	0.0	
100	256QAM	1	1	18.05	18.08	18.01	18.7	0.0	
Channel				648668	656000	662334			
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	18.05	18.10	18.08	18.7	0.0	
Channel				649334	656000	662668			
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	18.00	18.05	17.97	18.7	0.0	
Channel				649200	656000	663000			
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	17.95	18.01	17.97	18.7	0.0	
Channel				648668	656000	663334			
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	17.94	17.98	17.97	18.7	0.0	
Channel				648334	656000	663668			
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	1	17.96	18.01	18.05	18.7	0.0	
Channel				648000	656000	664000			
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	18.02	17.96	18.05	18.7	0.0	
Channel				647668	656000	664334			
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	17.92	18.03	18.05	18.7	0.0	
Channel				647500	656000	664500			
Frequency (MHz)				3712.5	3840	3967.5			
25	QPSK	1	1	17.94	18.07	18.06	18.7	0.0	
Channel				647334	656000	664668			
Frequency (MHz)				647334	3840	3970.02			
20	QPSK	1	1	18.00	18.00	17.99	18.7	0.0	
Channel				647168	656000	664834			
Frequency (MHz)				3710	3840	3972.51			
15	QPSK	1	1	17.97	17.99	18.02	18.7	0.0	
Channel				647000	656000	665000			
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	17.96	17.96	17.97	18.7	0.0	

Part27Q n77 Ant4 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1	17.99					
100	1/2 BPSK	1	137	17.96			18.7	0.0	
100	1/2 BPSK	1	271	17.99					
100	1/2 BPSK	135	0	17.97			18.7	0.0	
100	1/2 BPSK	135	69	18.09			18.7	0.0	
100	1/2 BPSK	135	138	18.04			18.7	0.0	
100	1/2 BPSK	270	0	17.95			18.7	0.0	
100	QPSK	1	1	18.10					
100	QPSK	1	137	18.04			18.7	0.0	
100	QPSK	1	271	17.96					
100	QPSK	135	0	17.98			18.7	0.0	
100	QPSK	135	69	18.04			18.7	0.0	
100	QPSK	135	138	17.93			18.7	0.0	
100	QPSK	270	0	18.01					
100	16QAM	1	1	18.04			18.7	0.0	
100	64QAM	1	1	18.04			18.7	0.0	
100	256QAM	1	1	18.08			18.7	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	18.05	18.01	17.97	18.7	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	17.96	18.01	18.02	18.7	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	17.97	18.01	18.01	18.7	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	18.04	18.07	17.96	18.7	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	17.97	17.98	18.05	18.7	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	18.03	18.04	18.04	18.7	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	17.95	18.07	18.03	18.7	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	18.01	18.02	18.06	18.7	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	18.00	18.00	18.01	18.7	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	18.01	18.03	18.07	18.7	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	17.97	18.00	18.02	18.7	0.0	

Part27Q n77 PC2 Ant4 DS15									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)		
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1	21.05					
100	1/2 BPSK	1	137	20.97		21.7	0.0		
100	1/2 BPSK	1	271	21.01					
100	1/2 BPSK	135	0	20.92		21.7	0.0		
100	1/2 BPSK	135	69	21.05		21.7	0.0		
100	1/2 BPSK	135	138	21.09		21.7	0.0		
100	1/2 BPSK	270	0	20.94					
100	QPSK	1	1	21.11					
100	QPSK	1	137	20.99		21.7	0.0		
100	QPSK	1	271	20.96					
100	QPSK	135	0	21.03		21.7	0.0		
100	QPSK	135	69	21.09		21.7	0.0		
100	QPSK	135	138	20.89		21.7	0.0		
100	QPSK	270	0	21.00					
100	16QAM	1	1	21.02		21.7	0.0		
100	64QAM	1	1	21.08		21.7	0.0		
100	256QAM	1	1	21.00		21.7	0.0		
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	20.95	20.96	21.01	21.7	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	21.00	20.90	20.95	21.7	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	20.97	21.00	20.96	21.7	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	20.99	20.96	20.89	21.7	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	20.93	20.94	20.90	21.7	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	20.92	20.99	20.96	21.7	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	20.95	20.92	20.90	21.7	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	20.96	20.96	20.92	21.7	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	20.91	20.91	20.94	21.7	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	20.93	20.97	20.94	21.7	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	20.97	20.95	20.95	21.7	0.0	

Part27O n78 Ant4 DSI5									
BW	Modulat	RB Size	RB Offset	Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.	Tune-up limit	MPR	
				Channel		650000			
				Frequency (MHz)					
100	1/2 BPSK	1	1		17.69				
100	1/2 BPSK	1	137		17.72		18.6	0.0	
100	1/2 BPSK	1	271		17.77				
100	1/2 BPSK	135	0		17.71		18.6	0.0	
100	1/2 BPSK	135	69		17.74		18.6	0.0	
100	1/2 BPSK	135	138		17.78		18.6	0.0	
100	1/2 BPSK	270	0		17.74		18.6	0.0	
100	QPSK	1	1		17.84				
100	QPSK	1	137		17.77		18.6	0.0	
100	QPSK	1	271		17.70				
100	QPSK	135	0		17.78		18.6	0.0	
100	QPSK	135	69		17.80		18.6	0.0	
100	QPSK	135	138		17.77		18.6	0.0	
100	QPSK	270	0		17.78		18.6	0.0	
100	16QAM	1	1		17.67		18.6	0.0	
100	64QAM	1	1		17.74		18.6	0.0	
100	256QAM	1	1		17.69		18.6	0.0	
				Channel		649668	650000	650334	
				Frequency (MHz)		3745.02	3750	3755.01	
90	QPSK	1	1	17.72	17.78	17.75	18.6	0.0	
				Channel		649334	650000	650668	
				Frequency (MHz)		3740.01	3750	3760.02	
80	QPSK	1	1	17.69	17.72	17.72	18.6	0.0	
				Channel		649000	650000	651000	
				Frequency (MHz)		3735	3750	3765	
70	QPSK	1	1	17.65	17.70	17.71	18.6	0.0	
				Channel		648668	650000	651334	
				Frequency (MHz)		3730.02	3750	3770.01	
60	QPSK	1	1	17.62	17.68	17.67	18.6	0.0	
				Channel		648334	650000	651668	
				Frequency (MHz)		3725.01	3750	3775.02	
50	QPSK	1	1	17.63	17.67	17.63	18.6	0.0	
				Channel		648000	650000	652000	
				Frequency (MHz)		3720	3750	3760	
40	QPSK	1	1	17.65	17.66	17.65	18.6	0.0	
				Channel		647668	650000	652334	
				Frequency (MHz)		3715.02	3750	3785.01	
30	QPSK	1	1	17.65	17.67	17.70	18.6	0.0	
				Channel		647500	650000	652500	
				Frequency (MHz)		3712.5	3750	3787.5	
25	QPSK	1	1	17.63	17.73	17.66	18.6	0.0	
				Channel		647334	650000	652668	
				Frequency (MHz)		6470.01	3750	3790.02	
20	QPSK	1	1	17.60	17.74	17.70	18.6	0.0	
				Channel		647168	650000	652834	
				Frequency (MHz)		64707.52	3750	3792.51	
15	QPSK	1	1	17.70	17.64	17.63	18.6	0.0	
				Channel		647000	650000	653000	
				Frequency (MHz)		3705	3750	3795	
10	QPSK	1	1	17.67	17.69	17.65	18.6	0.0	

Part27Q n78 Ant4 DSI5								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				633334	3500.01			
Frequency (MHz)					17.94			
100	1/2 BPSK	1	1		17.94			
100	1/2 BPSK	1	137		17.96		18.6	0.0
100	1/2 BPSK	1	271		17.91			
100	1/2 BPSK	135	0		17.86		18.6	0.0
100	1/2 BPSK	135	69		17.94		18.6	0.0
100	1/2 BPSK	135	138		17.93		18.6	0.0
100	1/2 BPSK	270	0		17.90		18.6	0.0
100	QPSK	1	1		18.09			
100	QPSK	1	137		17.94		18.6	0.0
100	QPSK	1	271		17.92			
100	QPSK	135	0		17.92		18.6	0.0
100	QPSK	135	69		18.00		18.6	0.0
100	QPSK	135	138		17.91		18.6	0.0
100	QPSK	270	0		18.03		18.6	0.0
100	16QAM	1	1		17.83		18.6	0.0
100	64QAM	1	1		17.97		18.6	0.0
100	256QAM	1	1		17.88		18.6	0.0
Channel				633000	633334	633668	tune-up	MPR
Frequency (MHz)				3498	3500.01	3505.02	up	(dB)
90	QPSK	1	1	17.88	17.86	17.92	18.6	0.0
Channel				632668	633334	634000	tune-up	MPR
Frequency (MHz)				3490.02	3500.01	3510	up	(dB)
80	QPSK	1	1	17.88	17.87	17.89	18.6	0.0
Channel				632334	633334	634334	tune-up	MPR
Frequency (MHz)				3485.01	3500.01	3515.01	up	(dB)
70	QPSK	1	1	17.81	17.86	17.91	18.6	0.0
Channel				632000	633334	634668	tune-up	MPR
Frequency (MHz)				3480	3500.01	3520.02	up	(dB)
60	QPSK	1	1	17.82	17.87	17.84	18.6	0.0
Channel				631668	633334	635000	tune-up	MPR
Frequency (MHz)				3475.02	3500.01	3525	up	(dB)
50	QPSK	1	1	17.88	17.91	17.83	18.6	0.0
Channel				631334	633334	635334	tune-up	MPR
Frequency (MHz)				3470.01	3500.01	3530.01	up	(dB)
40	QPSK	1	1	17.82	17.86	17.86	18.6	0.0
Channel				631000	633334	635668	tune-up	MPR
Frequency (MHz)				3465	3500.01	3535.02	up	(dB)
30	QPSK	1	1	17.84	17.86	17.89	18.6	0.0
Channel				630834	633334	635834	tune-up	MPR
Frequency (MHz)				3462.51	3500.01	3537.51	up	(dB)
25	QPSK	1	1	17.82	17.91	17.83	18.6	0.0
Channel				630668	633334	636000	tune-up	MPR
Frequency (MHz)				3460.02	3500.01	3540	up	(dB)
20	QPSK	1	1	17.79	17.93	17.86	18.6	0.0
Channel				630500	633334	636168	tune-up	MPR
Frequency (MHz)				3457.5	3500.01	3542.52	up	(dB)
15	QPSK	1	1	17.87	17.93	17.81	18.6	0.0
Channel				630334	633334	636334	tune-up	MPR
Frequency (MHz)				3455.01	3500.01	3545.01	up	(dB)
10	QPSK	1	1	17.83	17.94	17.83	18.6	0.0

Part27Q n78 PC2 Ant4 DSI5								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				633334	3500.01			
Frequency (MHz)					20.90			
100	1/2 BPSK	1	1		20.90			
100	1/2 BPSK	1	137		20.97		21.6	0.0
100	1/2 BPSK	1	271		20.96			
100	1/2 BPSK	135	0		20.91		21.6	0.0
100	1/2 BPSK	135	69		20.96		21.6	0.0
100	1/2 BPSK	135	138		20.99		21.6	0.0
100	1/2 BPSK	270	0		20.96		21.6	0.0
100	QPSK	1	1		21.11			
100	QPSK	1	137		20.89		21.6	0.0
100	QPSK	1	271		20.96			
100	QPSK	135	0		20.89		21.6	0.0
100	QPSK	135	69		20.99		21.6	0.0
100	QPSK	135	138		20.93		21.6	0.0
100	QPSK	270	0		20.98		21.6	0.0
100	16QAM	1	1		20.78		21.6	0.0
100	64QAM	1	1		20.94		21.6	0.0
100	256QAM	1	1		20.92		21.6	0.0
Channel				633000	633334	633668	tune-up	MPR
Frequency (MHz)				3495	3500.01	3505.02	up	(dB)
90	QPSK	1	1	21.06	21.02	21.01	21.6	0.0
Channel				632668	633334	634000	tune-up	MPR
Frequency (MHz)				3490.02	3500.01	3510	up	(dB)
80	QPSK	1	1	20.95	21.04	20.99	21.6	0.0
Channel				632334	633334	634334	tune-up	MPR
Frequency (MHz)				3485.01	3500.01	3515.01	up	(dB)
70	QPSK	1	1	20.98	20.97	21.03	21.6	0.0
Channel				632000	633334	634668	tune-up	MPR
Frequency (MHz)				3480	3500.01	3520.02	up	(dB)
60	QPSK	1	1	21.06	21.03	20.97	21.6	0.0
Channel				631668	633334	635000	tune-up	MPR
Frequency (MHz)				3475.02	3500.01	3525	up	(dB)
50	QPSK	1	1	20.97	21.04	21.05	21.6	0.0
Channel				631334	633334	635334	tune-up	MPR
Frequency (MHz)				3470.01	3500.01	3530.01	up	(dB)
40	QPSK	1	1	21.07	20.98	20.98	21.6	0.0
Channel				631000	633334	635668	tune-up	MPR
Frequency (MHz)				3465	3500.01	3535.02	up	(dB)
30	QPSK	1	1	20.96	21.04	20.95	21.6	0.0
Channel				630834	633334	635834	tune-up	MPR
Frequency (MHz)				3462.51	3500.01	3537.51	up	(dB)
25	QPSK	1	1	21.06	20.96	21.00	21.6	0.0
Channel				630668	633334	636000	tune-up	MPR
Frequency (MHz)				3460.02	3500.01	3540	up	(dB)
20	QPSK	1	1	21.06	21.06	21.06	21.6	0.0
Channel				630500	633334	636168	tune-up	MPR
Frequency (MHz)				3457.5	3500.01	3542.52	up	(dB)
15	QPSK	1	1	20.98	21.01	21.01	21.6	0.0
Channel				630334	633334	636334	tune-up	MPR
Frequency (MHz)				3455.01	3500.01	3545.01	up	(dB)
10	QPSK	1	1	21.07	21.05	20.98	21.6	0.0

n2 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				374000	376000	378000			
Frequency (MHz)				1870	1880	1890			
40	1/2 BPSK	1	1	20.49	20.43	20.47			
40	1/2 BPSK	1	108	20.43	20.53	20.48	21.8	0.0	
40	1/2 BPSK	1	214	20.44	20.49	20.39			
40	1/2 BPSK	108	0	20.48	20.45	20.40	21.8	0.0	
40	1/2 BPSK	108	54	20.44	20.49	20.45	21.8	0.0	
40	1/2 BPSK	108	108	20.45	20.47	20.41			
40	1/2 BPSK	216	0	20.47	20.43	20.46	21.8	0.0	
40	QPSK	1	1	20.44	20.55	20.42			
40	QPSK	1	108	20.46	20.53	20.37	21.8	0.0	
40	QPSK	1	214	20.46	20.48	20.42			
40	QPSK	108	0	20.48	20.47	20.48	21.8	0.0	
40	QPSK	108	54	20.42	20.49	20.40	21.8	0.0	
40	QPSK	108	108	20.48	20.46	20.38			
40	QPSK	216	0	20.45	20.53	20.38	21.8	0.0	
40	16QAM	1	1	20.42	20.50	20.38	21.8	0.0	
40	64QAM	1	1	19.40	19.53	19.36	20.8	1.0	
40	256QAM	1	1	17.45	17.59	17.42	18.8	3.0	
Channel				373500	376000	378500			
Frequency (MHz)				1887.5	1880	1892.5			
35	QPSK	1	1	20.30	20.49	20.27	21.8	0.0	
Channel				373000	376000	379000			
Frequency (MHz)				1865	1880	1895			
30	QPSK	1	1	20.38	20.49	20.32	21.8	0.0	
Channel				372500	376000	379500			
Frequency (MHz)				1862.5	1880	1897.5			
25	QPSK	1	1	20.30	20.44	20.31	21.8	0.0	
Channel				372000	376000	380000			
Frequency (MHz)				1860	1870	1900			
20	QPSK	1	1	20.29	20.42	20.28	21.8	0.0	
Channel				371500	376000	380500			
Frequency (MHz)				1857.5	1880	1902.5			
15	QPSK	1	1	20.33	20.50	20.35	21.8	0.0	
Channel				371000	376000	381000			
Frequency (MHz)				1855	1860	1905			
10	QPSK	1	1	20.31	20.41	20.30	21.8	0.0	
Channel				370500	376000	381500			
Frequency (MHz)				1852.5	1880	1907.5			
5	QPSK	1	1	20.35	20.50	20.32	21.8	0.0	

n7 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	19.61	19.71	19.49			
50	1/2 BPSK	1	138	19.70	19.74	19.55	20.6	0.0	
50	1/2 BPSK	1	268	19.70	19.66	19.57			
50	1/2 BPSK	135	0	19.60	19.73	19.57	20.6	0.0	
50	1/2 BPSK	135	68	19.61	19.72	19.49	20.6	0.0	
50	1/2 BPSK	135	138	19.63	19.71	19.48			
50	1/2 BPSK	270	0	19.70	19.71	19.50			
50	QPSK	1	1	19.60	19.82	19.59			
50	QPSK	1	138	19.67	19.69	19.58	20.6	0.0	
50	QPSK	1	268	19.67	19.65	19.52			
50	QPSK	135	0	19.62	19.68	19.49	20.6	0.0	
50	QPSK	135	68	19.67	19.73	19.54	20.6	0.0	
50	QPSK	135	138	19.66	19.65	19.52			
50	QPSK	270	0	19.65	19.71	19.51			
50	16QAM	1	1	19.65	19.73	19.49	20.6	0.0	
50	64QAM	1	1	19.69	19.63	19.55	20.6	0.0	
50	256QAM	1	1	19.62	19.72	19.45	20.6	0.0	
Channel				504000	507000	510000			
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	19.46	19.77	19.51	20.6	0.0	
Channel				503500	507000	510500			
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	19.52	19.66	19.44	20.6	0.0	
Channel				503000	507000	511000			
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	19.51	19.74	19.52	20.6	0.0	
Channel				502500	507000	511500			
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	19.48	19.67	19.40	20.6	0.0	
Channel				502000	507000	512000			
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	19.48	19.68	19.54	20.6	0.0	
Channel				501500	507000	512500			
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	19.51	19.73	19.43	20.6	0.0	
Channel				501000	507000	513000			
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	19.48	19.73	19.46	20.6	0.0	
Channel				500500	507000	513500			
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	19.44	19.67	19.45	20.6	0.0	

n25 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				374000	376500	379000			
Frequency (MHz)				1870	1882.5	1895			
40	1/2 BPSK	1	1	20.53	20.45	20.47			
40	1/2 BPSK	1	108	20.50	20.60	20.50	21.8	0.0	
40	1/2 BPSK	1	214	20.53	20.50	20.49			
40	1/2 BPSK	108	0	20.58	20.54	20.45	21.8	0.0	
40	1/2 BPSK	108	54	20.55	20.48	20.44	21.8	0.0	
40	1/2 BPSK	108	108	20.45	20.55	20.50			
40	1/2 BPSK	216	0	20.53	20.49	20.55	21.8	0.0	
40	QPSK	1	1	20.45	20.63	20.46			
40	QPSK	1	108	20.54	20.62	20.45	21.8	0.0	
40	QPSK	1	214	20.47	20.55	20.46			
40	QPSK	108	0	20.59	20.53	20.57	21.8	0.0	
40	QPSK	108	54	20.43	20.60	20.44	21.8	0.0	
40	QPSK	108	108	20.55	20.50	20.41			
40	QPSK	216	0	20.50	20.62	20.42	21.8	0.0	
40	16QAM	1	1	20.43	20.49	20.40	21.8	0.0	
40	64QAM	1	1	19.40	19.52	19.38	20.8	1.0	
40	256QAM	1	1	17.53	17.66	17.44	18.8	3.0	
Channel				373500	376500	379500			
Frequency (MHz)				1867.5	1882.5	1897.5			
35	QPSK	1	1	20.32	20.53	20.36	21.8	0.0	
Channel				373000	376500	380000			
Frequency (MHz)				1865	1882.5	1900			
30	QPSK	1	1	20.30	20.56	20.39	21.8	0.0	
Channel				372500	376500	380500			
Frequency (MHz)				1862.5	1882.5	1902.5			
25	QPSK	1	1	20.36	20.47	20.33	21.8	0.0	
Channel				372000	376500	381000			
Frequency (MHz)				1860	1882.5	1905			
20	QPSK	1	1	20.30	20.50	20.41	21.8	0.0	
Channel				371500	376500	381500			
Frequency (MHz)				1857.5	1882.5	1907.5			
15	QPSK	1	1	20.39	20.47	20.41			
Channel				371000	376500	382000			
Frequency (MHz)				1855	1882.5	1910			
10	QPSK	1	1	20.38	20.52	20.36	21.8	0.0	
Channel				370500	376500	382500			
Frequency (MHz)				1852.5	1882.5	1912.5			
5	QPSK	1	1	20.36	20.57	20.31	21.8	0.0	

n38 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				516004	516000	516996			
Frequency (MHz)				2590.02	2595	2595.98			
40	1/2 BPSK	1	1	19.87	19.89	19.87			
40	1/2 BPSK	1	53	19.93	19.91	19.86	20.9	0.0	
40	1/2 BPSK	1	104	19.87	19.96	19.93			
40	1/2 BPSK	50	0	19.87	19.97	19.92	20.9	0.0	
40	1/2 BPSK	50	28	19.94	19.97	19.86	20.9	0.0	
40	1/2 BPSK	50	56	19.91	19.92	19.86			
40	1/2 BPSK	100	0	19.86	19.96	19.91	20.9	0.0	
40	QPSK	1	1	19.94	19.91	19.86			
40	QPSK	1	53	19.93	19.94	19.92	20.9	0.0	
40	QPSK	1	104	19.87	19.89	19.87			
40	QPSK	50	0	19.89	19.90	19.88	20.9	0.0	
40	QPSK	50	28	19.99	19.99	19.87	20.9	0.0	
40	QPSK	50	56	19.92	19.98	19.87			
40	QPSK	100	0	19.95	19.96	19.90	20.9	0.0	
40	16QAM	1	1	19.90	19.99	19.89	20.9	0.0	
40	64QAM	1	1	19.93	19.88	19.86	20.9	0.0	
40	256QAM	1	1	19.90	19.92	19.86	20.9	0.0	
Channel				517002	516000	520996			
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	19.86	19.87	19.81	20.9	0.0	
Channel				516504	519000	521496			
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	19.84	19.79	19.61	20.9	0.0	
Channel				516000	517000	522000			
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	19.89	19.82	19.72	20.9	0.0	
Channel				515502	519000	522498			
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	19.79	19.90	19.79	20.9	0.0	
Channel				516004	516000	522996			
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	19.83	19.90	19.70	20.9	0.0	

n41 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518596	528090			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	19.17	19.26	19.26			
100	1/2 BPSK	1	137	19.11	19.29	19.16	20.6	0.0	
100	1/2 BPSK	1	271	19.11	19.24	19.18			
100	1/2 BPSK	135	0	19.12	19.30	19.21	20.6	0.0	
100	1/2 BPSK	135	69	19.16	19.29	19.22	20.6	0.0	
100	1/2 BPSK	135	138	19.14	19.28	19.16			
100	1/2 BPSK	270	0	19.18	19.26	19.25	20.6	0.0	
100	QPSK	1	1	19.12	19.33	19.23			
100	QPSK	1	137	19.17	19.31	19.21	20.6	0.0	
100	QPSK	1	271	19.10	19.30	19.22			
100	QPSK	135	0	19.15	19.22	19.22	20.6	0.0	
100	QPSK	135	69	19.12	19.30	19.20	20.6	0.0	
100	QPSK	135	138	19.11	19.30	19.24			
100	QPSK	270	0	19.11	19.31	19.23	20.6	0.0	
100	16QAM	1	1	19.12	19.31	19.22	20.6	0.0	
100	64QAM	1	1	19.11	19.29	19.21	20.6	0.0	
100	256QAM	1	1	19.16	19.30	19.20	20.6	0.0	
Channel				520000	518596	529996			
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	18.98	19.22	19.17	20.6	0.0	
Channel				507204	518596	529996			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	19.02	19.28	19.16	20.6	0.0	
Channel				520000	511596	531000			
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	19.00	19.25	19.13	20.6	0.0	
Channel				505200	518596	531996			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	19.05	19.24	19.17	20.6	0.0	
Channel				520000	511596	532000			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	18.98	19.26	19.14	20.6	0.0	
Channel				503700	518596	533496			
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	19.04	19.20	19.16	20.6	0.0	
Channel				520000	511596	533000			
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	19.04	19.23	19.12	20.6	0.0	
Channel				502704	518596	534496			
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	19.07	19.21	19.10	20.6	0.0	
Channel				520000	511596	533996			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	19.08	19.25	19.08	20.6	0.0	
Channel				501702	518596	535500			
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	19.01	19.22	19.13	20.6	0.0	
Channel				501204	518596	535996			
Frequency (MHz)				2506.52	2592.99	2679.99			
20	QPSK	1	1	19.00	19.28	19.17	20.6	0.0	
Channel				500700	518596	536496			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	19.01	19.25	19.07	20.6	0.0	
Channel				500202	518596	537000			
Frequency (MHz)				2501.51	2592.99	2685			
10	QPSK	1	1	18.97	19.23	19.09	20.6	0.0	

Part270 n77 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				650000	656000	662000			
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	17.25	17.31	17.15			
100	1/2 BPSK	1	137	17.21	17.27	17.20	18.7	0.0	0.0
100	1/2 BPSK	1	271	17.14	17.32	17.15			
100	1/2 BPSK	135	0	17.13	17.34	17.16	18.7	0.0	0.0
100	1/2 BPSK	135	69	17.23	17.42	17.23	18.7	0.0	0.0
100	1/2 BPSK	135	138	17.07	17.44	17.29			
100	1/2 BPSK	270	0	17.20	17.42	17.27	18.7	0.0	0.0
100	QPSK	1	1	17.14	17.47	17.23			
100	QPSK	1	137	17.11	17.32	17.26	18.7	0.0	0.0
100	QPSK	1	271	17.22	17.29	17.22			
100	QPSK	135	0	17.18	17.31	17.21	18.7	0.0	0.0
100	QPSK	135	69	17.07	17.41	17.20	18.7	0.0	0.0
100	QPSK	135	138	17.11	17.40	17.22			
100	QPSK	270	0	17.20	17.27	17.23	18.7	0.0	0.0
100	16QAM	1	1	17.26	17.34	17.16	18.7	0.0	0.0
100	64QAM	1	1	17.11	17.42	17.28	18.7	0.0	0.0
100	256QAM	1	1	17.23	17.29	17.20	18.7	0.0	0.0
Channel				648668	656000	662334			
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	17.10	17.29	17.14	18.7	0.0	0.0
Channel				649334	656000	662668			
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	17.09	17.30	17.08	18.7	0.0	0.0
Channel				649000	656000	662000			
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	17.05	17.30	17.10	18.7	0.0	0.0
Channel				648668	656000	662334			
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	17.01	17.33	17.10	18.7	0.0	0.0
Channel				648334	656000	662000			
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	1	17.00	17.36	17.11	18.7	0.0	0.0
Channel				648000	656000	664000			
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	17.00	17.38	17.11	18.7	0.0	0.0
Channel				647658	656000	664334			
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	17.09	17.34	17.12	18.7	0.0	0.0
Channel				647330	656000	664500			
Frequency (MHz)				3712.5	3840	397.5			
25	QPSK	1	1	17.00	17.36	17.10	18.7	0.0	0.0
Channel				647004	656000	664000			
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	1	16.99	17.30	17.15	18.7	0.0	0.0
Channel				647168	656000	664834			
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	17.00	17.36	17.10	18.7	0.0	0.0
Channel				647000	656000	665000			
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	17.03	17.27	17.11	18.7	0.0	0.0

Part27Q n77 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334		3500.01			
Frequency (MHz)									
100	1/2 BPSK	1	1		17.18				
100	1/2 BPSK	1	137		17.15		18.7	0.0	
100	1/2 BPSK	1	271		17.21				
100	1/2 BPSK	135	0		17.25		18.7	0.0	
100	1/2 BPSK	135	69		17.35		18.7	0.0	
100	1/2 BPSK	135	138		17.35		18.7	0.0	
100	1/2 BPSK	270	0		17.38				
100	QPSK	1	1		17.39				
100	QPSK	1	137		17.22		18.7	0.0	
100	QPSK	1	271		17.21				
100	QPSK	135	0		17.25		18.7	0.0	
100	QPSK	135	69		17.35		18.7	0.0	
100	QPSK	135	138		17.34		18.7	0.0	
100	QPSK	270	0		17.13				
100	16QAM	1	1		17.20		18.7	0.0	
100	64QAM	1	1		17.27		18.7	0.0	
100	256QAM	1	1		17.21		18.7	0.0	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	17.32	17.27	17.29	18.7	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	17.25	17.31	17.27	18.7	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	17.27	17.26	17.31	18.7	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	17.29	17.32	17.32	18.7	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	17.29	17.31	17.27	18.7	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	17.32	17.25	17.25	18.7	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	17.26	17.24	17.33	18.7	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	17.26	17.31	17.24	18.7	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	17.34	17.31	17.32	18.7	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	17.32	17.31	17.33	18.7	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	17.30	17.32	17.30	18.7	0.0	

Part27Q n77 PC2 Ant6 DS15									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		20.19				
100	1/2 BPSK	1	137		20.28		21.7	0.0	
100	1/2 BPSK	1	271		20.19				
100	1/2 BPSK	135	0		20.13		21.7	0.0	
100	1/2 BPSK	135	69		20.39		21.7	0.0	
100	1/2 BPSK	135	138		20.38		21.7	0.0	
100	1/2 BPSK	270	0		20.34				
100	QPSK	1	1		20.41				
100	QPSK	1	137		20.29		21.7	0.0	
100	QPSK	1	271		20.16				
100	QPSK	135	0		20.28		21.7	0.0	
100	QPSK	135	69		20.30		21.7	0.0	
100	QPSK	135	138		20.29		21.7	0.0	
100	QPSK	270	0		20.11				
100	16QAM	1	1		20.28		21.7	0.0	
100	64QAM	1	1		20.35		21.7	0.0	
100	256QAM	1	1		19.83		21.2	0.5	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	20.35	20.30	20.27	21.7	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	20.33	20.34	20.31	21.7	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	20.34	20.27	20.33	21.7	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	20.26	20.24	20.28	21.7	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	20.30	20.32	20.34	21.7	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	20.28	20.27	20.35	21.7	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	20.30	20.33	20.34	21.7	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	20.32	20.34	20.26	21.7	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	20.33	20.25	20.24	21.7	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	20.23	20.31	20.28	21.7	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	20.29	20.24	20.29	21.7	0.0	

Part27O n78 Ant6 DSI5									
BW	Modulat	RB Size	RB Offset	Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.	Tune-up limit	MPR	
				Channel		3750			
				Frequency (MHz)					
100	1/2 BPSK	1	1		16.89				
100	1/2 BPSK	1	137		16.86		18.2	0.0	
100	1/2 BPSK	1	271		16.83				
100	1/2 BPSK	135	0		16.94		18.2	0.0	
100	1/2 BPSK	135	69		16.93		18.2	0.0	
100	1/2 BPSK	135	138		16.90		18.2	0.0	
100	1/2 BPSK	270	0		16.93				
100	QPSK	1	1		16.96				
100	QPSK	1	137		16.84		18.2	0.0	
100	QPSK	1	271		16.92				
100	QPSK	135	0		16.91		18.2	0.0	
100	QPSK	135	69		16.93		18.2	0.0	
100	QPSK	135	138		16.92		18.2	0.0	
100	QPSK	270	0		16.83				
100	16QAM	1	1		16.84		18.2	0.0	
100	64QAM	1	1		16.90		18.2	0.0	
100	256QAM	1	1		16.91		18.2	0.0	
				Channel		649668	650000	650334	
				Frequency (MHz)		3745.02	3750	3755.01	
90	QPSK	1	1	16.69	16.72	16.68	18.2	0.0	
				Channel		649334	650000	650668	
				Frequency (MHz)		3740.01	3750	3760.02	
80	QPSK	1	1	16.76	16.80	16.76	18.2	0.0	
				Channel		649000	650000	651000	
				Frequency (MHz)		3735	3750	3765	
70	QPSK	1	1	16.75	16.73	16.80	18.2	0.0	
				Channel		648668	650000	651334	
				Frequency (MHz)		3730.02	3750	3770.01	
60	QPSK	1	1	16.75	16.73	16.71	18.2	0.0	
				Channel		648334	650000	651668	
				Frequency (MHz)		3725.01	3750	3775.02	
50	QPSK	1	1	16.73	16.71	16.71	18.2	0.0	
				Channel		648000	650000	652000	
				Frequency (MHz)		3720	3750	3760	
40	QPSK	1	1	16.71	16.70	16.71	18.2	0.0	
				Channel		647668	650000	652334	
				Frequency (MHz)		3715.02	3750	3785.01	
30	QPSK	1	1	16.72	16.75	16.78	18.2	0.0	
				Channel		647500	650000	652500	
				Frequency (MHz)		3712.5	3750	3787.5	
25	QPSK	1	1	16.70	16.73	16.73	18.2	0.0	
				Channel		647334	650000	652668	
				Frequency (MHz)		3710.01	3750	3790.02	
20	QPSK	1	1	16.80	16.70	16.80	18.2	0.0	
				Channel		647168	650000	652834	
				Frequency (MHz)		3707.5	3750	3792.51	
15	QPSK	1	1	16.70	16.69	16.68	18.2	0.0	
				Channel		647000	650000	653000	
				Frequency (MHz)		3705	3750	3795	
10	QPSK	1	1	16.71	16.73	16.69	18.2	0.0	

Part27Q n78 Ant6 DSI5								
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				633334		3500.01		
Frequency (MHz)								
100	1/2 BPSK	1	1		16.75			
100	1/2 BPSK	1	137		16.81		18.2	0.0
100	1/2 BPSK	1	271		16.70			
100	1/2 BPSK	135	0		16.86		18.2	0.0
100	1/2 BPSK	135	69		16.86		18.2	0.0
100	1/2 BPSK	135	138		16.82			
100	1/2 BPSK	270	0		16.78		18.2	0.0
100	QPSK	1	1		16.89			
100	QPSK	1	137		16.76		18.2	0.0
100	QPSK	1	271		16.85			
100	QPSK	135	0		16.81		18.2	0.0
100	QPSK	135	69		16.85		18.2	0.0
100	QPSK	135	138		16.80			
100	QPSK	270	0		16.78		18.2	0.0
100	16QAM	1	1		16.73		18.2	0.0
100	64QAM	1	1		16.83		18.2	0.0
100	256QAM	1	1		16.85		18.2	0.0
Channel				633000	633334	633668	18.2	0.0
Frequency (MHz)				3498	3500.01	3505.02		
90	QPSK	1	1	16.66	16.64	16.66	18.2	0.0
Channel				632668	633334	634000	18.2	0.0
Frequency (MHz)				3490.02	3500.01	3510		
80	QPSK	1	1	16.75	16.75	16.75	18.2	0.0
Channel				632334	633334	634334	18.2	0.0
Frequency (MHz)				3485.01	3500.01	3515.01		
70	QPSK	1	1	16.70	16.70	16.72	18.2	0.0
Channel				632000	633334	634668	18.2	0.0
Frequency (MHz)				3480	3500.01	3520.02		
60	QPSK	1	1	16.71	16.73	16.75	18.2	0.0
Channel				631668	633334	635000	18.2	0.0
Frequency (MHz)				3475.02	3500.01	3525		
50	QPSK	1	1	16.69	16.71	16.74	18.2	0.0
Channel				631334	633334	635334	18.2	0.0
Frequency (MHz)				3470.01	3500.01	3530.01		
40	QPSK	1	1	16.68	16.67	16.75	18.2	0.0
Channel				631000	633334	635668	18.2	0.0
Frequency (MHz)				3465	3500.01	3535.02		
30	QPSK	1	1	16.65	16.74	16.76	18.2	0.0
Channel				630634	633334	635834	18.2	0.0
Frequency (MHz)				3462.51	3500.01	3537.51		
25	QPSK	1	1	16.70	16.69	16.67	18.2	0.0
Channel				630668	633334	635900	18.2	0.0
Frequency (MHz)				3460.02	3500.01	3540		
20	QPSK	1	1	16.75	16.76	16.73	18.2	0.0
Channel				630500	633334	636168	18.2	0.0
Frequency (MHz)				3457.5	3500.01	3542.52		
15	QPSK	1	1	16.64	16.66	16.65	18.2	0.0
Channel				630334	633334	636334	18.2	0.0
Frequency (MHz)				3455.01	3500.01	3545.01		
10	QPSK	1	1	16.74	16.68	16.75	18.2	0.0

Part27Q n78 PC2 Ant6 DSI5								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				3500.01				
Frequency (MHz)								
100	1/2 BPSK	1	1		19.83		21.2	0.0
100	1/2 BPSK	1	137		19.75			
100	1/2 BPSK	1	271		19.78			
100	1/2 BPSK	135	0		19.82			
100	1/2 BPSK	135	69		19.86		21.2	0.0
100	1/2 BPSK	135	138		19.77		21.2	0.0
100	1/2 BPSK	270	0		19.82			
100	QPSK	1	1		19.95		21.2	0.0
100	QPSK	1	137		19.84			
100	QPSK	1	271		19.83			
100	QPSK	135	0		19.76			
100	QPSK	135	69		19.92		21.2	0.0
100	QPSK	135	138		19.88		21.2	0.0
100	QPSK	270	0		19.86			
100	16QAM	1	1		19.64		21.2	0.0
100	64QAM	1	1		19.76		21.2	0.0
100	256QAM	1	1		19.81		21.2	0.0
Channel				633000	633334	633668	18.2	0.0
Frequency (MHz)				3495	3500.01	3505.02		
90	QPSK	1	1	19.91	19.82	19.80	21.2	0.0
Channel				632668	633334	634000	18.2	0.0
Frequency (MHz)				3490.02	3500.01	3510		
80	QPSK	1	1	19.84	19.87	19.87	21.2	0.0
Channel				632334	633334	634334	18.2	0.0
Frequency (MHz)				3485.01	3500.01	3515.01		
70	QPSK	1	1	19.84	19.85	19.87	21.2	0.0
Channel				632000	633334	634668	18.2	0.0
Frequency (MHz)				3480	3500.01	3520.02		
60	QPSK	1	1	19.84	19.81	19.89	21.2	0.0
Channel				631668	633334	635000	18.2	0.0
Frequency (MHz)				3475.02	3500.01	3525		
50	QPSK	1	1	19.83	19.89	19.87	21.2	0.0
Channel				631334	633334	635334	18.2	0.0
Frequency (MHz)				3470.01	3500.01	3530.01		
40	QPSK	1	1	19.80	19.88	19.88	21.2	0.0
Channel				631000	633334	635668	18.2	0.0
Frequency (MHz)				3465	3500.01	3535.02		
30	QPSK	1	1	19.90	19.82	19.82	21.2	0.0
Channel				630634	633334	635834	18.2	0.0
Frequency (MHz)				3462.51	3500.01	3537.51		
25	QPSK	1	1	19.82	19.80	19.82	21.2	0.0
Channel				630668	633334	635900	18.2	0.0
Frequency (MHz)				3460.02	3500.01	3540		
20	QPSK	1	1	19.89	19.88	19.81	21.2	0.0
Channel				630500	633334	636168	18.2	0.0
Frequency (MHz)				3457.5	3500.01	3542.52		
15	QPSK	1	1	19.80	19.88	19.90	21.2	0.0
Channel				630334	633334	636334	18.2	0.0
Frequency (MHz)				3455.01	3500.01	3545.01		
10	QPSK	1	1	19.89	19.89	19.83	21.2	0.0

n2 Ant7 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376000	378000			
Frequency (MHz)				1870	1880	1890			
40	1/2 BPSK	1	1	19.03	19.10	19.08			
40	1/2 BPSK	1	108	19.04	19.10	19.05	20.3	0.0	
40	1/2 BPSK	1	214	18.96	19.07	19.01			
40	1/2 BPSK	108	0	18.98	19.04	19.03	20.3	0.0	
40	1/2 BPSK	108	54	18.97	19.10	19.06	20.3	0.0	
40	1/2 BPSK	108	108	18.94	19.01	19.05	20.3	0.0	
40	1/2 BPSK	216	0	19.01	19.11	19.09			
40	QPSK	1	1	18.99	19.15	18.99			
40	QPSK	1	108	18.98	19.05	19.10	20.3	0.0	
40	QPSK	1	214	19.02	19.04	19.06			
40	QPSK	108	0	19.01	19.10	19.03	20.3	0.0	
40	QPSK	108	54	18.96	19.11	19.06	20.3	0.0	
40	QPSK	108	108	18.95	19.08	19.04			
40	QPSK	216	0	19.04	19.09	19.07	20.3	0.0	
40	16QAM	1	1	18.94	19.02	19.05	20.3	0.0	
40	64QAM	1	1	17.55	17.59	17.46	18.6	1.5	
40	256QAM	1	1	15.44	15.68	15.53	16.8	3.5	
Channel				373500	376000	376500			
Frequency (MHz)				1887.5	1880	1892.5			
35	QPSK	1	1	18.87	19.11	18.94	20.3	0.0	
Channel				373000	376000	378000			
Frequency (MHz)				1865	1880	1895			
30	QPSK	1	1	18.94	19.00	18.91	20.3	0.0	
Channel				372500	376000	376500			
Frequency (MHz)				1862.5	1880	1897.5			
25	QPSK	1	1	18.94	19.07	18.85	20.3	0.0	
Channel				372000	376000	380000			
Frequency (MHz)				1860	1870	1900			
20	QPSK	1	1	18.91	19.01	18.93	20.3	0.0	
Channel				371500	376000	380500			
Frequency (MHz)				1857.5	1880	1902.5			
15	QPSK	1	1	18.83	19.03	18.86	20.3	0.0	
Channel				371000	376000	381000			
Frequency (MHz)				1855	1860	1905			
10	QPSK	1	1	18.91	19.09	18.93	20.3	0.0	
Channel				370500	376000	381500			
Frequency (MHz)				1852.5	1880	1907.5			
5	QPSK	1	1	18.89	19.09	18.86	20.3	0.0	

n7 Ant7 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	17.64	17.59	17.60			
50	1/2 BPSK	1	135	17.68	17.58	17.53	19.0	0.0	
50	1/2 BPSK	1	268	17.64	17.60	17.60			
50	1/2 BPSK	135	0	17.52	17.65	17.54	19.0	0.0	
50	1/2 BPSK	135	68	17.59	17.65	17.62	19.0	0.0	
50	1/2 BPSK	135	135	17.55	17.60	17.62	19.0	0.0	
50	1/2 BPSK	270	0	17.56	17.74	17.53			
50	QPSK	1	1	17.59	17.61	17.54			
50	QPSK	1	135	17.57	17.60	17.51	19.0	0.0	
50	QPSK	1	268	17.61	17.67	17.51			
50	QPSK	135	0	17.51	17.66	17.64	19.0	0.0	
50	QPSK	135	68	17.59	17.75	17.57	19.0	0.0	
50	QPSK	135	135	17.58	17.72	17.52			
50	QPSK	270	0	17.53	17.63	17.48	19.0	0.0	
50	16QAM	1	1	17.60	17.65	17.64	19.0	0.0	
50	64QAM	1	1	17.56	17.58	17.65	19.0	0.0	
50	256QAM	1	1	17.14	17.27	17.02	18.5	0.5	
Channel				504000	507000	510000			
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	17.38	17.46	17.39	19.0	0.0	
Channel				503500	507000	510500			
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	17.34	17.43	17.38	19.0	0.0	
Channel				503000	507000	511000			
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	17.44	17.42	17.34	19.0	0.0	
Channel				502500	507000	511500			
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	17.33	17.45	17.41	19.0	0.0	
Channel				502000	507000	512000			
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	17.34	17.41	17.42	19.0	0.0	
Channel				501500	507000	512500			
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	17.42	17.49	17.40	19.0	0.0	
Channel				501000	507000	513000			
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	17.44	17.42	17.36	19.0	0.0	
Channel				500500	507000	513500			
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	17.37	17.45	17.36	19.0	0.0	

n25 Ant7 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq. (dBm)	Power Middle Ch. / Freq. (dBm)	Power High Ch. / Freq. (dBm)	Tune-up limit (dBm)	MPR (dB)	
Channel				374000	376500	379000			
Frequency (MHz)				1870	1882.5	1895			
40	1/2 BPSK	1	1	19.86	19.91	19.85			
40	1/2 BPSK	1	108	19.79	19.90	19.78	21.3	0.0	
40	1/2 BPSK	1	214	19.77	19.89	19.85			
40	1/2 BPSK	108	0	19.33	19.46	19.46	20.6	0.5	
40	1/2 BPSK	108	54	19.78	19.85	19.86	21.3	0.0	
40	1/2 BPSK	108	108	19.44	19.43	19.42			
40	1/2 BPSK	216	0	19.36	19.46	19.43	20.8	0.5	
40	QPSK	1	1	19.89	19.94	19.91			
40	QPSK	1	108	19.81	19.80	19.82	21.3	0.0	
40	QPSK	1	214	19.82	19.82	19.88			
40	QPSK	108	0	18.90	18.92	18.92	20.3	1.0	
40	QPSK	108	54	19.77	19.91	19.88	21.3	0.0	
40	QPSK	108	108	18.87	18.89	18.88			
40	QPSK	216	0	18.90	18.99	18.89	20.3	1.0	
40	16QAM	1	1	18.88	18.93	18.93	20.3	1.0	
40	64QAM	1	1	17.43	17.48	17.46	18.8	2.5	
40	256QAM	1	1	15.43	15.39	15.41	16.8	4.5	
Channel				373500	376500	379500			
Frequency (MHz)				1867.5	1882.5	1897.5			
35	QPSK	1	1	19.78	19.81	19.77	21.3	0.0	
Channel				373000	376500	380000			
Frequency (MHz)				1865	1882.5	1900			
30	QPSK	1	1	19.77	19.90	19.88	21.3	0.0	
Channel				372500	376500	380500			
Frequency (MHz)				1862.5	1882.5	1902.5			
25	QPSK	1	1	19.78	19.91	19.77	21.3	0.0	
Channel				372000	376500	381000			
Frequency (MHz)				1860	1882.5	1905			
20	QPSK	1	1	19.86	19.84	19.80	21.3	0.0	
Channel				371500	376500	381500			
Frequency (MHz)				1857.5	1882.5	1907.5			
15	QPSK	1	1	19.80	19.83	19.83	21.3	0.0	
Channel				371000	376500	382000			
Frequency (MHz)				1855	1882.5	1910			
10	QPSK	1	1	19.83	19.82	19.85	21.3	0.0	
Channel				370500	376500	382500			
Frequency (MHz)				1852.5	1882.5	1912.5			
5	QPSK	1	1	19.86	19.86	19.88	21.3	0.0	

n38 Ant7 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	17.24	17.36	17.41	18.7	0.0	
40	1/2 BPSK	1	53	17.27	17.44	17.41			
40	1/2 BPSK	1	104	17.24	17.38	17.38			
40	1/2 BPSK	50	0	17.25	17.39	17.32	18.7	0.0	
40	1/2 BPSK	50	28	17.32	17.39	17.31	18.7	0.0	
40	1/2 BPSK	50	56	17.25	17.41	17.31	18.7	0.0	
40	1/2 BPSK	100	0	17.32	17.38	17.34			
40	QPSK	1	1	17.23	17.45	17.31	18.7	0.0	
40	QPSK	1	53	17.26	17.43	17.31			
40	QPSK	1	104	17.25	17.38	17.32	18.7	0.0	
40	QPSK	50	0	17.33	17.41	17.38	18.7	0.0	
40	QPSK	50	28	17.26	17.42	17.40	18.7	0.0	
40	QPSK	50	56	17.30	17.38	17.37	18.7	0.0	
40	QPSK	100	0	17.28	17.41	17.39	18.7	0.0	
40	16QAM	1	1	17.34	17.42	17.41	18.7	0.0	
40	64QAM	1	1	17.23	17.41	17.33	18.7	0.0	
40	256QAM	1	1	17.34	17.40	17.37	18.7	0.0	
Channel				517002	519000	520998	tune-up limit	MPR (dB)	
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	17.08	17.22	17.24	18.7	0.0	
Channel				516504	519000	521496	tune-up limit	MPR (dB)	
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	17.13	17.19	17.23	18.7	0.0	
Channel				516000	519000	522000	tune-up limit	MPR (dB)	
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	17.17	17.30	17.25	18.7	0.0	
Channel				515502	519000	522498	tune-up limit	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	17.12	17.21	17.21	18.7	0.0	
Channel				515004	519000	522996	tune-up limit	MPR (dB)	
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	17.14	17.26	17.20	18.7	0.0	

n41 Ant7 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	18.45	18.51	18.43	20.0	0.0	
100	1/2 BPSK	1	137	18.51	18.59	18.37			
100	1/2 BPSK	1	271	18.49	18.60	18.37			
100	1/2 BPSK	135	0	18.49	18.58	18.46	20.0	0.0	
100	1/2 BPSK	135	69	18.50	18.51	18.46	20.0	0.0	
100	1/2 BPSK	135	138	18.47	18.58	18.47	20.0	0.0	
100	1/2 BPSK	270	0	18.52	18.53	18.41			
100	QPSK	1	1	18.53	18.68	18.46	20.0	0.0	
100	QPSK	1	137	18.50	18.55	18.38			
100	QPSK	1	271	18.47	18.56	18.46	20.0	0.0	
100	QPSK	135	0	18.48	18.53	18.41	20.0	0.0	
100	QPSK	135	69	18.50	18.55	18.37	20.0	0.0	
100	QPSK	135	138	18.50	18.59	18.40	20.0	0.0	
100	QPSK	270	0	18.52	18.53	18.42	20.0	0.0	
100	16QAM	1	1	18.51	18.55	18.38	20.0	0.0	
100	64QAM	1	1	18.46	18.56	18.39	20.0	0.0	
100	256QAM	1	1	18.51	18.60	18.46	19.0	1.0	
Channel				508200	518598	528996	tune-up limit	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	18.44	18.62	18.41	20.0	0.0	
Channel				507204	518598	529998	tune-up limit	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	18.39	18.53	18.36	20.0	0.0	
Channel				506202	518598	531000	tune-up limit	MPR (dB)	
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	18.42	18.51	18.35	20.0	0.0	
Channel				505200	518598	531996	tune-up limit	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	18.46	18.56	18.38	20.0	0.0	
Channel				504204	518598	532998	tune-up limit	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	18.45	18.60	18.30	20.0	0.0	
Channel				503700	518598	533496	tune-up limit	MPR (dB)	
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	18.43	18.59	18.38	20.0	0.0	
Channel				503202	518598	534000	tune-up limit	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	18.48	18.59	18.32	20.0	0.0	
Channel				502704	518598	534498	tune-up limit	MPR (dB)	
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	18.39	18.64	18.39	20.0	0.0	
Channel				502200	518598	534996	tune-up limit	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	18.47	18.59	18.30	20.0	0.0	
Channel				501702	518598	535500	tune-up limit	MPR (dB)	
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	18.44	18.54	18.33	20.0	0.0	
Channel				501204	518598	535998	tune-up limit	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	18.48	18.55	18.39	20.0	0.0	
Channel				500700	518598	536496	tune-up limit	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	18.45	18.59	18.30	20.0	0.0	
Channel				500202	518598	537000	tune-up limit	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	18.38	18.63	18.40	20.0	0.0	

n48 Ant10 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				638000	641666	646332			
Frequency (MHz)				3570	3624.99	3679.98			
40	1/2 BPSK	1	1	22.40	22.54	22.51			
40	1/2 BPSK	1	53	22.37	22.51	22.45	24.0	0.0	
40	1/2 BPSK	1	104	22.38	22.52	22.45			
40	1/2 BPSK	50	0	22.43	22.49	22.46	24.0	0.0	
40	1/2 BPSK	50	28	22.35	22.43	22.46	24.0	0.0	
40	1/2 BPSK	50	56	22.35	22.52	22.46			
40	1/2 BPSK	100	0	22.42	22.50	22.49	24.0	0.0	
40	QPSK	1	1	22.37	22.55	22.42			
40	QPSK	1	53	22.36	22.46	22.44	24.0	0.0	
40	QPSK	1	104	22.38	22.49	22.41			
40	QPSK	50	0	22.38	22.50	22.41	24.0	0.0	
40	QPSK	50	28	22.36	22.53	22.42	24.0	0.0	
40	QPSK	50	56	22.45	22.42	22.40			
40	QPSK	100	0	22.39	22.51	22.50	24.0	0.0	
40	16QAM	1	1	22.37	22.43	22.43	24.0	0.0	
40	64QAM	1	1	20.92	20.92	20.88	22.5	1.5	
40	256QAM	1	1	18.92	19.01	18.96	20.5	3.5	
Channel				637668	641666	645666			
Frequency (MHz)				3565.02	3624.99	3684.99			
30	QPSK	1	1	22.33	22.39	22.28	24.0	0.0	
Channel				637334	641666	646000			
Frequency (MHz)				3560.01	3624.99	3690			
20	QPSK	1	1	22.26	22.34	22.35	24.0	0.0	
Channel				637163	641666	645163			
Frequency (MHz)				3557.52	3624.99	3692.49			
15	QPSK	1	1	22.29	22.40	22.28	24.0	0.0	
Channel				637000	641666	646332			
Frequency (MHz)				3565	3624.99	3694.98			
10	QPSK	1	1	22.28	22.34	22.27	24.0	0.0	

Part270 n77 Ant10 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				650000	656000	662000			
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	22.21	22.29	22.23			
100	1/2 BPSK	1	137	22.12	22.31	22.21	22.5	0.0	
100	1/2 BPSK	1	271	22.14	22.20	22.24			
100	1/2 BPSK	135	0	22.13	22.29	22.17	22.5	0.0	
100	1/2 BPSK	135	69	22.20	22.21	22.17	22.5	0.0	
100	1/2 BPSK	135	138	22.18	22.28	22.18			
100	1/2 BPSK	270	0	22.19	22.22	22.19	22.5	0.0	
100	QPSK	1	1	22.11	22.33	22.19			
100	QPSK	1	137	22.19	22.24	22.25	22.5	0.0	
100	QPSK	1	271	22.12	22.29	22.18			
100	QPSK	135	0	22.13	22.31	22.25	22.5	0.0	
100	QPSK	135	69	22.19	22.32	22.24	22.5	0.0	
100	QPSK	135	138	22.19	22.24	22.23			
100	QPSK	270	0	22.18	22.23	22.22	22.5	0.0	
100	16QAM	1	1	22.11	22.26	22.19	22.5	0.0	
100	64QAM	1	1	22.10	22.25	22.26	22.5	0.0	
100	256QAM	1	1	22.15	22.32	22.25	22.5	0.0	
Channel				648668	656000	662334			
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	22.07	22.15	22.08	22.5	0.0	
Channel				649334	656000	662668			
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	21.98	22.18	22.04	22.5	0.0	
Channel				649000	656000	663000			
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	21.96	22.26	22.14	22.5	0.0	
Channel				648668	656000	663334			
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	21.95	22.20	22.14	22.5	0.0	
Channel				648334	656000	663668			
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	1	21.98	22.18	22.07	22.5	0.0	
Channel				648000	656000	664000			
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	21.97	22.15	22.14	22.5	0.0	
Channel				647668	656000	664334			
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	22.02	22.14	22.04	22.5	0.0	
Channel				647500	656000	664500			
Frequency (MHz)				3712.5	3840	3967.5			
25	QPSK	1	1	22.04	22.21	22.03	22.5	0.0	
Channel				647334	656000	664668			
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	1	22.02	22.15	22.05	22.5	0.0	
Channel				647168	656000	664834			
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	22.00	22.23	22.05	22.5	0.0	
Channel				647000	656000	665000			
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	22.04	22.18	22.10	22.5	0.0	

Part270 n77 PC2 Ant10 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq. (kHz)	Power Middle Ch. / Freq. (kHz)	Power High Ch. / Freq. (kHz)	Tune-up limit (dBm)	MPR (dB)	
Channel				650000	656000	662000			
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	25.71	25.85	25.67			
100	1/2 BPSK	1	137	25.60	25.86	25.70	26.0	0.0	
100	1/2 BPSK	1	271	25.58	25.65	25.69			
100	1/2 BPSK	135	0	25.59	25.85	25.68	26.0	0.0	
100	1/2 BPSK	135	69	25.70	25.68	25.83	26.0	0.0	
100	1/2 BPSK	135	138	25.71	25.74	25.74			
100	1/2 BPSK	270	0	25.69	25.70	25.70	26.0	0.0	
100	QPSK	1	1	25.57	25.87	25.70			
100	QPSK	1	137	25.73	25.77	25.80	26.0	0.0	
100	QPSK	1	271	25.64	25.81	25.66			
100	QPSK	135	0	25.61	25.76	25.77	26.0	0.0	
100	QPSK	135	69	25.70	25.61	25.76	26.0	0.0	
100	QPSK	135	138	25.72	25.69	25.76			
100	QPSK	270	0	25.72	25.77	25.76	26.0	0.0	
100	16QAM	1	1	25.58	25.70	25.66	26.0	0.0	
100	64QAM	1	1	25.56	25.80	25.82	26.0	0.0	
100	256QAM	1	1	24.20	24.20	24.50	24.5	1.5	
Channel				649668	656000	662334			
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	25.41	25.76	25.57	26.0	0.0	
Channel				649334	656000	662668			
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	25.47	25.77	25.55	26.0	0.0	
Channel				649000	656000	663000			
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	25.48	25.78	25.54	26.0	0.0	
Channel				648668	656000	663334			
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	25.48	25.73	25.57	26.0	0.0	
Channel				648334	656000	663668			
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	1	25.52	25.72	25.60	26.0	0.0	
Channel				648000	656000	664000			
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	25.43	25.77	25.60	26.0	0.0	
Channel				647668	656000	664334			
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	25.41	25.81	25.65	26.0	0.0	
Channel				647334	656000	664500			
Frequency (MHz)				3712.5	3840	397.5			
25	QPSK	1	1	25.50	25.71	25.54	26.0	0.0	
Channel				647000	656000	664668			
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	1	25.52	25.75	25.57	26.0	0.0	
Channel				647168	656000	664834			
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	25.53	25.76	25.58	26.0	0.0	
Channel				647000	656000	664800			
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	25.51	25.82	25.59	26.0	0.0	

Part27Q n77 PC2 Ant10 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)		
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		25.81				
100	1/2 BPSK	1	137		25.78		26.0	0.0	
100	1/2 BPSK	1	271		25.60				
100	1/2 BPSK	135	0		25.70		26.0	0.0	
100	1/2 BPSK	135	69		25.57		26.0	0.0	
100	1/2 BPSK	135	138		25.63				
100	1/2 BPSK	270	0		25.57		26.0	0.0	
100	QPSK	1	1		25.83				
100	QPSK	1	137		25.67		26.0	0.0	
100	QPSK	1	271		25.76				
100	QPSK	135	0		25.64		26.0	0.0	
100	QPSK	135	69		25.76		26.0	0.0	
100	QPSK	135	138		25.59				
100	QPSK	270	0		25.70		26.0	0.0	
100	16QAM	1	1		25.60		26.0	0.0	
100	64QAM	1	1		25.75		26.0	0.0	
100	256QAM	1	1		24.20		24.5	1.5	
Channel				633000	633333	633668			
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	25.74	25.68	25.78	26.0	0.0	
Channel				632668	633334	634000			MPR (dB)
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	25.71	25.77	25.71	26.0	0.0	
Channel				632334	633334	634334			MPR (dB)
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	25.74	25.73	25.69	26.0	0.0	
Channel				632000	633334	634668			MPR (dB)
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	25.73	25.70	25.76	26.0	0.0	
Channel				631668	633334	635000			MPR (dB)
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	25.76	25.68	25.75	26.0	0.0	
Channel				631334	633334	635334			MPR (dB)
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	25.78	25.75	25.77	26.0	0.0	
Channel				631000	633334	635668			MPR (dB)
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	25.75	25.78	25.69	26.0	0.0	
Channel				630834	633334	635834			MPR (dB)
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	25.73	25.78	25.68	26.0	0.0	
Channel				630500	633334	636000			MPR (dB)
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	25.70	25.70	25.70	26.0	0.0	
Channel				630500	633334	636168			MPR (dB)
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	25.71	25.72	25.76	26.0	0.0	
Channel				630334	633334	636334			MPR (dB)
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	25.74	25.73	25.67	26.0	0.0	

Part270 n78 Ant10 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750					
100	1/2 BPSK	1	1		23.02				
100	1/2 BPSK	1	137		23.01		23.5	0.0	
100	1/2 BPSK	1	271		23.09				
100	1/2 BPSK	135	0		23.03		23.5	0.0	
100	1/2 BPSK	135	69		23.03		23.5	0.0	
100	1/2 BPSK	135	138		23.05				
100	1/2 BPSK	270	0		23.08		23.5	0.0	
100	QPSK	1	1		23.15				
100	QPSK	1	137		23.02		23.5	0.0	
100	QPSK	1	271		23.06				
100	QPSK	135	0		23.10		23.5	0.0	
100	QPSK	135	69		23.15		23.5	0.0	
100	QPSK	135	138		23.08				
100	QPSK	270	0		23.07		23.5	0.0	
100	16QAM	1	1		23.04		23.5	0.0	
100	64QAM	1	1		23.12		23.5	0.0	
100	256QAM	1	1		23.08		23.5	0.0	
Channel				649668	650000	650334		MPR (dB)	
Frequency (MHz)				3745.02	3750	3755.01			
90	QPSK	1	1	22.94	22.96	22.93	23.5	0.0	
Channel				649334	650000	650668		MPR (dB)	
Frequency (MHz)				3740.01	3750	3760.02			
80	QPSK	1	1	22.86	22.94	22.93	23.5	0.0	
Channel				649000	650000	651000		MPR (dB)	
Frequency (MHz)				3735	3750	3765			
70	QPSK	1	1	22.92	22.89	22.91	23.5	0.0	
Channel				648668	650000	651334		MPR (dB)	
Frequency (MHz)				3730.02	3750	3770.01			
60	QPSK	1	1	22.87	22.91	22.95	23.5	0.0	
Channel				648334	650000	651668		MPR (dB)	
Frequency (MHz)				3725.01	3750	3775.02			
50	QPSK	1	1	22.88	22.90	22.96	23.5	0.0	
Channel				648000	650000	652000		MPR (dB)	
Frequency (MHz)				3720	3750	3780			
40	QPSK	1	1	22.82	22.91	22.94	23.5	0.0	
Channel				647668	650000	652334		MPR (dB)	
Frequency (MHz)				3715.02	3750	3785.01			
30	QPSK	1	1	22.98	22.94	22.89	23.5	0.0	
Channel				647500	650000	652500		MPR (dB)	
Frequency (MHz)				3712.5	3750	3787.5			
25	QPSK	1	1	22.96	22.94	22.97	23.5	0.0	
Channel				647334	650000	652668		MPR (dB)	
Frequency (MHz)				3710.01	3750	3790.02			
20	QPSK	1	1	22.89	22.94	22.92	23.5	0.0	
Channel				647168	650000	652834		MPR (dB)	
Frequency (MHz)				3707.52	3750	3792.51			
15	QPSK	1	1	22.97	22.89	22.90	23.5	0.0	
Channel				647000	650000	653000		MPR (dB)	
Frequency (MHz)				3705	3750	3795			
10	QPSK	1	1	22.87	22.88	22.96	23.5	0.0	

Part270 n78 PC2 Ant10 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750					
100	1/2 BPSK	1	1		26.54				
100	1/2 BPSK	1	137		26.56		27.0	0.0	
100	1/2 BPSK	1	271		26.61				
100	1/2 BPSK	135	0		26.56		27.0	0.0	
100	1/2 BPSK	135	69		26.59		27.0	0.0	
100	1/2 BPSK	135	138		26.54				
100	1/2 BPSK	270	0		26.60		27.0	0.0	
100	QPSK	1	1		26.71				
100	QPSK	1	137		26.48		27.0	0.0	
100	QPSK	1	271		26.58				
100	QPSK	135	0		26.56		27.0	0.0	
100	QPSK	135	69		26.59		27.0	0.0	
100	QPSK	135	138		26.55				
100	QPSK	270	0		26.54		27.0	0.0	
100	16QAM	1	1		26.59		27.0	0.0	
100	64QAM	1	1		26.10		26.5	0.5	
100	256QAM	1	1		24.10		24.5	2.5	
Channel									
Frequency (MHz)				64866	65000	65234	up	MPR	
90	QPSK	1	1	26.58	26.60	26.59	27.0	0.0	
Channel				64868	65000	65068	up	MPR	
Frequency (MHz)				3740.01	3750	3760.02	up	(dB)	
80	QPSK	1	1	26.57	26.56	26.57	27.0	0.0	
Channel				47003	47000	47000	up	MPR	
Frequency (MHz)				3735	3750	3765	up	(dB)	
70	QPSK	1	1	26.58	26.59	26.60	27.0	0.0	
Channel				64866	65000	65134	up	MPR	
Frequency (MHz)				3730.02	3750	3770.01	up	(dB)	
60	QPSK	1	1	26.66	26.67	26.60	27.0	0.0	
Channel				44034	44000	44000	up	MPR	
Frequency (MHz)				3725.01	3750	3775.02	up	(dB)	
50	QPSK	1	1	26.61	26.64	26.67	27.0	0.0	
Channel				64800	65000	65200	up	MPR	
Frequency (MHz)				3720	3750	3780	up	(dB)	
40	QPSK	1	1	26.59	26.62	26.66	27.0	0.0	
Channel				47068	47000	47000	up	MPR	
Frequency (MHz)				3715.02	3750	3785.01	up	(dB)	
30	QPSK	1	1	26.65	26.61	26.60	27.0	0.0	
Channel				64700	65000	65250	up	MPR	
Frequency (MHz)				3712.5	3750	3787.5	up	(dB)	
25	QPSK	1	1	26.64	26.68	26.62	27.0	0.0	
Channel				47034	47000	47000	up	MPR	
Frequency (MHz)				3710.01	3750	3790.02	up	(dB)	
20	QPSK	1	1	26.56	26.64	26.64	27.0	0.0	
Channel				64718	65000	65264	up	MPR	
Frequency (MHz)				3707.52	3750	3792.51	up	(dB)	
15	QPSK	1	1	26.58	26.61	26.62	27.0	0.0	
Channel				47000	47000	47000	up	MPR	
Frequency (MHz)				3705	3750	3795	up	(dB)	
10	QPSK	1	1	26.65	26.60	26.64	27.0	0.0	

Part27Q n78 PC2 Ant10 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune up limit (dBm)	MPR (dB)	
Channel				633334			27.0	0.0	
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1	26.39			27.0	0.0	
100	1/2 BPSK	1	137	26.40					
100	1/2 BPSK	1	271	26.48			27.0	0.0	
100	1/2 BPSK	135	0	26.32					
100	1/2 BPSK	135	69	26.46			27.0	0.0	
100	1/2 BPSK	135	138	26.41					
100	1/2 BPSK	270	0	26.45			27.0	0.0	
100	QPSK	1	1	26.50					
100	QPSK	1	137	26.52			27.0	0.0	
100	QPSK	1	271	26.43					
100	QPSK	135	0	26.48			27.0	0.0	
100	QPSK	135	69	26.36					
100	QPSK	135	138	26.52			27.0	0.0	
100	QPSK	270	0	26.51					
100	16QAM	1	1	26.40			27.0	0.0	
100	64QAM	1	1	26.10				26.5	
100	256QAM	1	1	24.01			24.5		2.5
Channel				633000	633334	633668	Tune up limit	MPR	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	26.52	26.50	26.53	27.0	0.0	
Channel				632668	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510	Tune up limit	MPR	
80	QPSK	1	1	26.48	26.52	26.54		27.0	
Channel				632314	633334	634354	Tune up limit	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	26.49	26.47	26.47	Tune up limit	27.0	
Channel				632000	633334	634668			
Frequency (MHz)				3480	3500.01	3520.02	Tune up limit	MPR	
60	QPSK	1	1	26.54	26.53	26.49		27.0	
Channel				631668	633334	635000	Tune up limit	MPR	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	26.54	26.46	26.52	Tune up limit	27.0	
Channel				631334	633334	635334			
Frequency (MHz)				3470.01	3500.01	3530.01	Tune up limit	MPR	
40	QPSK	1	1	26.54	26.48	26.47		27.0	
Channel				631000	633334	635668	Tune up limit	MPR	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	26.46	26.52	26.45	Tune up limit	27.0	
Channel				630834	633334	635834			
Frequency (MHz)				3462.51	3500.01	3537.51	Tune up limit	MPR	
25	QPSK	1	1	26.55	26.53	26.48		27.0	
Channel				630500	633334	636000	Tune up limit	MPR	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	26.45	26.48	26.49	Tune up limit	27.0	
Channel				630500	633334	636168			
Frequency (MHz)				3457.5	3500.01	3542.52	Tune up limit	MPR	
15	QPSK	1	1	26.52	26.48	26.53		27.0	
Channel				630334	633334	636334	Tune up limit	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	26.47	26.54	26.46	27.0		0.0

Full & Default Power Mode_Other PA

n7 Ant5 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	21.74	21.71	21.60			
50	1/2 BPSK	1	135	21.71	21.72	21.62	22.5	0.0	
50	1/2 BPSK	1	268	21.64	21.74	21.58			
50	1/2 BPSK	135	0	21.33	21.26	21.24	22.0	0.5	
50	1/2 BPSK	135	68	21.74	21.71	21.57	22.5	0.0	
50	1/2 BPSK	135	135	21.31	21.36	21.20	22.0	0.5	
50	1/2 BPSK	270	0	21.32	21.31	21.15			
50	QPSK	1	1	21.77	21.82	21.70			
50	QPSK	1	135	21.66	21.70	21.57	22.5	0.0	
50	QPSK	1	268	21.74	21.67	21.65			
50	QPSK	135	0	20.71	20.78	20.73	21.5	1.0	
50	QPSK	135	68	21.69	21.76	21.57	22.5	0.0	
50	QPSK	135	135	20.77	20.80	20.74	21.5	1.0	
50	QPSK	270	0	20.78	20.81	20.64			
50	16QAM	1	1	20.77	20.79	20.76	21.5	1.0	
50	64QAM	1	1	19.26	19.27	19.20	20.0	2.5	
50	256QAM	1	1	17.24	17.35	17.20	18.0	4.5	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	21.64	21.69	21.59	22.5	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	21.68	21.71	21.67	22.5	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	21.69	21.75	21.60	22.5	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	21.67	21.66	21.67	22.5	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	21.69	21.68	21.66	22.5	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	21.72	21.75	21.56	22.5	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	21.66	21.75	21.67	22.5	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	21.73	21.72	21.58	22.5	0.0	

n66 Ant5 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	21.73	21.68	21.65			
45	1/2 BPSK	1	120	21.76	21.72	21.72	22.8	0.0	
45	1/2 BPSK	1	240	21.71	21.68	21.70			
45	1/2 BPSK	120	0	21.28	21.37	21.23	22.3	0.5	
45	1/2 BPSK	120	60	21.74	21.75	21.74	22.8	0.0	
45	1/2 BPSK	120	120	21.29	21.34	21.26	22.3	0.5	
45	1/2 BPSK	240	0	21.28	21.32	21.24			
45	QPSK	1	1	21.79	21.82	21.76			
45	QPSK	1	120	21.69	21.75	21.72	22.8	0.0	
45	QPSK	1	240	21.66	21.72	21.70			
45	QPSK	120	0	20.77	20.84	20.71	21.8	1.0	
45	QPSK	120	60	21.75	21.76	21.74	22.8	0.0	
45	QPSK	120	120	20.80	20.79	20.72	21.8	1.0	
45	QPSK	240	0	20.76	20.87	20.73			
45	16QAM	1	1	20.81	20.78	20.75	21.8	1.0	
45	64QAM	1	1	19.30	19.37	19.25	20.3	2.5	
45	256QAM	1	1	17.25	17.37	17.31	18.3	4.5	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	21.72	21.71	21.64	22.8	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	21.76	21.79	21.69	22.8	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	21.67	21.72	21.70	22.8	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	21.69	21.78	21.67	22.8	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	21.73	21.77	21.70	22.8	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	21.76	21.71	21.65	22.8	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	21.69	21.77	21.73	22.8	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	21.71	21.71	21.64	22.8	0.0	

n38 Ant5 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				516004	516000	516996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	21.65	21.70	21.65			
40	1/2 BPSK	1	53	21.59	21.67	21.65	22.5	0.0	
40	1/2 BPSK	1	104	21.67	21.71	21.63			
40	1/2 BPSK	50	0	21.24	21.28	21.18	22.0	0.5	
40	1/2 BPSK	50	26	21.96	21.85	21.86	22.5	0.0	
40	1/2 BPSK	50	56	21.21	21.31	21.23			
40	1/2 BPSK	100	0	21.17	21.24	21.22	22.0	0.5	
40	QPSK	1	1	21.71	21.76	21.74			
40	QPSK	1	53	21.66	21.70	21.66	22.5	0.0	
40	QPSK	1	104	21.64	21.69	21.64			
40	QPSK	50	0	20.70	20.79	20.70	21.5	1.0	
40	QPSK	50	26	21.63	21.72	21.62	22.5	0.0	
40	QPSK	50	56	20.65	20.78	20.72			
40	QPSK	100	0	20.76	20.80	20.68	21.5	1.0	
40	16QAM	1	1	20.68	20.74	20.73	21.5	1.0	
40	64QAM	1	1	19.26	19.24	19.29	20.0	2.5	
40	256QAM	1	1	17.18	17.21	17.24	18.0	4.5	
Channel				517002	516000	520998			
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	21.81	21.82	21.61	22.5	0.0	
Channel				516504	519000	521496			
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	21.58	21.73	21.66	22.5	0.0	
Channel				516000	519000	522000			
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	21.68	21.72	21.63	22.5	0.0	
Channel				515502	519000	522498			
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	21.68	21.67	21.64	22.5	0.0	
Channel				515004	518000	522996			
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	21.62	21.71	21.71	22.5	0.0	

n41 Ant5 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518596	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	21.51	21.50	21.42			
100	1/2 BPSK	1	137	21.46	21.55	21.52	22.6	0.0	
100	1/2 BPSK	1	271	21.52	21.56	21.45			
100	1/2 BPSK	135	0	21.09	21.12	21.10	22.1	0.5	
100	1/2 BPSK	135	69	21.50	21.49	21.43	22.6	0.0	
100	1/2 BPSK	135	138	21.01	21.13	21.06			
100	1/2 BPSK	270	0	21.12	21.09	21.03	22.1	0.5	
100	QPSK	1	1	21.57	21.61	21.58			
100	QPSK	1	137	21.45	21.54	21.51	22.6	0.0	
100	QPSK	1	271	21.47	21.52	21.47			
100	QPSK	135	0	20.60	20.64	20.55	21.6	1.0	
100	QPSK	135	69	21.54	21.57	21.49	22.6	0.0	
100	QPSK	135	138	20.62	20.62	20.54			
100	QPSK	270	0	20.62	20.65	20.57	21.6	1.0	
100	16QAM	1	1	20.52	20.61	20.52	21.6	1.0	
100	64QAM	1	1	19.11	19.07	19.07	20.1	2.5	
100	256QAM	1	1	17.08	17.11	17.10	18.1	4.5	
Channel				505200	518596	529996			
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	21.43	21.55	21.51	22.6	0.0	
Channel				507204	518596	529996			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	21.46	21.49	21.45	22.6	0.0	
Channel				503200	511596	531000			
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	21.46	21.58	21.47	22.6	0.0	
Channel				505200	518596	531996			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	21.51	21.56	21.48	22.6	0.0	
Channel				504204	511596	532996			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	21.55	21.59	21.53	22.6	0.0	
Channel				503700	518596	533496			
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	21.52	21.50	21.42	22.6	0.0	
Channel				502200	511596	534000			
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	21.43	21.51	21.50	22.6	0.0	
Channel				502704	518596	534496			
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	21.45	21.55	21.50	22.6	0.0	
Channel				502200	511596	534996			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	21.47	21.48	21.49	22.6	0.0	
Channel				501702	518596	535500			
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	21.48	21.48	21.45	22.6	0.0	
Channel				501204	518596	535996			
Frequency (MHz)				2506.52	2592.99	2679.99			
20	QPSK	1	1	21.43	21.50	21.49	22.6	0.0	
Channel				500700	518596	536496			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	21.46	21.51	21.46	22.6	0.0	
Channel				500202	518596	537000			
Frequency (MHz)				2501.51	2592.99	2685			
10	QPSK	1	1	21.54	21.48	21.44	22.6	0.0	

Part270 n77 Ant5 Default									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				650000	656000	662000			
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	23.78	23.89	23.81			
100	1/2 BPSK	1	137	23.73	23.90	23.83	25.3	0.0	
100	1/2 BPSK	1	271	23.76	23.81	23.82			
100	1/2 BPSK	135	0	23.35	23.48	23.41	24.8	0.5	
100	1/2 BPSK	135	69	23.76	23.87	23.86	25.3	0.0	
100	1/2 BPSK	135	138	23.35	23.90	23.42	24.8	0.5	
100	1/2 BPSK	270	0	23.34	23.45	23.48			
100	QPSK	1	1	23.86	23.95	23.93			
100	QPSK	1	137	23.78	23.85	23.86	25.3	0.0	
100	QPSK	1	271	23.80	23.82	23.80			
100	QPSK	135	0	22.89	22.94	22.91	24.3	1.0	
100	QPSK	135	69	23.83	23.92	23.88	25.3	0.0	
100	QPSK	135	138	22.86	22.97	22.89			
100	QPSK	270	0	22.85	22.98	22.90	24.3	1.0	
100	16QAM	1	1	22.87	22.93	22.94	24.3	1.0	
100	64QAM	1	1	21.32	21.44	21.41	22.8	2.5	
100	256QAM	1	1	19.32	19.40	19.42	20.8	4.5	
Channel				648668	656000	662314			
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	23.80	23.88	23.89	25.3	0.0	
Channel				649334	656000	662668			
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	23.77	23.87	23.81	25.3	0.0	
Channel				649668	656000	662300			
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	23.72	23.91	23.89	25.3	0.0	
Channel				648668	656000	663334			
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	23.80	23.84	23.84	25.3	0.0	
Channel				649334	656000	662314			
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	1	23.76	23.83	23.81	25.3	0.0	
Channel				648000	656000	662400			
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	23.81	23.88	23.87	25.3	0.0	
Channel				649668	656000	662434			
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	23.82	23.88	23.80	25.3	0.0	
Channel				648000	656000	664500			
Frequency (MHz)				3712.5	3840	3975.5			
25	QPSK	1	1	23.76	23.90	23.86	25.3	0.0	
Channel				649334	656000	662314			
Frequency (MHz)				3710.01	3840	3978.02			
20	QPSK	1	1	23.79	23.92	23.89	25.3	0.0	
Channel				647168	656000	664834			
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	23.81	23.91	23.82	25.3	0.0	
Channel				647000	656000	665000			
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	23.75	23.82	23.84	25.3	0.0	

Part27Q n77 Ant5 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		23.56				
100	1/2 BPSK	1	137		23.63		25.3	0.0	
100	1/2 BPSK	1	271		23.54				
100	1/2 BPSK	135	0		23.19		24.8	0.5	
100	1/2 BPSK	135	69		23.62		25.3	0.0	
100	1/2 BPSK	135	138		23.19		24.8	0.5	
100	1/2 BPSK	270	0		23.09				
100	QPSK	1	1		23.69				
100	QPSK	1	137		23.50		25.3	0.0	
100	QPSK	1	271		23.47				
100	QPSK	135	0		22.62		24.3	1.0	
100	QPSK	135	69		22.51		25.3	0.0	
100	QPSK	135	138		22.72		24.3	1.0	
100	QPSK	270	0		22.64				
100	16QAM	1	1		22.67		24.3	1.0	
100	64QAM	1	1		21.11		22.8	2.5	
100	256QAM	1	1		19.07		20.8	4.5	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	23.54	23.57	23.58	25.3	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	23.56	23.59	23.53	25.3	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	23.45	23.56	23.63	25.3	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	23.52	23.57	23.65	25.3	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	23.52	23.56	23.58	25.3	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	23.51	23.62	23.58	25.3	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	23.46	23.57	23.63	25.3	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	23.46	23.55	23.54	25.3	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	23.49	23.53	23.55	25.3	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	23.52	23.57	23.57	25.3	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	23.45	23.60	23.64	25.3	0.0	

Part27Q n77 PC2 Ant5 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)		
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		25.40				
100	1/2 BPSK	1	137		25.34		27.2	0.0	
100	1/2 BPSK	1	271		25.51				
100	1/2 BPSK	135	0		25.08		26.7	0.5	
100	1/2 BPSK	135	69		25.39		27.2	0.0	
100	1/2 BPSK	135	138		25.02		26.7	0.5	
100	1/2 BPSK	270	0		25.05				
100	QPSK	1	1		25.54				
100	QPSK	1	137		25.36		27.2	0.0	
100	QPSK	1	271		25.51				
100	QPSK	135	0		24.49		26.2	1.0	
100	QPSK	135	69		25.51		27.2	0.0	
100	QPSK	135	138		24.45		26.2	1.0	
100	QPSK	270	0		24.52				
100	16QAM	1	1		24.49		26.2	1.0	
100	64QAM	1	1		23.12		24.7	2.5	
100	256QAM	1	1		21.01		22.7	4.5	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	25.39	25.41	25.39	27.2	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	25.34	25.44	25.35	27.2	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	25.42	25.42	25.36	27.2	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	25.38	25.40	25.35	27.2	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	25.38	25.48	25.31	27.2	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	25.41	25.43	25.34	27.2	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	25.35	25.43	25.32	27.2	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	25.45	25.44	25.33	27.2	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	25.45	25.44	25.34	27.2	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	25.39	25.42	25.33	27.2	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	25.40	25.46	25.40	27.2	0.0	

Part270 n78 Ant5 Default									
BW	Modulat	RB Size	RB Offset	Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.	Tune-up limit		
				Channel		650000			
				Frequency (MHz)		3750			
100	1/2 BPSK	1	1		23.74				
100	1/2 BPSK	1	137		23.76		25.0	0.0	
100	1/2 BPSK	1	271		23.70				
100	1/2 BPSK	135	0		23.32		24.5	0.5	
100	1/2 BPSK	135	69		23.75		25.0	0.0	
100	1/2 BPSK	135	138		23.30		24.5	0.5	
100	1/2 BPSK	270	0		23.33				
100	QPSK	1	1		23.84				
100	QPSK	1	137		23.80		25.0	0.0	
100	QPSK	1	271		23.78				
100	QPSK	135	0		22.84		24.0	1.0	
100	QPSK	135	69		23.80		25.0	0.0	
100	QPSK	135	138		22.82		24.0	1.0	
100	QPSK	270	0		22.89				
100	16QAM	1	1		22.84		24.0	1.0	
100	64QAM	1	1		21.36		22.5	2.5	
100	256QAM	1	1		19.35		20.5	4.5	
				Channel		649668	650000	650334	
				Frequency (MHz)		3745.02	3750	3755.01	
90	QPSK	1	1	23.81	23.82	23.78	25.0	0.0	
				Channel		649334	650000	650668	
				Frequency (MHz)		3740.01	3750	3760.02	
80	QPSK	1	1	23.69	23.80	23.74	25.0	0.0	
				Channel		649000			
				Frequency (MHz)		3735	3750	3765	
70	QPSK	1	1	23.69	23.74	23.71	25.0	0.0	
				Channel		648668	650000	651334	
				Frequency (MHz)		3730.02	3750	3770.01	
60	QPSK	1	1	23.77	23.71	23.66	25.0	0.0	
				Channel		648334	650000	651000	
				Frequency (MHz)		3725.01	3750	3775.02	
50	QPSK	1	1	23.73	23.75	23.70	25.0	0.0	
				Channel		648000	650000	652000	
				Frequency (MHz)		3720	3750	3760	
40	QPSK	1	1	23.71	23.76	23.74	25.0	0.0	
				Channel		647668	650000	652334	
				Frequency (MHz)		3715.02	3750	3785.01	
30	QPSK	1	1	23.73	23.76	23.70	25.0	0.0	
				Channel		647500	650000	652500	
				Frequency (MHz)		3712.5	3750	3787.5	
25	QPSK	1	1	23.70	23.76	23.74	25.0	0.0	
				Channel		647334	650000	652668	
				Frequency (MHz)		3710.01	3750	3790.02	
20	QPSK	1	1	23.69	23.79	23.72	25.0	0.0	
				Channel		647168	650000	652834	
				Frequency (MHz)		3707.50	3750	3792.51	
15	QPSK	1	1	23.77	23.76	23.66	25.0	0.0	
				Channel		647000	650000	653000	
				Frequency (MHz)		3705	3750	3795	
10	QPSK	1	1	23.75	23.77	23.69	25.0	0.0	

Part27Q n78 Ant5 Default							
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)
Channel				633334		3500.01	
Frequency (MHz)				23.37			
100	1/2 BPSK	1	1		23.37		25.0
100	1/2 BPSK	1	137		23.37		25.0
100	1/2 BPSK	1	271		23.32		25.0
100	1/2 BPSK	135	0		22.93		24.5
100	1/2 BPSK	135	69		23.43		25.0
100	1/2 BPSK	135	138		22.92		24.5
100	1/2 BPSK	270	0		22.98		25.0
100	QPSK	1	1		23.48		25.0
100	QPSK	1	137		23.41		25.0
100	QPSK	1	271		23.40		25.0
100	QPSK	135	0		22.48		24.0
100	QPSK	135	69		23.46		25.0
100	QPSK	135	138		22.50		24.0
100	QPSK	270	0		22.53		24.0
100	16QAM	1	1		22.47		24.0
100	64QAM	1	1		20.98		22.5
100	256QAM	1	1		19.05		20.5
Channel				633000	633334	633668	MPR
Frequency (MHz)				3498	3500.01	3505.02	up
90	QPSK	1	1	23.46	23.42	23.43	25.0
Channel				632668	633334	634000	MPR
Frequency (MHz)				3490.02	3500.01	3510	up
80	QPSK	1	1	23.42	23.40	23.31	25.0
Channel				632334	633334	634334	MPR
Frequency (MHz)				3485.01	3500.01	3515.01	up
70	QPSK	1	1	23.40	23.31	23.34	25.0
Channel				632000	633334	634668	MPR
Frequency (MHz)				3480	3500.01	3520.02	up
60	QPSK	1	1	23.42	23.33	23.37	25.0
Channel				631668	633334	635000	MPR
Frequency (MHz)				3475.02	3500.01	3525	up
50	QPSK	1	1	23.32	23.37	23.40	25.0
Channel				631334	633334	635334	MPR
Frequency (MHz)				3470.01	3500.01	3530.01	up
40	QPSK	1	1	23.35	23.32	23.38	25.0
Channel				631000	633334	635668	MPR
Frequency (MHz)				3465	3500.01	3535.02	up
30	QPSK	1	1	23.35	23.39	23.35	25.0
Channel				630834	633334	635834	MPR
Frequency (MHz)				3462.51	3500.01	3537.51	up
25	QPSK	1	1	23.42	23.28	23.40	25.0
Channel				630568	633334	636000	MPR
Frequency (MHz)				3460.02	3500.01	3540	up
20	QPSK	1	1	23.32	23.35	23.37	25.0
Channel				630500	633334	636168	MPR
Frequency (MHz)				3457.5	3500.01	3542.52	up
15	QPSK	1	1	23.44	23.37	23.33	25.0
Channel				630334	633334	636334	MPR
Frequency (MHz)				3455.01	3500.01	3545.01	up
10	QPSK	1	1	23.39	23.30	23.40	25.0

Part27Q n78 PC2 Ant5 Default							
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)
Channel				633334		3500.01	
Frequency (MHz)				25.38			
100	1/2 BPSK	1	1		25.38		26.7
100	1/2 BPSK	1	137		25.35		26.7
100	1/2 BPSK	1	271		25.25		26.2
100	1/2 BPSK	135	0		24.90		26.2
100	1/2 BPSK	135	69		25.36		26.7
100	1/2 BPSK	135	138		24.92		26.2
100	1/2 BPSK	270	0		24.96		26.2
100	QPSK	1	1		25.46		26.7
100	QPSK	1	137		25.33		26.7
100	QPSK	1	271		25.32		26.7
100	QPSK	135	0		24.45		25.7
100	QPSK	135	69		25.43		26.7
100	QPSK	135	138		24.43		25.7
100	QPSK	270	0		24.52		25.7
100	16QAM	1	1		24.48		25.7
100	64QAM	1	1		22.96		24.2
100	256QAM	1	1		20.98		22.2
Channel				633000	633334	633668	MPR
Frequency (MHz)				3495	3500.01	3505.02	up
90	QPSK	1	1	25.39	25.36	25.42	26.7
Channel				632668	633334	634000	MPR
Frequency (MHz)				3490.02	3500.01	3510	up
80	QPSK	1	1	25.31	25.33	25.40	26.7
Channel				632334	633334	634334	MPR
Frequency (MHz)				3485.01	3500.01	3515.01	up
70	QPSK	1	1	25.30	25.23	25.32	26.7
Channel				632000	633334	634668	MPR
Frequency (MHz)				3480	3500.01	3520.02	up
60	QPSK	1	1	25.36	25.30	25.38	26.7
Channel				631668	633334	635000	MPR
Frequency (MHz)				3475.02	3500.01	3525	up
50	QPSK	1	1	25.34	25.25	25.40	26.7
Channel				631334	633334	635334	MPR
Frequency (MHz)				3470.01	3500.01	3530.01	up
40	QPSK	1	1	25.32	25.29	25.31	26.7
Channel				631000	633334	635668	MPR
Frequency (MHz)				3465	3500.01	3535.02	up
30	QPSK	1	1	25.34	25.27	25.33	26.7
Channel				630834	633334	635834	MPR
Frequency (MHz)				3462.51	3500.01	3537.51	up
25	QPSK	1	1	25.33	25.32	25.36	26.7
Channel				630568	633334	636000	MPR
Frequency (MHz)				3460.02	3500.01	3540	up
20	QPSK	1	1	25.37	25.24	25.39	26.7
Channel				630500	633334	636168	MPR
Frequency (MHz)				3457.5	3500.01	3542.52	up
15	QPSK	1	1	25.29	25.31	25.30	26.7
Channel				630334	633334	636334	MPR
Frequency (MHz)				3455.01	3500.01	3545.01	up
10	QPSK	1	1	25.35	25.28	25.38	26.7

n7 Ant4 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	23.40	23.50	23.43	24.7	0.0	
50	1/2 BPSK	1	135	23.47	23.52	23.38			
50	1/2 BPSK	1	268	23.40	23.45	23.40			
50	1/2 BPSK	135	0	23.04	23.12	23.04	24.2	0.5	
50	1/2 BPSK	135	68	23.46	23.46	23.39	24.7	0.0	
50	1/2 BPSK	135	135	23.00	23.14	23.05	24.2	0.5	
50	1/2 BPSK	270	0	22.97	23.13	22.96			
50	QPSK	1	1	23.51	23.58	23.52	24.7	0.0	
50	QPSK	1	135	23.44	23.48	23.42			
50	QPSK	1	268	23.42	23.55	23.50			
50	QPSK	135	0	22.55	22.61	22.53	23.7	1.0	
50	QPSK	135	68	23.44	23.56	23.41	24.7	0.0	
50	QPSK	135	135	22.56	22.54	22.55	23.7	1.0	
50	QPSK	270	0	22.55	22.62	22.51			
50	16QAM	1	1	22.54	22.53	22.56	23.7	1.0	
50	64QAM	1	1	21.03	21.03	20.98	22.2	2.5	
50	256QAM	1	1	18.99	19.06	18.97	20.2	4.5	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	23.40	23.54	23.49	24.7	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	23.46	23.53	23.49	24.7	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	23.43	23.50	23.42	24.7	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	23.41	23.48	23.50	24.7	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	23.41	23.52	23.43	24.7	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	23.43	23.51	23.39	24.7	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	23.43	23.55	23.43	24.7	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	23.43	23.48	23.48	24.7	0.0	

n66 Ant4 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	24.13	24.16	24.05	24.8	0.0	
45	1/2 BPSK	1	120	24.06	24.17	24.08			
45	1/2 BPSK	1	240	24.07	24.18	24.02			
45	1/2 BPSK	120	0	23.71	23.66	23.64	24.3	0.5	
45	1/2 BPSK	120	60	24.07	24.13	24.05	24.8	0.0	
45	1/2 BPSK	120	120	23.66	23.76	23.66	24.3	0.5	
45	1/2 BPSK	240	0	23.74	23.67	23.71			
45	QPSK	1	1	24.19	24.22	24.16	24.8	0.0	
45	QPSK	1	120	24.16	24.16	24.10			
45	QPSK	1	240	24.10	24.11	24.10			
45	QPSK	120	0	23.21	23.25	23.12	23.8	1.0	
45	QPSK	120	60	24.16	24.19	24.11	24.8	0.0	
45	QPSK	120	120	23.25	23.18	23.14	23.8	1.0	
45	QPSK	240	0	23.20	23.27	23.13			
45	16QAM	1	1	23.16	23.24	23.20	23.8	1.0	
45	64QAM	1	1	21.67	21.69	21.64	22.3	2.5	
45	256QAM	1	1	19.63	19.72	19.61	20.3	4.5	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	24.08	24.15	24.10	24.8	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	24.13	24.11	24.04	24.8	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	24.09	24.18	24.12	24.8	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	24.06	24.15	24.03	24.8	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	24.15	24.20	24.13	24.8	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	24.11	24.18	24.04	24.8	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	24.05	24.08	24.10	24.8	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	24.10	24.13	24.12	24.8	0.0	

n38 Ant4 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	23.28	23.25	23.18			
40	1/2 BPSK	1	53	23.31	23.30	23.27	24.7	0.0	
40	1/2 BPSK	1	104	23.29	23.33	23.22			
40	1/2 BPSK	50	0	22.85	22.85	22.79	24.2	0.5	
40	1/2 BPSK	50	26	23.26	23.24	23.25	24.7	0.0	
40	1/2 BPSK	50	56	22.87	22.84	22.77			
40	1/2 BPSK	100	0	22.84	22.88	22.80	24.2	0.5	
40	QPSK	1	1	23.35	23.30	23.31			
40	QPSK	1	53	23.32	23.28	23.27	24.7	0.0	
40	QPSK	1	104	23.24	23.29	23.23			
40	QPSK	50	0	22.32	22.33	22.36	23.7	1.0	
40	QPSK	50	26	23.21	23.34	23.21	24.7	0.0	
40	QPSK	50	56	22.35	22.32	22.33			
40	QPSK	100	0	22.34	22.35	22.31	23.7	1.0	
40	16QAM	1	1	22.38	22.31	22.32	23.7	1.0	
40	64QAM	1	1	20.87	20.89	20.81	22.2	2.5	
40	256QAM	1	1	18.87	18.81	18.77	20.2	4.5	
Channel				517002	516000	520998			
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	23.31	23.27	23.27	24.7	0.0	
Channel				516504	519000	521496			
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	23.35	23.36	23.22	24.7	0.0	
Channel				515000	519000	522000			
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	23.32	23.26	23.25	24.7	0.0	
Channel				515502	519000	522498			
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	23.32	23.25	23.24	24.7	0.0	
Channel				515004	519000	522500			
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	23.23	23.28	23.21	24.7	0.0	

n41 Ant4 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				509002	518598	526000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	23.04	23.21	23.18			
100	1/2 BPSK	1	137	23.09	23.19	23.20	24.7	0.0	
100	1/2 BPSK	1	271	23.02	23.12	23.19			
100	1/2 BPSK	135	0	22.68	22.70	22.75	24.2	0.5	
100	1/2 BPSK	135	69	23.07	23.14	23.17	24.7	0.0	
100	1/2 BPSK	135	138	22.65	22.76	22.75			
100	1/2 BPSK	270	0	22.62	22.70	22.78	24.2	0.5	
100	QPSK	1	1	23.16	23.25	23.23			
100	QPSK	1	137	23.08	23.19	23.17	24.7	0.0	
100	QPSK	1	271	23.04	23.23	23.18			
100	QPSK	135	0	22.14	22.27	22.24	23.7	1.0	
100	QPSK	135	69	23.05	23.20	23.14	24.7	0.0	
100	QPSK	135	138	22.22	22.19	22.21			
100	QPSK	270	0	22.13	22.30	22.22	23.7	1.0	
100	16QAM	1	1	22.16	22.23	22.28	23.7	1.0	
100	64QAM	1	1	20.62	20.76	20.73	22.2	2.5	
100	256QAM	1	1	18.62	18.50	18.75	20.2	4.5	
Channel				508000	518598	525998			
Frequency (MHz)				2541	2592.99	2644.99			
90	QPSK	1	1	23.10	23.12	23.11	24.7	0.0	
Channel				507204	518598	525998			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	23.09	23.22	23.14	24.7	0.0	
Channel				506202	518598	531000			
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	23.03	23.18	23.18	24.7	0.0	
Channel				505200	518598	531996			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	23.08	23.13	23.20	24.7	0.0	
Channel				504204	518598	532098			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	23.05	23.12	23.17	24.7	0.0	
Channel				503700	518598	533496			
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	23.03	23.14	23.14	24.7	0.0	
Channel				502802	518598	533500			
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	23.09	23.20	23.18	24.7	0.0	
Channel				502704	518598	534498			
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	23.11	23.15	23.13	24.7	0.0	
Channel				502200	518598	533598			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	23.09	23.21	23.18	24.7	0.0	
Channel				501702	518598	535500			
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	23.04	23.11	23.13	24.7	0.0	
Channel				501204	518598	535998			
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	23.08	23.11	23.17	24.7	0.0	
Channel				500700	518598	536496			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	23.02	23.21	23.11	24.7	0.0	
Channel				500202	518598	537000			
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	23.05	23.22	23.14	24.7	0.0	

n48 Ant4 Default									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR	
Channel				638000	641666	645332			
Frequency (MHz)				3570	3624.99	3679.98			
40	1/2 BPSK	1	1	23.04	23.13	22.97			
40	1/2 BPSK	1	53	23.03	23.04	22.96	24.5	0.0	
40	1/2 BPSK	1	104	22.99	23.04	22.94			
40	1/2 BPSK	50	0	22.69	22.64	22.52	24.0	0.5	
40	1/2 BPSK	50	26	23.10	23.12	22.99	24.5	0.0	
40	1/2 BPSK	50	56	22.69	22.62	22.55			
40	1/2 BPSK	100	0	22.67	22.63	22.52	24.0	0.5	
40	QPSK	1	1	23.13	23.16	23.05			
40	QPSK	1	53	23.05	23.10	22.96	24.5	0.0	
40	QPSK	1	104	23.02	23.09	23.01			
40	QPSK	50	0	22.15	22.15	21.99	23.5	1.0	
40	QPSK	50	26	23.01	23.11	22.97	24.5	0.0	
40	QPSK	50	56	22.13	22.17	22.03			
40	QPSK	100	0	22.17	22.22	22.03	23.5	1.0	
40	16QAM	1	1	22.17	22.11	22.06	23.5	1.0	
40	64QAM	1	1	20.57	20.66	20.59	22.0	2.5	
40	256QAM	1	1	18.62	18.71	18.59	20.0	4.5	
Channel				637668	641666	645566			
Frequency (MHz)				3565.02	3624.99	3684.99			
30	QPSK	1	1	23.08	23.07	23.02	24.5	0.0	
Channel				637334	641666	646000			
Frequency (MHz)				3560.01	3624.99	3690			
20	QPSK	1	1	23.06	23.12	22.96	24.5	0.0	
Channel				637168	641666	645168			
Frequency (MHz)				3557.22	3624.99	3672.29			
15	QPSK	1	1	23.11	23.08	22.92	24.5	0.0	
Channel				637000	641666	645332			
Frequency (MHz)				3555	3624.99	3694.98			
10	QPSK	1	1	23.05	23.11	22.99	24.5	0.0	

Part270 n77 PC2 Ant4 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3790	3840	3930			
100	1/2 BPSK	1	1	27.74	27.89	27.83			
100	1/2 BPSK	1	137	27.79	27.78	27.81	28.5	0.0	
100	1/2 BPSK	1	271	27.68	27.74	27.82			
100	1/2 BPSK	135	0	27.36	27.39	27.37	28.0	0.5	
100	1/2 BPSK	135	69	27.75	27.86	27.94	28.5	0.0	
100	1/2 BPSK	135	138	27.35	27.35	27.37			
100	1/2 BPSK	270	0	27.39	27.42	27.45	28.0	0.5	
100	QPSK	1	1	27.90	27.95	27.91			
100	QPSK	1	137	27.78	27.75	27.85	28.5	0.0	
100	QPSK	1	271	27.70	27.74	27.78			
100	QPSK	135	0	26.79	27.00	26.82	27.5	1.0	
100	QPSK	135	69	27.69	27.92	27.81	28.5	0.0	
100	QPSK	135	138	26.85	26.84	26.90			
100	QPSK	270	0	26.79	27.00	26.91	27.5	1.0	
100	16QAM	1	1	26.79	26.86	26.93	27.5	1.0	
100	64QAM	1	1	25.36	25.42	25.40	26.0	2.5	
100	256QAM	1	1	23.42	23.52	23.41	24.0	4.5	
Channel				646668	650000	662334			
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	27.86	27.87	27.80	28.5	0.0	
Channel				649334	650000	662668			
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	27.84	27.83	27.83	28.5	0.0	
Channel				649200	650000	663000			
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	27.78	27.84	27.78	28.5	0.0	
Channel				648668	650000	663334			
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	27.87	27.87	27.80	28.5	0.0	
Channel				648334	650000	663668			
Frequency (MHz)				3725.01	3840	3985.02			
50	QPSK	1	1	27.88	27.87	27.81	28.5	0.0	
Channel				648000	650000	664000			
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	27.77	27.93	27.87	28.5	0.0	
Channel				647200	650000	664334			
Frequency (MHz)				3715.02	3840	3985.01			
30	QPSK	1	1	27.84	27.88	27.86	28.5	0.0	
Channel				647500	650000	664500			
Frequency (MHz)				3712.5	3840	3967.5			
25	QPSK	1	1	27.81	27.85	27.85	28.5	0.0	
Channel				647334	650000	664668			
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	1	27.81	27.84	27.88	28.5	0.0	
Channel				647168	650000	664834			
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	27.88	27.90	27.78	28.5	0.0	
Channel				647000	650000	665000			
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	27.77	27.90	27.85	28.5	0.0	

Part27Q n77 Ant4 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3600.01	633334				
100	1/2 BPSK	1	1		25.48				
100	1/2 BPSK	1	137		25.43		26.0	0.0	
100	1/2 BPSK	1	271		25.45				
100	1/2 BPSK	135	0		24.99		25.5	0.5	
100	1/2 BPSK	135	69		25.41		26.0	0.0	
100	1/2 BPSK	135	138		25.02				
100	1/2 BPSK	270	0		25.13		25.5	0.5	
100	QPSK	1	1		25.50				
100	QPSK	1	137		25.41		26.0	0.0	
100	QPSK	1	271		25.43				
100	QPSK	135	0		24.58		25.0	1.0	
100	QPSK	135	69		25.49		26.0	0.0	
100	QPSK	135	138		24.55		25.0	1.0	
100	QPSK	270	0		24.66		25.0	1.0	
100	16QAM	1	1		24.57		25.0	1.0	
100	64QAM	1	1		23.03		23.5	2.5	
100	256QAM	1	1		21.12		21.5	4.5	
Channel									
Frequency (MHz)				633000	633334	633668			
90	QPSK	1	1	25.42	25.45	25.45	26.0	0.0	
Channel				632668	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	25.45	25.47	25.45	26.0	0.0	
Channel				632334	633334	634334			
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	25.47	25.47	25.47	26.0	0.0	
Channel				632000	633334	634668			
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	25.41	25.42	25.45	26.0	0.0	
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	25.32	25.33	25.41	26.0	0.0	
Channel				631334	633334	635334			
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	25.28	25.36	25.36	26.0	0.0	
Channel				631000	633334	635668			
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	25.35	25.40	25.38	26.0	0.0	
Channel				630834	633334	635834			
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	25.35	25.37	25.38	26.0	0.0	
Channel				630668	633334	636000			
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	25.32	25.38	25.39	26.0	0.0	
Channel				630500	633334	636168			
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	25.30	25.36	25.38	26.0	0.0	
Channel				630334	633334	636334			
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	25.32	25.41	25.31	26.0	0.0	

Part27Q n77 PC2 Ant4 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		27.53				
100	1/2 BPSK	1	137		27.49		28.5	0.0	
100	1/2 BPSK	1	271		27.53				
100	1/2 BPSK	135	0		27.06		28.0	0.5	
100	1/2 BPSK	135	69		27.45		28.5	0.0	
100	1/2 BPSK	135	138		27.05				
100	1/2 BPSK	270	0		27.14		28.0	0.5	
100	QPSK	1	1		27.55				
100	QPSK	1	137		27.50		28.5	0.0	
100	QPSK	1	271		27.44				
100	QPSK	135	0		26.80		27.5	1.0	
100	QPSK	135	69		27.54		28.5	0.0	
100	QPSK	135	138		26.54		27.5	1.0	
100	QPSK	270	0		26.69				
100	16QAM	1	1		26.57		27.5	1.0	
100	64QAM	1	1		25.11		28.0	2.5	
100	256QAM	1	1		23.16		24.0	4.5	
Channel				633335					
Frequency (MHz)				3495.3600			3668.96		
90	QPSK	1	1	27.56	27.53	27.49	28.5	0.0	
Channel				632668 633334 634000					
Frequency (MHz)				3490.02 3500.01 3510					
80	QPSK	1	1	27.44	27.49	27.43	28.5	0.0	
Channel				632631 633335 634315					
Frequency (MHz)				3485.01 3500.01 3515.01					
70	QPSK	1	1	27.42	27.45	27.35	28.5	0.0	
Channel				632000 633334 634668					
Frequency (MHz)				3490.3500 3500.01 3520.02					
60	QPSK	1	1	27.44	27.42	27.46	28.5	0.0	
Channel				631168 633334 635000					
Frequency (MHz)				3475.02 3500.01 3525					
50	QPSK	1	1	27.39	27.48	27.43	28.5	0.0	
Channel				631334 633334 635334					
Frequency (MHz)				3470.01 3500.01 3530.01					
40	QPSK	1	1	27.42	27.51	27.44	28.5	0.0	
Channel				631005 633334 635665					
Frequency (MHz)				3465.3500 3500.01 3535.02					
30	QPSK	1	1	27.49	27.48	27.38	28.5	0.0	
Channel				630834 633334 635834					
Frequency (MHz)				3462.51 3500.01 3537.51					
25	QPSK	1	1	27.45	27.51	27.39	28.5	0.0	
Channel				630668 633334 636068					
Frequency (MHz)				3460.02 3500.01 3540					
20	QPSK	1	1	27.41	27.41	27.41	28.5	0.0	
Channel				630500 633334 636168					
Frequency (MHz)				3457.5 3500.01 3542.52					
15	QPSK	1	1	27.45	27.51	27.41	28.5	0.0	
Channel				630334 633334 636334					
Frequency (MHz)				3455.01 3500.01 3545.01					
10	QPSK	1	1	27.47	27.40	27.46	28.5	0.0	

Part270 n78 PC2 Ant4 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	1/2 BPS	1	1		27.83				
100	1/2 BPS	1	137		27.78		28.5	0.0	
100	1/2 BPS	1	271		27.77				
100	1/2 BPS	135	0		27.94		28.0	0.5	
100	1/2 BPS	135	69		27.85		28.5	0.0	
100	1/2 BPS	135	138		27.32				
100	1/2 BPS	270	0		27.30		28.0	0.5	
100	QPSK	1	1		27.85				
100	QPSK	1	137		27.77		28.5	0.0	
100	QPSK	1	271		27.79				
100	QPSK	135	0		26.88		27.5	1.0	
100	QPSK	135	69		27.83		28.5	0.0	
100	QPSK	135	138		26.81		27.5	1.0	
100	QPSK	270	0		26.85				
100	16QAM	1	1		26.83		27.5	1.0	
100	64QAM	1	1		26.32		26.0	2.5	
100	256QAM	1	1		23.30		24.0	4.5	
Channel				648668	650000	650334	up		
Frequency (MHz)				3745.02	3750	3755.01	up		
90	QPSK	1	1	27.70	27.80	27.80	28.5	0.0	
Channel				649334	650000	650668	up		
Frequency (MHz)				3740.01	3750	3760.02	up		
80	QPSK	1	1	27.65	27.71	27.71	28.5	0.0	
Channel				649000	650000	651000	up		
Frequency (MHz)				3735	3750	3765	up		
70	QPSK	1	1	27.56	27.70	27.76	28.5	0.0	
Channel				648668	650000	651334	up		
Frequency (MHz)				3730.02	3750	3770.01	up		
60	QPSK	1	1	27.67	27.75	27.69	28.5	0.0	
Channel				648334	650000	651668	up		
Frequency (MHz)				3725.01	3750	3775.02	up		
50	QPSK	1	1	27.68	27.71	27.69	28.5	0.0	
Channel				648000	650000	652000	up		
Frequency (MHz)				3720	3750	3780	up		
40	QPSK	1	1	27.65	27.69	27.76	28.5	0.0	
Channel				647668	650000	652334	up		
Frequency (MHz)				3715.02	3750	3785.01	up		
30	QPSK	1	1	27.57	27.69	27.75	28.5	0.0	
Channel				647500	650000	652500	up		
Frequency (MHz)				3712.5	3750	3787.5	up		
25	QPSK	1	1	27.59	27.69	27.75	28.5	0.0	
Channel				647334	650000	652668	up		
Frequency (MHz)				3710.01	3750	3790.02	up		
20	QPSK	1	1	27.63	27.70	27.75	28.5	0.0	
Channel				647168	650000	652834	up		
Frequency (MHz)				3707.52	3750	3792.51	up		
15	QPSK	1	1	27.56	27.76	27.69	28.5	0.0	
Channel				647000	650000	653000	up		
Frequency (MHz)				3705	3750	3795	up		
10	QPSK	1	1	27.60	27.77	27.68	28.5	0.0	

Part27Q n78 Ant4 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		25.56				
100	1/2 BPS	1	137		25.60		26.0	0.0	
100	1/2 BPS	1	271		25.60				
100	1/2 BPS	135	0		25.09		25.5	0.5	
100	1/2 BPS	135	69		25.48		26.0	0.0	
100	1/2 BPS	138	138		25.07				
100	1/2 BPS	270	0		25.04		25.5	0.5	
100	QPSK	1	1		25.61				
100	QPSK	1	137		25.53		26.0	0.0	
100	QPSK	1	271		25.56				
100	QPSK	135	0		24.68		25.0	1.0	
100	QPSK	135	69		25.59		26.0	0.0	
100	QPSK	138	138		24.64		25.0	1.0	
100	QPSK	270	0		24.61				
100	16QAM	1	1		24.58		25.0	1.0	
100	64QAM	1	1		23.11		23.5	2.5	
100	256QAM	1	1		21.08		21.5	4.5	
Channel				633000	633334	633668	up		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	25.46	25.54	25.56	26.0	0.0	
Channel				632668	633334	634000	up		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	25.42	25.41	25.42	26.0	0.0	
Channel				632334	633334	634334	up		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	25.40	25.51	25.52	26.0	0.0	
Channel				632000	633334	634668	up		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	25.37	25.45	25.44	26.0	0.0	
Channel				631668	633334	635000	up		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	25.39	25.52	25.42	26.0	0.0	
Channel				631334	633334	635334	up		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	25.41	25.44	25.48	26.0	0.0	
Channel				631000	633334	635668	up		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	25.38	25.45	25.44	26.0	0.0	
Channel				630834	633334	635834	up		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	25.36	25.48	25.46	26.0	0.0	
Channel				630568	633334	636000	up		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	25.33	25.51	25.48	26.0	0.0	
Channel				630500	633334	636168	up		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	25.34	25.51	25.52	26.0	0.0	
Channel				630334	633334	636334	up		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	25.41	25.51	25.48	26.0	0.0	

Part27Q n78 PC2 Ant4 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		27.54				
100	1/2 BPS	1	137		27.46		28.5	0.0	
100	1/2 BPS	1	271		27.50				
100	1/2 BPS	135	0		27.02		28.0	0.5	
100	1/2 BPS	135	69		27.37		28.5	0.0	
100	1/2 BPS	135	138		27.01				
100	1/2 BPS	270	0		27.04		28.0	0.5	
100	QPSK	1	1		27.58				
100	QPSK	1	137		27.45		28.5	0.0	
100	QPSK	1	271		27.50				
100	QPSK	135	0		26.80		27.5	1.0	
100	QPSK	135	69		27.53		28.5	0.0	
100	QPSK	135	138		26.54		27.5	1.0	
100	QPSK	270	0		26.53				
100	16QAM	1	1		26.51		27.5	1.0	
100	64QAM	1	1		25.00		26.0	2.5	
100	256QAM	1	1		22.98		24.0	4.5	
Channel				633000	633334	633668	up		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	27.34	27.46	27.44	28.5	0.0	
Channel				632668	633334	634000	up		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	27.34	27.52	27.46	28.5	0.0	
Channel				633234	633334	633434	up		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	27.41	27.54	27.45	28.5	0.0	
Channel				632000	633334	634668	up		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	27.34	27.47	27.50	28.5	0.0	
Channel				631668	633334	635000	up		
Frequency (MHz)				3475.02	3500.01	3525.02	up		
50	QPSK	1	1	27.45	27.52	27.51	28.5	0.0	
Channel				631334	633334	635334	up		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	27.34	27.52	27.53	28.5	0.0	
Channel				631000	633334	635668	up		
Frequency (MHz)				3465	3500.01	3536.02	up		
30	QPSK	1	1	27.40	27.52	27.49	28.5	0.0	
Channel				630834	633334	635834	up		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	27.38	27.48	27.47	28.5	0.0	
Channel				631000	633334	635834	up		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	27.43	27.52	27.46	28.5	0.0	
Channel				630500	633334	631668	up		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	27.35	27.56	27.54	28.5	0.0	
Channel				630834	633334	635834	up		
Frequency (MHz)				3456.01	3500.01	3546.01	up		
10	QPSK	1	1	27.35	27.48	27.49	28.5	0.0	

n7 Ant6 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	25.17	25.22	25.18	25.5	0.0	
50	1/2 BPSK	1	135	25.17	25.17	25.19			
50	1/2 BPSK	1	268	25.14	25.15	25.20			
50	1/2 BPSK	135	0	24.70	24.80	24.71	25.0	0.5	
50	1/2 BPSK	135	68	25.10	25.21	25.13	25.5	0.0	
50	1/2 BPSK	135	135	24.70	24.81	24.78			
50	1/2 BPSK	270	0	24.75	24.76	24.71	25.0	0.5	
50	QPSK	1	1	25.23	25.25	25.22			
50	QPSK	1	135	25.13	25.11	25.20	25.5	0.0	
50	QPSK	1	268	25.19	25.13	25.15			
50	QPSK	135	0	24.19	24.26	24.25	24.5	1.0	
50	QPSK	135	68	25.14	25.20	25.12	25.5	0.0	
50	QPSK	135	135	24.21	24.25	24.20			
50	QPSK	270	0	24.26	24.27	24.20	24.5	1.0	
50	16QAM	1	1	24.27	24.24	24.28	24.5	1.0	
50	64QAM	1	1	22.77	22.71	22.68	23.0	2.5	
50	256QAM	1	1	20.70	20.76	20.77	21.0	4.5	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	25.10	25.15	25.15	25.5	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	25.13	25.19	25.13	25.5	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	25.16	25.21	25.12	25.5	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	25.17	25.22	25.09	25.5	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	25.12	25.20	25.18	25.5	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	25.15	25.21	25.18	25.5	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	25.19	25.13	25.18	25.5	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	25.16	25.15	25.19	25.5	0.0	

n66 Ant6 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	24.87	24.96	24.84			
45	1/2 BPSK	1	120	24.89	24.92	24.87	25.5	0.0	
45	1/2 BPSK	1	240	24.88	24.94	24.96			
45	1/2 BPSK	120	0	24.41	24.46	24.46	25.0	0.5	
45	1/2 BPSK	120	60	24.89	24.90	24.90	25.5	0.0	
45	1/2 BPSK	120	120	24.48	24.50	24.45	25.0	0.5	
45	1/2 BPSK	240	0	24.44	24.47	24.53			
45	QPSK	1	1	24.93	25.01	24.98			
45	QPSK	1	120	24.88	24.95	24.88	25.5	0.0	
45	QPSK	1	240	24.81	24.96	24.94			
45	QPSK	120	0	23.87	23.97	24.02	24.5	1.0	
45	QPSK	120	60	24.82	24.97	24.90	25.5	0.0	
45	QPSK	120	120	23.92	24.01	23.96			
45	QPSK	240	0	23.90	24.04	24.01	24.5	1.0	
45	16QAM	1	1	23.95	23.99	23.93	24.5	1.0	
45	64QAM	1	1	22.41	22.50	22.54	23.0	2.5	
45	256QAM	1	1	20.40	20.51	20.52	21.0	4.5	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	24.80	24.96	24.85	25.5	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	24.80	24.91	24.95	25.5	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	24.88	24.95	24.94	25.5	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	24.84	24.95	24.86	25.5	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	24.80	24.90	24.89	25.5	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	24.87	24.89	24.90	25.5	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	24.85	24.93	24.93	25.5	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	24.89	24.98	24.87	25.5	0.0	

n38 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				518004	519000	519996	2590.02	2595	2599.98
40	1/2 BPSK	1	1	24.98	24.99	24.96			
40	1/2 BPSK	1	53	25.03	25.00	24.96	25.5	0.0	
40	1/2 BPSK	1	104	24.96	25.05	24.95			
40	1/2 BPSK	50	0	24.56	24.55	24.54	25.0	0.5	
40	1/2 BPSK	50	26	24.96	25.02	24.99	25.5	0.0	
40	1/2 BPSK	50	56	24.59	24.61	24.51			
40	1/2 BPSK	100	0	24.59	24.60	24.53	25.0	0.5	
40	QPSK	1	1	25.08	25.10	25.06			
40	QPSK	1	53	24.99	24.99	24.98	25.5	0.0	
40	QPSK	1	104	25.01	25.07	25.00			
40	QPSK	50	0	24.10	24.07	24.05	24.5	1.0	
40	QPSK	50	26	25.03	25.07	24.96	25.5	0.0	
40	QPSK	50	56	24.07	24.11	24.01			
40	QPSK	100	0	24.12	24.13	24.10	24.5	1.0	
40	16QAM	1	1	24.05	24.09	24.06	24.5	1.0	
40	64QAM	1	1	22.59	22.62	22.52	23.0	2.5	
40	256QAM	1	1	20.64	20.60	20.51	21.0	4.5	
Channel				517002	518000	518998			
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	25.05	25.07	25.02	25.5	0.0	
Channel				516504	519000	521496			
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	25.05	24.98	25.02	25.5	0.0	
Channel				511000	512000	522000			
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	24.99	25.02	25.01	25.5	0.0	
Channel				515502	519000	522498			
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	25.02	25.04	25.02	25.5	0.0	
Channel				515004	519000	522506			
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	25.02	24.97	24.97	25.5	0.0	

n41 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				509002	516598	526000	2546.01	2592.99	2640
100	1/2 BPSK	1	1	24.93	24.93	24.87			
100	1/2 BPSK	1	137	25.04	24.91	24.96	25.5	0.0	
100	1/2 BPSK	1	271	24.93	24.98	24.92			
100	1/2 BPSK	135	0	24.55	24.49	24.48	25.0	0.5	
100	1/2 BPSK	135	69	24.97	25.00	24.94	25.5	0.0	
100	1/2 BPSK	135	138	24.53	24.54	24.46			
100	1/2 BPSK	270	0	24.61	24.54	24.51	25.0	0.5	
100	QPSK	1	1	25.09	25.13	24.97			
100	QPSK	1	137	24.90	24.94	24.96	25.5	0.0	
100	QPSK	1	271	24.93	25.04	24.99			
100	QPSK	135	0	24.04	24.02	24.06	24.5	1.0	
100	QPSK	135	69	24.98	25.09	24.93	25.5	0.0	
100	QPSK	135	138	24.05	24.06	23.92			
100	QPSK	270	0	24.11	24.16	24.06	24.5	1.0	
100	16QAM	1	1	24.01	24.11	24.06	24.5	1.0	
100	64QAM	1	1	22.56	22.63	22.54	23.0	2.5	
100	256QAM	1	1	20.63	20.56	20.49	21.0	4.5	
Channel				508000	516598	526098			
Frequency (MHz)				2541	2592.99	2644.99			
90	QPSK	1	1	25.04	25.05	24.93	25.5	0.0	
Channel				507204	518598	529998			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	25.05	25.00	24.91	25.5	0.0	
Channel				505002	516598	531000			
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	25.02	25.01	24.91	25.5	0.0	
Channel				505000	518598	531996			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	24.98	25.10	24.87	25.5	0.0	
Channel				504204	516598	532098			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	25.03	25.07	24.86	25.5	0.0	
Channel				503700	518598	533496			
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	25.02	25.07	24.92	25.5	0.0	
Channel				503002	516598	533000			
Frequency (MHz)				2516.01	2592.98	2670			
40	QPSK	1	1	25.00	25.06	24.94	25.5	0.0	
Channel				502704	518598	534498			
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	24.97	25.08	24.87	25.5	0.0	
Channel				502200	516598	533098			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	25.02	24.99	24.88	25.5	0.0	
Channel				501702	518598	535500			
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	24.98	25.07	24.93	25.5	0.0	
Channel				501204	516598	533998			
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	25.06	25.05	24.92	25.5	0.0	
Channel				500700	518598	536496			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	24.97	25.01	24.89	25.5	0.0	
Channel				500202	516598	537000			
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	25.06	25.01	24.89	25.5	0.0	

n48 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				638000	641666	645332	3570	3624.99	3679.98
40	1/2 BPSK	1	1	22.04	22.02	22.05			
40	1/2 BPSK	1	53	22.07	22.10	22.01	23.6	0.0	
40	1/2 BPSK	1	104	22.01	22.04	22.03			
40	1/2 BPSK	50	0	21.62	21.65	21.60	23.1	0.5	
40	1/2 BPSK	50	26	22.05	22.01	21.94	23.6	0.0	
40	1/2 BPSK	50	56	21.57	21.62	21.61			
40	1/2 BPSK	100	0	21.61	21.68	21.59	23.1	0.5	
40	QPSK	1	1	22.09	22.15	22.08			
40	QPSK	1	53	21.97	22.03	21.99	23.6	0.0	
40	QPSK	1	104	22.03	22.11	22.03			
40	QPSK	50	0	21.13	21.21	21.04	22.6	1.0	
40	QPSK	50	26	22.00	22.11	22.03	23.6	0.0	
40	QPSK	50	56	21.09	21.14	21.08			
40	QPSK	100	0	21.11	21.18	21.06	22.6	1.0	
40	16QAM	1	1	21.04	21.15	21.13	22.6	1.0	
40	64QAM	1	1	19.63	19.67	19.59	21.1	2.5	
40	256QAM	1	1	17.62	17.65	17.60	19.1	4.5	
Channel				637168	641666	645956			
Frequency (MHz)				3565.02	3624.99	3684.99			
30	QPSK	1	1	21.95	22.01	22.02	23.6	0.0	
Channel				637334	641666	646000			
Frequency (MHz)				3560.01	3624.99	3690			
20	QPSK	1	1	21.98	22.07	21.94	23.6	0.0	
Channel				637100	641666	647106			
Frequency (MHz)				3557.52	3624.99	3692.49			
15	QPSK	1	1	21.95	22.13	21.97	23.6	0.0	
Channel				637000	641666	646332			
Frequency (MHz)				3555	3624.99	3694.98			
10	QPSK	1	1	21.98	22.03	22.03	23.6	0.0	

Part270 n77 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch / Freq	Power Middle Ch / Freq	Power High Ch / Freq	Tune- up Mode	MPR (dB)	
Channel				650000	656000	662000			
Frequency (MHz)									
100	1/2 BPSK	1	1	23.97	24.09	23.83			
100	1/2 BPSK	1	137	23.99	24.12	23.92	25.3	0.0	
100	1/2 BPSK	1	271	23.97	24.01	23.91			
100	1/2 BPSK	135	0	23.48	23.65	23.43	24.8	0.5	
100	1/2 BPSK	135	69	23.97	24.07	23.91	25.3	0.0	
100	1/2 BPSK	135	138	23.54	23.69	23.50		24.8	0.5
100	1/2 BPSK	270	0	23.58	23.70	23.47		24.8	0.5
100	QPSK	1	1	24.04	24.15	23.95			
100	QPSK	1	137	23.99	24.06	23.91	25.3	0.0	
100	QPSK	1	271	23.95	24.08	23.90			
100	QPSK	135	0	23.05	23.17	22.96	24.3	1.0	
100	QPSK	135	69	24.04	24.15	23.96	25.3	0.0	
100	QPSK	135	138	23.04	23.15	22.95		24.3	1.0
100	QPSK	270	0	23.10	23.19	22.90			
100	16QAM	1	1	23.07	23.16	22.93	24.3	1.0	
100	64QAM	1	1	21.59	21.70	21.48	24.8	2.5	
100	256QAM	1	1	19.51	19.61	19.50	20.8	4.5	
Channel				656000	662000				
Frequency (MHz)									
90	QPSK	1	1	23.91	24.02	23.90	25.3	0.0	
Channel				649334	656000	662666			
Frequency (MHz)									
80	QPSK	1	1	23.99	24.11	23.92	25.3	0.0	
Channel				3740	3840	3940			
Frequency (MHz)									
70	QPSK	1	1	23.95	24.01	23.90	25.3	0.0	
Channel				646666	656000	663334			
Frequency (MHz)									
60	QPSK	1	1	23.88	24.09	23.86	25.3	0.0	
Channel				1430	1530	1630			
Frequency (MHz)									
50	QPSK	1	1	23.76	24.01	23.95	25.3	0.0	
Channel				3792	24.02	23.86	25.3	0.0	
Channel				648000	656000	664000			
Frequency (MHz)									
40	QPSK	1	1	23.70	23.94	23.90	25.3	0.0	
Channel				47668	65000	66340			
Frequency (MHz)									
30	QPSK	1	1	23.95	24.07	23.87	25.3	0.0	
Channel				646000	656000	664500			
Frequency (MHz)									
25	QPSK	1	1	3712.5	3840	3957.5	25.3	0.0	
Channel				3712.5	24.08	23.98	25.3	0.0	
Channel				647334	65000	664666			
Frequency (MHz)									
20	QPSK	1	1	3710	3840	3970	25.3	0.0	
Channel				647168	656000	664834			
Frequency (MHz)									
15	QPSK	1	1	3707.5	3840	3972.5	25.3	0.0	
Channel				24.00	24.11	23.99	25.3	0.0	
Channel				647000	65000	664000			
Frequency (MHz)									
10	QPSK	1	1	3705	3840	3975	25.3	0.0	

Part270 n77 PC2 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	25.97	26.08	25.77			
100	1/2 BPSK	1	137	25.97	26.08	25.96	27.3	0.0	
100	1/2 BPSK	1	271	26.01	26.07	25.90			
100	1/2 BPSK	135	0	25.45	25.61	25.41	26.8	0.5	
100	1/2 BPSK	135	69	26.00	26.10	25.93	27.3	0.0	
100	1/2 BPSK	135	138	25.60	25.63	25.53		26.8	0.5
100	1/2 BPSK	270	0	25.56	25.72	25.42	26.8		
100	QPSK	1	1	25.98	26.17	25.99			
100	QPSK	1	137	26.04	26.11	25.86	27.3	0.0	
100	QPSK	1	271	25.97	26.12	25.63			
100	QPSK	135	0	25.02	25.17	24.96	26.3	1.0	
100	QPSK	135	69	26.00	26.14	25.91	27.3	0.0	
100	QPSK	135	138	25.08	25.16	24.85		26.3	1.0
100	QPSK	270	0	25.05	25.15	25.06	26.3		
100	16QAM	1	1	25.09	25.13	24.98	26.3	1.0	
100	64QAM	1	1	23.64	23.69	23.37	24.8	2.5	
100	256QAM	1	1	21.52	21.66	21.44	22.8	4.5	
Channel				646668	650000	662334	MPR (dB)		
Frequency (MHz)				3745.02	3840	3935.01	up (dB)		
90	QPSK	1	1	25.95	26.07	25.91	27.3	0.0	
Channel				649334	650000	662668	MPR (dB)		
Frequency (MHz)				3740.01	3840	3940.02	up (dB)		
80	QPSK	1	1	25.92	26.09	25.91	27.3	0.0	
Channel				649200	650000	662000	MPR (dB)		
Frequency (MHz)				3735	3840	3945	up (dB)		
70	QPSK	1	1	25.88	26.06	25.94	27.3	0.0	
Channel				648668	650000	663334	MPR (dB)		
Frequency (MHz)				3730.02	3840	3950.01	up (dB)		
60	QPSK	1	1	25.87	26.05	25.88	27.3	0.0	
Channel				648334	650000	661668	MPR (dB)		
Frequency (MHz)				3725.01	3840	3955.02	up (dB)		
50	QPSK	1	1	25.87	26.04	25.93	27.3	0.0	
Channel				648000	650000	664000	MPR (dB)		
Frequency (MHz)				3720	3840	3960	up (dB)		
40	QPSK	1	1	25.93	26.08	25.95	27.3	0.0	
Channel				647668	650000	661334	MPR (dB)		
Frequency (MHz)				3715.02	3840	3965.01	up (dB)		
30	QPSK	1	1	25.93	26.05	25.88	27.3	0.0	
Channel				647500	650000	664500	MPR (dB)		
Frequency (MHz)				3712.5	3840	3967.5	up (dB)		
25	QPSK	1	1	25.94	26.04	25.90	27.3	0.0	
Channel				647334	650000	661334	MPR (dB)		
Frequency (MHz)				3710.01	3840	3970.02	up (dB)		
20	QPSK	1	1	25.94	26.09	25.87	27.3	0.0	
Channel				647168	650000	664834	MPR (dB)		
Frequency (MHz)				3707.52	3840	3972.51	up (dB)		
15	QPSK	1	1	25.88	26.07	25.91	27.3	0.0	
Channel				647000	650000	663000	MPR (dB)		
Frequency (MHz)				3705	3840	3975	up (dB)		
10	QPSK	1	1	25.95	26.04	25.85	27.3	0.0	

Part27Q n77 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3600.01	363334				
100	1/2 BPSK	1	1		23.58				
100	1/2 BPSK	1	137		23.58		25.3	0.0	
100	1/2 BPSK	1	271		23.50				
100	1/2 BPSK	135	0		23.17		24.8	0.5	
100	1/2 BPSK	135	69		23.57		25.3	0.0	
100	1/2 BPSK	135	138		23.15		24.8	0.5	
100	1/2 BPSK	270	0		23.15				
100	QPSK	1	1		23.65				
100	QPSK	1	137		23.52		25.3	0.0	
100	QPSK	1	271		23.52				
100	QPSK	135	0		22.99		24.3	1.0	
100	QPSK	135	69		23.62		25.3	0.0	
100	QPSK	135	138		22.72		24.3	1.0	
100	QPSK	270	0		22.62		24.3	1.0	
100	16QAM	1	1		22.67		24.3	1.0	
100	64QAM	1	1		21.17		22.8	2.5	
100	256QAM	1	1		19.08		20.8	4.5	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up (dB)		
90	QPSK	1	1	23.56	23.54	23.52	25.3	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up (dB)		
80	QPSK	1	1	23.58	23.57	23.50	25.3	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up (dB)		
70	QPSK	1	1	23.58	23.51	23.57	25.3	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up (dB)		
60	QPSK	1	1	23.56	23.52	23.54	25.3	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up (dB)		
50	QPSK	1	1	23.53	23.60	23.60	25.3	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up (dB)		
40	QPSK	1	1	23.56	23.49	23.51	25.3	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up (dB)		
30	QPSK	1	1	23.51	23.57	23.58	25.3	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up (dB)		
25	QPSK	1	1	23.59	23.54	23.56	25.3	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up (dB)		
20	QPSK	1	1	23.56	23.52	23.55	25.3	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up (dB)		
15	QPSK	1	1	23.61	23.56	23.50	25.3	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up (dB)		
10	QPSK	1	1	23.57	23.54	23.53	25.3	0.0	

Part27Q n77 PC2 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3500.01	633334				
100	1/2 BPSK	1	1		25.64				
100	1/2 BPSK	1	137		25.57		27.3	0.0	
100	1/2 BPSK	1	271		25.61				
100	1/2 BPSK	135	0		25.06		26.8	0.5	
100	1/2 BPSK	135	69		25.54		27.3	0.0	
100	1/2 BPSK	135	138		25.16			26.8	0.5
100	QPSK	1	1		25.66				
100	QPSK	1	137		25.65		27.3	0.0	
100	QPSK	1	271		25.57				
100	QPSK	135	0		24.72		26.3	1.0	
100	QPSK	135	69		24.59		27.3	0.0	
100	QPSK	135	138		24.61			26.3	1.0
100	QPSK	270	0		24.65				
100	16QAM	1	1		24.64		26.3	1.0	
100	64QAM	1	1		23.21		24.8	2.5	
100	256QAM	1	1		21.21		22.8	4.5	
Channel									
Frequency (MHz)				3495.00	633333	3666.00			
90	QPSK	1	1	25.59	25.51	25.58	27.3	0.0	
Channel				632666	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	25.51	25.54	25.62	27.3	0.0	
Channel				332314	333333	334333			
Frequency (MHz)				3488.01	3500.01	3515.01			
70	QPSK	1	1	25.60	25.62	25.54	27.3	0.0	
Channel				632000	633334	634666			
Frequency (MHz)				3490.01	3500.01	3502.02			
60	QPSK	1	1	25.62	25.57	25.56	27.3	0.0	
Channel				331166	333333	335000			
Frequency (MHz)				3476.02	3500.01	3505			
50	QPSK	1	1	25.58	25.53	25.58	27.3	0.0	
Channel				631334	633334	633334			
Frequency (MHz)				3470.01	3500.01	3508.01			
40	QPSK	1	1	25.61	25.59	25.58	27.3	0.0	
Channel				631005	633334	632666			
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	25.59	25.61	25.57	27.3	0.0	
Channel				630834	633334	633834			
Frequency (MHz)				3460.51	3500.01	3537.51			
25	QPSK	1	1	25.61	25.53	25.59	27.3	0.0	
Channel				630668	633334	632000			
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	25.53	25.55	25.56	27.3	0.0	
Channel				630500	633334	630168			
Frequency (MHz)				3467.3	3500.01	3542.2			
15	QPSK	1	1	25.61	25.56	25.53	27.3	0.0	
Channel				630374	633334	630334			
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	25.56	25.59	25.51	27.3	0.0	

Part270 n78 PC2 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	1/2 BPS	1	1		26.05				
100	1/2 BPS	1	137		26.05		27.2	0.0	
100	1/2 BPS	1	271		26.02				
100	1/2 BPS	135	0		25.53		26.7	0.5	
100	1/2 BPS	135	69		26.06		27.2	0.0	
100	1/2 BPS	135	138		25.49				
100	1/2 BPS	270	0		25.60		26.7	0.5	
100	QPSK	1	1		26.13				
100	QPSK	1	137		26.09		27.2	0.0	
100	QPSK	1	271		26.10				
100	QPSK	135	0		24.93		26.2	1.0	
100	QPSK	135	69		25.98		27.2	0.0	
100	QPSK	135	138		24.98				
100	QPSK	270	0		24.98		26.2	1.0	
100	16QAM	1	1		24.96		26.2	1.0	
100	64QAM	1	1		22.91		24.7	2.5	
100	256QAM	1	1		20.77		22.7	4.5	
Channel				648668	650000	650334	up	MPR	
Frequency (MHz)				3745.02	3750	3755.01	up		
90	QPSK	1	1	26.07	25.98	26.05	27.2	0.0	
Channel				649334	650000	650668	up	MPR	
Frequency (MHz)				3740.01	3750	3760.02	up		
80	QPSK	1	1	26.06	26.07	26.05	27.2	0.0	
Channel				649000	650000	651000	up	MPR	
Frequency (MHz)				3735	3750	3765	up		
70	QPSK	1	1	26.09	26.04	26.01	27.2	0.0	
Channel				648668	650000	651334	up	MPR	
Frequency (MHz)				3730.02	3750	3770.01	up		
60	QPSK	1	1	26.06	26.08	26.01	27.2	0.0	
Channel				648334	650000	651668	up	MPR	
Frequency (MHz)				3725.01	3750	3775.02	up		
50	QPSK	1	1	26.08	26.03	26.00	27.2	0.0	
Channel				648000	650000	652000	up	MPR	
Frequency (MHz)				3720	3750	3780	up		
40	QPSK	1	1	26.04	25.98	26.08	27.2	0.0	
Channel				647668	650000	652334	up	MPR	
Frequency (MHz)				3715.02	3750	3785.01	up		
30	QPSK	1	1	25.98	26.01	25.99	27.2	0.0	
Channel				647500	650000	652500	up	MPR	
Frequency (MHz)				3712.5	3750	3787.5	up		
25	QPSK	1	1	26.00	26.07	26.04	27.2	0.0	
Channel				647334	650000	652668	up	MPR	
Frequency (MHz)				3710.01	3750	3790.02	up		
20	QPSK	1	1	25.98	25.97	25.97	27.2	0.0	
Channel				647168	650000	652834	up	MPR	
Frequency (MHz)				3707.52	3750	3792.51	up		
15	QPSK	1	1	26.05	26.03	25.97	27.2	0.0	
Channel				647000	650000	653000	up	MPR	
Frequency (MHz)				3705	3750	3795	up		
10	QPSK	1	1	25.98	26.09	26.04	27.2	0.0	

Part270Q n78 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		23.54				
100	1/2 BPS	1	137		23.60		25.3	0.0	
100	1/2 BPS	1	271		23.54				
100	1/2 BPS	135	0		23.10		24.8	0.5	
100	1/2 BPS	135	69		23.51		25.3	0.0	
100	1/2 BPS	135	138		23.17				
100	1/2 BPS	270	0		23.21		24.8	0.5	
100	QPSK	1	1		23.72				
100	QPSK	1	137		23.53		25.3	0.0	
100	QPSK	1	271		23.45				
100	QPSK	135	0		22.87		24.3	1.0	
100	QPSK	135	69		23.81		25.3	0.0	
100	QPSK	135	138		22.72				
100	QPSK	270	0		22.57		24.3	1.0	
100	16QAM	1	1		22.84		24.3	1.0	
100	64QAM	1	1		21.21		22.8	2.5	
100	256QAM	1	1		19.12		20.8	4.5	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	23.66	23.56	23.58	25.3	0.0	
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	23.56	23.67	23.62	25.3	0.0	
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	23.57	23.58	23.62	25.3	0.0	
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	23.62	23.65	23.58	25.3	0.0	
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	23.57	23.59	23.58	25.3	0.0	
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	23.57	23.67	23.57	25.3	0.0	
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	23.67	23.64	23.57	25.3	0.0	
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	23.58	23.63	23.57	25.3	0.0	
Channel				630568	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	23.67	23.63	23.61	25.3	0.0	
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	23.61	23.59	23.62	25.3	0.0	
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	23.62	23.63	23.58	25.3	0.0	

Part270Q n78 PC2 Ant6 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		25.50				
100	1/2 BPS	1	137		25.51		27.2	0.0	
100	1/2 BPS	1	271		25.49				
100	1/2 BPS	135	0		25.04		26.7	0.5	
100	1/2 BPS	135	69		25.50		27.2	0.0	
100	1/2 BPS	135	138		24.99				
100	1/2 BPS	270	0		25.12		26.7	0.5	
100	QPSK	1	1		25.69				
100	QPSK	1	137		25.64		27.2	0.0	
100	QPSK	1	271		25.65				
100	QPSK	135	0		24.46		26.2	1.0	
100	QPSK	135	69		25.49		27.2	0.0	
100	QPSK	135	138		24.43				
100	QPSK	270	0		24.62		26.2	1.0	
100	16QAM	1	1		24.48		26.2	1.0	
100	64QAM	1	1		23.16		24.7	2.5	
100	256QAM	1	1		21.14		22.7	4.5	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3485	3500.01	3505.02	up		
90	QPSK	1	1	25.63	25.60	25.59	27.2	0.0	
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	25.60	25.62	25.62	27.2	0.0	
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	25.59	25.57	25.57	27.2	0.0	
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	25.57	25.63	25.62	27.2	0.0	
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	25.64	25.58	25.56	27.2	0.0	
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	25.58	25.61	25.56	27.2	0.0	
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	25.58	25.56	25.54	27.2	0.0	
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	25.63	25.66	25.57	27.2	0.0	
Channel				630668	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	25.65	25.60	25.62	27.2	0.0	
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	25.56	25.61	25.61	27.2	0.0	
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	25.60	25.57	25.62	27.2	0.0	

n7 Ant7 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	22.64	22.62	22.52			
50	1/2 BPSK	1	135	22.65	22.66	22.54	23.8	0.0	
50	1/2 BPSK	1	268	22.53	22.57	22.47			
50	1/2 BPSK	135	0	22.21	22.15	22.15	23.3	0.5	
50	1/2 BPSK	135	68	22.68	22.63	22.42	23.8	0.0	
50	1/2 BPSK	135	135	22.16	22.21	22.09	23.3	0.5	
50	1/2 BPSK	270	0	22.22	22.17	22.01			
50	QPSK	1	1	22.68	22.75	22.71			
50	QPSK	1	135	22.51	22.62	22.44	23.8	0.0	
50	QPSK	1	268	22.69	22.61	22.57			
50	QPSK	135	0	21.58	21.63	21.59	22.8	1.0	
50	QPSK	135	68	22.57	22.69	22.43	23.8	0.0	
50	QPSK	135	135	21.70	21.68	21.64	22.8	1.0	
50	QPSK	270	0	21.71	21.73	21.52			
50	16QAM	1	1	21.66	21.70	21.64	22.8	1.0	
50	64QAM	1	1	20.19	20.19	20.08	21.3	2.5	
50	256QAM	1	1	18.18	18.20	18.10	19.3	4.5	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	22.63	22.68	22.62	23.8	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	22.56	22.68	22.57	23.8	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	22.63	22.59	22.59	23.8	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	22.55	22.66	22.59	23.8	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	22.54	22.63	22.63	23.8	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	22.55	22.60	22.58	23.8	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	22.57	22.60	22.63	23.8	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	22.60	22.67	22.58	23.8	0.0	

n66 Ant7 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	21.89	21.91	21.85			
45	1/2 BPSK	1	120	21.98	22.00	21.84	23.2	0.0	
45	1/2 BPSK	1	240	21.86	21.85	21.77			
45	1/2 BPSK	120	0	21.51	21.41	21.47	22.7	0.5	
45	1/2 BPSK	120	60	21.96	21.92	21.76	23.2	0.0	
45	1/2 BPSK	120	120	21.44	21.57	21.38	22.7	0.5	
45	1/2 BPSK	240	0	21.52	21.52	21.26			
45	QPSK	1	1	22.02	22.08	22.05			
45	QPSK	1	120	21.80	21.87	21.77	23.2	0.0	
45	QPSK	1	240	22.04	21.86	21.85			
45	QPSK	120	0	20.91	20.97	20.94	22.2	1.0	
45	QPSK	120	60	21.83	21.98	21.68	23.2	0.0	
45	QPSK	120	120	20.99	21.00	20.91	22.2	1.0	
45	QPSK	240	0	20.91	20.97	20.77			
45	16QAM	1	1	20.94	20.98	20.96	22.2	1.0	
45	64QAM	1	1	19.55	19.55	19.42	20.7	2.5	
45	256QAM	1	1	17.49	17.44	17.43	18.7	4.5	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	21.93	22.00	21.98	23.2	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	21.93	21.98	22.00	23.2	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	21.92	21.99	21.98	23.2	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	21.88	21.95	21.93	23.2	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	21.96	22.03	21.95	23.2	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	21.93	21.98	21.99	23.2	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	21.93	22.01	21.98	23.2	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	21.95	21.97	21.93	23.2	0.0	

n38 Ant7 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	22.58	22.66	22.46			
40	1/2 BPSK	1	53	22.65	22.62	22.50	23.6	0.0	
40	1/2 BPSK	1	104	22.54	22.62	22.47			
40	1/2 BPSK	50	0	22.18	22.12	22.17	23.1	0.5	
40	1/2 BPSK	50	28	22.62	22.58	22.44	23.6	0.0	
40	1/2 BPSK	50	56	22.14	22.25	22.06	23.1	0.5	
40	1/2 BPSK	100	0	22.22	22.19	21.96			
40	QPSK	1	1	22.73	22.78	22.75			
40	QPSK	1	53	22.56	22.64	22.43	23.6	0.0	
40	QPSK	1	104	22.69	22.58	22.55			
40	QPSK	50	0	21.60	21.60	21.54	22.6	1.0	
40	QPSK	50	28	22.56	22.68	22.41	23.6	0.0	
40	QPSK	50	56	21.72	21.70	21.69	22.6	1.0	
40	QPSK	100	0	21.66	21.75	21.55			
40	16QAM	1	1	21.62	21.66	21.62	22.6	1.0	
40	64QAM	1	1	20.24	20.14	20.12	21.1	2.5	
40	256QAM	1	1	18.22	18.20	18.10	19.1	4.5	
Channel				517002	519000	520998	tune-up limit	MPR (dB)	
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	22.60	22.66	22.63	23.6	0.0	
Channel				516504	519000	521496	tune-up limit	MPR (dB)	
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	22.67	22.72	22.60	23.6	0.0	
Channel				516000	519000	522000	tune-up limit	MPR (dB)	
Frequency (MHz)				2560	2595	2610			
20	QPSK	1	1	22.53	22.63	22.61	23.6	0.0	
Channel				515502	519000	522498	tune-up limit	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	22.68	22.65	22.60	23.6	0.0	
Channel				515004	519000	522996	tune-up limit	MPR (dB)	
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	22.61	22.64	22.70	23.6	0.0	

n41 Ant7 Default									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	22.63	22.67	22.43			
100	1/2 BPSK	1	137	22.59	22.67	22.55	23.7	0.0	
100	1/2 BPSK	1	271	22.54	22.61	22.51			
100	1/2 BPSK	135	0	22.16	22.09	22.12	23.2	0.5	
100	1/2 BPSK	135	69	22.57	22.61	22.47	23.7	0.0	
100	1/2 BPSK	135	138	22.10	22.22	22.10	23.2	0.5	
100	1/2 BPSK	270	0	22.21	22.24	21.96			
100	QPSK	1	1	22.67	22.79	22.72			
100	QPSK	1	137	22.54	22.67	22.43	23.7	0.0	
100	QPSK	1	271	22.72	22.63	22.54			
100	QPSK	135	0	21.56	21.59	21.58	22.7	1.0	
100	QPSK	135	69	22.50	22.63	22.45	23.7	0.0	
100	QPSK	135	138	21.72	21.76	21.64	22.7	1.0	
100	QPSK	270	0	21.70	21.77	21.59			
100	16QAM	1	1	21.63	21.68	21.65	22.7	1.0	
100	64QAM	1	1	20.20	20.14	20.12	21.2	2.5	
100	256QAM	1	1	18.18	18.15	18.12	19.2	4.5	
Channel				508200	518598	528996	tune-up limit	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	22.34	22.51	22.44	23.7	0.0	
Channel				507204	518598	529998	tune-up limit	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	22.39	22.49	22.48	23.7	0.0	
Channel				506202	518598	531000	tune-up limit	MPR (dB)	
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	22.37	22.43	22.45	23.7	0.0	
Channel				505200	518598	531996	tune-up limit	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	22.43	22.45	22.48	23.7	0.0	
Channel				504204	518598	532998	tune-up limit	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	22.31	22.52	22.41	23.7	0.0	
Channel				503700	518598	533496	tune-up limit	MPR (dB)	
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	22.36	22.53	22.37	23.7	0.0	
Channel				503202	518598	534000	tune-up limit	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	22.40	22.46	22.38	23.7	0.0	
Channel				502704	518598	534498	tune-up limit	MPR (dB)	
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	22.43	22.45	22.40	23.7	0.0	
Channel				502200	518598	534996	tune-up limit	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	22.36	22.50	22.35	23.7	0.0	
Channel				501702	518598	535500	tune-up limit	MPR (dB)	
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	22.33	22.44	22.39	23.7	0.0	
Channel				501204	518598	535998	tune-up limit	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	22.42	22.44	22.46	23.7	0.0	
Channel				500700	518598	536496	tune-up limit	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	22.42	22.52	22.37	23.7	0.0	
Channel				500202	518598	537000	tune-up limit	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	22.40	22.49	22.40	23.7	0.0	

Part270 n78 Ant10 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq. 650000	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750					
100	1/2 BPSK	1	1		24.04				
100	1/2 BPSK	1	137		24.02		24.9	0.0	
100	1/2 BPSK	1	271		23.99				
100	1/2 BPSK	135	0		23.57		24.4	0.5	
100	1/2 BPSK	135	69		23.96		24.9	0.0	
100	1/2 BPSK	135	138		23.50		24.4	0.5	
100	1/2 BPSK	270	0		23.54				
100	QPSK	1	1		24.13				
100	QPSK	1	137		23.92		24.9	0.0	
100	QPSK	1	271		23.95				
100	QPSK	135	0		23.01		23.9	1.0	
100	QPSK	135	69		23.95		24.9	0.0	
100	QPSK	135	138		23.02		23.9	1.0	
100	QPSK	270	0		23.11				
100	16QAM	1	1		23.13		23.9	1.0	
100	64QAM	1	1		21.52		22.4	2.5	
100	256QAM	1	1		19.64		20.4	4.5	
Channel				649668	650000	650334		MPR (dB)	
Frequency (MHz)				3745.02	3750	3755.01			
90	QPSK	1	1	23.98	24.06	24.00	24.9	0.0	
Channel				649334	650000	650668		MPR (dB)	
Frequency (MHz)				3740.01	3750	3760.02			
80	QPSK	1	1	23.89	23.97	23.89	24.9	0.0	
Channel				649200	650000	651000		MPR (dB)	
Frequency (MHz)				3735	3750	3765			
70	QPSK	1	1	23.87	23.99	23.97	24.9	0.0	
Channel				648668	650000	651334		MPR (dB)	
Frequency (MHz)				3730.02	3750	3770.01			
60	QPSK	1	1	23.93	24.03	23.98	24.9	0.0	
Channel				648334	650000	651668		MPR (dB)	
Frequency (MHz)				3725.01	3750	3775.02			
50	QPSK	1	1	23.97	24.04	23.99	24.9	0.0	
Channel				648000	650000	652000		MPR (dB)	
Frequency (MHz)				3720	3750	3780			
40	QPSK	1	1	23.94	23.95	23.96	24.9	0.0	
Channel				647650	650000	652334		MPR (dB)	
Frequency (MHz)				3715.02	3750	3785.01			
30	QPSK	1	1	23.91	23.95	23.90	24.9	0.0	
Channel				647500	650000	652500		MPR (dB)	
Frequency (MHz)				3712.5	3750	3787.5			
25	QPSK	1	1	23.96	24.06	23.95	24.9	0.0	
Channel				647334	650000	652668		MPR (dB)	
Frequency (MHz)				3710.01	3750	3790.02			
20	QPSK	1	1	23.94	24.03	23.89	24.9	0.0	
Channel				647168	650000	652834		MPR (dB)	
Frequency (MHz)				3707.52	3750	3792.51			
15	QPSK	1	1	23.88	23.98	23.91	24.9	0.0	
Channel				647000	650000	653000		MPR (dB)	
Frequency (MHz)				3705	3750	3795			
10	QPSK	1	1	23.96	24.05	23.90	24.9	0.0	

Part270 n78 PC2 Ant10 Default									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)		
Channel					650000				
Frequency (MHz)					3750				
100	1/2 BPSK	1	1		25.98				
100	1/2 BPSK	1	137		25.88		26.8	0.0	
100	1/2 BPSK	1	271		25.89				
100	1/2 BPSK	135	0		25.48		26.3	0.5	
100	1/2 BPSK	135	69		25.81		26.8	0.0	
100	1/2 BPSK	135	138		25.35		26.3	0.5	
100	1/2 BPSK	270	0		25.43				
100	QPSK	1	1		26.03				
100	QPSK	1	137		25.79		26.8	0.0	
100	QPSK	1	271		25.85				
100	QPSK	135	0		24.96		25.8	1.0	
100	QPSK	135	69		25.85		26.8	0.0	
100	QPSK	135	138		24.93		25.8	1.0	
100	QPSK	270	0		24.95				
100	16QAM	1	1		25.05		25.8	1.0	
100	64QAM	1	1		23.44		24.3	2.5	
100	256QAM	1	1		21.60		22.3	4.5	
Channel				649668	650000	650334			
Frequency (MHz)				3745.02	3750	3755.01			
90	QPSK	1	1	25.86	25.91	25.84	26.8	0.0	
Channel				649334	650000	650668			
Frequency (MHz)				3740.01	3750	3760.02			
80	QPSK	1	1	25.85	25.95	25.89	26.8	0.0	
Channel				649200	650000	651000			
Frequency (MHz)				3735	3750	3765			
70	QPSK	1	1	25.92	25.99	25.85	26.8	0.0	
Channel				648668	650000	651334			
Frequency (MHz)				3730.02	3750	3770.01			
60	QPSK	1	1	25.82	26.00	25.93	26.8	0.0	
Channel				648334	650000	651668			
Frequency (MHz)				3725.01	3750	3775.02			
50	QPSK	1	1	25.84	25.97	25.92	26.8	0.0	
Channel				648000	650000	652000			
Frequency (MHz)				3720	3750	3780			
40	QPSK	1	1	25.85	25.98	25.93	26.8	0.0	
Channel				647650	650000	652334			
Frequency (MHz)				3715.02	3750	3785.01			
30	QPSK	1	1	25.93	26.00	25.85	26.8	0.0	
Channel				647500	650000	652500			
Frequency (MHz)				3712.5	3750	3787.5			
25	QPSK	1	1	25.94	26.01	25.88	26.8	0.0	
Channel				647334	650000	652668			
Frequency (MHz)				3710.01	3750	3790.02			
20	QPSK	1	1	25.89	26.00	25.90	26.8	0.0	
Channel				647168	650000	652834			
Frequency (MHz)				3707.52	3750	3792.51			
15	QPSK	1	1	25.91	26.00	25.94	26.8	0.0	
Channel				647000	650000	653000			
Frequency (MHz)				3705	3750	3795			
10	QPSK	1	1	25.85	25.95	25.96	26.8	0.0	

Part27Q n78 Ant10 Default									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)		
Channel									
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		23.61				
100	1/2 BPSK	1	137		23.81		24.9	0.0	
100	1/2 BPSK	1	271		23.64				
100	1/2 BPSK	135	0		23.14		24.4	0.5	
100	1/2 BPSK	135	69		23.53		24.9	0.0	
100	1/2 BPSK	135	138		23.05		24.4	0.5	
100	1/2 BPSK	270	0		23.16				
100	QPSK	1	1		23.74				
100	QPSK	1	137		23.47		24.9	0.0	
100	QPSK	1	271		23.56				
100	QPSK	135	0		22.57		23.9	1.0	
100	QPSK	135	69		23.54		24.9	0.0	
100	QPSK	135	138		22.66		23.9	1.0	
100	QPSK	270	0		22.67				
100	16QAM	1	1		22.89		23.9	1.0	
100	64QAM	1	1		21.09		22.4	2.5	
100	256QAM	1	1		19.24		20.8	4.5	
Channel									
Frequency (MHz)				34900	35334	35658.02			
90	QPSK	1	1	23.268	23.67	23.64	24.9	0.0	
Channel				35368	35334	35334	4000	0.0	
Frequency (MHz)				3460.02	3500.01	3510			
80	QPSK	1	1	23.56	23.64	23.55	24.9	0.0	
Channel				35334	35334	35334	3000	0.0	
Frequency (MHz)				3465.01	3500.01	3515.01			
70	QPSK	1	1	23.55	23.63	23.59	24.9	0.0	
Channel				35200	35334	35468			
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	23.54	23.65	23.58	24.9	0.0	
Channel				35168	35334	35500			
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	23.53	23.64	23.57	24.9	0.0	
Channel				35134	35334	35534			
Frequency (MHz)				3470.1	3500.01	3530.01			
40	QPSK	1	1	23.63	23.67	23.55	24.9	0.0	
Channel				35200	35334	35568			
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	23.56	23.62	23.59	24.9	0.0	
Channel				35084	35334	35584			
Frequency (MHz)				3462.5	3500.01	3537.51			
25	QPSK	1	1	23.58	23.65	23.61	24.9	0.0	
Channel				35069	35334	35520			
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	23.63	23.65	23.60	24.9	0.0	
Channel				35050	35334	35616			
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	23.58	23.71	23.63	24.9	0.0	
Channel				35334	35334	35334			
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	23.60	23.67	23.65	24.9	0.0	

Reduced Power Mode for DSI1_Other PA

n7 Ant5 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	14.33	14.27	14.18			
50	1/2 BPSK	1	135	14.22	14.31	14.14	15.0	0.0	
50	1/2 BPSK	1	268	14.26	14.29	14.25			
50	1/2 BPSK	135	0	14.28	14.37	14.22	15.0	0.0	
50	1/2 BPSK	135	68	14.27	14.33	14.22	15.0	0.0	
50	1/2 BPSK	135	135	14.33	14.27	14.23			
50	1/2 BPSK	270	0	14.29	14.33	14.25	15.0	0.0	
50	QPSK	1	1	14.26	14.41	14.22			
50	QPSK	1	135	14.30	14.27	14.24	15.0	0.0	
50	QPSK	1	268	14.21	14.37	14.16			
50	QPSK	135	0	14.33	14.37	14.21	15.0	0.0	
50	QPSK	135	68	14.30	14.39	14.15	15.0	0.0	
50	QPSK	135	135	14.24	14.34	14.25	15.0	0.0	
50	QPSK	270	0	14.23	14.30	14.21			
50	16QAM	1	1	14.29	14.26	14.22	15.0	0.0	
50	64QAM	1	1	14.22	14.27	14.18	15.0	0.0	
50	256QAM	1	1	14.31	14.32	14.18	15.0	0.0	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	14.14	14.23	14.11	15.0	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	14.15	14.31	14.10	15.0	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	14.17	14.29	14.12	15.0	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	14.16	14.27	14.10	15.0	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	14.15	14.24	14.12	15.0	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	14.15	14.25	14.07	15.0	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	14.20	14.27	14.18	15.0	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	14.20	14.21	14.07	15.0	0.0	

n66 Ant5 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	14.84	14.82	14.74			
45	1/2 BPSK	1	120	14.83	14.87	14.74	15.8	0.0	
45	1/2 BPSK	1	240	14.80	14.86	14.77			
45	1/2 BPSK	120	0	14.80	14.76	14.72	15.8	0.0	
45	1/2 BPSK	120	60	14.74	14.79	14.76	15.8	0.0	
45	1/2 BPSK	120	120	14.81	14.78	14.78			
45	1/2 BPSK	240	0	14.80	14.77	14.79	15.8	0.0	
45	QPSK	1	1	14.77	14.89	14.71			
45	QPSK	1	120	14.76	14.87	14.74	15.8	0.0	
45	QPSK	1	240	14.83	14.80	14.76			
45	QPSK	120	0	14.81	14.86	14.72	15.8	0.0	
45	QPSK	120	60	14.81	14.87	14.75	15.8	0.0	
45	QPSK	120	120	14.80	14.86	14.71	15.8	0.0	
45	QPSK	240	0	14.82	14.83	14.71			
45	16QAM	1	1	14.84	14.84	14.82	15.8	0.0	
45	64QAM	1	1	14.79	14.83	14.80	15.8	0.0	
45	256QAM	1	1	14.83	14.82	14.72	15.8	0.0	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	14.72	14.74	14.66	15.8	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	14.64	14.72	14.59	15.8	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	14.63	14.75	14.56	15.8	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	14.70	14.79	14.63	15.8	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	14.72	14.74	14.60	15.8	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	14.65	14.82	14.58	15.8	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	14.68	14.81	14.66	15.8	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	14.65	14.77	14.65	15.8	0.0	

Part27Q n78 Ant5 DSI1									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334		3500.01			
Frequency (MHz)						3500.01			
100	1/2 BPSK	1	1		13.98				
100	1/2 BPSK	1	137		13.94		15.5	0.0	
100	1/2 BPSK	1	271		14.01				
100	1/2 BPSK	135	0		14.01		15.5	0.0	
100	1/2 BPSK	135	69		13.95		15.5	0.0	
100	1/2 BPSK	135	138		13.94				
100	1/2 BPSK	270	0		13.99		15.5	0.0	
100	QPSK	1	1		14.05				
100	QPSK	1	137		14.04		15.5	0.0	
100	QPSK	1	271		13.96				
100	QPSK	135	0		14.09		15.5	0.0	
100	QPSK	135	69		14.01		15.5	0.0	
100	QPSK	135	138		13.98				
100	QPSK	270	0		13.93		15.5	0.0	
100	16QAM	1	1		13.95		15.5	0.0	
100	64QAM	1	1		13.94		15.5	0.0	
100	256QAM	1	1		13.95		15.5	0.0	
Channel				633000	633334	633668	15.5	MPR	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	13.78	13.77	13.85	15.5	0.0	
Channel				632668	633334	634000	15.5	MPR	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	13.87	13.77	13.75	15.5	0.0	
Channel				632334	633334	634334	15.5	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	13.79	13.88	13.82	15.5	0.0	
Channel				632000	633334	634668	15.5	MPR	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	13.85	13.75	13.77	15.5	0.0	
Channel				631668	633334	635000	15.5	MPR	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	13.87	13.82	13.85	15.5	0.0	
Channel				631334	633334	635334	15.5	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	13.88	13.82	13.84	15.5	0.0	
Channel				631000	633334	635668	15.5	MPR	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	13.84	13.82	13.86	15.5	0.0	
Channel				630634	633334	635834	15.5	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	13.79	13.77	13.80	15.5	0.0	
Channel				630268	633334	636000	15.5	MPR	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	13.86	13.81	13.82	15.5	0.0	
Channel				630500	633334	636168	15.5	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	13.83	13.86	13.78	15.5	0.0	
Channel				630134	633334	636334	15.5	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	13.84	13.86	13.78	15.5	0.0	

Part27Q n78 PC2 Ant5 DSI1									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334		3500.01			
Frequency (MHz)						3500.01			
100	1/2 BPSK	1	1		16.96				
100	1/2 BPSK	1	137		16.90		18.5	0.0	
100	1/2 BPSK	1	271		16.97				
100	1/2 BPSK	135	0		17.00		18.5	0.0	
100	1/2 BPSK	135	69		16.99		18.5	0.0	
100	1/2 BPSK	135	138		16.99				
100	1/2 BPSK	270	0		17.04		18.5	0.0	
100	QPSK	1	1		17.09				
100	QPSK	1	137		17.07		18.5	0.0	
100	QPSK	1	271		16.92				
100	QPSK	135	0		17.03		18.5	0.0	
100	QPSK	135	69		17.06		18.5	0.0	
100	QPSK	135	138		16.93				
100	QPSK	270	0		16.99		18.5	0.0	
100	16QAM	1	1		16.98		18.5	0.0	
100	64QAM	1	1		16.99		18.5	0.0	
100	256QAM	1	1		16.94		18.5	0.0	
Channel				633000	633334	633668	15.5	MPR	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	16.92	17.00	16.91	18.5	0.0	
Channel				632668	633334	634000	15.5	MPR	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	17.02	16.98	16.98	18.5	0.0	
Channel				632334	633334	634334	15.5	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	16.97	16.94	16.92	18.5	0.0	
Channel				632000	633334	634668	15.5	MPR	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	16.99	16.99	16.91	18.5	0.0	
Channel				631668	633334	635000	15.5	MPR	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	16.95	16.97	16.99	18.5	0.0	
Channel				631334	633334	635334	15.5	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	17.00	16.94	16.92	18.5	0.0	
Channel				631000	633334	635668	15.5	MPR	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	16.92	16.95	16.94	18.5	0.0	
Channel				630634	633334	635834	15.5	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	17.02	17.01	16.98	18.5	0.0	
Channel				630268	633334	636000	15.5	MPR	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	16.94	16.96	16.93	18.5	0.0	
Channel				630500	633334	636168	15.5	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	16.93	16.94	17.03	18.5	0.0	
Channel				630134	633334	636334	15.5	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	17.02	17.02	16.98	18.5	0.0	

n7 Ant4 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	17.00	17.03	17.05			
50	1/2 BPSK	1	135	17.03	17.10	17.03	18.2	0.0	
50	1/2 BPSK	1	268	16.97	17.03	17.01			
50	1/2 BPSK	135	0	17.06	17.13	16.97	18.2	0.0	
50	1/2 BPSK	135	68	17.05	17.09	17.00	18.2	0.0	
50	1/2 BPSK	135	135	17.03	17.06	17.01	18.2	0.0	
50	1/2 BPSK	270	0	17.00	17.06	17.06			
50	QPSK	1	1	16.97	17.15	16.98			
50	QPSK	1	135	16.98	17.10	16.98	18.2	0.0	
50	QPSK	1	268	16.97	17.03	16.98			
50	QPSK	135	0	17.07	17.05	16.99	18.2	0.0	
50	QPSK	135	68	17.03	17.10	17.02	18.2	0.0	
50	QPSK	135	135	16.96	17.03	16.96			
50	QPSK	270	0	17.02	17.09	17.01	18.2	0.0	
50	16QAM	1	1	17.03	17.14	17.04	18.2	0.0	
50	64QAM	1	1	17.03	17.07	17.03	18.2	0.0	
50	256QAM	1	1	16.99	17.14	17.05	18.2	0.0	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	16.83	17.04	16.88	18.2	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	16.86	17.01	16.91	18.2	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	16.90	17.00	16.94	18.2	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	16.91	17.01	16.90	18.2	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	16.85	17.00	16.83	18.2	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	16.81	17.02	16.87	18.2	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	16.91	17.09	16.90	18.2	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	16.82	16.97	16.85	18.2	0.0	

n66 Ant4 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	16.21	16.17	16.15			
45	1/2 BPSK	1	120	16.22	16.22	16.11	16.8	0.0	
45	1/2 BPSK	1	240	16.20	16.26	16.11			
45	1/2 BPSK	120	0	16.16	16.22	16.15	16.8	0.0	
45	1/2 BPSK	120	60	16.14	16.21	16.18	16.8	0.0	
45	1/2 BPSK	120	120	16.16	16.26	16.14	16.8	0.0	
45	1/2 BPSK	240	0	16.24	16.26	16.10			
45	QPSK	1	1	16.22	16.28	16.21			
45	QPSK	1	120	16.24	16.22	16.19	16.8	0.0	
45	QPSK	1	240	16.19	16.17	16.21			
45	QPSK	120	0	16.14	16.19	16.10	16.8	0.0	
45	QPSK	120	60	16.18	16.25	16.13	16.8	0.0	
45	QPSK	120	120	16.15	16.24	16.22			
45	QPSK	240	0	16.21	16.24	16.20	16.8	0.0	
45	16QAM	1	1	16.21	16.26	16.18	16.8	0.0	
45	64QAM	1	1	16.21	16.26	16.18	16.8	0.0	
45	256QAM	1	1	16.17	16.25	16.10	16.8	0.0	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	16.14	16.13	16.16	16.8	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	16.11	16.06	16.16	16.8	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	16.08	16.06	16.09	16.8	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	16.16	16.06	16.06	16.8	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	16.07	16.08	16.11	16.8	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	16.18	16.03	16.13	16.8	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	16.13	16.10	16.08	16.8	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	16.18	16.09	16.14	16.8	0.0	

Part270 n77 PC2 Ant4 DSI1									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930		3750	
100	1/2 BPSK	1	1	22.87	22.81	22.86			
100	1/2 BPSK	1	137	22.85	22.90	22.82	23.0	0.0	
100	1/2 BPSK	1	271	22.80	22.89	22.76			
100	1/2 BPSK	135	0	22.84	22.84	22.76	23.0	0.0	
100	1/2 BPSK	135	69	22.87	22.85	22.77	23.0	0.0	
100	1/2 BPSK	135	138	22.79	22.88	22.85			
100	1/2 BPSK	270	0	22.77	22.85	22.80	23.0	0.0	
100	QPSK	1	1	22.75	22.95	22.87			
100	QPSK	1	137	22.81	22.92	22.79	23.0	0.0	
100	QPSK	1	271	22.73	22.93	22.82			
100	QPSK	135	0	22.77	22.87	22.96	23.0	0.0	
100	QPSK	135	69	22.72	22.92	22.78	23.0	0.0	
100	QPSK	135	138	22.81	22.83	22.79			
100	QPSK	270	0	22.72	22.91	22.83	23.0	0.0	
100	16QAM	1	1	22.77	22.84	22.77	23.0	0.0	
100	64QAM	1	1	22.79	22.82	22.75	23.0	0.0	
100	256QAM	1	1	22.81	22.90	22.76	23.0	0.0	
Channel				648668	650000	652334	MPR		
Frequency (MHz)				3745.02	3840	3935.01	up		
90	QPSK	1	1	22.70	22.90	22.75	23.0	0.0	
Channel				649334	650000	652668	MPR		
Frequency (MHz)				3740.01	3840	3940.02	up		
80	QPSK	1	1	22.66	22.86	22.73	23.0	0.0	
Channel				649200	650000	653000	MPR		
Frequency (MHz)				3735	3840	3945	up		
70	QPSK	1	1	22.61	22.84	22.75	23.0	0.0	
Channel				648668	650000	663334	MPR		
Frequency (MHz)				3730.02	3840	3950.01	up		
60	QPSK	1	1	22.68	22.80	22.77	23.0	0.0	
Channel				648334	650000	653668	MPR		
Frequency (MHz)				3725.01	3840	3955.02	up		
50	QPSK	1	1	22.67	22.79	22.75	23.0	0.0	
Channel				648000	650000	664000	MPR		
Frequency (MHz)				3720	3840	3960	up		
40	QPSK	1	1	22.70	22.83	22.76	23.0	0.0	
Channel				647668	650000	664334	MPR		
Frequency (MHz)				3715.02	3840	3965.01	up		
30	QPSK	1	1	22.60	22.81	22.73	23.0	0.0	
Channel				647500	650000	664500	MPR		
Frequency (MHz)				3712.5	3840	3967.5	up		
25	QPSK	1	1	22.65	22.81	22.76	23.0	0.0	
Channel				647250	650000	664334	MPR		
Frequency (MHz)				3710.01	3840	3970.02	up		
20	QPSK	1	1	22.70	22.87	22.77	23.0	0.0	
Channel				647168	650000	664834	MPR		
Frequency (MHz)				3707.52	3840	3972.51	up		
15	QPSK	1	1	22.70	22.84	22.72	23.0	0.0	
Channel				647000	650000	665000	MPR		
Frequency (MHz)				3705	3840	3975	up		
10	QPSK	1	1	22.71	22.87	22.76	23.0	0.0	

Part27Q n77 Ant4 DSI1									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel					633334				
Frequency (MHz)					3500.01				
100	1/2 BPSK	1	1		19.05				
100	1/2 BPSK	1	137		19.03		19.5	0.0	
100	1/2 BPSK	1	271		19.04				
100	1/2 BPSK	135	0		18.98		19.5	0.0	
100	1/2 BPSK	135	69		18.96		19.5	0.0	
100	1/2 BPSK	135	138		19.06				
100	1/2 BPSK	270	0		19.03		19.5	0.0	
100	QPSK	1	1		19.07				
100	QPSK	1	137		19.05		19.5	0.0	
100	QPSK	1	271		18.99				
100	QPSK	135	0		19.00		19.5	0.0	
100	QPSK	135	69		19.01		19.5	0.0	
100	QPSK	135	138		18.97		19.5	0.0	
100	QPSK	270	0		19.00		19.5	0.0	
100	16QAM	1	1		19.05		19.5	0.0	
100	64QAM	1	1		18.94		19.5	0.0	
100	256QAM	1	1		19.05		19.5	0.0	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	18.98	18.89	18.91	19.5	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	18.94	18.89	18.96	19.5	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	18.89	18.98	18.97	19.5	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	18.99	18.96	18.94	19.5	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	18.92	18.91	18.96	19.5	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	18.96	18.90	18.97	19.5	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	18.96	18.91	18.95	19.5	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	18.94	18.96	18.92	19.5	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	18.93	18.96	18.91	19.5	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	18.91	18.97	18.90	19.5	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	18.97	18.91	18.95	19.5	0.0	

Part27Q n77 PC2 Ant4 DSI1									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3300.01					
100	1/2 BPSK	1	1		22.49				
100	1/2 BPSK	1	137		22.57		23.0	0.0	
100	1/2 BPSK	1	271		22.55				
100	1/2 BPSK	135	0		22.52		23.0	0.0	
100	1/2 BPSK	135	69		22.46		23.0	0.0	
100	1/2 BPSK	135	138		22.61				
100	1/2 BPSK	270	0		22.58		23.0	0.0	
100	QPSK	1	1		22.62				
100	QPSK	1	137		22.51		23.0	0.0	
100	QPSK	1	271		22.51				
100	QPSK	135	0		22.55		23.0	0.0	
100	QPSK	135	69		22.56		23.0	0.0	
100	QPSK	135	138		22.56				
100	QPSK	270	0		22.47		23.0	0.0	
100	16QAM	1	1		22.51		23.0	0.0	
100	64QAM	1	1		22.41		23.0	0.0	
100	256QAM	1	1		22.58		23.0	0.0	
Channel									
Frequency (MHz)				34300	35000	333668			
90	QPSK	1	1	22.56	22.56	22.51			
Channel				33268	33334	334000			
Frequency (MHz)				3400	3500	3510			
80	QPSK	1	1	22.57	22.48	22.51	23.0	0.0	
Channel				33324	33334	33334			
Frequency (MHz)				34650	35000	35150			
70	QPSK	1	1	22.56	22.47	22.55	23.0	0.0	
Channel				332000	33334	334688			
Frequency (MHz)				3480	3500	3520	0.0		
60	QPSK	1	1	22.54	22.54	22.50	23.0	0.0	
Channel				331668	33334	332000			
Frequency (MHz)				34750	35000	35250			
50	QPSK	1	1	22.54	22.49	22.57	23.0	0.0	
Channel				331234	33334	333534			
Frequency (MHz)				34100	35000	35300	0.0		
40	QPSK	1	1	22.58	22.49	22.52	23.0	0.0	
Channel				330700	33334	333668			
Frequency (MHz)				3465	35000	35350	0.0		
30	QPSK	1	1	22.48	22.51	22.52	23.0	0.0	
Channel				630834	33334	336834			
Frequency (MHz)				34620	35000	35370	0.0		
25	QPSK	1	1	22.53	22.56	22.56	23.0	0.0	
Channel				330668	33334	332000			
Frequency (MHz)				34000	35000	35400			
20	QPSK	1	1	22.52	22.50	22.46	23.0	0.0	
Channel				630500	33334	336168			
Frequency (MHz)				34375	35000	35420			
15	QPSK	1	1	22.58	22.50	22.49	23.0	0.0	
Channel				330334	33334	333534			
Frequency (MHz)				34550	35000	35450	0.0		
10	QPSK	1	1	22.49	22.55	22.49	23.0	0.0	

Part270 n78 PC2 Ant4 DSI1									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	1/2 BPS	1	1		22.87				
100	1/2 BPS	1	137		22.71		23.0	0.0	
100	1/2 BPS	1	271		22.79				
100	1/2 BPS	135	0		22.83		23.0	0.0	
100	1/2 BPS	135	69		22.75		23.0	0.0	
100	1/2 BPS	135	138		22.73				
100	1/2 BPS	270	0		22.80		23.0	0.0	
100	QPSK	1	1		22.95				
100	QPSK	1	137		22.82		23.0	0.0	
100	QPSK	1	271		22.77				
100	QPSK	135	0		22.78		23.0	0.0	
100	QPSK	135	69		22.91		23.0	0.0	
100	QPSK	135	138		22.88				
100	QPSK	270	0		22.70		23.0	0.0	
100	16QAM	1	1		22.81		23.0	0.0	
100	64QAM	1	1		22.85		23.0	0.0	
100	256QAM	1	1		22.84		23.0	0.0	
Channel				648668	650000	650334	up	MPR	
Frequency (MHz)				3745.02	3750	3755.01	up	(dB)	
90	QPSK	1	1		22.83	22.89	22.91	23.0	0.0
Channel				649334	650000	650668	up	MPR	
Frequency (MHz)				3740.01	3750	3760.02	up	(dB)	
80	QPSK	1	1		22.87	22.86	22.86	23.0	0.0
Channel				649000	650000	651000	up	MPR	
Frequency (MHz)				3735	3750	3765	up	(dB)	
70	QPSK	1	1		22.81	22.89	22.80	23.0	0.0
Channel				648668	650000	651334	up	MPR	
Frequency (MHz)				3730.02	3750	3770.01	up	(dB)	
60	QPSK	1	1		22.82	22.88	22.90	23.0	0.0
Channel				649334	650000	651668	up	MPR	
Frequency (MHz)				3725.01	3750	3775.02	up	(dB)	
50	QPSK	1	1		22.84	22.88	22.91	23.0	0.0
Channel				648000	650000	652000	up	MPR	
Frequency (MHz)				3720	3750	3780	up	(dB)	
40	QPSK	1	1		22.82	22.84	22.82	23.0	0.0
Channel				647668	650000	652334	up	MPR	
Frequency (MHz)				3715.02	3750	3785.01	up	(dB)	
30	QPSK	1	1		22.85	22.83	22.81	23.0	0.0
Channel				647500	650000	652500	up	MPR	
Frequency (MHz)				3712.5	3750	3787.5	up	(dB)	
25	QPSK	1	1		22.83	22.84	22.81	23.0	0.0
Channel				647334	650000	652668	up	MPR	
Frequency (MHz)				3710.01	3750	3790.02	up	(dB)	
20	QPSK	1	1		22.80	22.83	22.88	23.0	0.0
Channel				647168	650000	652834	up	MPR	
Frequency (MHz)				3707.52	3750	3792.51	up	(dB)	
15	QPSK	1	1		22.86	22.88	22.91	23.0	0.0
Channel				647000	650000	653000	up	MPR	
Frequency (MHz)				3705	3750	3795	up	(dB)	
10	QPSK	1	1		22.84	22.85	22.90	23.0	0.0

Part27Q n78 Ant4 DSI1									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		19.08				
100	1/2 BPS	1	137		19.05		19.5	0.0	
100	1/2 BPS	1	271		19.13				
100	1/2 BPS	135	0		19.11		19.5	0.0	
100	1/2 BPS	135	69		19.05		19.5	0.0	
100	1/2 BPS	135	138		19.08				
100	1/2 BPS	270	0		19.14		19.5	0.0	
100	QPSK	1	1		19.15				
100	QPSK	1	137		19.07		19.5	0.0	
100	QPSK	1	271		19.14				
100	QPSK	135	0		19.10		19.5	0.0	
100	QPSK	135	69		19.14		19.5	0.0	
100	QPSK	135	138		19.06				
100	QPSK	270	0		19.15		19.5	0.0	
100	16QAM	1	1		19.13		19.5	0.0	
100	64QAM	1	1		19.10		19.5	0.0	
100	256QAM	1	1		19.06		19.5	0.0	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02	up	(dB)	
90	QPSK	1	1		19.03	18.96	19.03	19.5	0.0
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up	(dB)	
80	QPSK	1	1		19.00	19.04	19.01	19.5	0.0
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up	(dB)	
70	QPSK	1	1		19.02	18.96	18.94	19.5	0.0
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up	(dB)	
60	QPSK	1	1		18.95	18.94	18.96	19.5	0.0
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525	up	(dB)	
50	QPSK	1	1		18.95	18.97	18.93	19.5	0.0
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up	(dB)	
40	QPSK	1	1		19.02	18.94	19.01	19.5	0.0
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	up	(dB)	
30	QPSK	1	1		18.94	19.02	18.96	19.5	0.0
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up	(dB)	
25	QPSK	1	1		19.00	18.97	18.98	19.5	0.0
Channel				630668	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up	(dB)	
20	QPSK	1	1		19.05	18.99	19.03	19.5	0.0
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up	(dB)	
15	QPSK	1	1		18.96	19.05	18.96	19.5	0.0
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up	(dB)	
10	QPSK	1	1		18.96	18.98	19.02	19.5	0.0

Part27Q n78 PC2 Ant4 DSI1									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		22.53				
100	1/2 BPS	1	137		22.58		23.0	0.0	
100	1/2 BPS	1	271		22.57				
100	1/2 BPS	135	0		22.56		23.0	0.0	
100	1/2 BPS	135	69		22.57		23.0	0.0	
100	1/2 BPS	135	138		22.55				
100	1/2 BPS	270	0		22.59		23.0	0.0	
100	QPSK	1	1		22.70				
100	QPSK	1	137		22.54		23.0	0.0	
100	QPSK	1	271		22.69				
100	QPSK	135	0		22.63		23.0	0.0	
100	QPSK	135	69		22.66		23.0	0.0	
100	QPSK	135	138		22.54				
100	QPSK	270	0		22.66		23.0	0.0	
100	16QAM	1	1		22.63		23.0	0.0	
100	64QAM	1	1		22.57		23.0	0.0	
100	256QAM	1	1		22.59		23.0	0.0	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02	up	(dB)	
90	QPSK	1	1		22.58	22.63	22.55	23.0	0.0
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up	(dB)	
80	QPSK	1	1		22.66	22.54	22.63	23.0	0.0
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up	(dB)	
70	QPSK	1	1		22.59	22.60	22.61	23.0	0.0
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up	(dB)	
60	QPSK	1	1		22.66	22.66	22.56	23.0	0.0
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525.03	up	(dB)	
50	QPSK	1	1		22.57	22.56	22.56	23.0	0.0
Channel				631334	633334	633334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up	(dB)	
40	QPSK	1	1		22.65	22.60	22.64	23.0	0.0
Channel				631000	633334	633668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	up	(dB)	
30	QPSK	1	1		22.55	22.64	22.64	23.0	0.0
Channel				630834	633334	633834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up	(dB)	
25	QPSK	1	1		22.65	22.57	22.54	23.0	0.0
Channel				630668	633334	633834	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up	(dB)	
20	QPSK	1	1		22.58	22.63	22.63	23.0	0.0
Channel				630500	633334	633834	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up	(dB)	
15	QPSK	1	1		22.57	22.55	22.63	23.0	0.0
Channel				630334	633334	633834	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up	(dB)	
10	QPSK	1	1		22.57	22.57	22.56	23.0	0.0

n7 Ant6 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	25.17	25.22	25.18	25.5	0.0	
50	1/2 BPSK	1	135	25.17	25.17	25.19			
50	1/2 BPSK	1	268	25.14	25.15	25.20			
50	1/2 BPSK	135	0	24.70	24.80	24.71	25.0	0.5	
50	1/2 BPSK	135	68	25.10	25.21	25.13	25.5	0.0	
50	1/2 BPSK	135	135	24.70	24.81	24.78			
50	1/2 BPSK	270	0	24.75	24.76	24.71	25.0	0.5	
50	QPSK	1	1	25.23	25.25	25.22			
50	QPSK	1	135	25.13	25.11	25.20	25.5	0.0	
50	QPSK	1	268	25.19	25.13	25.15			
50	QPSK	135	0	24.19	24.26	24.25	24.5	1.0	
50	QPSK	135	68	25.14	25.20	25.12	25.5	0.0	
50	QPSK	135	135	24.21	24.25	24.20			
50	QPSK	270	0	24.26	24.27	24.20	24.5	1.0	
50	16QAM	1	1	24.27	24.24	24.28	24.5	1.0	
50	64QAM	1	1	22.77	22.71	22.68	23.0	2.5	
50	256QAM	1	1	20.70	20.76	20.77	21.0	4.5	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	25.10	25.15	25.15	25.5	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	25.13	25.19	25.13	25.5	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	25.16	25.21	25.12	25.5	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	25.17	25.22	25.09	25.5	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	25.12	25.20	25.18	25.5	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	25.15	25.21	25.18	25.5	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	25.19	25.13	25.18	25.5	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	25.16	25.15	25.19	25.5	0.0	

n66 Ant6 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	24.87	24.96	24.84			
45	1/2 BPSK	1	120	24.89	24.92	24.87	25.5	0.0	
45	1/2 BPSK	1	240	24.88	24.94	24.96			
45	1/2 BPSK	120	0	24.41	24.46	24.46	25.0	0.5	
45	1/2 BPSK	120	60	24.89	24.90	24.90	25.5	0.0	
45	1/2 BPSK	120	120	24.48	24.50	24.45	25.0	0.5	
45	1/2 BPSK	240	0	24.44	24.47	24.53			
45	QPSK	1	1	24.93	25.01	24.98			
45	QPSK	1	120	24.88	24.95	24.88	25.5	0.0	
45	QPSK	1	240	24.81	24.96	24.94			
45	QPSK	120	0	23.87	23.97	24.02	24.5	1.0	
45	QPSK	120	60	24.82	24.97	24.90	25.5	0.0	
45	QPSK	120	120	23.92	24.01	23.96			
45	QPSK	240	0	23.90	24.04	24.01	24.5	1.0	
45	16QAM	1	1	23.95	23.99	23.93	24.5	1.0	
45	64QAM	1	1	22.41	22.50	22.54	23.0	2.5	
45	256QAM	1	1	20.40	20.51	20.52	21.0	4.5	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	24.80	24.96	24.85	25.5	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	24.80	24.91	24.95	25.5	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	24.88	24.95	24.94	25.5	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	24.84	24.95	24.86	25.5	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	24.80	24.90	24.89	25.5	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	24.87	24.89	24.90	25.5	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	24.85	24.93	24.93	25.5	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	24.89	24.98	24.87	25.5	0.0	

n38 Ant6 DS11									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				518004	519000	519996	2590.02	2595	2599.98
40	1/2 BPSK	1	1	24.98	24.99	24.96			
40	1/2 BPSK	1	53	25.03	25.00	24.96	25.5	0.0	
40	1/2 BPSK	1	104	24.96	25.05	24.95			
40	1/2 BPSK	50	0	24.56	24.55	24.54	25.0	0.5	
40	1/2 BPSK	50	26	24.96	25.02	24.99	25.5	0.0	
40	1/2 BPSK	50	56	24.59	24.61	24.51			
40	1/2 BPSK	100	0	24.59	24.60	24.53	25.0	0.5	
40	QPSK	1	1	25.08	25.10	25.06			
40	QPSK	1	53	24.99	24.99	24.98	25.5	0.0	
40	QPSK	1	104	25.01	25.07	25.00			
40	QPSK	50	0	24.10	24.07	24.05	24.5	1.0	
40	QPSK	50	26	25.03	25.07	24.96	25.5	0.0	
40	QPSK	50	56	24.07	24.11	24.01			
40	QPSK	100	0	24.12	24.13	24.10	24.5	1.0	
40	16QAM	1	1	24.05	24.09	24.06	24.5	1.0	
40	64QAM	1	1	22.59	22.62	22.52	23.0	2.5	
40	256QAM	1	1	20.64	20.60	20.51	21.0	4.5	
Channel				517002	518000	518998			
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	25.05	25.07	25.02	25.5	0.0	
Channel				516504	519000	521496			
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	25.05	24.98	25.02	25.5	0.0	
Channel				511000	512000	522000			
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	24.99	25.02	25.01	25.5	0.0	
Channel				515502	519000	522498			
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	25.02	25.04	25.02	25.5	0.0	
Channel				515004	519000	522506			
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	25.02	24.97	24.97	25.5	0.0	

n41 Ant6 DS11									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				5260.02	516598	526200	2546.01	2592.99	2640
100	1/2 BPSK	1	1	24.93	24.93	24.87			
100	1/2 BPSK	1	137	25.04	24.91	24.96	25.5	0.0	
100	1/2 BPSK	1	271	24.93	24.98	24.92			
100	1/2 BPSK	135	0	24.55	24.49	24.48	25.0	0.5	
100	1/2 BPSK	135	69	24.97	25.00	24.94	25.5	0.0	
100	1/2 BPSK	135	138	24.53	24.54	24.46			
100	1/2 BPSK	270	0	24.61	24.54	24.51	25.0	0.5	
100	QPSK	1	1	25.09	25.13	24.97			
100	QPSK	1	137	24.90	24.94	24.96	25.5	0.0	
100	QPSK	1	271	24.93	25.04	24.99			
100	QPSK	135	0	24.04	24.02	24.06	24.5	1.0	
100	QPSK	135	69	24.98	25.09	24.93	25.5	0.0	
100	QPSK	135	138	24.05	24.06	23.92			
100	QPSK	270	0	24.11	24.16	24.06	24.5	1.0	
100	16QAM	1	1	24.01	24.11	24.06	24.5	1.0	
100	64QAM	1	1	22.56	22.63	22.54	23.0	2.5	
100	256QAM	1	1	20.63	20.56	20.49	21.0	4.5	
Channel				505000	518598	532598			
Frequency (MHz)				2541	2592.99	2644.99			
90	QPSK	1	1	25.04	25.05	24.93	25.5	0.0	
Channel				507204	518598	529998			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	25.05	25.00	24.91	25.5	0.0	
Channel				505002	518598	531000			
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	25.02	25.01	24.91	25.5	0.0	
Channel				505000	518598	531996			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	24.98	25.10	24.87	25.5	0.0	
Channel				504204	518598	532098			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	25.03	25.07	24.86	25.5	0.0	
Channel				503700	518598	533496			
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	25.02	25.07	24.92	25.5	0.0	
Channel				503002	518598	533000			
Frequency (MHz)				2516.01	2592.98	2670			
40	QPSK	1	1	25.00	25.06	24.94	25.5	0.0	
Channel				502704	518598	534498			
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	24.97	25.08	24.87	25.5	0.0	
Channel				502200	518598	533998			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	25.02	24.99	24.88	25.5	0.0	
Channel				501702	518598	535500			
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	24.98	25.07	24.93	25.5	0.0	
Channel				501204	518598	535098			
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	25.06	25.05	24.92	25.5	0.0	
Channel				500700	518598	536496			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	24.97	25.01	24.89	25.5	0.0	
Channel				500202	518598	537000			
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	25.06	25.01	24.89	25.5	0.0	

n48 Ant6 DS11									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				638000	641666	645332	3570	3624.99	3679.98
40	1/2 BPSK	1	1	22.04	22.02	22.05			
40	1/2 BPSK	1	53	22.07	22.10	22.01	23.6	0.0	
40	1/2 BPSK	1	104	22.01	22.04	22.03			
40	1/2 BPSK	50	0	21.62	21.65	21.60	23.1	0.5	
40	1/2 BPSK	50	26	22.05	22.01	21.94	23.6	0.0	
40	1/2 BPSK	50	56	21.57	21.62	21.61			
40	1/2 BPSK	100	0	21.61	21.68	21.59	23.1	0.5	
40	QPSK	1	1	22.09	22.15	22.08			
40	QPSK	1	53	21.97	22.03	21.99	23.6	0.0	
40	QPSK	1	104	22.03	22.11	22.03			
40	QPSK	50	0	21.13	21.21	21.04	22.6	1.0	
40	QPSK	50	26	22.00	22.11	22.03	23.6	0.0	
40	QPSK	50	56	21.09	21.14	21.08			
40	QPSK	100	0	21.11	21.18	21.06	22.6	1.0	
40	16QAM	1	1	21.04	21.15	21.13	22.6	1.0	
40	64QAM	1	1	19.63	19.67	19.59	21.1	2.5	
40	256QAM	1	1	17.62	17.65	17.60	19.1	4.5	
Channel				631668	641666	645566			
Frequency (MHz)				3565.02	3624.99	3684.99			
30	QPSK	1	1	21.95	22.01	22.02	23.6	0.0	
Channel				637334	641666	646000			
Frequency (MHz)				3560.01	3624.99	3690			
20	QPSK	1	1	21.98	22.07	21.94	23.6	0.0	
Channel				637100	641666	647106			
Frequency (MHz)				3557.52	3624.99	3692.49			
15	QPSK	1	1	21.95	22.13	21.97	23.6	0.0	
Channel				637000	641666	646332			
Frequency (MHz)				3555	3624.99	3694.98			
10	QPSK	1	1	21.98	22.03	22.03	23.6	0.0	

Part270 n77 Ant6 DS11									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch / Freq	Power Middle Ch / Freq	Power High Ch / Freq	Tune- up limit (dBm)	MPR (dB)	
Channel				650000	656000	662000	3750	3840	3930
100	1/2 BPSK	1	1	23.97	24.09	23.83			
100	1/2 BPSK	1	137	23.99	24.12	23.92	25.3	0.0	
100	1/2 BPSK	1	271	23.97	24.01	23.91			
100	1/2 BPSK	135	0	23.48	23.65	23.43	24.8	0.5	
100	1/2 BPSK	135	69	23.97	24.07	23.91	25.3	0.0	
100	1/2 BPSK	135	138	23.54	23.69	23.50		24.8	0.5
100	1/2 BPSK	270	0	23.58	23.70	23.47	24.8		
100	QPSK	1	1	24.04	24.15	23.95			
100	QPSK	1	137	23.99	24.06	23.91	25.3	0.0	
100	QPSK	1	271	23.95	24.08	23.90			
100	QPSK	135	0	23.05	23.17	22.96	24.3	1.0	
100	QPSK	135	69	24.04	24.15	23.96	25.3	0.0	
100	QPSK	135	138	23.04	23.15	22.96		24.3	1.0
100	QPSK	270	0	23.10	23.19	23.00			
100	16QAM	1	1	23.07	23.16	22.93	24.3	1.0	
100	64QAM	1	1	21.59	21.70	21.48	24.8	2.5	
100	256QAM	1	1	19.51	19.61	19.50	20.8	4.5	
Channel				656000	662000	668000	3840	3930	4020
90	QPSK	1	1	23.91	24.02	23.90	25.3	0.0	
Channel				649334	656000	662666			
80	QPSK	1	1	23.99	24.11	23.92	25.3	0.0	
Channel				3740	3840	3940			
80	QPSK	1	1	23.95	24.06	23.88	25.3	0.0	
Channel				3735	3840	3945			
70	QPSK	1	1	23.95	24.10	23.90	25.3	0.0	
Channel				646666	656000	663334			
60	QPSK	1	1	3730	3840	3950			
Channel				3730	3840	3950			
60	QPSK	1	1	23.88	24.09	23.88	25.3	0.0	
Channel				3728	3840	3952			
50	QPSK	1	1	23.92	24.01	23.95			
Channel				648000	656000	664000			
40	QPSK	1	1	3730	3840	3950			
Channel				3730	3840	3950			
40	QPSK	1	1	23.91	24.02	23.90	25.3	0.0	
Channel				647668	656000	664332			
30	QPSK	1	1	3735	3840	3965			
Channel				646000	656000	666000			
25	QPSK	1	1	3712.5	3840	3957.5			
Channel				3712.5	3840	3957.5			
25	QPSK	1	1	23.98	24.08	23.92	25.3	0.0	
Channel				647334	656000	664666			
20	QPSK	1	1	3710	3840	3970			
Channel				647168	656000	664834			
15	QPSK	1	1	3707.5	3840	3972.5			
Channel				3707.5	3840	3972.5			
15	QPSK	1	1	24.00	24.11	23.93	25.3	0.0	
Channel				647000	656000	665000			
10	QPSK	1	1	3705	3840	3975			
Channel				3705	3840	3975			
10	QPSK	1	1	23.91	24.11	23.91	25.3	0.0	

Part270 n77 PC2 Ant6 DSI1									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	25.97	26.08	25.77			
100	1/2 BPSK	1	137	25.97	26.08	25.96	27.3	0.0	
100	1/2 BPSK	1	271	26.01	26.07	25.90			
100	1/2 BPSK	135	0	25.45	25.61	25.41	26.8	0.5	
100	1/2 BPSK	135	69	26.00	26.10	25.93	27.3	0.0	
100	1/2 BPSK	135	138	25.60	25.63	25.53		26.8	0.5
100	1/2 BPSK	270	0	25.56	25.72	25.42	26.8		
100	QPSK	1	1	25.98	26.17	25.99			
100	QPSK	1	137	26.04	26.11	25.86	27.3	0.0	
100	QPSK	1	271	25.97	26.12	25.63			
100	QPSK	135	0	25.02	25.17	24.96	26.3	1.0	
100	QPSK	135	69	26.00	26.14	25.91	27.3	0.0	
100	QPSK	135	138	25.08	25.16	24.85		26.3	1.0
100	QPSK	270	0	25.05	25.15	25.06	26.3		
100	16QAM	1	1	25.09	25.13	24.98	26.3	1.0	
100	64QAM	1	1	23.64	23.69	23.37	24.8	2.5	
100	256QAM	1	1	21.52	21.66	21.44	22.8	4.5	
Channel				646668	650000	662334	MPR		
Frequency (MHz)				3745.02	3840	3935.01	up (dB)		
90	QPSK	1	1	25.95	26.07	25.91	27.3	0.0	
Channel				649334	650000	662668	MPR		
Frequency (MHz)				3740.01	3840	3940.02	up (dB)		
80	QPSK	1	1	25.92	26.09	25.91	27.3	0.0	
Channel				649200	650000	662000	MPR		
Frequency (MHz)				3735	3840	3945	up (dB)		
70	QPSK	1	1	25.88	26.06	25.94	27.3	0.0	
Channel				648668	650000	663334	MPR		
Frequency (MHz)				3730.02	3840	3950.01	up (dB)		
60	QPSK	1	1	25.87	26.05	25.88	27.3	0.0	
Channel				648334	650000	662668	MPR		
Frequency (MHz)				3725.01	3840	3955.02	up (dB)		
50	QPSK	1	1	25.87	26.04	25.93	27.3	0.0	
Channel				648000	650000	664000	MPR		
Frequency (MHz)				3720	3840	3960	up (dB)		
40	QPSK	1	1	25.93	26.08	25.95	27.3	0.0	
Channel				647668	650000	662334	MPR		
Frequency (MHz)				3715.02	3840	3965.01	up (dB)		
30	QPSK	1	1	25.93	26.05	25.88	27.3	0.0	
Channel				647500	650000	664500	MPR		
Frequency (MHz)				3712.5	3840	3967.5	up (dB)		
25	QPSK	1	1	25.94	26.04	25.90	27.3	0.0	
Channel				647334	650000	664334	MPR		
Frequency (MHz)				3710.01	3840	3970.02	up (dB)		
20	QPSK	1	1	25.94	26.09	25.87	27.3	0.0	
Channel				647168	650000	664834	MPR		
Frequency (MHz)				3707.52	3840	3972.51	up (dB)		
15	QPSK	1	1	25.88	26.07	25.91	27.3	0.0	
Channel				647000	650000	665000	MPR		
Frequency (MHz)				3705	3840	3975	up (dB)		
10	QPSK	1	1	25.95	26.04	25.85	27.3	0.0	

Part27Q n77 Ant6 DSI1									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3600.01	633334				
100	1/2 BPSK	1	1		23.58				
100	1/2 BPSK	1	137		23.58		25.3	0.0	
100	1/2 BPSK	1	271		23.50				
100	1/2 BPSK	135	0		23.17		24.8	0.5	
100	1/2 BPSK	135	69		23.57		25.3	0.0	
100	1/2 BPSK	135	138		23.15		24.8	0.5	
100	1/2 BPSK	270	0		23.15				
100	QPSK	1	1		23.65				
100	QPSK	1	137		23.52		25.3	0.0	
100	QPSK	1	271		23.52				
100	QPSK	135	0		22.99		24.3	1.0	
100	QPSK	135	69		23.62		25.3	0.0	
100	QPSK	135	138		22.72		24.3	1.0	
100	QPSK	270	0		22.62		24.3	1.0	
100	16QAM	1	1		22.67		24.3	1.0	
100	64QAM	1	1		21.17		22.8	2.5	
100	256QAM	1	1		19.08		20.8	4.5	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up (dB)		
90	QPSK	1	1	23.56	23.54	23.52	25.3	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up (dB)		
80	QPSK	1	1	23.58	23.57	23.50	25.3	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up (dB)		
70	QPSK	1	1	23.58	23.51	23.57	25.3	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up (dB)		
60	QPSK	1	1	23.56	23.52	23.54	25.3	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up (dB)		
50	QPSK	1	1	23.53	23.60	23.60	25.3	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up (dB)		
40	QPSK	1	1	23.56	23.49	23.51	25.3	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up (dB)		
30	QPSK	1	1	23.51	23.57	23.58	25.3	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up (dB)		
25	QPSK	1	1	23.59	23.54	23.56	25.3	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up (dB)		
20	QPSK	1	1	23.56	23.52	23.55	25.3	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up (dB)		
15	QPSK	1	1	23.61	23.56	23.50	25.3	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up (dB)		
10	QPSK	1	1	23.57	23.54	23.53	25.3	0.0	

Part27Q n77 PC2 Ant6 DSI1									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit [dBm]	MPR [dB]	
Channel									
Frequency (MHz)				3500.01	633334				
100	1/2 BPSK	1	1		25.64				
100	1/2 BPSK	1	137		25.57		27.3	0.0	
100	1/2 BPSK	1	271		25.61				
100	1/2 BPSK	135	0		25.06		26.8	0.5	
100	1/2 BPSK	135	69		25.54		27.3	0.0	
100	1/2 BPSK	135	138		25.16				
100	1/2 BPSK	270	0		25.18		26.8	0.5	
100	QPSK	1	1		25.66				
100	QPSK	1	137		25.65		27.3	0.0	
100	QPSK	1	271		25.57				
100	QPSK	135	0		24.72		26.3	1.0	
100	QPSK	135	69		24.59		27.3	0.0	
100	QPSK	135	138		24.61				
100	QPSK	270	0		24.65		26.3	1.0	
100	16QAM	1	1		24.64		26.3	1.0	
100	64QAM	1	1		23.21		24.8	2.5	
100	256QAM	1	1		21.21		22.8	4.5	
Channel									
Frequency (MHz)				3500.01	633333	3506.00			
90	QPSK	1	1	25.59	25.51	25.58	27.3	0.0	
Channel				632666	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	25.51	25.54	25.62	27.3	0.0	
Channel				632315	633333	634333			
Frequency (MHz)				3486.01	3500.01	3515.01			
70	QPSK	1	1	25.60	25.62	25.54	27.3	0.0	
Channel				632000	633334	634666			
Frequency (MHz)				3490.01	3500.01	3502.02			
60	QPSK	1	1	25.62	25.57	25.56	27.3	0.0	
Channel				631166	633333	635000			
Frequency (MHz)				3476.02	3500.01	3505			
50	QPSK	1	1	25.58	25.53	25.58	27.3	0.0	
Channel				631334	633334	633334			
Frequency (MHz)				3470.01	3500.01	3508.01			
40	QPSK	1	1	25.61	25.59	25.58	27.3	0.0	
Channel				631005	633333	633666			
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	25.59	25.61	25.57	27.3	0.0	
Channel				630834	633334	633934			
Frequency (MHz)				3460.51	3500.01	3537.51			
25	QPSK	1	1	25.61	25.53	25.59	27.3	0.0	
Channel				630668	633333	634000			
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	25.53	25.55	25.56	27.3	0.0	
Channel				630500	633334	636166			
Frequency (MHz)				3467.3	3500.01	3542.2			
15	QPSK	1	1	25.61	25.56	25.53	27.3	0.0	
Channel				630374	633333	634334			
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	25.56	25.59	25.51	27.3	0.0	

Part270 n78 PC2 Ant6 DSI1									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit [dBm]	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	1/2 BPS	1	1		26.05				
100	1/2 BPS	1	137		26.05		27.2	0.0	
100	1/2 BPS	1	271		26.02				
100	1/2 BPS	135	0		25.53		26.7	0.5	
100	1/2 BPS	135	69		26.06		27.2	0.0	
100	1/2 BPS	135	138		25.49				
100	1/2 BPS	270	0		25.60		26.7	0.5	
100	QPSK	1	1		26.13				
100	QPSK	1	137		26.09		27.2	0.0	
100	QPSK	1	271		26.10				
100	QPSK	135	0		24.93		26.2	1.0	
100	QPSK	135	69		25.98		27.2	0.0	
100	QPSK	135	138		24.98				
100	QPSK	270	0		24.98		26.2	1.0	
100	16QAM	1	1		24.96		26.2	1.0	
100	64QAM	1	1		22.91		24.7	2.5	
100	256QAM	1	1		20.77		22.7	4.5	
Channel				648668	650000	650334	up	MPR	
Frequency (MHz)				3745.02	3750	3755.01	up		
90	QPSK	1	1	26.07	25.98	26.05	27.2	0.0	
Channel				649334	650000	650668	up	MPR	
Frequency (MHz)				3740.01	3750	3760.02	up		
80	QPSK	1	1	26.06	26.07	26.05	27.2	0.0	
Channel				649000	650000	651000	up	MPR	
Frequency (MHz)				3735	3750	3765	up		
70	QPSK	1	1	26.09	26.04	26.01	27.2	0.0	
Channel				648668	650000	651334	up	MPR	
Frequency (MHz)				3730.02	3750	3770.01	up		
60	QPSK	1	1	26.06	26.08	26.01	27.2	0.0	
Channel				648334	650000	651668	up	MPR	
Frequency (MHz)				3725.01	3750	3775.02	up		
50	QPSK	1	1	26.08	26.03	26.00	27.2	0.0	
Channel				648000	650000	652000	up	MPR	
Frequency (MHz)				3720	3750	3780	up		
40	QPSK	1	1	26.04	25.98	26.08	27.2	0.0	
Channel				647668	650000	652334	up	MPR	
Frequency (MHz)				3715.02	3750	3785.01	up		
30	QPSK	1	1	25.98	26.01	25.99	27.2	0.0	
Channel				647500	650000	652500	up	MPR	
Frequency (MHz)				3712.5	3750	3787.5	up		
25	QPSK	1	1	26.00	26.07	26.04	27.2	0.0	
Channel				647334	650000	652668	up	MPR	
Frequency (MHz)				3710.01	3750	3790.02	up		
20	QPSK	1	1	25.98	25.97	25.97	27.2	0.0	
Channel				647168	650000	652834	up	MPR	
Frequency (MHz)				3707.52	3750	3792.51	up		
15	QPSK	1	1	26.05	26.03	25.97	27.2	0.0	
Channel				647000	650000	653000	up	MPR	
Frequency (MHz)				3705	3750	3795	up		
10	QPSK	1	1	25.98	26.09	26.04	27.2	0.0	

Part27Q n78 Ant6 DSI1									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		23.54				
100	1/2 BPS	1	137		23.60		25.3	0.0	
100	1/2 BPS	1	271		23.54				
100	1/2 BPS	135	0		23.10		24.8	0.5	
100	1/2 BPS	135	69		23.51		25.3	0.0	
100	1/2 BPS	135	138		23.17				
100	1/2 BPS	270	0		23.21		24.8	0.5	
100	QPSK	1	1		23.72				
100	QPSK	1	137		23.53		25.3	0.0	
100	QPSK	1	271		23.45				
100	QPSK	135	0		22.87		24.3	1.0	
100	QPSK	135	69		23.81		25.3	0.0	
100	QPSK	135	138		22.72				
100	QPSK	270	0		22.57		24.3	1.0	
100	16QAM	1	1		22.84		24.3	1.0	
100	64QAM	1	1		21.21		22.8	2.5	
100	256QAM	1	1		19.12		20.8	4.5	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3485	3500.01	3505.02	up		
90	QPSK	1	1	23.66	23.56	23.58	25.3	0.0	
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	23.56	23.67	23.62	25.3	0.0	
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	23.57	23.58	23.62	25.3	0.0	
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	23.62	23.65	23.58	25.3	0.0	
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	23.57	23.59	23.58	25.3	0.0	
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	23.57	23.67	23.57	25.3	0.0	
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	23.67	23.64	23.57	25.3	0.0	
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	23.58	23.63	23.57	25.3	0.0	
Channel				630568	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	23.67	23.63	23.81	25.3	0.0	
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	23.61	23.59	23.62	25.3	0.0	
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	23.62	23.63	23.58	25.3	0.0	

Part27Q n78 PC2 Ant6 DSI1									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		25.50				
100	1/2 BPS	1	137		25.51		27.2	0.0	
100	1/2 BPS	1	271		25.49				
100	1/2 BPS	135	0		25.04		26.7	0.5	
100	1/2 BPS	135	69		25.50		27.2	0.0	
100	1/2 BPS	135	138		24.99				
100	1/2 BPS	270	0		25.12		26.7	0.5	
100	QPSK	1	1		25.69				
100	QPSK	1	137		25.64		27.2	0.0	
100	QPSK	1	271		25.65				
100	QPSK	135	0		24.46		26.2	1.0	
100	QPSK	135	69		25.49		27.2	0.0	
100	QPSK	135	138		24.43				
100	QPSK	270	0		24.62		26.2	1.0	
100	16QAM	1	1		24.48		26.2	1.0	
100	64QAM	1	1		23.16		24.7	2.5	
100	256QAM	1	1		21.14		22.7	4.5	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3485	3500.01	3505.02	up		
90	QPSK	1	1	25.63	25.60	25.59	27.2	0.0	
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	25.60	25.62	25.62	27.2	0.0	
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	25.59	25.57	25.57	27.2	0.0	
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	25.57	25.63	25.62	27.2	0.0	
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	25.64	25.58	25.61	27.2	0.0	
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	25.56	25.61	25.56	27.2	0.0	
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3536.02	up		
30	QPSK	1	1	25.58	25.55	25.54	27.2	0.0	
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	25.63	25.66	25.57	27.2	0.0	
Channel				630668	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	25.65	25.60	25.62	27.2	0.0	
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	25.55	25.61	25.61	27.2	0.0	
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	25.60	25.57	25.62	27.2	0.0	

n7 Ant7 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	18.68	18.72	18.75			
50	1/2 BPSK	1	135	18.70	18.78	18.68	19.8	0.0	
50	1/2 BPSK	1	268	18.66	18.80	18.69			
50	1/2 BPSK	135	0	18.72	18.81	18.76	19.8	0.0	
50	1/2 BPSK	135	68	18.67	18.79	18.74	19.8	0.0	
50	1/2 BPSK	135	135	18.64	18.72	18.75	19.8	0.0	
50	1/2 BPSK	270	0	18.70	18.77	18.67			
50	QPSK	1	1	18.72	18.83	18.72			
50	QPSK	1	135	18.73	18.77	18.75	19.8	0.0	
50	QPSK	1	268	18.70	18.74	18.68			
50	QPSK	135	0	18.65	18.77	18.73	19.8	0.0	
50	QPSK	135	68	18.70	18.78	18.70	19.8	0.0	
50	QPSK	135	135	18.71	18.77	18.67			
50	QPSK	270	0	18.65	18.75	18.74	19.8	0.0	
50	16QAM	1	1	18.67	18.69	18.66	19.8	0.0	
50	64QAM	1	1	18.66	18.77	18.73	19.8	0.0	
50	256QAM	1	1	18.23	18.27	18.22	19.3	0.5	
Channel				504000	507000	510000	tune up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	18.57	18.65	18.62	19.8	0.0	
Channel				503500	507000	510500	tune up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	18.66	18.66	18.58	19.8	0.0	
Channel				503000	507000	511000	tune up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	18.60	18.68	18.64	19.8	0.0	
Channel				502500	507000	511500	tune up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	18.67	18.71	18.64	19.8	0.0	
Channel				502000	507000	512000	tune up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	18.59	18.73	18.60	19.8	0.0	
Channel				501500	507000	512500	tune up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	18.67	18.72	18.67	19.8	0.0	
Channel				501000	507000	513000	tune up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	18.64	18.65	18.67	19.8	0.0	
Channel				500500	507000	513500	tune up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	18.58	18.71	18.57	19.8	0.0	

n66 Ant7 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	18.57	18.53	18.56			
45	1/2 BPSK	1	120	18.49	18.57	18.50	19.7	0.0	
45	1/2 BPSK	1	240	18.57	18.58	18.51			
45	1/2 BPSK	120	0	18.57	18.56	18.50	19.7	0.0	
45	1/2 BPSK	120	60	18.51	18.54	18.57	19.7	0.0	
45	1/2 BPSK	120	120	18.53	18.57	18.53	19.7	0.0	
45	1/2 BPSK	240	0	18.48	18.58	18.49			
45	QPSK	1	1	18.50	18.65	18.53			
45	QPSK	1	120	18.54	18.53	18.50	19.7	0.0	
45	QPSK	1	240	18.50	18.53	18.54			
45	QPSK	120	0	18.57	18.60	18.55	19.7	0.0	
45	QPSK	120	60	18.53	18.63	18.51	19.7	0.0	
45	QPSK	120	120	18.50	18.58	18.58			
45	QPSK	240	0	18.47	18.53	18.52	19.7	0.0	
45	16QAM	1	1	18.51	18.54	18.53	19.7	0.0	
45	64QAM	1	1	18.56	18.64	18.58	19.7	0.0	
45	256QAM	1	1	17.52	17.68	17.57	18.7	1.0	
Channel				346000	349000	352000	tune up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	18.35	18.38	18.44	19.7	0.0	
Channel				345500	349000	352500	tune up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	18.41	18.46	18.46	19.7	0.0	
Channel				345000	349000	353000	tune up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	18.36	18.47	18.45	19.7	0.0	
Channel				344500	349000	353500	tune up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	18.36	18.46	18.38	19.7	0.0	
Channel				344000	349000	354000	tune up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	18.46	18.39	18.37	19.7	0.0	
Channel				343500	349000	354500	tune up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	18.43	18.49	18.40	19.7	0.0	
Channel				343000	349000	355000	tune up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	18.46	18.45	18.46	19.7	0.0	
Channel				342500	349000	355500	tune up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	18.38	18.40	18.39	19.7	0.0	

n38 Ant7 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	18.25	18.33	18.19			
40	1/2 BPSK	1	53	18.21	18.33	18.23	19.1	0.0	
40	1/2 BPSK	1	104	18.17	18.25	18.23			
40	1/2 BPSK	50	0	18.19	18.28	18.26	19.1	0.0	
40	1/2 BPSK	50	28	18.20	18.25	18.20	19.1	0.0	
40	1/2 BPSK	50	56	18.19	18.34	18.19			
40	1/2 BPSK	100	0	18.19	18.27	18.26	19.1	0.0	
40	QPSK	1	1	18.17	18.35	18.29			
40	QPSK	1	53	18.25	18.28	18.27	19.1	0.0	
40	QPSK	1	104	18.22	18.26	18.27			
40	QPSK	50	0	18.17	18.30	18.21	19.1	0.0	
40	QPSK	50	28	18.22	18.33	18.28	19.1	0.0	
40	QPSK	50	56	18.29	18.23	18.21			
40	QPSK	100	0	18.28	18.32	18.20	19.1	0.0	
40	16QAM	1	1	18.18	18.27	18.24	19.1	0.0	
40	64QAM	1	1	18.25	18.26	18.30	19.1	0.0	
40	256QAM	1	1	18.28	18.29	18.24	19.1	0.0	
Channel				517002	519000	520998	tune-up limit	MPR (dB)	
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	18.04	18.17	18.18	19.1	0.0	
Channel				516504	519000	521496	tune-up limit	MPR (dB)	
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	18.10	18.24	18.19	19.1	0.0	
Channel				516000	519000	522000	tune-up limit	MPR (dB)	
Frequency (MHz)				2569	2595	2610			
20	QPSK	1	1	18.04	18.28	18.15	19.1	0.0	
Channel				515502	519000	522498	tune-up limit	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	18.02	18.27	18.14	19.1	0.0	
Channel				515004	519000	522996	tune-up limit	MPR (dB)	
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	18.02	18.23	18.24	19.1	0.0	

n41 Ant7 DSI1									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	19.22	19.32	19.22			
100	1/2 BPSK	1	137	19.17	19.32	19.22	20.2	0.0	
100	1/2 BPSK	1	271	19.13	19.35	19.17			
100	1/2 BPSK	135	0	19.17	19.24	19.25	20.2	0.0	
100	1/2 BPSK	135	69	19.20	19.33	19.22	20.2	0.0	
100	1/2 BPSK	135	138	19.19	19.34	19.19			
100	1/2 BPSK	270	0	19.16	19.29	19.17	20.2	0.0	
100	QPSK	1	1	19.22	19.36	19.16			
100	QPSK	1	137	19.18	19.27	19.22	20.2	0.0	
100	QPSK	1	271	19.13	19.32	19.15			
100	QPSK	135	0	19.16	19.32	19.19	20.2	0.0	
100	QPSK	135	69	19.15	19.33	19.25	20.2	0.0	
100	QPSK	135	138	19.16	19.24	19.26			
100	QPSK	270	0	19.17	19.28	19.27	20.2	0.0	
100	16QAM	1	1	19.23	19.28	19.18	20.2	0.0	
100	64QAM	1	1	19.17	19.30	19.28	20.2	0.0	
100	256QAM	1	1	18.27	18.35	18.21	19.2	1.0	
Channel				508200	518598	528996	tune-up limit	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	19.11	19.24	19.04	20.2	0.0	
Channel				507204	518598	529998	tune-up limit	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	19.10	19.23	19.11	20.2	0.0	
Channel				506202	518598	531000	tune-up limit	MPR (dB)	
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	19.11	19.24	19.05	20.2	0.0	
Channel				505200	518598	531996	tune-up limit	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	19.08	19.19	19.08	20.2	0.0	
Channel				504204	518598	532998	tune-up limit	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	19.08	19.28	19.06	20.2	0.0	
Channel				503700	518598	533496	tune-up limit	MPR (dB)	
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	19.17	19.19	19.06	20.2	0.0	
Channel				503202	518598	534000	tune-up limit	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	19.06	19.25	19.01	20.2	0.0	
Channel				502704	518598	534498	tune-up limit	MPR (dB)	
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	19.18	19.26	19.05	20.2	0.0	
Channel				502200	518598	534996	tune-up limit	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	19.11	19.30	19.01	20.2	0.0	
Channel				501702	518598	535500	tune-up limit	MPR (dB)	
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	19.06	19.19	19.09	20.2	0.0	
Channel				501204	518598	535998	tune-up limit	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	19.07	19.21	19.08	20.2	0.0	
Channel				500700	518598	536496	tune-up limit	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	19.18	19.27	19.03	20.2	0.0	
Channel				500202	518598	537000	tune-up limit	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	19.06	19.28	19.01	20.2	0.0	

Reduced Power Mode for DSI3_Other PA

n7 Ant5 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	16.72	16.80	16.66			
50	1/2 BPSK	1	135	16.80	16.83	16.69	17.5	0.0	
50	1/2 BPSK	1	268	16.80	16.83	16.74			
50	1/2 BPSK	135	0	16.83	16.86	16.71	17.5	0.0	
50	1/2 BPSK	135	68	16.72	16.87	16.72	17.5	0.0	
50	1/2 BPSK	135	135	16.77	16.76	16.66			
50	1/2 BPSK	270	0	16.76	16.82	16.66	17.5	0.0	
50	QPSK	1	1	16.74	16.89	16.70			
50	QPSK	1	135	16.81	16.76	16.72	17.5	0.0	
50	QPSK	1	268	16.77	16.85	16.74			
50	QPSK	135	0	16.82	16.83	16.65	17.5	0.0	
50	QPSK	135	68	16.78	16.85	16.72	17.5	0.0	
50	QPSK	135	135	16.81	16.84	16.69			
50	QPSK	270	0	16.82	16.83	16.64	17.5	0.0	
50	16QAM	1	1	16.78	16.77	16.65	17.5	0.0	
50	64QAM	1	1	16.77	16.79	16.71	17.5	0.0	
50	256QAM	1	1	16.75	16.86	16.66	17.5	0.0	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	16.59	16.72	16.62	17.5	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	16.64	16.69	16.64	17.5	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	16.69	16.66	16.64	17.5	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	16.70	16.71	16.62	17.5	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	16.59	16.68	16.60	17.5	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	16.64	16.73	16.54	17.5	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	16.66	16.76	16.61	17.5	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	16.68	16.66	16.63	17.5	0.0	

n66 Ant5 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	18.24	18.36	18.27			
45	1/2 BPSK	1	120	18.26	18.31	18.21	19.3	0.0	
45	1/2 BPSK	1	240	18.32	18.37	18.26			
45	1/2 BPSK	120	0	18.31	18.29	18.26	19.3	0.0	
45	1/2 BPSK	120	60	18.24	18.33	18.29	19.3	0.0	
45	1/2 BPSK	120	120	18.24	18.27	18.30	19.3	0.0	
45	1/2 BPSK	240	0	18.28	18.34	18.26			
45	QPSK	1	1	18.25	18.38	18.23			
45	QPSK	1	120	18.35	18.31	18.20	19.3	0.0	
45	QPSK	1	240	18.31	18.27	18.25			
45	QPSK	120	0	18.25	18.32	18.23	19.3	0.0	
45	QPSK	120	60	18.27	18.35	18.25	19.3	0.0	
45	QPSK	120	120	18.30	18.32	18.30	19.3	0.0	
45	QPSK	240	0	18.33	18.34	18.29			
45	16QAM	1	1	18.29	18.29	18.25	19.3	0.0	
45	64QAM	1	1	18.26	18.37	18.29	19.3	0.0	
45	256QAM	1	1	17.23	17.33	17.28	18.3	1.0	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	18.16	18.30	18.18	19.3	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	18.12	18.23	18.14	19.3	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	18.11	18.24	18.10	19.3	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	18.13	18.21	18.11	19.3	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	18.19	18.26	18.13	19.3	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	18.17	18.29	18.11	19.3	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	18.19	18.26	18.07	19.3	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	18.13	18.26	18.13	19.3	0.0	

n7 Ant4 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	18.97	19.03	18.97			
50	1/2 BPSK	1	135	19.05	19.10	19.02	20.2	0.0	
50	1/2 BPSK	1	268	18.96	19.05	19.01			
50	1/2 BPSK	135	0	19.07	19.10	19.03	20.2	0.0	
50	1/2 BPSK	135	68	19.06	19.03	19.05	20.2	0.0	
50	1/2 BPSK	135	135	18.96	19.04	19.02	20.2	0.0	
50	1/2 BPSK	270	0	19.00	19.11	19.03			
50	QPSK	1	1	19.02	19.12	19.00			
50	QPSK	1	135	19.07	19.06	19.07	20.2	0.0	
50	QPSK	1	268	18.99	19.11	18.98			
50	QPSK	135	0	19.01	19.04	19.00	20.2	0.0	
50	QPSK	135	68	19.03	19.10	18.98	20.2	0.0	
50	QPSK	135	135	19.05	19.09	19.01			
50	QPSK	270	0	19.03	19.07	19.06	20.2	0.0	
50	16QAM	1	1	18.95	19.04	19.03	20.2	0.0	
50	64QAM	1	1	19.05	19.06	18.96	20.2	0.0	
50	256QAM	1	1	18.99	19.09	19.00	20.2	0.0	
Channel				504000	507000	510000	tune up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	18.96	18.97	18.89	20.2	0.0	
Channel				503500	507000	510500	tune up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	18.86	19.02	18.95	20.2	0.0	
Channel				503000	507000	511000	tune up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	18.97	19.03	18.90	20.2	0.0	
Channel				502500	507000	511500	tune up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	18.87	18.96	18.89	20.2	0.0	
Channel				502000	507000	512000	tune up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	18.94	19.02	18.89	20.2	0.0	
Channel				501500	507000	512500	tune up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	18.93	18.96	18.90	20.2	0.0	
Channel				501000	507000	513000	tune up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	18.87	19.04	18.87	20.2	0.0	
Channel				500500	507000	513500	tune up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	18.88	19.05	18.89	20.2	0.0	

n66 Ant4 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	21.21	21.34	21.09			
45	1/2 BPSK	1	120	21.17	21.25	21.16	21.8	0.0	
45	1/2 BPSK	1	240	21.21	21.35	21.12			
45	1/2 BPSK	120	0	21.17	21.24	21.13	21.8	0.0	
45	1/2 BPSK	120	60	21.24	21.34	21.16	21.8	0.0	
45	1/2 BPSK	120	120	21.22	21.24	21.18	21.8	0.0	
45	1/2 BPSK	240	0	21.22	21.34	21.14			
45	QPSK	1	1	21.19	21.36	21.12			
45	QPSK	1	120	21.16	21.31	21.10	21.8	0.0	
45	QPSK	1	240	21.14	21.30	21.13			
45	QPSK	120	0	21.21	21.31	21.15	21.8	0.0	
45	QPSK	120	60	21.23	21.33	21.09	21.8	0.0	
45	QPSK	120	120	21.13	21.31	21.18	21.8	0.0	
45	QPSK	240	0	21.17	21.26	21.20			
45	16QAM	1	1	21.18	21.26	21.14	21.8	0.0	
45	64QAM	1	1	21.10	21.21	21.00	21.8	0.0	
45	256QAM	1	1	20.73	20.83	20.58	21.3	0.5	
Channel				346000	349000	352000	tune up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	21.11	21.17	21.07	21.8	0.0	
Channel				345500	349000	352500	tune up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	21.08	21.15	20.98	21.8	0.0	
Channel				345000	349000	353000	tune up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	21.12	21.16	21.05	21.8	0.0	
Channel				344500	349000	353500	tune up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	21.14	21.14	21.01	21.8	0.0	
Channel				344000	349000	354000	tune up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	21.05	21.24	21.06	21.8	0.0	
Channel				343500	349000	354500	tune up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	21.09	21.16	21.02	21.8	0.0	
Channel				343000	349000	355000	tune up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	21.11	21.19	20.99	21.8	0.0	
Channel				342500	349000	355500	tune up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	21.04	21.14	21.03	21.8	0.0	

Part270 n77 PC2 Ant4 DS13									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	23.35	23.38	23.31			
100	1/2 BPSK	1	137	23.31	23.45	23.28	23.5	0.0	
100	1/2 BPSK	1	271	23.27	23.37	23.45			
100	1/2 BPSK	135	0	23.32	23.39	23.30	23.5	0.0	
100	1/2 BPSK	135	69	23.26	23.35	23.35	23.5	0.0	
100	1/2 BPSK	135	138	23.38	23.34	23.33	23.5	0.0	
100	1/2 BPSK	270	0	23.29	23.37	23.42	23.5	0.0	
100	QPSK	1	1	23.21	23.48	23.40			
100	QPSK	1	137	23.34	23.29	23.30	23.5	0.0	
100	QPSK	1	271	23.21	23.40	23.40			
100	QPSK	135	0	23.32	23.40	23.40	23.5	0.0	
100	QPSK	135	69	23.29	23.42	23.34	23.5	0.0	
100	QPSK	135	138	23.29	23.38	23.29	23.5	0.0	
100	QPSK	270	0	23.37	23.39	23.33	23.5	0.0	
100	16QAM	1	1	23.28	23.36	23.34	23.5	0.0	
100	64QAM	1	1	23.33	23.38	23.26	23.5	0.0	
100	256QAM	1	1	23.37	23.36	23.32	23.5	0.0	
Channel				648668	650000	662334			
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	23.13	23.43	23.35	23.5	0.0	
Channel				649334	650000	662668			
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	23.13	23.42	23.30	23.5	0.0	
Channel				649200	650000	663000			
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	23.16	23.40	23.28	23.5	0.0	
Channel				648668	650000	663334			
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	23.07	23.39	23.32	23.5	0.0	
Channel				648334	650000	663668			
Frequency (MHz)				3725.01	3840	3965.02			
50	QPSK	1	1	23.08	23.35	23.31	23.5	0.0	
Channel				648000	650000	664000			
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	23.08	23.35	23.32	23.5	0.0	
Channel				647668	650000	664334			
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	23.10	23.37	23.28	23.5	0.0	
Channel				647500	650000	664500			
Frequency (MHz)				3712.5	3840	3967.5			
25	QPSK	1	1	23.10	23.33	23.28	23.5	0.0	
Channel				647334	650000	664668			
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	1	23.12	23.34	23.35	23.5	0.0	
Channel				647168	650000	664834			
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	23.16	23.41	23.33	23.5	0.0	
Channel				647000	650000	665000			
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	23.09	23.38	23.26	23.5	0.0	

Part27Q n77 Ant4 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3500.01	633334				
100	1/2 BPSK	1	1		19.55				
100	1/2 BPSK	1	137		19.49		20.0	0.0	
100	1/2 BPSK	1	271		19.53				
100	1/2 BPSK	135	0		19.49		20.0	0.0	
100	1/2 BPSK	135	69		19.50		20.0	0.0	
100	1/2 BPSK	135	138		19.51				
100	1/2 BPSK	270	0		19.54		20.0	0.0	
100	QPSK	1	1		19.58				
100	QPSK	1	137		19.51		20.0	0.0	
100	QPSK	1	271		19.44				
100	QPSK	135	0		19.55		20.0	0.0	
100	QPSK	135	69		19.55		20.0	0.0	
100	QPSK	135	138		19.51				
100	QPSK	270	0		19.55		20.0	0.0	
100	16QAM	1	1		19.54		20.0	0.0	
100	64QAM	1	1		19.52		20.0	0.0	
100	256QAM	1	1		19.47		20.0	0.0	
Channel				633000	633334	633668			
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	19.46	19.39	19.40	20.0	0.0	
Channel				632668	633334	634000			
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	19.46	19.38	19.44	20.0	0.0	
Channel				632334	633334	634334			
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	19.43	19.47	19.46	20.0	0.0	
Channel				632000	633334	634668			
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	19.40	19.39	19.39	20.0	0.0	
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	19.45	19.44	19.47	20.0	0.0	
Channel				631334	633334	635334			
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	19.48	19.48	19.44	20.0	0.0	
Channel				631000	633334	635668			
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	19.45	19.44	19.41	20.0	0.0	
Channel				630834	633334	635834			
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	19.49	19.46	19.43	20.0	0.0	
Channel				630668	633334	636000			
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	19.49	19.42	19.50	20.0	0.0	
Channel				630500	633334	636168			
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	19.44	19.42	19.48	20.0	0.0	
Channel				630334	633334	636334			
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	19.40	19.43	19.41	20.0	0.0	

Part27Q n77 PC2 Ant4 DSI3									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit [dBm]	MPR [dB]	
Channel									
Frequency [MHz]				3500.01	633334				
100	1/2 BPSK	1	1		23.01				
100	1/2 BPSK	1	137		23.00		23.5	0.0	
100	1/2 BPSK	1	271		22.99				
100	1/2 BPSK	135	0		23.00		23.5	0.0	
100	1/2 BPSK	135	69		23.00		23.5	0.0	
100	1/2 BPSK	135	138		22.98				
100	1/2 BPSK	270	0		23.08		23.5	0.0	
100	QPSK	1	1		23.12				
100	QPSK	1	137		23.04		23.5	0.0	
100	QPSK	1	271		23.00				
100	QPSK	135	0		23.07		23.5	0.0	
100	QPSK	135	69		23.11		23.5	0.0	
100	QPSK	135	138		22.97				
100	QPSK	270	0		23.08		23.5	0.0	
100	16QAM	1	1		23.05		23.5	0.0	
100	16QAM	1	1		23.05		23.5	0.0	
100	256QAM	1	1		22.97				
Channel				3499.99	633334	3499.99			
Frequency [MHz]				3499.99	3500.01	3505.02			
90	QPSK	1	1	23.02	23.02	23.02	23.5	0.0	
Channel				3496.98	633334	634006			
Frequency [MHz]				3496.98	3500.01	3510			
80	QPSK	1	1	22.97	23.07	22.97	23.5	0.0	
Channel				3493.94	633334	343334			
Frequency [MHz]				3493.94	3500.01	3515.01			
70	QPSK	1	1	23.00	23.04	22.99	23.5	0.0	
Channel				632000	633334	634668			
Frequency [MHz]				3480	3500.01	3520.02			
60	QPSK	1	1	23.07	23.03	22.98	23.5	0.0	
Channel				631668	633334	632000			
Frequency [MHz]				3475.02	3500.01	3525			
50	QPSK	1	1	23.01	23.05	23.07	23.5	0.0	
Channel				631334	633334	633334			
Frequency [MHz]				3470.01	3500.01	3530.01			
40	QPSK	1	1	23.03	23.06	22.98	23.5	0.0	
Channel				631000	633334	632668			
Frequency [MHz]				3468	3500.01	3535.02			
30	QPSK	1	1	23.05	23.00	23.03	23.5	0.0	
Channel				630834	633334	633834			
Frequency [MHz]				3462.51	3500.01	3537.51			
25	QPSK	1	1	23.03	23.09	23.08	23.5	0.0	
Channel				630668	633334	632000			
Frequency [MHz]				3460.02	3500.01	3540			
20	QPSK	1	1	22.98	23.04	23.06	23.5	0.0	
Channel				630500	633334	631668			
Frequency [MHz]				3457.5	3500.01	3542.52			
15	QPSK	1	1	23.02	23.08	23.01	23.5	0.0	
Channel				630334	633334	633334			
Frequency [MHz]				3455.01	3500.01	3545.01			
10	QPSK	1	1	22.98	23.02	23.01	23.5	0.0	

Part270 n78 PC2 Ant4 DSI3									
BW MHz	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	1/2 BPS	1	1		22.87				
100	1/2 BPS	1	137		22.71		23.0	0.0	
100	1/2 BPS	1	271		22.79				
100	1/2 BPS	135	0		22.83		23.0	0.0	
100	1/2 BPS	135	69		22.75				
100	1/2 BPS	135	138		22.73		23.0	0.0	
100	1/2 BPS	270	0		22.80		23.0	0.0	
100	QPSK	1	1		22.95				
100	QPSK	1	137		22.82		23.0	0.0	
100	QPSK	1	271		22.77				
100	QPSK	135	0		22.78		23.0	0.0	
100	QPSK	135	69		22.91		23.0	0.0	
100	QPSK	135	138		22.88				
100	QPSK	270	0		22.70		23.0	0.0	
100	16QAM	1	1		22.81		23.0	0.0	
100	64QAM	1	1		22.85		23.0	0.0	
100	256QAM	1	1		22.84		23.0	0.0	
Channel				648668	650000	650334	up	MPR	
Frequency (MHz)				3745.02	3750	3755.01	up	(dB)	
90	QPSK	1	1		22.83	22.89	22.91	23.0	0.0
Channel				649334	650000	650668	up	MPR	
Frequency (MHz)				3740.01	3750	3760.02	up	(dB)	
80	QPSK	1	1		22.87	22.86	22.86	23.0	0.0
Channel				649000	650000	651000	up	MPR	
Frequency (MHz)				3735	3750	3765	up	(dB)	
70	QPSK	1	1		22.81	22.89	22.80	23.0	0.0
Channel				648668	650000	651334	up	MPR	
Frequency (MHz)				3730.02	3750	3770.01	up	(dB)	
60	QPSK	1	1		22.82	22.88	22.90	23.0	0.0
Channel				649334	650000	651668	up	MPR	
Frequency (MHz)				3725.01	3750	3775.02	up	(dB)	
50	QPSK	1	1		22.84	22.88	22.91	23.0	0.0
Channel				648000	650000	652000	up	MPR	
Frequency (MHz)				3720	3750	3780	up	(dB)	
40	QPSK	1	1		22.82	22.84	22.82	23.0	0.0
Channel				647668	650000	652334	up	MPR	
Frequency (MHz)				3715.02	3750	3785.01	up	(dB)	
30	QPSK	1	1		22.85	22.83	22.81	23.0	0.0
Channel				647500	650000	652500	up	MPR	
Frequency (MHz)				3712.5	3750	3787.5	up	(dB)	
25	QPSK	1	1		22.83	22.84	22.81	23.0	0.0
Channel				647334	650000	652668	up	MPR	
Frequency (MHz)				3710.01	3750	3790.02	up	(dB)	
20	QPSK	1	1		22.80	22.83	22.88	23.0	0.0
Channel				647168	650000	652834	up	MPR	
Frequency (MHz)				3707.52	3750	3792.51	up	(dB)	
15	QPSK	1	1		22.86	22.88	22.91	23.0	0.0
Channel				647000	650000	653000	up	MPR	
Frequency (MHz)				3705	3750	3795	up	(dB)	
10	QPSK	1	1		22.84	22.85	22.90	23.0	0.0

Part27Q n78 Ant4 DSI3									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		19.08				
100	1/2 BPS	1	137		19.05		19.5	0.0	
100	1/2 BPS	1	271		19.13				
100	1/2 BPS	135	0		19.11		19.5	0.0	
100	1/2 BPS	135	69		19.05		19.5	0.0	
100	1/2 BPS	135	138		19.08				
100	1/2 BPS	270	0		19.14		19.5	0.0	
100	QPSK	1	1		19.15				
100	QPSK	1	137		19.07		19.5	0.0	
100	QPSK	1	271		19.14				
100	QPSK	135	0		19.10		19.5	0.0	
100	QPSK	135	69		19.14		19.5	0.0	
100	QPSK	135	138		19.06				
100	QPSK	270	0		19.15		19.5	0.0	
100	16QAM	1	1		19.13		19.5	0.0	
100	64QAM	1	1		19.10		19.5	0.0	
100	256QAM	1	1		19.06		19.5	0.0	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02	up	(dB)	
90	QPSK	1	1		19.03	18.96	19.03	19.5	0.0
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up	(dB)	
80	QPSK	1	1		19.00	19.04	19.01	19.5	0.0
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up	(dB)	
70	QPSK	1	1		19.02	18.96	18.94	19.5	0.0
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up	(dB)	
60	QPSK	1	1		18.95	18.94	18.96	19.5	0.0
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525	up	(dB)	
50	QPSK	1	1		18.95	18.97	18.93	19.5	0.0
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up	(dB)	
40	QPSK	1	1		19.02	18.94	19.01	19.5	0.0
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	up	(dB)	
30	QPSK	1	1		18.94	19.02	18.96	19.5	0.0
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up	(dB)	
25	QPSK	1	1		19.00	18.97	18.98	19.5	0.0
Channel				630668	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up	(dB)	
20	QPSK	1	1		19.05	18.99	19.03	19.5	0.0
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up	(dB)	
15	QPSK	1	1		18.96	19.05	18.96	19.5	0.0
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up	(dB)	
10	QPSK	1	1		18.96	18.98	19.02	19.5	0.0

Part27Q n78 PC2 Ant4 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		22.53				
100	1/2 BPS	1	137		22.58		23.0	0.0	
100	1/2 BPS	1	271		22.57				
100	1/2 BPS	135	0		22.56		23.0	0.0	
100	1/2 BPS	135	69		22.57			23.0	0.0
100	1/2 BPS	135	138		22.55		23.0	0.0	
100	1/2 BPS	270	0		22.59				
100	QPSK	1	1		22.70				
100	QPSK	1	137		22.54		23.0	0.0	
100	QPSK	1	271		22.69				
100	QPSK	135	0		22.63		23.0	0.0	
100	QPSK	135	69		22.66				
100	QPSK	135	138		22.54		23.0	0.0	
100	QPSK	270	0		22.66				
100	16QAM	1	1		22.63		23.0	0.0	
100	64QAM	1	1		22.57		23.0	0.0	
100	256QAM	1	1		22.59		23.0	0.0	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02	up	(dB)	
90	QPSK	1	1		22.58	22.63	22.55	23.0	0.0
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up	(dB)	
80	QPSK	1	1		22.66	22.54	22.63	23.0	0.0
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up	(dB)	
70	QPSK	1	1		22.59	22.60	22.61	23.0	0.0
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up	(dB)	
60	QPSK	1	1		22.66	22.66	22.56	23.0	0.0
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525.03	up	(dB)	
50	QPSK	1	1		22.57	22.56	22.56	23.0	0.0
Channel				631334	633334	633334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up	(dB)	
40	QPSK	1	1		22.65	22.60	22.64	23.0	0.0
Channel				631000	633334	633668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	up	(dB)	
30	QPSK	1	1		22.55	22.64	22.64	23.0	0.0
Channel				630834	633334	633834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up	(dB)	
25	QPSK	1	1		22.65	22.57	22.54	23.0	0.0
Channel				630668	633334	633668	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up	(dB)	
20	QPSK	1	1		22.58	22.63	22.63	23.0	0.0
Channel				630500	633334	633668	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up	(dB)	
15	QPSK	1	1		22.57	22.55	22.63	23.0	0.0
Channel				630334	633334	633334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up	(dB)	
10	QPSK	1	1		22.57	22.57	22.56	23.0	0.0

n7 Ant6 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	20.71	20.71	20.66			
50	1/2 BPSK	1	135	20.79	20.72	20.76	21.0	0.0	
50	1/2 BPSK	1	268	20.73	20.70	20.75			
50	1/2 BPSK	135	0	20.70	20.80	20.70	21.0	0.0	
50	1/2 BPSK	135	68	20.71	20.71	20.74	21.0	0.0	
50	1/2 BPSK	135	135	20.75	20.78	20.70	21.0	0.0	
50	1/2 BPSK	270	0	20.72	20.70	20.71			
50	QPSK	1	1	20.70	20.81	20.66			
50	QPSK	1	135	20.76	20.73	20.75	21.0	0.0	
50	QPSK	1	268	20.69	20.74	20.67			
50	QPSK	135	0	20.71	20.70	20.68	21.0	0.0	
50	QPSK	135	68	20.76	20.78	20.67	21.0	0.0	
50	QPSK	135	135	20.71	20.72	20.69			
50	QPSK	270	0	20.72	20.77	20.76	21.0	0.0	
50	16QAM	1	1	20.70	20.72	20.77	21.0	0.0	
50	64QAM	1	1	20.79	20.73	20.68	21.0	0.0	
50	256QAM	1	1	20.69	20.74	20.71	21.0	0.0	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	20.64	20.64	20.58	21.0	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	20.58	20.57	20.61	21.0	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	20.61	20.58	20.50	21.0	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	20.62	20.65	20.51	21.0	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	20.64	20.59	20.55	21.0	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	20.57	20.55	20.57	21.0	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	20.58	20.65	20.62	21.0	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	20.64	20.56	20.60	21.0	0.0	

n66 Ant6 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	20.38	20.50	20.44			
45	1/2 BPSK	1	120	20.38	20.49	20.50	21.0	0.0	
45	1/2 BPSK	1	240	20.48	20.47	20.53			
45	1/2 BPSK	120	0	20.38	20.50	20.46	21.0	0.0	
45	1/2 BPSK	120	60	20.41	20.55	20.47	21.0	0.0	
45	1/2 BPSK	120	120	20.48	20.48	20.45	21.0	0.0	
45	1/2 BPSK	240	0	20.40	20.51	20.51			
45	QPSK	1	1	20.41	20.56	20.42			
45	QPSK	1	120	20.44	20.46	20.47	21.0	0.0	
45	QPSK	1	240	20.38	20.47	20.45			
45	QPSK	120	0	20.40	20.47	20.44	21.0	0.0	
45	QPSK	120	60	20.49	20.54	20.46	21.0	0.0	
45	QPSK	120	120	20.43	20.50	20.46			
45	QPSK	240	0	20.49	20.51	20.49	21.0	0.0	
45	16QAM	1	1	20.38	20.53	20.42	21.0	0.0	
45	64QAM	1	1	20.44	20.55	20.48	21.0	0.0	
45	256QAM	1	1	20.47	20.46	20.48	21.0	0.0	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	20.26	20.39	20.30	21.0	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	20.33	20.34	20.27	21.0	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	20.29	20.39	20.33	21.0	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	20.35	20.37	20.27	21.0	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	20.25	20.35	20.30	21.0	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	20.37	20.41	20.28	21.0	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	20.26	20.32	20.27	21.0	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	20.36	20.32	20.27	21.0	0.0	

n38 Ant6 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				518004	519000	519996			
Channel				2590.02	2599	2599.98			
40	1/2 BPSK	1	1	20.62	20.59	20.61			
40	1/2 BPSK	1	53	20.61	20.58	20.59	21.0	0.0	
40	1/2 BPSK	1	104	20.61	20.64	20.56			
40	1/2 BPSK	50	0	20.56	20.63	20.53	21.0	0.0	
40	1/2 BPSK	50	26	20.57	20.65	20.53	21.0	0.0	
40	1/2 BPSK	50	56	20.63	20.56	20.52			
40	1/2 BPSK	100	0	20.58	20.66	20.54	21.0	0.0	
40	QPSK	1	1	20.59	20.67	20.61			
40	QPSK	1	53	20.63	20.55	20.55	21.0	0.0	
40	QPSK	1	104	20.61	20.57	20.57			
40	QPSK	50	0	20.56	20.59	20.57	21.0	0.0	
40	QPSK	50	26	20.60	20.66	20.58	21.0	0.0	
40	QPSK	50	56	20.63	20.60	20.55			
40	QPSK	100	0	20.52	20.57	20.53	21.0	0.0	
40	16QAM	1	1	20.61	20.56	20.61	21.0	0.0	
40	64QAM	1	1	20.59	20.64	20.61	21.0	0.0	
40	256QAM	1	1	20.54	20.57	20.51	21.0	0.0	
Channel				517002	516000	520998			
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	20.49	20.48	20.46	21.0	0.0	
Channel				516504	519000	521496			
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	20.46	20.47	20.54	21.0	0.0	
Channel				515000	519000	522000			
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	20.53	20.51	20.56	21.0	0.0	
Channel				515502	519000	522498			
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	20.54	20.51	20.46	21.0	0.0	
Channel				515004	519000	522996			
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	20.49	20.46	20.53	21.0	0.0	

n41 Ant6 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				509002	516598	526000			
Channel				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	20.05	20.14	19.93			
100	1/2 BPSK	1	137	20.13	20.10	19.97	20.5	0.0	
100	1/2 BPSK	1	271	20.14	20.12	20.00			
100	1/2 BPSK	135	0	20.04	20.18	19.97	20.5	0.0	
100	1/2 BPSK	135	69	20.14	20.16	19.94	20.5	0.0	
100	1/2 BPSK	135	138	20.06	20.17	19.97			
100	1/2 BPSK	270	0	20.05	20.13	19.95	20.5	0.0	
100	QPSK	1	1	20.05	20.15	20.03			
100	QPSK	1	137	20.08	20.07	19.91	20.5	0.0	
100	QPSK	1	271	20.11	20.09	19.95			
100	QPSK	135	0	20.12	20.11	19.99	20.5	0.0	
100	QPSK	135	69	20.13	20.16	20.02	20.5	0.0	
100	QPSK	135	138	20.13	20.15	19.92			
100	QPSK	270	0	20.04	20.19	19.95	20.5	0.0	
100	16QAM	1	1	20.14	20.15	19.91	20.5	0.0	
100	64QAM	1	1	20.08	20.12	19.98	20.5	0.0	
100	256QAM	1	1	20.12	20.12	19.99	20.5	0.0	
Channel				505000	516598	526998			
Frequency (MHz)				2541	2592.99	2644.99			
90	QPSK	1	1	19.97	19.92	19.93	20.5	0.0	
Channel				507204	516598	529998			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	19.99	19.94	19.90	20.5	0.0	
Channel				505002	516598	531000			
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	19.96	19.93	19.97	20.5	0.0	
Channel				505000	516598	531996			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	19.93	19.98	19.92	20.5	0.0	
Channel				504204	516598	532998			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	19.91	20.03	19.99	20.5	0.0	
Channel				503700	516598	533496			
Frequency (MHz)				2516.5	2592.99	2667.48			
45	QPSK	1	1	19.96	20.03	19.88	20.5	0.0	
Channel				503002	516598	534000			
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	19.89	19.94	19.95	20.5	0.0	
Channel				502704	516598	534498			
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	19.92	19.95	19.94	20.5	0.0	
Channel				502200	516598	534998			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	19.90	19.98	19.94	20.5	0.0	
Channel				501702	516598	535500			
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	19.91	20.01	19.93	20.5	0.0	
Channel				501204	516598	535998			
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	19.92	20.02	19.87	20.5	0.0	
Channel				500700	516598	536496			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	20.01	19.94	19.88	20.5	0.0	
Channel				500202	516598	537000			
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	19.95	20.01	19.97	20.5	0.0	

n48 Ant6 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				638000	641666	645332			
Frequency (MHz)				3570	3624.99	3679.98			
40	1/2 BPSK	1	1	18.57	18.62	18.57			
40	1/2 BPSK	1	53	18.65	18.66	18.60	20.1	0.0	
40	1/2 BPSK	1	104	18.54	18.69	18.61			
40	1/2 BPSK	50	0	18.60	18.61	18.54	20.1	0.0	
40	1/2 BPSK	50	26	18.63	18.61	18.59	20.1	0.0	
40	1/2 BPSK	50	56	18.63	18.63	18.57			
40	1/2 BPSK	100	0	18.57	18.61	18.56	20.1	0.0	
40	QPSK	1	1	18.54	18.78	18.56			
40	QPSK	1	53	18.61	18.65	18.53	20.1	0.0	
40	QPSK	1	104	18.53	18.59	18.63			
40	QPSK	50	0	18.55	18.71	18.54	20.1	0.0	
40	QPSK	50	26	18.54	18.73	18.60	20.1	0.0	
40	QPSK	50	56	18.54	18.60	18.62			
40	QPSK	100	0	18.54	18.69	18.56	20.1	0.0	
40	16QAM	1	1	18.54	18.66	18.56	20.1	0.0	
40	64QAM	1	1	18.62	18.69	18.58	20.1	0.0	
40	256QAM	1	1	17.49	17.69	17.53	19.1	1.0	
Channel				637668	641666	645998			
Frequency (MHz)				3565.02	3624.99	3684.99			
30	QPSK	1	1	18.47	18.55	18.47	20.1	0.0	
Channel				637334	641666	646000			
Frequency (MHz)				3560.00	3624.99	3680.00			
20	QPSK	1	1	18.43	18.55	18.42	20.1	0.0	
Channel				637168	641666	646166			
Frequency (MHz)				3557.52	3624.99	3692.49			
15	QPSK	1	1	18.43	18.51	18.40	20.1	0.0	
Channel				637000	641666	646332			
Frequency (MHz)				3555.00	3624.99	3694.98			
10	QPSK	1	1	18.47	18.55	18.40	20.1	0.0	

Part270 n77 PC2 Ant6 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	21.94	22.17	21.95			
100	1/2 BPSK	1	137	22.03	22.16	21.96	23.3	0.0	
100	1/2 BPSK	1	271	22.14	22.20	22.04			
100	1/2 BPSK	135	0	22.02	22.18	21.96	23.3	0.0	
100	1/2 BPSK	135	69	22.05	22.11	21.99	23.3	0.0	
100	1/2 BPSK	135	138	22.09	22.13	21.90	23.3	0.0	
100	1/2 BPSK	270	0	22.04	22.13	21.94			
100	QPSK	1	1	22.07	22.26	21.96			
100	QPSK	1	137	22.06	22.21	21.97	23.3	0.0	
100	QPSK	1	271	22.02	22.11	21.97			
100	QPSK	135	0	22.08	22.15	21.92	23.3	0.0	
100	QPSK	135	69	21.99	22.16	21.93	23.3	0.0	
100	QPSK	135	138	22.09	22.12	21.87			
100	QPSK	270	0	22.11	22.12	21.98			
100	16QAM	1	1	22.04	22.11	21.91	23.3	0.0	
100	64QAM	1	1	21.97	22.19	21.99	23.3	0.0	
100	256QAM	1	1	22.02	22.12	22.00	23.3	0.0	
Channel									
Frequency (MHz)				3745.02	3840	3935.01		MPR	
90	QPSK	1	1	21.95	22.22	21.85	23.3	0.0	
Channel									
Frequency (MHz)				3740.01	3840	3940.02		MPR	
80	QPSK	1	1	21.93	22.13	21.88	23.3	0.0	
Channel									
Frequency (MHz)				3735	3840	3945		MPR	
70	QPSK	1	1	21.93	22.17	21.84	23.3	0.0	
Channel									
Frequency (MHz)				3730.02	3840	3950.01		MPR	
60	QPSK	1	1	21.99	22.14	21.80	23.3	0.0	
Channel									
Frequency (MHz)				3725.01	3840	3955.02		MPR	
50	QPSK	1	1	21.94	22.13	21.86	23.3	0.0	
Channel									
Frequency (MHz)				3720	3840	3960		MPR	
40	QPSK	1	1	21.92	22.11	21.81	23.3	0.0	
Channel									
Frequency (MHz)				3715.02	3840	3965.01		MPR	
30	QPSK	1	1	21.95	22.20	21.86	23.3	0.0	
Channel									
Frequency (MHz)				3710.01	3840	3970.02		MPR	
25	QPSK	1	1	21.91	22.14	21.81	23.3	0.0	
Channel									
Frequency (MHz)				3707.52	3840	3972.51		MPR	
20	QPSK	1	1	21.96	22.15	21.90	23.3	0.0	
Channel									
Frequency (MHz)				3707.52	3840	3972.51		MPR	
15	QPSK	1	1	21.96	22.17	21.83	23.3	0.0	
Channel									
Frequency (MHz)				3707.52	3840	3972.51		MPR	
10	QPSK	1	1	21.95	22.16	21.82	23.3	0.0	

Part27Q n77 Ant6 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		18.69				
100	1/2 BPSK	1	137		18.68		20.3		0.0
100	1/2 BPSK	1	271		18.60				
100	1/2 BPSK	135	0		18.60		20.3		0.0
100	1/2 BPSK	135	69		18.59		20.3		0.0
100	1/2 BPSK	135	138		18.63		20.3		0.0
100	1/2 BPSK	270	0		18.64				
100	QPSK	1	1		18.71				
100	QPSK	1	137		18.67		20.3		0.0
100	QPSK	1	271		18.67				
100	QPSK	135	0		18.63		20.3		0.0
100	QPSK	135	69		18.65		20.3		0.0
100	QPSK	135	138		18.60				
100	QPSK	270	0		18.61				
100	16QAM	1	1		18.63		20.3		0.0
100	64QAM	1	1		18.67		20.3		0.0
100	256QAM	1	1		18.70		20.3		0.0
Channel				633000	633334	633668		MPR	
Frequency (MHz)				3495	3500.01	3505.02		(dB)	
90	QPSK	1	1	18.49	18.56	18.56	20.3		0.0
Channel				632668	633334	634000		MPR	
Frequency (MHz)				3490.02	3500.01	3510		(dB)	
80	QPSK	1	1	18.64	18.53	18.56	20.3		0.0
Channel				632334	633334	634334		MPR	
Frequency (MHz)				3485.01	3500.01	3515.01		(dB)	
70	QPSK	1	1	18.53	18.56	18.52	20.3		0.0
Channel				632000	633334	634668		MPR	
Frequency (MHz)				3480	3500.01	3520.02		(dB)	
60	QPSK	1	1	18.55	18.60	18.58	20.3		0.0
Channel				631668	633334	635000		MPR	
Frequency (MHz)				3475.02	3500.01	3525		(dB)	
50	QPSK	1	1	18.56	18.61	18.58	20.3		0.0
Channel				631334	633334	635334		MPR	
Frequency (MHz)				3470.01	3500.01	3530.01		(dB)	
40	QPSK	1	1	18.51	18.59	18.60	20.3		0.0
Channel				631000	633334	635668		MPR	
Frequency (MHz)				3465	3500.01	3535.02		(dB)	
30	QPSK	1	1	18.52	18.51	18.58	20.3		0.0
Channel				630834	633334	635834		MPR	
Frequency (MHz)				3462.51	3500.01	3537.51		(dB)	
25	QPSK	1	1	18.52	18.54	18.57	20.3		0.0
Channel				630668	633334	636000		MPR	
Frequency (MHz)				3460.02	3500.01	3540		(dB)	
20	QPSK	1	1	18.51	18.53	18.50	20.3		0.0
Channel				630500	633334	636168		MPR	
Frequency (MHz)				3457.5	3500.01	3542.52		(dB)	
15	QPSK	1	1	18.51	18.58	18.60	20.3		0.0
Channel				630334	633334	636334		MPR	
Frequency (MHz)				3455.01	3500.01	3545.01		(dB)	
10	QPSK	1	1	18.60	18.50	18.59	20.3		0.0

Part27Q n77 PC2 Ant6 DSI3									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit [dBm]	MPR [dBm]	
Channel									
Frequency (MHz)				3500.01	633334			3500.01	
100	1/2 BPSK	1	1		21.71				
100	1/2 BPSK	1	137		21.70		23.3	0.0	
100	1/2 BPSK	1	271		21.60				
100	1/2 BPSK	135	0		21.59		23.3	0.0	
100	1/2 BPSK	135	69		21.65		23.3	0.0	
100	1/2 BPSK	135	138		21.67		23.3	0.0	
100	1/2 BPSK	270	0		21.67				
100	QPSK	1	1		21.73				
100	QPSK	1	137		21.64		23.3	0.0	
100	QPSK	1	271		21.69				
100	QPSK	135	0		21.63		23.3	0.0	
100	QPSK	135	69		21.66		23.3	0.0	
100	QPSK	135	138		21.66				
100	QPSK	270	0		21.65		23.3	0.0	
100	16QAM	1	1		21.64		23.3	0.0	
100	16QAM	1	1		21.69		23.3	0.0	
100	256QAM	1	1		21.65		23.3	0.0	
Channel									
Frequency (MHz)				363000	633334	363668		363000	
90	QPSK	1	1	21.65	21.62	21.57	23.3	0.0	
Channel				362668	633334	634000		362668	
Frequency (MHz)				3460.02	3500.01	3510		3460.02	
80	QPSK	1	1	21.61	21.62	21.62	23.3	0.0	
Channel				33234	633334	33334		33234	
Frequency (MHz)				3465.01	3500.01	3515.01		3465.01	
70	QPSK	1	1	21.54	21.53	21.54	23.3	0.0	
Channel				632000	633334	634668		632000	
Frequency (MHz)				3460	3500.01	3520.02		3460	
60	QPSK	1	1	21.54	21.57	21.54	23.3	0.0	
Channel				331668	633334	332668		331668	
Frequency (MHz)				3475.02	3500.01	3525		3475.02	
50	QPSK	1	1	21.64	21.63	21.62	23.3	0.0	
Channel				631334	633334	633334		631334	
Frequency (MHz)				3470.01	3500.01	3530.01		3470.01	
40	QPSK	1	1	21.62	21.56	21.58	23.3	0.0	
Channel				632000	633334	633668		632000	
Frequency (MHz)				3465	3500.01	3535.02		3465	
30	QPSK	1	1	21.60	21.64	21.58	23.3	0.0	
Channel				630834	633334	633834		630834	
Frequency (MHz)				3462.51	3500.01	3537.51		3462.51	
25	QPSK	1	1	21.58	21.54	21.60	23.3	0.0	
Channel				630668	633334	632000		630668	
Frequency (MHz)				3460.02	3500.01	3540		3460.02	
20	QPSK	1	1	21.63	21.63	21.53	23.3	0.0	
Channel				630500	633334	631668		630500	
Frequency (MHz)				3497.5	3500.01	3542.52		3497.5	
15	QPSK	1	1	21.54	21.46	21.63	23.3	0.0	
Channel				633334	633334	633334		633334	
Frequency (MHz)				3455.01	3500.01	3545.01		3455.01	
10	QPSK	1	1	21.63	21.57	21.54	23.3	0.0	

Part270 n78 PC2 Ant6 DSI3									
BW MHz	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	1/2 BPS	1	1		21.64				
100	1/2 BPS	1	137		21.65		22.8	0.0	
100	1/2 BPS	1	271		21.68				
100	1/2 BPS	135	0		21.67		22.8	0.0	
100	1/2 BPS	135	69		21.69		22.8	0.0	
100	1/2 BPS	135	138		21.73				
100	1/2 BPS	270	0		21.71		22.8	0.0	
100	QPSK	1	1		21.75				
100	QPSK	1	137		21.66		22.8	0.0	
100	QPSK	1	271		21.67				
100	QPSK	135	0		21.69		22.8	0.0	
100	QPSK	135	69		21.71		22.8	0.0	
100	QPSK	135	138		21.66				
100	QPSK	270	0		21.62		22.8	0.0	
100	16QAM	1	1		21.65		22.8	0.0	
100	64QAM	1	1		21.62		22.8	0.0	
100	256QAM	1	1		21.66		22.8	0.0	
Channel				649668	650000	650334	MPR		
Frequency (MHz)				3745.02	3750	3755.01	up		
90	QPSK	1	1	21.59	21.58	21.57	22.8	0.0	
Channel				649334	650000	650668	MPR		
Frequency (MHz)				3740.01	3750	3760.02	up		
80	QPSK	1	1	21.52	21.51	21.57	22.8	0.0	
Channel				649000	650000	651000	MPR		
Frequency (MHz)				3735	3750	3765	up		
70	QPSK	1	1	21.52	21.55	21.52	22.8	0.0	
Channel				648668	650000	651334	MPR		
Frequency (MHz)				3730.02	3750	3770.01	up		
60	QPSK	1	1	21.57	21.52	21.57	22.8	0.0	
Channel				648334	650000	651668	MPR		
Frequency (MHz)				3725.01	3750	3775.02	up		
50	QPSK	1	1	21.58	21.54	21.57	22.8	0.0	
Channel				648000	650000	652000	MPR		
Frequency (MHz)				3720	3750	3780	up		
40	QPSK	1	1	21.53	21.57	21.58	22.8	0.0	
Channel				647668	650000	652334	MPR		
Frequency (MHz)				3715.02	3750	3785.01	up		
30	QPSK	1	1	21.56	21.61	21.57	22.8	0.0	
Channel				647500	650000	652500	MPR		
Frequency (MHz)				3712.5	3750	3787.5	up		
25	QPSK	1	1	21.55	21.56	21.53	22.8	0.0	
Channel				647334	650000	652668	MPR		
Frequency (MHz)				3710.01	3750	3790.02	up		
20	QPSK	1	1	21.59	21.58	21.55	22.8	0.0	
Channel				647168	650000	652834	MPR		
Frequency (MHz)				3707.52	3750	3792.51	up		
15	QPSK	1	1	21.57	21.56	21.58	22.8	0.0	
Channel				647000	650000	653000	MPR		
Frequency (MHz)				3705	3750	3795	up		
10	QPSK	1	1	21.58	21.60	21.53	22.8	0.0	

Part27Q n78 Ant6 DSI3									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		18.20				
100	1/2 BPS	1	137		18.17		19.8	0.0	
100	1/2 BPS	1	271		18.28				
100	1/2 BPS	135	0		18.26		19.8	0.0	
100	1/2 BPS	135	69		18.26		19.8	0.0	
100	1/2 BPS	135	138		18.23				
100	1/2 BPS	270	0		18.22		19.8	0.0	
100	QPSK	1	1		18.29				
100	QPSK	1	137		18.21		19.8	0.0	
100	QPSK	1	271		18.19				
100	QPSK	135	0		18.17		19.8	0.0	
100	QPSK	135	69		18.23		19.8	0.0	
100	QPSK	135	138		18.22				
100	QPSK	270	0		18.23		19.8	0.0	
100	16QAM	1	1		18.26		19.8	0.0	
100	64QAM	1	1		18.21		19.8	0.0	
100	256QAM	1	1		18.20		19.8	0.0	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	18.20	18.16	18.21	19.8	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	18.22	18.20	18.23	19.8	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	18.22	18.18	18.15	19.8	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	18.17	18.13	18.13	19.8	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	18.17	18.22	18.19	19.8	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	18.16	18.17	18.17	19.8	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	18.11	18.20	18.18	19.8	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	18.14	18.22	18.12	19.8	0.0	
Channel				630500	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	18.17	18.19	18.14	19.8	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	18.18	18.15	18.19	19.8	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	18.16	18.20	18.17	19.8	0.0	

Part27Q n78 PC2 Ant6 DSI3									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		21.24				
100	1/2 BPS	1	137		21.12		22.8	0.0	
100	1/2 BPS	1	271		21.31				
100	1/2 BPS	135	0		21.22		22.8	0.0	
100	1/2 BPS	135	69		21.23		22.8	0.0	
100	1/2 BPS	135	138		21.25				
100	1/2 BPS	270	0		21.18		22.8	0.0	
100	QPSK	1	1		21.32				
100	QPSK	1	137		21.19		22.8	0.0	
100	QPSK	1	271		21.22				
100	QPSK	135	0		21.20		22.8	0.0	
100	QPSK	135	69		21.29		22.8	0.0	
100	QPSK	135	138		21.28				
100	QPSK	270	0		21.27		22.8	0.0	
100	16QAM	1	1		21.31		22.8	0.0	
100	64QAM	1	1		21.23		22.8	0.0	
100	256QAM	1	1		21.20		22.8	0.0	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	21.15	21.16	21.15	22.8	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	21.13	21.08	21.19	22.8	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	21.19	21.10	21.09	22.8	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	21.12	21.14	21.16	22.8	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	21.18	21.19	21.13	22.8	0.0	
Channel				631334	633334	633334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	21.13	21.17	21.11	22.8	0.0	
Channel				631000	633334	633000	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	21.17	21.16	21.09	22.8	0.0	
Channel				630834	633334	633834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	21.12	21.19	21.14	22.8	0.0	
Channel				630668	633334	633668	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	21.11	21.11	21.11	22.8	0.0	
Channel				630500	633334	633668	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	21.16	21.12	21.12	22.8	0.0	
Channel				630334	633334	633334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	21.18	21.11	21.18	22.8	0.0	

n7 Ant7 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	19.70	19.81	19.68			
50	1/2 BPSK	1	135	19.74	19.75	19.70	20.8	0.0	
50	1/2 BPSK	1	268	19.70	19.75	19.71			
50	1/2 BPSK	135	0	19.65	19.75	19.75	20.8	0.0	
50	1/2 BPSK	135	68	19.70	19.73	19.71	20.8	0.0	
50	1/2 BPSK	135	135	19.64	19.71	19.76	20.8	0.0	
50	1/2 BPSK	270	0	19.69	19.79	19.66			
50	QPSK	1	1	19.64	19.85	19.73			
50	QPSK	1	135	19.67	19.78	19.67	20.8	0.0	
50	QPSK	1	268	19.70	19.78	19.75			
50	QPSK	135	0	19.69	19.70	19.74	20.8	0.0	
50	QPSK	135	68	19.71	19.79	19.69	20.8	0.0	
50	QPSK	135	135	19.65	19.70	19.72	20.8	0.0	
50	QPSK	270	0	19.66	19.76	19.73			
50	16QAM	1	1	19.64	19.74	19.66	20.8	0.0	
50	64QAM	1	1	19.70	19.76	19.75	20.8	0.0	
50	256QAM	1	1	18.14	18.19	18.27	19.3	1.5	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	19.56	19.62	19.58	20.8	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	19.51	19.55	19.68	20.8	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	19.59	19.55	19.69	20.8	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	19.55	19.65	19.59	20.8	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	19.57	19.60	19.63	20.8	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	19.48	19.64	19.68	20.8	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	19.58	19.65	19.62	20.8	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	19.55	19.62	19.62	20.8	0.0	

n66 Ant7 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	19.50	19.58	19.53			
45	1/2 BPSK	1	120	19.52	19.63	19.50	20.7	0.0	
45	1/2 BPSK	1	240	19.47	19.56	19.60			
45	1/2 BPSK	120	0	19.47	19.64	19.54	20.7	0.0	
45	1/2 BPSK	120	60	19.57	19.56	19.51	20.7	0.0	
45	1/2 BPSK	120	120	19.49	19.54	19.56	20.7	0.0	
45	1/2 BPSK	240	0	19.53	19.54	19.51			
45	QPSK	1	1	19.51	19.65	19.50			
45	QPSK	1	120	19.55	19.61	19.61	20.7	0.0	
45	QPSK	1	240	19.47	19.55	19.56			
45	QPSK	120	0	19.56	19.54	19.53	20.7	0.0	
45	QPSK	120	60	19.48	19.61	19.56	20.7	0.0	
45	QPSK	120	120	19.51	19.60	19.57	20.7	0.0	
45	QPSK	240	0	19.55	19.62	19.59			
45	16QAM	1	1	19.56	19.53	19.59	20.7	0.0	
45	64QAM	1	1	19.48	19.54	19.56	20.7	0.0	
45	256QAM	1	1	17.46	17.66	17.54	18.7	2.0	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	19.35	19.51	19.44	20.7	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	19.39	19.53	19.41	20.7	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	19.42	19.44	19.41	20.7	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	19.36	19.56	19.39	20.7	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	19.36	19.44	19.38	20.7	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	19.44	19.53	19.37	20.7	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	19.45	19.45	19.44	20.7	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	19.37	19.52	19.38	20.7	0.0	

n38 Ant7 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	19.75	19.77	19.73			
40	1/2 BPSK	1	53	19.74	19.74	19.74	20.6	0.0	
40	1/2 BPSK	1	104	19.79	19.81	19.82			
40	1/2 BPSK	50	0	19.70	19.82	19.77	20.6	0.0	
40	1/2 BPSK	50	28	19.78	19.81	19.73	20.6	0.0	
40	1/2 BPSK	50	56	19.66	19.72	19.78			
40	1/2 BPSK	100	0	19.66	19.80	19.82	20.6	0.0	
40	QPSK	1	1	19.75	19.83	19.79			
40	QPSK	1	53	19.72	19.74	19.73	20.6	0.0	
40	QPSK	1	104	19.66	19.74	19.68			
40	QPSK	50	0	19.74	19.81	19.76	20.6	0.0	
40	QPSK	50	28	19.76	19.83	19.76	20.6	0.0	
40	QPSK	50	56	19.78	19.76	19.79			
40	QPSK	100	0	19.70	19.80	19.75	20.6	0.0	
40	16QAM	1	1	19.79	19.81	19.76	20.6	0.0	
40	64QAM	1	1	19.77	19.80	19.80	20.6	0.0	
40	256QAM	1	1	17.74	17.71	17.76	19.1	1.5	
Channel				517002	519000	520998	tune-up limit	MPR (dB)	
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	19.24	19.35	19.28	20.6	0.0	
Channel				516504	519000	521496	tune-up limit	MPR (dB)	
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	19.23	19.30	19.30	20.6	0.0	
Channel				516000	519000	522000	tune-up limit	MPR (dB)	
Frequency (MHz)				2560	2595	2610			
20	QPSK	1	1	19.24	19.35	19.31	20.6	0.0	
Channel				515502	519000	522498	tune-up limit	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	19.24	19.35	19.32	20.6	0.0	
Channel				515004	519000	522996	tune-up limit	MPR (dB)	
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	19.24	19.31	19.28	20.6	0.0	

n41 Ant7 DSI3									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	19.22	19.32	19.22			
100	1/2 BPSK	1	137	19.17	19.32	19.22	20.2	0.0	
100	1/2 BPSK	1	271	19.13	19.35	19.17			
100	1/2 BPSK	135	0	19.17	19.24	19.25	20.2	0.0	
100	1/2 BPSK	135	69	19.20	19.33	19.22	20.2	0.0	
100	1/2 BPSK	135	138	19.19	19.34	19.19			
100	1/2 BPSK	270	0	19.16	19.29	19.17	20.2	0.0	
100	QPSK	1	1	19.22	19.36	19.16			
100	QPSK	1	137	19.18	19.27	19.22	20.2	0.0	
100	QPSK	1	271	19.13	19.32	19.16			
100	QPSK	135	0	19.16	19.32	19.19	20.2	0.0	
100	QPSK	135	69	19.15	19.33	19.25	20.2	0.0	
100	QPSK	135	138	19.16	19.24	19.26			
100	QPSK	270	0	19.17	19.28	19.27	20.2	0.0	
100	16QAM	1	1	19.23	19.28	19.18	20.2	0.0	
100	64QAM	1	1	19.17	19.30	19.28	20.2	0.0	
100	256QAM	1	1	18.27	18.35	18.21	19.2	1.0	
Channel				508200	518598	528996	tune-up limit	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	19.11	19.24	19.04	20.2	0.0	
Channel				507204	518598	529998	tune-up limit	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	19.10	19.23	19.11	20.2	0.0	
Channel				506202	518598	531000	tune-up limit	MPR (dB)	
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	19.11	19.24	19.06	20.2	0.0	
Channel				505200	518598	531996	tune-up limit	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	19.08	19.19	19.08	20.2	0.0	
Channel				504204	518598	532998	tune-up limit	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	19.08	19.28	19.06	20.2	0.0	
Channel				503700	518598	533496	tune-up limit	MPR (dB)	
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	19.17	19.19	19.06	20.2	0.0	
Channel				503202	518598	534000	tune-up limit	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	19.06	19.25	19.01	20.2	0.0	
Channel				502704	518598	534498	tune-up limit	MPR (dB)	
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	19.18	19.26	19.06	20.2	0.0	
Channel				502200	518598	534996	tune-up limit	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	19.11	19.30	19.01	20.2	0.0	
Channel				501702	518598	535500	tune-up limit	MPR (dB)	
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	19.06	19.19	19.09	20.2	0.0	
Channel				501204	518598	535998	tune-up limit	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	19.07	19.21	19.08	20.2	0.0	
Channel				500700	518598	536496	tune-up limit	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	19.18	19.27	19.03	20.2	0.0	
Channel				500202	518598	537000	tune-up limit	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	19.06	19.28	19.01	20.2	0.0	

Reduced Power Mode for DSI4_Other PA

n7 Ant5 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	21.74	21.71	21.60			
50	1/2 BPSK	1	135	21.71	21.72	21.62	22.5	0.0	
50	1/2 BPSK	1	268	21.64	21.74	21.58			
50	1/2 BPSK	135	0	21.33	21.26	21.24	22.0	0.5	
50	1/2 BPSK	135	68	21.74	21.71	21.57	22.5	0.0	
50	1/2 BPSK	135	135	21.31	21.36	21.20	22.0	0.5	
50	1/2 BPSK	270	0	21.32	21.31	21.15			
50	QPSK	1	1	21.77	21.82	21.70			
50	QPSK	1	135	21.66	21.70	21.57	22.5	0.0	
50	QPSK	1	268	21.74	21.67	21.65			
50	QPSK	135	0	20.71	20.78	20.73	21.5	1.0	
50	QPSK	135	68	21.69	21.76	21.57	22.5	0.0	
50	QPSK	135	135	20.77	20.80	20.74	21.5	1.0	
50	QPSK	270	0	20.78	20.81	20.64			
50	16QAM	1	1	20.77	20.79	20.76	21.5	1.0	
50	64QAM	1	1	19.26	19.27	19.20	20.0	2.5	
50	256QAM	1	1	17.24	17.35	17.20	18.0	4.5	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	21.64	21.69	21.59	22.5	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	21.68	21.71	21.67	22.5	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	21.69	21.75	21.60	22.5	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	21.67	21.66	21.67	22.5	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	21.69	21.68	21.66	22.5	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	21.72	21.75	21.56	22.5	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	21.66	21.75	21.67	22.5	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	21.73	21.72	21.58	22.5	0.0	

n66 Ant5 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	21.73	21.68	21.65			
45	1/2 BPSK	1	120	21.76	21.72	21.72	22.8	0.0	
45	1/2 BPSK	1	240	21.71	21.68	21.70			
45	1/2 BPSK	120	0	21.28	21.37	21.23	22.3	0.5	
45	1/2 BPSK	120	60	21.74	21.75	21.74	22.8	0.0	
45	1/2 BPSK	120	120	21.29	21.34	21.26	22.3	0.5	
45	1/2 BPSK	240	0	21.28	21.32	21.24			
45	QPSK	1	1	21.79	21.82	21.76			
45	QPSK	1	120	21.69	21.75	21.72	22.8	0.0	
45	QPSK	1	240	21.66	21.72	21.70			
45	QPSK	120	0	20.77	20.84	20.71	21.8	1.0	
45	QPSK	120	60	21.75	21.76	21.74	22.8	0.0	
45	QPSK	120	120	20.80	20.79	20.72	21.8	1.0	
45	QPSK	240	0	20.76	20.87	20.73			
45	16QAM	1	1	20.81	20.78	20.75	21.8	1.0	
45	64QAM	1	1	19.30	19.37	19.25	20.3	2.5	
45	256QAM	1	1	17.25	17.37	17.31	18.3	4.5	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	21.72	21.71	21.64	22.8	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	21.76	21.79	21.69	22.8	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	21.67	21.72	21.70	22.8	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	21.69	21.78	21.67	22.8	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	21.73	21.77	21.70	22.8	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	21.76	21.71	21.65	22.8	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	21.69	21.77	21.73	22.8	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	21.71	21.71	21.64	22.8	0.0	

Part27Q n78 Ant5 DSI4									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334		3500.01			
Frequency (MHz)						21.35			
100	1/2 BPSK	1	1			21.35			
100	1/2 BPSK	1	137			21.49		23.0	0.0
100	1/2 BPSK	1	271			21.44			
100	1/2 BPSK	135	0			21.48		23.0	0.0
100	1/2 BPSK	135	69			21.42		23.0	0.0
100	1/2 BPSK	135	138			21.45			
100	1/2 BPSK	270	0			21.43		23.0	0.0
100	QPSK	1	1			21.54			
100	QPSK	1	137			21.53		23.0	0.0
100	QPSK	1	271			21.46			
100	QPSK	135	0			21.44		23.0	0.0
100	QPSK	135	69			21.52		23.0	0.0
100	QPSK	135	138			21.47			
100	QPSK	270	0			21.39		23.0	0.0
100	16QAM	1	1			21.40		23.0	0.0
100	64QAM	1	1			20.87		22.5	0.5
100	256QAM	1	1			18.53		20.5	2.5
Channel				633000	633334	633668	up	MPR (dB)	
Frequency (MHz)				3498	3500.01	3505.02			
90	QPSK	1	1	21.44	21.37	21.45	23.0	0.0	
Channel				632668	633334	634000	up	MPR (dB)	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	21.40	21.30	21.34	23.0	0.0	
Channel				632334	633334	634334	up	MPR (dB)	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	21.44	21.44	21.33	23.0	0.0	
Channel				632000	633334	634668	up	MPR (dB)	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	21.35	21.41	21.34	23.0	0.0	
Channel				631668	633334	635000	up	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	21.38	21.40	21.41	23.0	0.0	
Channel				631334	633334	635334	up	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	21.34	21.40	21.33	23.0	0.0	
Channel				631000	633334	635668	up	MPR (dB)	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	21.35	21.37	21.45	23.0	0.0	
Channel				630834	633334	635884	up	MPR (dB)	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	21.42	21.39	21.44	23.0	0.0	
Channel				630668	633334	636000	up	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	21.44	21.40	21.35	23.0	0.0	
Channel				630500	633334	636168	up	MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	21.39	21.34	21.34	23.0	0.0	
Channel				630334	633334	636334	up	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	21.43	21.39	21.35	23.0	0.0	

Part27Q n78 PC2 Ant5 DSI4									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334		3500.01			
Frequency (MHz)						24.54			
100	1/2 BPSK	1	1			24.54			
100	1/2 BPSK	1	137			24.59		26.0	0.0
100	1/2 BPSK	1	271			24.52			
100	1/2 BPSK	135	0			24.63		26.0	0.0
100	1/2 BPSK	135	69			24.46		26.0	0.0
100	1/2 BPSK	135	138			24.53			
100	1/2 BPSK	270	0			24.59		26.0	0.0
100	QPSK	1	1			24.66			
100	QPSK	1	137			24.60		26.0	0.0
100	QPSK	1	271			24.63			
100	QPSK	135	0			24.58		26.0	0.0
100	QPSK	135	69			24.60		26.0	0.0
100	QPSK	135	138			24.53			
100	QPSK	270	0			24.51		26.0	0.0
100	16QAM	1	1			24.48		26.0	0.0
100	64QAM	1	1			23.97		24.5	1.5
100	256QAM	1	1			21.56		22.0	4.0
Channel				633000	633334	633668	up	MPR (dB)	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	24.58	24.53	24.59	26.0	0.0	
Channel				632668	633334	634000	up	MPR (dB)	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	24.59	24.61	24.53	26.0	0.0	
Channel				632334	633334	634334	up	MPR (dB)	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	24.57	24.52	24.60	26.0	0.0	
Channel				632000	633334	634668	up	MPR (dB)	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	24.54	24.57	24.51	26.0	0.0	
Channel				631668	633334	635000	up	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	24.59	24.62	24.57	26.0	0.0	
Channel				631334	633334	635334	up	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	24.61	24.61	24.52	26.0	0.0	
Channel				631000	633334	635668	up	MPR (dB)	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	24.54	24.57	24.58	26.0	0.0	
Channel				630834	633334	635884	up	MPR (dB)	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	24.51	24.62	24.51	26.0	0.0	
Channel				630668	633334	636000	up	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	24.56	24.60	24.61	26.0	0.0	
Channel				630500	633334	636168	up	MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	24.61	24.61	24.52	26.0	0.0	
Channel				630334	633334	636334	up	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	24.57	24.60	24.58	26.0	0.0	

n7 Ant4 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	18.97	19.03	18.97			
50	1/2 BPSK	1	135	19.05	19.10	19.02	20.2	0.0	
50	1/2 BPSK	1	268	18.96	19.05	19.01			
50	1/2 BPSK	135	0	19.07	19.10	19.03	20.2	0.0	
50	1/2 BPSK	135	68	19.06	19.03	19.05	20.2	0.0	
50	1/2 BPSK	135	135	18.96	19.04	19.02	20.2	0.0	
50	1/2 BPSK	270	0	19.00	19.11	19.03			
50	QPSK	1	1	19.02	19.12	19.00			
50	QPSK	1	135	19.07	19.06	19.07	20.2	0.0	
50	QPSK	1	268	18.99	19.11	18.98			
50	QPSK	135	0	19.01	19.04	19.00	20.2	0.0	
50	QPSK	135	68	19.03	19.10	18.98	20.2	0.0	
50	QPSK	135	135	19.05	19.09	19.01			
50	QPSK	270	0	19.03	19.07	19.06	20.2	0.0	
50	16QAM	1	1	18.95	19.04	19.03	20.2	0.0	
50	64QAM	1	1	19.05	19.06	18.96	20.2	0.0	
50	256QAM	1	1	18.99	19.09	19.00	20.2	0.0	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	18.96	18.97	18.89	20.2	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	18.86	19.02	18.95	20.2	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	18.97	19.03	18.90	20.2	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	18.87	18.96	18.89	20.2	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	18.94	19.02	18.89	20.2	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	18.93	18.96	18.90	20.2	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	18.87	19.04	18.87	20.2	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	18.88	19.05	18.89	20.2	0.0	

n66 Ant4 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	21.21	21.34	21.09			
45	1/2 BPSK	1	120	21.17	21.25	21.16	21.8	0.0	
45	1/2 BPSK	1	240	21.21	21.35	21.12			
45	1/2 BPSK	120	0	21.17	21.24	21.13	21.8	0.0	
45	1/2 BPSK	120	60	21.24	21.34	21.16	21.8	0.0	
45	1/2 BPSK	120	120	21.22	21.24	21.18	21.8	0.0	
45	1/2 BPSK	240	0	21.22	21.34	21.14			
45	QPSK	1	1	21.19	21.36	21.12			
45	QPSK	1	120	21.16	21.31	21.10	21.8	0.0	
45	QPSK	1	240	21.14	21.30	21.13			
45	QPSK	120	0	21.21	21.31	21.15	21.8	0.0	
45	QPSK	120	60	21.23	21.33	21.09	21.8	0.0	
45	QPSK	120	120	21.13	21.31	21.18	21.8	0.0	
45	QPSK	240	0	21.17	21.26	21.20			
45	16QAM	1	1	21.18	21.26	21.14	21.8	0.0	
45	64QAM	1	1	21.10	21.21	21.00	21.8	0.0	
45	256QAM	1	1	20.73	20.83	20.58	21.3	0.5	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	21.11	21.17	21.07	21.8	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	21.08	21.15	20.98	21.8	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	21.12	21.16	21.05	21.8	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	21.14	21.14	21.01	21.8	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	21.05	21.24	21.06	21.8	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	21.09	21.16	21.02	21.8	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	21.11	21.19	20.99	21.8	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	21.04	21.14	21.03	21.8	0.0	

n7 Ant6 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	25.17	25.22	25.18	25.5	0.0	
50	1/2 BPSK	1	135	25.17	25.17	25.19			
50	1/2 BPSK	1	268	25.14	25.15	25.20			
50	1/2 BPSK	135	0	24.70	24.80	24.71	25.0	0.5	
50	1/2 BPSK	135	68	25.10	25.21	25.13	25.5	0.0	
50	1/2 BPSK	135	135	24.70	24.81	24.78			
50	1/2 BPSK	270	0	24.75	24.76	24.71	25.0	0.5	
50	QPSK	1	1	25.23	25.25	25.22			
50	QPSK	1	135	25.13	25.11	25.20	25.5	0.0	
50	QPSK	1	268	25.19	25.13	25.15			
50	QPSK	135	0	24.19	24.26	24.25	24.5	1.0	
50	QPSK	135	68	25.14	25.20	25.12	25.5	0.0	
50	QPSK	135	135	24.21	24.25	24.20			
50	QPSK	270	0	24.26	24.27	24.20	24.5	1.0	
50	16QAM	1	1	24.27	24.24	24.28	24.5	1.0	
50	64QAM	1	1	22.77	22.71	22.68	23.0	2.5	
50	256QAM	1	1	20.70	20.76	20.77	21.0	4.5	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	25.10	25.15	25.15	25.5	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	25.13	25.19	25.13	25.5	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	25.16	25.21	25.12	25.5	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	25.17	25.22	25.09	25.5	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	25.12	25.20	25.18	25.5	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	25.15	25.21	25.18	25.5	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	25.19	25.13	25.18	25.5	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	25.16	25.15	25.19	25.5	0.0	

n66 Ant6 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	24.87	24.96	24.84			
45	1/2 BPSK	1	120	24.89	24.92	24.87	25.5	0.0	
45	1/2 BPSK	1	240	24.88	24.94	24.96			
45	1/2 BPSK	120	0	24.41	24.46	24.46	25.0	0.5	
45	1/2 BPSK	120	60	24.89	24.90	24.90	25.5	0.0	
45	1/2 BPSK	120	120	24.48	24.50	24.45	25.0	0.5	
45	1/2 BPSK	240	0	24.44	24.47	24.53			
45	QPSK	1	1	24.93	25.01	24.98			
45	QPSK	1	120	24.88	24.95	24.88	25.5	0.0	
45	QPSK	1	240	24.81	24.96	24.94			
45	QPSK	120	0	23.87	23.97	24.02	24.5	1.0	
45	QPSK	120	60	24.82	24.97	24.90	25.5	0.0	
45	QPSK	120	120	23.92	24.01	23.96			
45	QPSK	240	0	23.90	24.04	24.01	24.5	1.0	
45	16QAM	1	1	23.95	23.99	23.93	24.5	1.0	
45	64QAM	1	1	22.41	22.50	22.54	23.0	2.5	
45	256QAM	1	1	20.40	20.51	20.52	21.0	4.5	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	24.80	24.96	24.85	25.5	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	24.80	24.91	24.95	25.5	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	24.88	24.95	24.94	25.5	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	24.84	24.95	24.86	25.5	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	24.80	24.90	24.89	25.5	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	24.87	24.89	24.90	25.5	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	24.85	24.93	24.93	25.5	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	24.89	24.98	24.87	25.5	0.0	

n7 Ant7 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	19.70	19.81	19.68			
50	1/2 BPSK	1	135	19.74	19.75	19.70	20.8	0.0	
50	1/2 BPSK	1	268	19.70	19.75	19.71			
50	1/2 BPSK	135	0	19.65	19.75	19.75	20.8	0.0	
50	1/2 BPSK	135	68	19.70	19.73	19.71	20.8	0.0	
50	1/2 BPSK	135	135	19.64	19.71	19.76	20.8	0.0	
50	1/2 BPSK	270	0	19.69	19.79	19.66			
50	QPSK	1	1	19.64	19.85	19.73			
50	QPSK	1	135	19.67	19.78	19.67	20.8	0.0	
50	QPSK	1	268	19.70	19.78	19.75			
50	QPSK	135	0	19.69	19.70	19.74	20.8	0.0	
50	QPSK	135	68	19.71	19.79	19.69	20.8	0.0	
50	QPSK	135	135	19.65	19.70	19.72	20.8	0.0	
50	QPSK	270	0	19.66	19.76	19.73			
50	16QAM	1	1	19.64	19.74	19.66	20.8	0.0	
50	64QAM	1	1	19.70	19.76	19.75	20.8	0.0	
50	256QAM	1	1	18.14	18.19	18.27	19.3	1.5	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	19.56	19.62	19.58	20.8	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	19.51	19.55	19.68	20.8	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	19.59	19.55	19.69	20.8	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	19.55	19.65	19.59	20.8	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	19.57	19.60	19.63	20.8	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	19.48	19.64	19.68	20.8	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	19.58	19.65	19.62	20.8	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	19.55	19.62	19.62	20.8	0.0	

n66 Ant7 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	21.89	21.91	21.85			
45	1/2 BPSK	1	120	21.98	22.00	21.84	23.2	0.0	
45	1/2 BPSK	1	240	21.86	21.85	21.77			
45	1/2 BPSK	120	0	21.51	21.41	21.47	22.7	0.5	
45	1/2 BPSK	120	60	21.96	21.92	21.76	23.2	0.0	
45	1/2 BPSK	120	120	21.44	21.57	21.38	22.7	0.5	
45	1/2 BPSK	240	0	21.52	21.52	21.26			
45	QPSK	1	1	22.02	22.08	22.05			
45	QPSK	1	120	21.80	21.87	21.77	23.2	0.0	
45	QPSK	1	240	22.04	21.86	21.85			
45	QPSK	120	0	20.91	20.97	20.94	22.2	1.0	
45	QPSK	120	60	21.83	21.98	21.68	23.2	0.0	
45	QPSK	120	120	20.99	21.00	20.91	22.2	1.0	
45	QPSK	240	0	20.91	20.97	20.77			
45	16QAM	1	1	20.94	20.98	20.96	22.2	1.0	
45	64QAM	1	1	19.55	19.55	19.42	20.7	2.5	
45	256QAM	1	1	17.49	17.44	17.43	18.7	4.5	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	21.93	22.00	21.98	23.2	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	21.93	21.98	22.00	23.2	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	21.92	21.99	21.98	23.2	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	21.88	21.95	21.93	23.2	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	21.96	22.03	21.95	23.2	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	21.93	21.98	21.99	23.2	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	21.93	22.01	21.98	23.2	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	21.95	21.97	21.93	23.2	0.0	

n38 Ant7 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	19.75	19.77	19.73			
40	1/2 BPSK	1	53	19.74	19.74	19.74	20.6	0.0	
40	1/2 BPSK	1	104	19.79	19.81	19.82			
40	1/2 BPSK	50	0	19.70	19.82	19.77	20.6	0.0	
40	1/2 BPSK	50	28	19.78	19.81	19.73	20.6	0.0	
40	1/2 BPSK	50	56	19.66	19.72	19.78			
40	1/2 BPSK	100	0	19.66	19.80	19.82	20.6	0.0	
40	QPSK	1	1	19.75	19.83	19.79			
40	QPSK	1	53	19.72	19.74	19.73	20.6	0.0	
40	QPSK	1	104	19.66	19.74	19.68			
40	QPSK	50	0	19.74	19.81	19.76	20.6	0.0	
40	QPSK	50	28	19.76	19.83	19.76	20.6	0.0	
40	QPSK	50	56	19.78	19.76	19.79			
40	QPSK	100	0	19.70	19.80	19.75	20.6	0.0	
40	16QAM	1	1	19.79	19.81	19.76	20.6	0.0	
40	64QAM	1	1	19.77	19.80	19.80	20.6	0.0	
40	256QAM	1	1	17.74	17.71	17.76	19.1	1.5	
Channel				517002	519000	520998	tune-up limit	MPR (dB)	
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	19.24	19.35	19.28	20.6	0.0	
Channel				516504	519000	521496	tune-up limit	MPR (dB)	
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	19.23	19.30	19.30	20.6	0.0	
Channel				516000	519000	522000	tune-up limit	MPR (dB)	
Frequency (MHz)				2560	2595	2610			
20	QPSK	1	1	19.24	19.35	19.31	20.6	0.0	
Channel				515502	519000	522498	tune-up limit	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	19.24	19.35	19.32	20.6	0.0	
Channel				515004	519000	522996	tune-up limit	MPR (dB)	
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	19.24	19.31	19.28	20.6	0.0	

n41 Ant7 DSI4									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	19.22	19.32	19.22			
100	1/2 BPSK	1	137	19.17	19.32	19.22	20.2	0.0	
100	1/2 BPSK	1	271	19.13	19.35	19.17			
100	1/2 BPSK	135	0	19.17	19.24	19.25	20.2	0.0	
100	1/2 BPSK	135	69	19.20	19.33	19.22	20.2	0.0	
100	1/2 BPSK	135	138	19.19	19.34	19.19			
100	1/2 BPSK	270	0	19.16	19.29	19.17	20.2	0.0	
100	QPSK	1	1	19.22	19.36	19.16			
100	QPSK	1	137	19.18	19.27	19.22	20.2	0.0	
100	QPSK	1	271	19.13	19.32	19.16			
100	QPSK	135	0	19.16	19.32	19.19	20.2	0.0	
100	QPSK	135	69	19.15	19.33	19.25	20.2	0.0	
100	QPSK	135	138	19.16	19.24	19.26			
100	QPSK	270	0	19.17	19.28	19.27	20.2	0.0	
100	16QAM	1	1	19.23	19.28	19.18	20.2	0.0	
100	64QAM	1	1	19.17	19.30	19.28	20.2	0.0	
100	256QAM	1	1	18.27	18.35	18.21	19.2	1.0	
Channel				508200	518598	528996	tune-up limit	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	19.11	19.24	19.04	20.2	0.0	
Channel				507204	518598	529998	tune-up limit	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	19.10	19.23	19.11	20.2	0.0	
Channel				506202	518598	531000	tune-up limit	MPR (dB)	
Frequency (MHz)				2531.01	2592.99	2635			
70	QPSK	1	1	19.11	19.24	19.06	20.2	0.0	
Channel				505200	518598	531996	tune-up limit	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	19.08	19.19	19.08	20.2	0.0	
Channel				504204	518598	532998	tune-up limit	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	19.08	19.28	19.06	20.2	0.0	
Channel				503700	518598	533496	tune-up limit	MPR (dB)	
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	19.17	19.19	19.06	20.2	0.0	
Channel				503202	518598	534000	tune-up limit	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	19.06	19.25	19.01	20.2	0.0	
Channel				502704	518598	534498	tune-up limit	MPR (dB)	
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	19.18	19.26	19.06	20.2	0.0	
Channel				502200	518598	534996	tune-up limit	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	19.11	19.30	19.01	20.2	0.0	
Channel				501702	518598	535500	tune-up limit	MPR (dB)	
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	19.06	19.19	19.09	20.2	0.0	
Channel				501204	518598	535998	tune-up limit	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	19.07	19.21	19.08	20.2	0.0	
Channel				500700	518598	536496	tune-up limit	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	19.18	19.27	19.03	20.2	0.0	
Channel				500202	518598	537000	tune-up limit	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	19.06	19.28	19.01	20.2	0.0	

Reduced Power Mode for DSI5_Other PA

n7 Ant5 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	14.33	14.27	14.18			
50	1/2 BPSK	1	135	14.22	14.31	14.14	15.0	0.0	
50	1/2 BPSK	1	268	14.26	14.29	14.25			
50	1/2 BPSK	135	0	14.28	14.37	14.22	15.0	0.0	
50	1/2 BPSK	135	68	14.27	14.33	14.22	15.0	0.0	
50	1/2 BPSK	135	135	14.33	14.27	14.23			
50	1/2 BPSK	270	0	14.29	14.33	14.25	15.0	0.0	
50	QPSK	1	1	14.26	14.41	14.22			
50	QPSK	1	135	14.30	14.27	14.24	15.0	0.0	
50	QPSK	1	268	14.21	14.37	14.16			
50	QPSK	135	0	14.33	14.37	14.21	15.0	0.0	
50	QPSK	135	68	14.30	14.39	14.15	15.0	0.0	
50	QPSK	135	135	14.24	14.34	14.25	15.0	0.0	
50	QPSK	270	0	14.23	14.30	14.21			
50	16QAM	1	1	14.29	14.26	14.22	15.0	0.0	
50	64QAM	1	1	14.22	14.27	14.18	15.0	0.0	
50	256QAM	1	1	14.31	14.32	14.18	15.0	0.0	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	14.14	14.23	14.11	15.0	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	14.15	14.31	14.10	15.0	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	14.17	14.29	14.12	15.0	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	14.16	14.27	14.10	15.0	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	14.15	14.24	14.12	15.0	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	14.15	14.25	14.07	15.0	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	14.20	14.27	14.18	15.0	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	14.20	14.21	14.07	15.0	0.0	

n66 Ant5 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	14.84	14.82	14.74			
45	1/2 BPSK	1	120	14.83	14.87	14.74	15.8	0.0	
45	1/2 BPSK	1	240	14.80	14.86	14.77			
45	1/2 BPSK	120	0	14.80	14.76	14.72	15.8	0.0	
45	1/2 BPSK	120	60	14.74	14.79	14.76	15.8	0.0	
45	1/2 BPSK	120	120	14.81	14.78	14.78			
45	1/2 BPSK	240	0	14.80	14.77	14.79	15.8	0.0	
45	QPSK	1	1	14.77	14.89	14.71			
45	QPSK	1	120	14.76	14.87	14.74	15.8	0.0	
45	QPSK	1	240	14.83	14.80	14.76			
45	QPSK	120	0	14.81	14.86	14.72	15.8	0.0	
45	QPSK	120	60	14.81	14.87	14.75	15.8	0.0	
45	QPSK	120	120	14.80	14.86	14.71	15.8	0.0	
45	QPSK	240	0	14.82	14.83	14.71			
45	16QAM	1	1	14.84	14.84	14.82	15.8	0.0	
45	64QAM	1	1	14.79	14.83	14.80	15.8	0.0	
45	256QAM	1	1	14.83	14.82	14.72	15.8	0.0	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	14.72	14.74	14.66	15.8	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	14.64	14.72	14.59	15.8	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	14.63	14.75	14.56	15.8	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	14.70	14.79	14.63	15.8	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	14.72	14.74	14.60	15.8	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	14.65	14.82	14.58	15.8	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	14.68	14.81	14.66	15.8	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	14.65	14.77	14.65	15.8	0.0	

Part27Q n78 Ant5 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334		3500.01			
Frequency (MHz)									
100	1/2 BPSK	1	1		13.98				
100	1/2 BPSK	1	137		13.94		15.5	0.0	
100	1/2 BPSK	1	271		14.01				
100	1/2 BPSK	135	0		14.01		15.5	0.0	
100	1/2 BPSK	135	69		13.95		15.5	0.0	
100	1/2 BPSK	135	138		13.94				
100	1/2 BPSK	270	0		13.99		15.5	0.0	
100	QPSK	1	1		14.05				
100	QPSK	1	137		14.04		15.5	0.0	
100	QPSK	1	271		13.96				
100	QPSK	135	0		14.09		15.5	0.0	
100	QPSK	135	69		14.01		15.5	0.0	
100	QPSK	135	138		13.98				
100	QPSK	270	0		13.93		15.5	0.0	
100	16QAM	1	1		13.95		15.5	0.0	
100	64QAM	1	1		13.94		15.5	0.0	
100	256QAM	1	1		13.95		15.5	0.0	
Channel				633000	633334	633668	tune-up	MPR (dB)	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	13.78	13.77	13.85	15.5	0.0	
Channel				632668	633334	634000	tune-up	MPR (dB)	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	13.87	13.77	13.75	15.5	0.0	
Channel				632334	633334	634334	tune-up	MPR (dB)	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	13.79	13.88	13.82	15.5	0.0	
Channel				632000	633334	634668	tune-up	MPR (dB)	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	13.85	13.75	13.77	15.5	0.0	
Channel				631668	633334	635000	tune-up	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	13.87	13.82	13.85	15.5	0.0	
Channel				631334	633334	635334	tune-up	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	13.88	13.82	13.84	15.5	0.0	
Channel				631000	633334	635668	tune-up	MPR (dB)	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	13.84	13.82	13.86	15.5	0.0	
Channel				630634	633334	635834	tune-up	MPR (dB)	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	13.79	13.77	13.80	15.5	0.0	
Channel				630268	633334	636000	tune-up	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	13.86	13.81	13.82	15.5	0.0	
Channel				630500	633334	636168	tune-up	MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	13.83	13.86	13.78	15.5	0.0	
Channel				630134	633334	636334	tune-up	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	13.84	13.86	13.78	15.5	0.0	

Part27Q n78 PC2 Ant5 DSI5									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334		3500.01			
Frequency (MHz)									
100	1/2 BPSK	1	1		16.96				
100	1/2 BPSK	1	137		16.90		18.5	0.0	
100	1/2 BPSK	1	271		16.97				
100	1/2 BPSK	135	0		17.00		18.5	0.0	
100	1/2 BPSK	135	69		16.99		18.5	0.0	
100	1/2 BPSK	135	138		16.99				
100	1/2 BPSK	270	0		17.04		18.5	0.0	
100	QPSK	1	1		17.09				
100	QPSK	1	137		17.07		18.5	0.0	
100	QPSK	1	271		16.92				
100	QPSK	135	0		17.03		18.5	0.0	
100	QPSK	135	69		17.06		18.5	0.0	
100	QPSK	135	138		16.93				
100	QPSK	270	0		16.99		18.5	0.0	
100	16QAM	1	1		16.98		18.5	0.0	
100	64QAM	1	1		16.99		18.5	0.0	
100	256QAM	1	1		16.94		18.5	0.0	
Channel				633000	633334	633668	tune-up	MPR (dB)	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	16.92	17.00	16.91	18.5	0.0	
Channel				632668	633334	634000	tune-up	MPR (dB)	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	17.02	16.98	16.98	18.5	0.0	
Channel				632334	633334	634334	tune-up	MPR (dB)	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	16.97	16.94	16.92	18.5	0.0	
Channel				632000	633334	634668	tune-up	MPR (dB)	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	16.99	16.99	16.91	18.5	0.0	
Channel				631668	633334	635000	tune-up	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	16.95	16.97	16.99	18.5	0.0	
Channel				631334	633334	635334	tune-up	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	17.00	16.94	16.92	18.5	0.0	
Channel				631000	633334	635668	tune-up	MPR (dB)	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	16.92	16.95	16.94	18.5	0.0	
Channel				630634	633334	635834	tune-up	MPR (dB)	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	17.02	17.01	16.98	18.5	0.0	
Channel				630268	633334	636000	tune-up	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	16.94	16.96	16.93	18.5	0.0	
Channel				630500	633334	636168	tune-up	MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	16.93	16.94	17.03	18.5	0.0	
Channel				630134	633334	636334	tune-up	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	17.02	17.02	16.98	18.5	0.0	

n7 Ant4 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	17.00	17.03	17.05		18.2	0.0
50	1/2 BPSK	1	135	17.03	17.10	17.03			
50	1/2 BPSK	1	268	16.97	17.03	17.01			
50	1/2 BPSK	135	0	17.06	17.13	16.97	18.2	0.0	
50	1/2 BPSK	135	68	17.05	17.09	17.00	18.2	0.0	
50	1/2 BPSK	135	135	17.03	17.06	17.01	18.2	0.0	
50	1/2 BPSK	270	0	17.00	17.06	17.06			
50	QPSK	1	1	16.97	17.15	16.98		18.2	0.0
50	QPSK	1	135	16.98	17.10	16.98			
50	QPSK	1	268	16.97	17.03	16.98			
50	QPSK	135	0	17.07	17.05	16.99	18.2	0.0	
50	QPSK	135	68	17.03	17.10	17.02	18.2	0.0	
50	QPSK	135	135	16.96	17.03	16.96			
50	QPSK	270	0	17.02	17.09	17.01	18.2	0.0	
50	16QAM	1	1	17.03	17.14	17.04	18.2	0.0	
50	64QAM	1	1	17.03	17.07	17.03	18.2	0.0	
50	256QAM	1	1	16.99	17.14	17.05	18.2	0.0	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	16.83	17.04	16.88	18.2	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	16.86	17.01	16.91	18.2	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	16.90	17.00	16.94	18.2	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	16.91	17.01	16.90	18.2	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	16.85	17.00	16.83	18.2	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	16.81	17.02	16.87	18.2	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	16.91	17.09	16.90	18.2	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	16.82	16.97	16.85	18.2	0.0	

n66 Ant4 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	16.21	16.17	16.15		16.8	0.0
45	1/2 BPSK	1	120	16.22	16.22	16.11			
45	1/2 BPSK	1	240	16.20	16.26	16.11			
45	1/2 BPSK	120	0	16.16	16.22	16.15	16.8	0.0	
45	1/2 BPSK	120	60	16.14	16.21	16.18	16.8	0.0	
45	1/2 BPSK	120	120	16.16	16.26	16.14	16.8	0.0	
45	1/2 BPSK	240	0	16.24	16.26	16.10			
45	QPSK	1	1	16.22	16.28	16.21		16.8	0.0
45	QPSK	1	120	16.24	16.22	16.19			
45	QPSK	1	240	16.19	16.17	16.21			
45	QPSK	120	0	16.14	16.19	16.10	16.8	0.0	
45	QPSK	120	60	16.18	16.25	16.13	16.8	0.0	
45	QPSK	120	120	16.15	16.24	16.22			
45	QPSK	240	0	16.21	16.24	16.20	16.8	0.0	
45	16QAM	1	1	16.21	16.26	16.18	16.8	0.0	
45	64QAM	1	1	16.21	16.26	16.18	16.8	0.0	
45	256QAM	1	1	16.17	16.25	16.10	16.8	0.0	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	16.14	16.13	16.16	16.8	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	16.11	16.06	16.16	16.8	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	16.08	16.06	16.09	16.8	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	16.16	16.06	16.06	16.8	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	16.07	16.08	16.11	16.8	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	16.18	16.03	16.13	16.8	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	16.13	16.10	16.08	16.8	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	16.18	16.09	16.14	16.8	0.0	

Part270 n77 PC2 Ant4 DSI5									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	22.87	22.81	22.86			
100	1/2 BPSK	1	137	22.85	22.90	22.82	23.0	0.0	
100	1/2 BPSK	1	271	22.80	22.89	22.76			
100	1/2 BPSK	135	0	22.84	22.84	22.76	23.0	0.0	
100	1/2 BPSK	135	69	22.87	22.85	22.77	23.0	0.0	
100	1/2 BPSK	135	138	22.79	22.88	22.85			
100	1/2 BPSK	270	0	22.77	22.85	22.80	23.0	0.0	
100	QPSK	1	1	22.75	22.95	22.87			
100	QPSK	1	137	22.81	22.92	22.79	23.0	0.0	
100	QPSK	1	271	22.73	22.93	22.82			
100	QPSK	135	0	22.77	22.87	22.96	23.0	0.0	
100	QPSK	135	69	22.72	22.92	22.78	23.0	0.0	
100	QPSK	135	138	22.81	22.83	22.79			
100	QPSK	270	0	22.72	22.91	22.83	23.0	0.0	
100	16QAM	1	1	22.77	22.84	22.77	23.0	0.0	
100	64QAM	1	1	22.79	22.82	22.75	23.0	0.0	
100	256QAM	1	1	22.81	22.90	22.76	23.0	0.0	
Channel				648668	650000	652334	MPR (dB)		
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	22.70	22.90	22.75	23.0	0.0	
Channel				649334	650000	652668	MPR (dB)		
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	22.66	22.86	22.73	23.0	0.0	
Channel				649200	650000	650500	MPR (dB)		
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	22.61	22.84	22.75	23.0	0.0	
Channel				648668	650000	653334	MPR (dB)		
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	22.68	22.80	22.77	23.0	0.0	
Channel				648334	650000	653668	MPR (dB)		
Frequency (MHz)				3725.01	3840	3965.02			
50	QPSK	1	1	22.67	22.79	22.75	23.0	0.0	
Channel				648000	650000	654000	MPR (dB)		
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	22.70	22.83	22.76	23.0	0.0	
Channel				647668	650000	654334	MPR (dB)		
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	22.60	22.81	22.73	23.0	0.0	
Channel				647500	650000	654500	MPR (dB)		
Frequency (MHz)				3712.5	3840	3967.5			
25	QPSK	1	1	22.65	22.81	22.76	23.0	0.0	
Channel				647334	650000	654668	MPR (dB)		
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	1	22.70	22.87	22.77	23.0	0.0	
Channel				647168	650000	654834	MPR (dB)		
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	22.70	22.84	22.72	23.0	0.0	
Channel				647000	650000	655000	MPR (dB)		
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	22.71	22.87	22.76	23.0	0.0	

Part27Q n77 Ant4 DSI5									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3500.01	3533.34	3566.68			
100	1/2 BPSK	1	1	19.05					
100	1/2 BPSK	1	137	19.03			19.5	0.0	
100	1/2 BPSK	1	271	19.04					
100	1/2 BPSK	135	0	18.98			19.5	0.0	
100	1/2 BPSK	135	69	18.95			19.5	0.0	
100	1/2 BPSK	135	138	19.06					
100	1/2 BPSK	270	0	19.03			19.5	0.0	
100	QPSK	1	1	19.07					
100	QPSK	1	137	19.05			19.5	0.0	
100	QPSK	1	271	18.99					
100	QPSK	135	0	19.00			19.5	0.0	
100	QPSK	135	69	19.01			19.5	0.0	
100	QPSK	135	138	18.97					
100	QPSK	270	0	19.00			19.5	0.0	
100	16QAM	1	1	19.05			19.5	0.0	
100	64QAM	1	1	18.94			19.5	0.0	
100	256QAM	1	1	19.05			19.5	0.0	
Channel				633000	633334	633668	MPR (dB)		
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	18.98	18.89	18.91	19.5	0.0	
Channel				632668	633334	634000	MPR (dB)		
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	18.94	18.80	18.65	19.5	0.0	
Channel				632334	633334	634334	MPR (dB)		
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	18.89	18.98	18.97	19.5	0.0	
Channel				632000	633334	634668	MPR (dB)		
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	18.99	18.96	18.94	19.5	0.0	
Channel				631668	633334	635000	MPR (dB)		
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	18.92	18.91	18.96	19.5	0.0	
Channel				631334	633334	635334	MPR (dB)		
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	18.96	18.90	18.97	19.5	0.0	
Channel				631000	633334	635668	MPR (dB)		
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	18.96	18.91	18.95	19.5	0.0	
Channel				630834	633334	635834	MPR (dB)		
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	18.94	18.96	18.92	19.5	0.0	
Channel				630668	633334	636000	MPR (dB)		
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	18.93	18.96	18.91	19.5	0.0	
Channel				630500	633334	636168	MPR (dB)		
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	18.91	18.97	18.90	19.5	0.0	
Channel				630334	633334	636334	MPR (dB)		
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	18.97	18.91	18.95	19.5	0.0	

Part27Q n77 PC2 Ant4 DSI5									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3500.01	633334				
100	1/2 BPSK	1	1	22.49					
100	1/2 BPSK	1	137	22.57			23.0	0.0	
100	1/2 BPSK	1	271	22.55					
100	1/2 BPSK	135	0	22.52			23.0	0.0	
100	1/2 BPSK	135	69	22.46			23.0	0.0	
100	1/2 BPSK	135	138	22.61					
100	1/2 BPSK	270	0	22.58			23.0	0.0	
100	QPSK	1	1	22.62					
100	QPSK	1	137	22.51			23.0	0.0	
100	QPSK	1	271	22.51					
100	QPSK	135	0	22.55			23.0	0.0	
100	QPSK	135	69	22.56			23.0	0.0	
100	QPSK	135	138	22.51					
100	QPSK	270	0	22.47			23.0	0.0	
100	16QAM	1	1	22.51			23.0	0.0	
100	64QAM	1	1	22.41			23.0	0.0	
100	256QAM	1	1	22.59			23.0	0.0	
Channel				633000	633334	633668	MPR (dB)		
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	22.56	22.56	22.51	23.0	0.0	
Channel				632668	633334	634000	MPR (dB)		
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	22.57	22.49	22.51	23.0	0.0	
Channel				632334	633334	634334	MPR (dB)		
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	22.56	22.47	22.55	23.0	0.0	
Channel				632000	633334	634668	MPR (dB)		
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	22.54	22.54	22.50	23.0	0.0	
Channel				631668	633334	635000	MPR (dB)		
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	22.54	22.49	22.57	23.0	0.0	</

Part270 n78 PC2 Ant4 DSI5									
BW MHz	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	1/2 BPS	1	1		22.87				
100	1/2 BPS	1	137		22.71		23.0	0.0	
100	1/2 BPS	1	271		22.79				
100	1/2 BPS	135	0		22.83		23.0	0.0	
100	1/2 BPS	135	69		22.75		23.0	0.0	
100	1/2 BPS	135	138		22.73				
100	1/2 BPS	270	0		22.80		23.0	0.0	
100	QPSK	1	1		22.95				
100	QPSK	1	137		22.82		23.0	0.0	
100	QPSK	1	271		22.77				
100	QPSK	135	0		22.78		23.0	0.0	
100	QPSK	135	69		22.91		23.0	0.0	
100	QPSK	135	138		22.88				
100	QPSK	270	0		22.70		23.0	0.0	
100	16QAM	1	1		22.81		23.0	0.0	
100	64QAM	1	1		22.85		23.0	0.0	
100	256QAM	1	1		22.84		23.0	0.0	
Channel				648668	650000	650334	up	MPR	
Frequency (MHz)				3745.02	3750	3755.01	up	(dB)	
90	QPSK	1	1		22.83	22.89	22.91	23.0	0.0
Channel				649334	650000	650668	up	MPR	
Frequency (MHz)				3740.01	3750	3760.02	up	(dB)	
80	QPSK	1	1		22.87	22.86	22.86	23.0	0.0
Channel				649000	650000	651000	up	MPR	
Frequency (MHz)				3735	3750	3765	up	(dB)	
70	QPSK	1	1		22.81	22.89	22.80	23.0	0.0
Channel				648668	650000	651334	up	MPR	
Frequency (MHz)				3730.02	3750	3770.01	up	(dB)	
60	QPSK	1	1		22.82	22.88	22.90	23.0	0.0
Channel				649334	650000	651668	up	MPR	
Frequency (MHz)				3725.01	3750	3775.02	up	(dB)	
50	QPSK	1	1		22.84	22.88	22.91	23.0	0.0
Channel				648000	650000	652000	up	MPR	
Frequency (MHz)				3720	3750	3780	up	(dB)	
40	QPSK	1	1		22.82	22.84	22.82	23.0	0.0
Channel				647668	650000	652334	up	MPR	
Frequency (MHz)				3715.02	3750	3785.01	up	(dB)	
30	QPSK	1	1		22.85	22.83	22.81	23.0	0.0
Channel				647500	650000	652500	up	MPR	
Frequency (MHz)				3712.5	3750	3787.5	up	(dB)	
25	QPSK	1	1		22.83	22.84	22.81	23.0	0.0
Channel				647334	650000	652668	up	MPR	
Frequency (MHz)				3710.01	3750	3790.02	up	(dB)	
20	QPSK	1	1		22.80	22.83	22.88	23.0	0.0
Channel				647168	650000	652834	up	MPR	
Frequency (MHz)				3707.52	3750	3792.51	up	(dB)	
15	QPSK	1	1		22.86	22.88	22.91	23.0	0.0
Channel				647000	650000	653000	up	MPR	
Frequency (MHz)				3705	3750	3795	up	(dB)	
10	QPSK	1	1		22.84	22.85	22.90	23.0	0.0

Part27Q n78 Ant4 DSI5									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		19.08				
100	1/2 BPS	1	137		19.05		19.5	0.0	
100	1/2 BPS	1	271		19.13				
100	1/2 BPS	135	0		19.11		19.5	0.0	
100	1/2 BPS	135	69		19.05		19.5	0.0	
100	1/2 BPS	135	138		19.08				
100	1/2 BPS	270	0		19.14		19.5	0.0	
100	QPSK	1	1		19.15				
100	QPSK	1	137		19.07		19.5	0.0	
100	QPSK	1	271		19.14				
100	QPSK	135	0		19.10		19.5	0.0	
100	QPSK	135	69		19.14		19.5	0.0	
100	QPSK	135	138		19.06				
100	QPSK	270	0		19.15		19.5	0.0	
100	16QAM	1	1		19.13		19.5	0.0	
100	64QAM	1	1		19.10		19.5	0.0	
100	256QAM	1	1		19.06		19.5	0.0	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02	up	(dB)	
90	QPSK	1	1		19.03	18.96	19.03	19.5	0.0
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up	(dB)	
80	QPSK	1	1		19.00	19.04	19.01	19.5	0.0
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up	(dB)	
70	QPSK	1	1		19.02	18.96	18.94	19.5	0.0
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up	(dB)	
60	QPSK	1	1		18.95	18.94	18.96	19.5	0.0
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525	up	(dB)	
50	QPSK	1	1		18.95	18.97	18.93	19.5	0.0
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up	(dB)	
40	QPSK	1	1		19.02	18.94	19.01	19.5	0.0
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	up	(dB)	
30	QPSK	1	1		18.94	19.02	18.96	19.5	0.0
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up	(dB)	
25	QPSK	1	1		19.00	18.97	18.98	19.5	0.0
Channel				630668	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up	(dB)	
20	QPSK	1	1		19.05	18.99	19.03	19.5	0.0
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up	(dB)	
15	QPSK	1	1		18.96	19.05	18.96	19.5	0.0
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up	(dB)	
10	QPSK	1	1		18.96	18.98	19.02	19.5	0.0

Part27Q n78 PC2 Ant4 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		22.53				
100	1/2 BPS	1	137		22.58		23.0	0.0	
100	1/2 BPS	1	271		22.57				
100	1/2 BPS	135	0		22.56		23.0	0.0	
100	1/2 BPS	135	69		22.57		23.0	0.0	
100	1/2 BPS	135	138		22.55				
100	1/2 BPS	270	0		22.59		23.0	0.0	
100	QPSK	1	1		22.70				
100	QPSK	1	137		22.54		23.0	0.0	
100	QPSK	1	271		22.69				
100	QPSK	135	0		22.63		23.0	0.0	
100	QPSK	135	69		22.66		23.0	0.0	
100	QPSK	135	138		22.54				
100	QPSK	270	0		22.66		23.0	0.0	
100	16QAM	1	1		22.63		23.0	0.0	
100	64QAM	1	1		22.57		23.0	0.0	
100	256QAM	1	1		22.59		23.0	0.0	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02	up	(dB)	
90	QPSK	1	1		22.58	22.63	22.55	23.0	0.0
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up	(dB)	
80	QPSK	1	1		22.66	22.54	22.63	23.0	0.0
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up	(dB)	
70	QPSK	1	1		22.59	22.60	22.61	23.0	0.0
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up	(dB)	
60	QPSK	1	1		22.66	22.66	22.56	23.0	0.0
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525.03	up	(dB)	
50	QPSK	1	1		22.57	22.56	22.56	23.0	0.0
Channel				631334	633334	633334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up	(dB)	
40	QPSK	1	1		22.65	22.60	22.64	23.0	0.0
Channel				631000	633334	633668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	up	(dB)	
30	QPSK	1	1		22.55	22.64	22.64	23.0	0.0
Channel				630634	633334	633634	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up	(dB)	
25	QPSK	1	1		22.65	22.57	22.54	23.0	0.0
Channel				630268	633334	633668	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up	(dB)	
20	QPSK	1	1		22.58	22.63	22.63	23.0	0.0
Channel				630000	633334	633668	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up	(dB)	
15	QPSK	1	1		22.57	22.55	22.63	23.0	0.0
Channel				629634	633334	633634	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up	(dB)	
10	QPSK	1	1		22.57	22.57	22.56	23.0	0.0

n7 Ant6 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	20.71	20.71	20.66			
50	1/2 BPSK	1	135	20.79	20.72	20.76	21.0	0.0	
50	1/2 BPSK	1	268	20.73	20.70	20.75			
50	1/2 BPSK	135	0	20.70	20.80	20.70	21.0	0.0	
50	1/2 BPSK	135	68	20.71	20.71	20.74	21.0	0.0	
50	1/2 BPSK	135	135	20.75	20.78	20.70	21.0	0.0	
50	1/2 BPSK	270	0	20.72	20.70	20.71			
50	QPSK	1	1	20.70	20.81	20.66			
50	QPSK	1	135	20.76	20.73	20.75	21.0	0.0	
50	QPSK	1	268	20.69	20.74	20.67			
50	QPSK	135	0	20.71	20.70	20.68	21.0	0.0	
50	QPSK	135	68	20.76	20.78	20.67	21.0	0.0	
50	QPSK	135	135	20.71	20.72	20.69			
50	QPSK	270	0	20.72	20.77	20.76	21.0	0.0	
50	16QAM	1	1	20.70	20.72	20.77	21.0	0.0	
50	64QAM	1	1	20.79	20.73	20.68	21.0	0.0	
50	256QAM	1	1	20.69	20.74	20.71	21.0	0.0	
Channel				504000	507000	510000	tune-up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	20.64	20.64	20.58	21.0	0.0	
Channel				503500	507000	510500	tune-up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	20.58	20.57	20.61	21.0	0.0	
Channel				503000	507000	511000	tune-up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	20.61	20.58	20.50	21.0	0.0	
Channel				502500	507000	511500	tune-up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	20.62	20.65	20.51	21.0	0.0	
Channel				502000	507000	512000	tune-up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	20.64	20.59	20.55	21.0	0.0	
Channel				501500	507000	512500	tune-up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	20.57	20.55	20.57	21.0	0.0	
Channel				501000	507000	513000	tune-up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	20.58	20.65	20.62	21.0	0.0	
Channel				500500	507000	513500	tune-up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	20.64	20.56	20.60	21.0	0.0	

n66 Ant6 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	20.38	20.50	20.44			
45	1/2 BPSK	1	120	20.38	20.49	20.50	21.0	0.0	
45	1/2 BPSK	1	240	20.48	20.47	20.53			
45	1/2 BPSK	120	0	20.38	20.50	20.46	21.0	0.0	
45	1/2 BPSK	120	60	20.41	20.55	20.47	21.0	0.0	
45	1/2 BPSK	120	120	20.48	20.48	20.45	21.0	0.0	
45	1/2 BPSK	240	0	20.40	20.51	20.51			
45	QPSK	1	1	20.41	20.56	20.42			
45	QPSK	1	120	20.44	20.46	20.47	21.0	0.0	
45	QPSK	1	240	20.38	20.47	20.45			
45	QPSK	120	0	20.40	20.47	20.44	21.0	0.0	
45	QPSK	120	60	20.49	20.54	20.46	21.0	0.0	
45	QPSK	120	120	20.43	20.50	20.46			
45	QPSK	240	0	20.49	20.51	20.49	21.0	0.0	
45	16QAM	1	1	20.38	20.53	20.42	21.0	0.0	
45	64QAM	1	1	20.44	20.55	20.48	21.0	0.0	
45	256QAM	1	1	20.47	20.46	20.48	21.0	0.0	
Channel				346000	349000	352000	tune-up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	20.26	20.39	20.30	21.0	0.0	
Channel				345500	349000	352500	tune-up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	20.33	20.34	20.27	21.0	0.0	
Channel				345000	349000	353000	tune-up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	20.29	20.39	20.33	21.0	0.0	
Channel				344500	349000	353500	tune-up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	20.35	20.37	20.27	21.0	0.0	
Channel				344000	349000	354000	tune-up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	20.25	20.35	20.30	21.0	0.0	
Channel				343500	349000	354500	tune-up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	20.37	20.41	20.28	21.0	0.0	
Channel				343000	349000	355000	tune-up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	20.26	20.32	20.27	21.0	0.0	
Channel				342500	349000	355500	tune-up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	20.36	20.32	20.27	21.0	0.0	

n38 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				518004	519000	519996			
Channel				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	20.62	20.59	20.61			
40	1/2 BPSK	1	53	20.61	20.58	20.59	21.0	0.0	
40	1/2 BPSK	1	104	20.61	20.64	20.56			
40	1/2 BPSK	50	0	20.56	20.63	20.53	21.0	0.0	
40	1/2 BPSK	50	26	20.57	20.65	20.53	21.0	0.0	
40	1/2 BPSK	50	56	20.63	20.56	20.52			
40	1/2 BPSK	100	0	20.58	20.66	20.54	21.0	0.0	
40	QPSK	1	1	20.59	20.67	20.61			
40	QPSK	1	53	20.63	20.55	20.55	21.0	0.0	
40	QPSK	1	104	20.61	20.57	20.57			
40	QPSK	50	0	20.56	20.56	20.57	21.0	0.0	
40	QPSK	50	26	20.60	20.66	20.56	21.0	0.0	
40	QPSK	50	56	20.63	20.60	20.55			
40	QPSK	100	0	20.52	20.57	20.53	21.0	0.0	
40	16QAM	1	1	20.61	20.56	20.61	21.0	0.0	
40	64QAM	1	1	20.59	20.64	20.61	21.0	0.0	
40	256QAM	1	1	20.54	20.57	20.51	21.0	0.0	
Channel				517002	516000	520998			
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	20.49	20.48	20.46	21.0	0.0	
Channel				516504	519000	521496			
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	20.46	20.47	20.54	21.0	0.0	
Channel				515000	519000	522000			
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	1	20.53	20.51	20.56	21.0	0.0	
Channel				515502	519000	522498			
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	20.54	20.51	20.46	21.0	0.0	
Channel				515004	519000	522996			
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	20.49	20.46	20.53	21.0	0.0	

n41 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Frequency (MHz)				509002	516598	526000			
Channel				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	20.05	20.14	19.93			
100	1/2 BPSK	1	137	20.13	20.10	19.97	20.5	0.0	
100	1/2 BPSK	1	271	20.14	20.12	20.00			
100	1/2 BPSK	135	0	20.04	20.18	19.97	20.5	0.0	
100	1/2 BPSK	135	69	20.14	20.16	19.94	20.5	0.0	
100	1/2 BPSK	135	138	20.06	20.17	19.97			
100	1/2 BPSK	270	0	20.05	20.13	19.95	20.5	0.0	
100	QPSK	1	1	20.05	20.15	20.03			
100	QPSK	1	137	20.08	20.07	19.91	20.5	0.0	
100	QPSK	1	271	20.11	20.09	19.95			
100	QPSK	135	0	20.12	20.11	19.99	20.5	0.0	
100	QPSK	135	69	20.13	20.16	20.02	20.5	0.0	
100	QPSK	135	138	20.13	20.15	19.92			
100	QPSK	270	0	20.04	20.19	19.95	20.5	0.0	
100	16QAM	1	1	20.14	20.15	19.91	20.5	0.0	
100	64QAM	1	1	20.08	20.12	19.98	20.5	0.0	
100	256QAM	1	1	20.12	20.12	19.99	20.5	0.0	
Channel				505000	516598	526998			
Frequency (MHz)				2541	2592.99	2644.99			
90	QPSK	1	1	19.97	19.92	19.93	20.5	0.0	
Channel				507204	516598	529998			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	19.99	19.94	19.90	20.5	0.0	
Channel				505002	516598	531000			
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	19.96	19.93	19.97	20.5	0.0	
Channel				505000	516598	531996			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	19.93	19.98	19.92	20.5	0.0	
Channel				504204	516598	532998			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	19.91	20.03	19.99	20.5	0.0	
Channel				503700	516598	533496			
Frequency (MHz)				2516.5	2592.99	2667.48			
45	QPSK	1	1	19.96	20.03	19.88	20.5	0.0	
Channel				503002	516598	534000			
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	19.89	19.94	19.95	20.5	0.0	
Channel				502704	516598	534498			
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	19.92	19.95	19.94	20.5	0.0	
Channel				502200	516598	534998			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	19.90	19.98	19.94	20.5	0.0	
Channel				501702	516598	535500			
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	19.91	20.01	19.93	20.5	0.0	
Channel				501204	516598	535998			
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	19.92	20.02	19.87	20.5	0.0	
Channel				500700	516598	536496			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	20.01	19.94	19.88	20.5	0.0	
Channel				500202	516598	537000			
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	19.95	20.01	19.97	20.5	0.0	

n48 Ant6 DSI5									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR	
Channel				638000	641666	645332			
Frequency (MHz)				3570	3624.99	3679.98			
40	1/2 BPSK	1	1	18.57	18.62	18.57			
40	1/2 BPSK	1	53	18.65	18.66	18.60	20.1	0.0	
40	1/2 BPSK	1	104	18.54	18.69	18.61			
40	1/2 BPSK	50	0	18.60	18.61	18.54	20.1	0.0	
40	1/2 BPSK	50	26	18.63	18.61	18.59	20.1	0.0	
40	1/2 BPSK	50	56	18.63	18.63	18.57			
40	1/2 BPSK	100	0	18.57	18.61	18.56	20.1	0.0	
40	QPSK	1	1	18.54	18.78	18.56			
40	QPSK	1	53	18.61	18.65	18.53	20.1		
40	QPSK	1	104	18.53	18.59	18.63			
40	QPSK	50	0	18.55	18.71	18.54	20.1	0.0	
40	QPSK	50	26	18.54	18.73	18.60	20.1	0.0	
40	QPSK	50	56	18.54	18.60	18.62			
40	QPSK	100	0	18.54	18.69	18.56	20.1		
40	16QAM	1	1	18.54	18.66	18.56	20.1		
40	64QAM	1	1	18.62	18.69	18.58	20.1		
40	256QAM	1	1	17.49	17.69	17.53	19.1	1.0	
Channel				631668	641666	645998			
Frequency (MHz)				3565.02	3624.99	3684.99			
30	QPSK	1	1	18.47	18.55	18.47	20.1		
Channel				637334	641666	646000			
Frequency (MHz)				3560.01	3624.99	3690			
20	QPSK	1	1	18.43	18.56	18.42	20.1		
Channel				631768	641666	645168			
Frequency (MHz)				3555.02	3624.99	3674.98			
15	QPSK	1	1	18.43	18.51	18.46	20.1		
Channel				635002	641666	645332			
Frequency (MHz)				3555	3624.99	3694.98			
10	QPSK	1	1	18.47	18.55	18.40	20.1		

Part270 n77 PC2 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	1/2 BPSK	1	1	21.94	22.17	21.95			
100	1/2 BPSK	1	137	22.03	22.16	21.96	23.3	0.0	
100	1/2 BPSK	1	271	22.14	22.20	22.04			
100	1/2 BPSK	135	0	22.02	22.18	21.96	23.3	0.0	
100	1/2 BPSK	135	69	22.05	22.11	21.99	23.3	0.0	
100	1/2 BPSK	135	138	22.09	22.13	21.90	23.3	0.0	
100	1/2 BPSK	270	0	22.04	22.13	21.94			
100	QPSK	1	1	22.07	22.26	21.96			
100	QPSK	1	137	22.06	22.21	21.97	23.3	0.0	
100	QPSK	1	271	22.02	22.11	21.97			
100	QPSK	135	0	22.08	22.15	21.92	23.3	0.0	
100	QPSK	135	69	21.99	22.16	21.93	23.3	0.0	
100	QPSK	135	138	22.09	22.12	21.87			
100	QPSK	270	0	22.11	22.12	21.98			
100	16QAM	1	1	22.04	22.11	21.91	23.3	0.0	
100	64QAM	1	1	21.97	22.19	21.99	23.3	0.0	
100	256QAM	1	1	22.02	22.12	22.00	23.3	0.0	
Channel				649668	650000	650334		MPR (dB)	
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	1	21.95	22.22	21.85	23.3	0.0	
Channel				649334	650000	650668		MPR (dB)	
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	1	21.93	22.13	21.88	23.3	0.0	
Channel				649000	650000	650000		MPR (dB)	
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	1	21.93	22.17	21.84	23.3	0.0	
Channel				648668	650000	653334		MPR (dB)	
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	1	21.99	22.14	21.80	23.3	0.0	
Channel				648334	650000	653668		MPR (dB)	
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	1	21.94	22.13	21.86	23.3	0.0	
Channel				648000	650000	654000		MPR (dB)	
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	1	21.92	22.11	21.81	23.3	0.0	
Channel				647668	650000	654334		MPR (dB)	
Frequency (MHz)				3715.02	3840	3965.01			
30	QPSK	1	1	21.95	22.20	21.86	23.3	0.0	
Channel				647500	650000	654500		MPR (dB)	
Frequency (MHz)				3712.5	3840	3967.5			
25	QPSK	1	1	21.91	22.14	21.81	23.3	0.0	
Channel				647334	650000	654668		MPR (dB)	
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	1	21.96	22.15	21.90	23.3	0.0	
Channel				647168	650000	654834		MPR (dB)	
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	1	21.96	22.17	21.83	23.3	0.0	
Channel				647000	650000	655000		MPR (dB)	
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	1	21.95	22.16	21.82	23.3	0.0	

Part27Q n77 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		18.69				
100	1/2 BPSK	1	137		18.68		20.3		0.0
100	1/2 BPSK	1	271		18.60				
100	1/2 BPSK	135	0		18.60		20.3		0.0
100	1/2 BPSK	135	69		18.59		20.3		0.0
100	1/2 BPSK	135	138		18.63		20.3		0.0
100	1/2 BPSK	270	0		18.64				
100	QPSK	1	1		18.71				
100	QPSK	1	137		18.67		20.3		0.0
100	QPSK	1	271		18.67				
100	QPSK	135	0		18.63		20.3		0.0
100	QPSK	135	69		18.65		20.3		0.0
100	QPSK	135	138		18.60				
100	QPSK	270	0		18.61				
100	16QAM	1	1		18.63		20.3		0.0
100	64QAM	1	1		18.67		20.3		0.0
100	256QAM	1	1		18.70		20.3		0.0
Channel				633000	633334	633668		MPR (dB)	
Frequency (MHz)				3495	3500.01	3505.02			
90	QPSK	1	1	18.49	18.56	18.56	20.3		0.0
Channel				632668	633334	634000		MPR (dB)	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	1	18.64	18.63	18.56	20.3		0.0
Channel				632334	633334	634334		MPR (dB)	
Frequency (MHz)				3485.01	3500.01	3515.01			
70	QPSK	1	1	18.53	18.56	18.52	20.3		0.0
Channel				632000	633334	634668		MPR (dB)	
Frequency (MHz)				3480	3500.01	3520.02			
60	QPSK	1	1	18.55	18.60	18.53	20.3		0.0
Channel				631668	633334	635000		MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	1	18.56	18.61	18.58	20.3		0.0
Channel				631334	633334	635334		MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3530.01			
40	QPSK	1	1	18.51	18.59	18.60	20.3		0.0
Channel				631000	633334	635668		MPR (dB)	
Frequency (MHz)				3465	3500.01	3535.02			
30	QPSK	1	1	18.52	18.51	18.58	20.3		0.0
Channel				630834	633334	635834		MPR (dB)	
Frequency (MHz)				3462.51	3500.01	3537.51			
25	QPSK	1	1	18.52	18.54	18.57	20.3		0.0
Channel				630668	633334	636000		MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	1	18.51	18.53	18.50	20.3		0.0
Channel				630500	633334	636168		MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.52			
15	QPSK	1	1	18.51	18.58	18.60	20.3		0.0
Channel				630334	633334	636334		MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3545.01			
10	QPSK	1	1	18.60	18.50	18.59	20.3		0.0

Part27Q n77 PC2 Ant6 DSI5									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit [dBm]	MPR [dBm]	
Channel									
Frequency [MHz]				3500.01	3533.34			3500.01	
100	1/2 BPSK	1	1		21.71				
100	1/2 BPSK	1	137		21.70		23.3	0.0	
100	1/2 BPSK	1	271		21.60				
100	1/2 BPSK	135	0		21.59		23.3	0.0	
100	1/2 BPSK	135	69		21.65		23.3	0.0	
100	1/2 BPSK	135	138		21.67		23.3	0.0	
100	1/2 BPSK	270	0		21.67				
100	QPSK	1	1		21.73				
100	QPSK	1	137		21.64		23.3	0.0	
100	QPSK	1	271		21.69				
100	QPSK	135	0		21.63		23.3	0.0	
100	QPSK	135	69		21.66		23.3	0.0	
100	QPSK	135	138		21.66				
100	QPSK	270	0		21.65		23.3	0.0	
100	16QAM	1	1		21.64		23.3	0.0	
100	16QAM	1	1		21.64		23.3	0.0	
100	256QAM	1	1		21.65		23.3	0.0	
Channel									
Frequency [MHz]				3500.01	3533.34	3565.92		3500.01	
90	QPSK	1	1	21.65	21.62	21.57			
Channel				3526.68	3533.34	3540.00		3526.68	
80	QPSK	1	1	21.61	21.62	21.62	23.3	0.0	
Channel				3523.34	3533.34	3543.34		3523.34	
Frequency [MHz]				3545.01	3550.01	3551.01			
70	QPSK	1	1	21.54	21.53	21.54	23.3	0.0	
Channel				3520.00	3533.34	3546.68		3520.00	
60	QPSK	1	1	21.54	21.57	21.54	23.3	0.0	
Channel				3516.68	3533.34	3550.00		3516.68	
Frequency [MHz]				3575.02	3580.01	3525			
50	QPSK	1	1	21.64	21.63	21.62	23.3	0.0	
Channel				3513.34	3533.34	3553.34		3513.34	
Frequency [MHz]				3570.01	3550.01	3530.01			
40	QPSK	1	1	21.62	21.56	21.58	23.3	0.0	
Channel				3520.00	3533.34	3556.68		3520.00	
Frequency [MHz]				3565	3550.01	3535.02			
30	QPSK	1	1	21.60	21.64	21.58	23.3	0.0	
Channel				3509.84	3533.34	3558.84		3509.84	
Frequency [MHz]				3562.51	3550.01	3537.51			
25	QPSK	1	1	21.58	21.54	21.60	23.3	0.0	
Channel				3506.68	3533.34	3552.00		3506.68	
Frequency [MHz]				3560.02	3550.01	3540			
20	QPSK	1	1	21.63	21.63	21.53	23.3	0.0	
Channel				3505.00	3533.34	3561.68		3505.00	
Frequency [MHz]				3573.5	3550.01	3542.52			
15	QPSK	1	1	21.54	21.45	21.63	23.3	0.0	
Channel				3503.34	3533.34	3553.34		3503.34	
Frequency [MHz]				3565.01	3550.01	3545.01			
10	QPSK	1	1	21.63	21.57	21.54	23.3	0.0	

Part270 n78 PC2 Ant6 DSI5									
BW MHz	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	1/2 BPS	1	1		21.64				
100	1/2 BPS	1	137		21.65		22.8	0.0	
100	1/2 BPS	1	271		21.68				
100	1/2 BPS	135	0		21.67		22.8	0.0	
100	1/2 BPS	135	69		21.69		22.8	0.0	
100	1/2 BPS	135	138		21.73				
100	1/2 BPS	270	0		21.71		22.8	0.0	
100	QPSK	1	1		21.75				
100	QPSK	1	137		21.66		22.8	0.0	
100	QPSK	1	271		21.67				
100	QPSK	135	0		21.69		22.8	0.0	
100	QPSK	135	69		21.71		22.8	0.0	
100	QPSK	135	138		21.66				
100	QPSK	270	0		21.62		22.8	0.0	
100	16QAM	1	1		21.65		22.8	0.0	
100	64QAM	1	1		21.62		22.8	0.0	
100	256QAM	1	1		21.66		22.8	0.0	
Channel				649668	650000	650334	MPR		
Frequency (MHz)				3745.02	3750	3755.01	up		
90	QPSK	1	1	21.59	21.58	21.57	22.8	0.0	
Channel				649334	650000	650668	MPR		
Frequency (MHz)				3740.01	3750	3760.02	up		
80	QPSK	1	1	21.52	21.51	21.57	22.8	0.0	
Channel				649000	650000	651000	MPR		
Frequency (MHz)				3735	3750	3765	up		
70	QPSK	1	1	21.52	21.55	21.52	22.8	0.0	
Channel				648668	650000	651334	MPR		
Frequency (MHz)				3730.02	3750	3770.01	up		
60	QPSK	1	1	21.57	21.52	21.57	22.8	0.0	
Channel				648334	650000	651668	MPR		
Frequency (MHz)				3725.01	3750	3775.02	up		
50	QPSK	1	1	21.58	21.54	21.57	22.8	0.0	
Channel				648000	650000	652000	MPR		
Frequency (MHz)				3720	3750	3780	up		
40	QPSK	1	1	21.53	21.57	21.58	22.8	0.0	
Channel				647668	650000	652334	MPR		
Frequency (MHz)				3715.02	3750	3785.01	up		
30	QPSK	1	1	21.56	21.61	21.57	22.8	0.0	
Channel				647500	650000	652500	MPR		
Frequency (MHz)				3712.5	3750	3787.5	up		
25	QPSK	1	1	21.55	21.56	21.53	22.8	0.0	
Channel				647334	650000	652668	MPR		
Frequency (MHz)				3710.01	3750	3790.02	up		
20	QPSK	1	1	21.59	21.58	21.55	22.8	0.0	
Channel				647168	650000	652834	MPR		
Frequency (MHz)				3707.52	3750	3792.51	up		
15	QPSK	1	1	21.57	21.56	21.58	22.8	0.0	
Channel				647000	650000	653000	MPR		
Frequency (MHz)				3705	3750	3795	up		
10	QPSK	1	1	21.58	21.60	21.53	22.8	0.0	

Part27Q n78 Ant6 DSI5									
BW [MHz]	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		18.20				
100	1/2 BPS	1	137		18.17		19.8	0.0	
100	1/2 BPS	1	271		18.28				
100	1/2 BPS	135	0		18.26		19.8	0.0	
100	1/2 BPS	135	69		18.26		19.8	0.0	
100	1/2 BPS	135	138		18.23				
100	1/2 BPS	270	0		18.22		19.8	0.0	
100	QPSK	1	1		18.29				
100	QPSK	1	137		18.21		19.8	0.0	
100	QPSK	1	271		18.19				
100	QPSK	135	0		18.17		19.8	0.0	
100	QPSK	135	69		18.23		19.8	0.0	
100	QPSK	135	138		18.22				
100	QPSK	270	0		18.23		19.8	0.0	
100	16QAM	1	1		18.26		19.8	0.0	
100	64QAM	1	1		18.21		19.8	0.0	
100	256QAM	1	1		18.20		19.8	0.0	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	18.20	18.16	18.21	19.8	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	18.22	18.20	18.23	19.8	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	18.22	18.18	18.15	19.8	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	18.17	18.13	18.13	19.8	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	18.17	18.22	18.19	19.8	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	18.16	18.17	18.17	19.8	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3535.02	up		
30	QPSK	1	1	18.11	18.20	18.18	19.8	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	18.14	18.22	18.12	19.8	0.0	
Channel				630500	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	18.17	18.19	18.14	19.8	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	18.18	18.15	18.19	19.8	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	18.16	18.20	18.17	19.8	0.0	

Part27Q n78 PC2 Ant6 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	1/2 BPS	1	1		21.24				
100	1/2 BPS	1	137		21.12		22.8	0.0	
100	1/2 BPS	1	271		21.31				
100	1/2 BPS	135	0		21.22		22.8	0.0	
100	1/2 BPS	135	69		21.23		22.8	0.0	
100	1/2 BPS	135	138		21.25				
100	1/2 BPS	270	0		21.18		22.8	0.0	
100	QPSK	1	1		21.32				
100	QPSK	1	137		21.19		22.8	0.0	
100	QPSK	1	271		21.22				
100	QPSK	135	0		21.20		22.8	0.0	
100	QPSK	135	69		21.29		22.8	0.0	
100	QPSK	135	138		21.28				
100	QPSK	270	0		21.27		22.8	0.0	
100	16QAM	1	1		21.31		22.8	0.0	
100	64QAM	1	1		21.23		22.8	0.0	
100	256QAM	1	1		21.20		22.8	0.0	
Channel				633000	633334	633668	MPR		
Frequency (MHz)				3495	3500.01	3505.02	up		
90	QPSK	1	1	21.15	21.16	21.15	22.8	0.0	
Channel				632668	633334	634000	MPR		
Frequency (MHz)				3490.02	3500.01	3510	up		
80	QPSK	1	1	21.13	21.08	21.19	22.8	0.0	
Channel				632334	633334	634334	MPR		
Frequency (MHz)				3485.01	3500.01	3515.01	up		
70	QPSK	1	1	21.19	21.10	21.09	22.8	0.0	
Channel				632000	633334	634668	MPR		
Frequency (MHz)				3480	3500.01	3520.02	up		
60	QPSK	1	1	21.12	21.14	21.16	22.8	0.0	
Channel				631668	633334	635000	MPR		
Frequency (MHz)				3475.02	3500.01	3525	up		
50	QPSK	1	1	21.18	21.19	21.13	22.8	0.0	
Channel				631334	633334	635334	MPR		
Frequency (MHz)				3470.01	3500.01	3530.01	up		
40	QPSK	1	1	21.13	21.17	21.11	22.8	0.0	
Channel				631000	633334	635668	MPR		
Frequency (MHz)				3465	3500.01	3536.02	up		
30	QPSK	1	1	21.17	21.16	21.09	22.8	0.0	
Channel				630834	633334	635834	MPR		
Frequency (MHz)				3462.51	3500.01	3537.51	up		
25	QPSK	1	1	21.12	21.19	21.14	22.8	0.0	
Channel				630668	633334	636000	MPR		
Frequency (MHz)				3460.02	3500.01	3540	up		
20	QPSK	1	1	21.11	21.11	21.11	22.8	0.0	
Channel				630500	633334	636168	MPR		
Frequency (MHz)				3457.5	3500.01	3542.52	up		
15	QPSK	1	1	21.16	21.12	21.12	22.8	0.0	
Channel				630334	633334	636334	MPR		
Frequency (MHz)				3455.01	3500.01	3545.01	up		
10	QPSK	1	1	21.18	21.11	21.18	22.8	0.0	

n7 Ant7 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				505000	507000	509000			
Frequency (MHz)				2525	2535	2545			
50	1/2 BPSK	1	1	18.68	18.72	18.75			
50	1/2 BPSK	1	135	18.70	18.78	18.68	19.8	0.0	
50	1/2 BPSK	1	268	18.66	18.80	18.69			
50	1/2 BPSK	135	0	18.72	18.81	18.76	19.8	0.0	
50	1/2 BPSK	135	68	18.67	18.79	18.74	19.8	0.0	
50	1/2 BPSK	135	135	18.64	18.72	18.75			
50	1/2 BPSK	270	0	18.70	18.77	18.67			
50	QPSK	1	1	18.72	18.83	18.72			
50	QPSK	1	135	18.73	18.77	18.75	19.8	0.0	
50	QPSK	1	268	18.70	18.74	18.68			
50	QPSK	135	0	18.65	18.77	18.73	19.8	0.0	
50	QPSK	135	68	18.70	18.78	18.70	19.8	0.0	
50	QPSK	135	135	18.71	18.77	18.67			
50	QPSK	270	0	18.65	18.75	18.74	19.8	0.0	
50	16QAM	1	1	18.67	18.69	18.66	19.8	0.0	
50	64QAM	1	1	18.66	18.77	18.73	19.8	0.0	
50	256QAM	1	1	18.23	18.27	18.22	19.3	0.5	
Channel				504000	507000	510000	tune up limit	MPR (dB)	
Frequency (MHz)				2520	2535	2550			
40	QPSK	1	1	18.57	18.65	18.62	19.8	0.0	
Channel				503500	507000	510500	tune up limit	MPR (dB)	
Frequency (MHz)				2517.5	2535	2552.5			
35	QPSK	1	1	18.66	18.66	18.58	19.8	0.0	
Channel				503000	507000	511000	tune up limit	MPR (dB)	
Frequency (MHz)				2515	2535	2555			
30	QPSK	1	1	18.60	18.68	18.64	19.8	0.0	
Channel				502500	507000	511500	tune up limit	MPR (dB)	
Frequency (MHz)				2512.5	2535	2557.5			
25	QPSK	1	1	18.67	18.71	18.64	19.8	0.0	
Channel				502000	507000	512000	tune up limit	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	1/2 BPSK	1	1	18.59	18.73	18.60	19.8	0.0	
Channel				501500	507000	512500	tune up limit	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	1	18.67	18.72	18.67	19.8	0.0	
Channel				501000	507000	513000	tune up limit	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	1	18.64	18.65	18.67	19.8	0.0	
Channel				500500	507000	513500	tune up limit	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	1	18.58	18.71	18.57	19.8	0.0	

n66 Ant7 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346500	349000	351500			
Frequency (MHz)				1732.5	1745	1757.5			
45	1/2 BPSK	1	1	18.57	18.53	18.56			
45	1/2 BPSK	1	120	18.49	18.57	18.50	19.7	0.0	
45	1/2 BPSK	1	240	18.57	18.58	18.51			
45	1/2 BPSK	120	0	18.57	18.56	18.50	19.7	0.0	
45	1/2 BPSK	120	60	18.51	18.54	18.57	19.7	0.0	
45	1/2 BPSK	120	120	18.53	18.57	18.53	19.7	0.0	
45	1/2 BPSK	240	0	18.48	18.58	18.49			
45	QPSK	1	1	18.50	18.65	18.53			
45	QPSK	1	120	18.54	18.53	18.50	19.7	0.0	
45	QPSK	1	240	18.50	18.53	18.54			
45	QPSK	120	0	18.57	18.60	18.55	19.7	0.0	
45	QPSK	120	60	18.53	18.63	18.51	19.7	0.0	
45	QPSK	120	120	18.50	18.58	18.58			
45	QPSK	240	0	18.47	18.53	18.52	19.7	0.0	
45	16QAM	1	1	18.51	18.54	18.53	19.7	0.0	
45	64QAM	1	1	18.56	18.64	18.58	19.7	0.0	
45	256QAM	1	1	17.52	17.68	17.57	18.7	1.0	
Channel				346000	349000	352000	tune up limit	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	QPSK	1	1	18.35	18.38	18.44	19.7	0.0	
Channel				345500	349000	352500	tune up limit	MPR (dB)	
Frequency (MHz)				1727.5	1745	1762.5			
35	QPSK	1	1	18.41	18.46	18.46	19.7	0.0	
Channel				345000	349000	353000	tune up limit	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	1	18.36	18.47	18.45	19.7	0.0	
Channel				344500	349000	353500	tune up limit	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	1	18.36	18.46	18.38	19.7	0.0	
Channel				344000	349000	354000	tune up limit	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	1	18.46	18.39	18.37	19.7	0.0	
Channel				343500	349000	354500	tune up limit	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	1	18.43	18.49	18.40	19.7	0.0	
Channel				343000	349000	355000	tune up limit	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	1	18.46	18.45	18.46	19.7	0.0	
Channel				342500	349000	355500	tune up limit	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	1	18.38	18.40	18.39	19.7	0.0	

n38 Ant7 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	1/2 BPSK	1	1	18.25	18.33	18.19			
40	1/2 BPSK	1	53	18.21	18.33	18.23	19.1	0.0	
40	1/2 BPSK	1	104	18.17	18.25	18.23			
40	1/2 BPSK	50	0	18.19	18.28	18.26	19.1	0.0	
40	1/2 BPSK	50	28	18.20	18.25	18.20	19.1	0.0	
40	1/2 BPSK	50	56	18.19	18.34	18.19			
40	1/2 BPSK	100	0	18.19	18.27	18.26	19.1	0.0	
40	QPSK	1	1	18.17	18.35	18.29			
40	QPSK	1	53	18.26	18.28	18.27	19.1	0.0	
40	QPSK	1	104	18.22	18.26	18.27			
40	QPSK	50	0	18.17	18.30	18.21	19.1	0.0	
40	QPSK	50	28	18.22	18.33	18.28	19.1	0.0	
40	QPSK	50	56	18.29	18.23	18.21			
40	QPSK	100	0	18.28	18.32	18.20	19.1	0.0	
40	16QAM	1	1	18.18	18.27	18.24	19.1	0.0	
40	64QAM	1	1	18.25	18.26	18.30	19.1	0.0	
40	256QAM	1	1	18.28	18.29	18.24	19.1	0.0	
Channel				517002	519000	520998	tune-up limit	MPR (dB)	
Frequency (MHz)				2585.01	2595	2604.99			
30	QPSK	1	1	18.04	18.17	18.18	19.1	0.0	
Channel				516504	519000	521496	tune-up limit	MPR (dB)	
Frequency (MHz)				2582.52	2595	2607.48			
25	QPSK	1	1	18.10	18.24	18.19	19.1	0.0	
Channel				516000	519000	522000	tune-up limit	MPR (dB)	
Frequency (MHz)				2569	2595	2610			
20	QPSK	1	1	18.04	18.28	18.15	19.1	0.0	
Channel				515502	519000	522498	tune-up limit	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	1	18.02	18.27	18.14	19.1	0.0	
Channel				515004	519000	522996	tune-up limit	MPR (dB)	
Frequency (MHz)				2575.02	2595	2614.98			
10	QPSK	1	1	18.02	18.23	18.24	19.1	0.0	

n41 Ant7 DSI5									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509202	518598	528000			
Frequency (MHz)				2546.01	2592.99	2640			
100	1/2 BPSK	1	1	19.22	19.32	19.22			
100	1/2 BPSK	1	137	19.17	19.32	19.22	20.2	0.0	
100	1/2 BPSK	1	271	19.13	19.35	19.17			
100	1/2 BPSK	135	0	19.17	19.24	19.25	20.2	0.0	
100	1/2 BPSK	135	69	19.20	19.33	19.22	20.2	0.0	
100	1/2 BPSK	135	138	19.19	19.34	19.19			
100	1/2 BPSK	270	0	19.16	19.29	19.17	20.2	0.0	
100	QPSK	1	1	19.22	19.36	19.16			
100	QPSK	1	137	19.18	19.27	19.22	20.2	0.0	
100	QPSK	1	271	19.13	19.32	19.15			
100	QPSK	135	0	19.16	19.32	19.19	20.2	0.0	
100	QPSK	135	69	19.15	19.33	19.25	20.2	0.0	
100	QPSK	135	138	19.16	19.24	19.26			
100	QPSK	270	0	19.17	19.28	19.27	20.2	0.0	
100	16QAM	1	1	19.23	19.28	19.18	20.2	0.0	
100	64QAM	1	1	19.17	19.30	19.28	20.2	0.0	
100	256QAM	1	1	18.27	18.35	18.21	19.2	1.0	
Channel				508200	518598	528996	tune-up limit	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	1	19.11	19.24	19.04	20.2	0.0	
Channel				507204	518598	529998	tune-up limit	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	1	19.10	19.23	19.11	20.2	0.0	
Channel				506202	518598	531000	tune-up limit	MPR (dB)	
Frequency (MHz)				2531.01	2592.99	2655			
70	QPSK	1	1	19.11	19.24	19.05	20.2	0.0	
Channel				505200	518598	531996	tune-up limit	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	1	19.08	19.19	19.08	20.2	0.0	
Channel				504204	518598	532998	tune-up limit	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	1	19.08	19.28	19.06	20.2	0.0	
Channel				503700	518598	533496	tune-up limit	MPR (dB)	
Frequency (MHz)				2518.5	2592.99	2667.48			
45	QPSK	1	1	19.17	19.19	19.06	20.2	0.0	
Channel				503202	518598	534000	tune-up limit	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	1	19.06	19.25	19.01	20.2	0.0	
Channel				502704	518598	534498	tune-up limit	MPR (dB)	
Frequency (MHz)				2513.52	2592.99	2672.49			
35	QPSK	1	1	19.18	19.26	19.05	20.2	0.0	
Channel				502200	518598	534996	tune-up limit	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	1	19.11	19.30	19.01	20.2	0.0	
Channel				501702	518598	535500	tune-up limit	MPR (dB)	
Frequency (MHz)				2508.51	2592.99	2677.5			
25	QPSK	1	1	19.06	19.19	19.09	20.2	0.0	
Channel				501204	518598	535998	tune-up limit	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	1	19.07	19.21	19.08	20.2	0.0	
Channel				500700	518598	536496	tune-up limit	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	1	19.18	19.27	19.03	20.2	0.0	
Channel				500202	518598	537000	tune-up limit	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	1	19.06	19.28	19.01	20.2	0.0	

Part270 n77 Ant10 DSI5

BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				65000	65000	65000		
Frequency (MHz)				3760	3840	3920		
100	1/2 BPSK	1	1	20.42	20.68	20.53		
100	1/2 BPSK	1	137	20.54	20.58	20.59	22.2	0.0
100	1/2 BPSK	1	271	20.48	20.64	20.55		
100	1/2 BPSK	135	0	20.39	20.63	20.51	22.2	0.0
100	1/2 BPSK	135	69	20.50	20.67	20.56	22.2	0.0
100	1/2 BPSK	135	138	20.41	20.58	20.55	22.2	0.0
100	1/2 BPSK	270	0	20.48	20.58	20.58		
100	QPSK	1	1	20.37	20.69	20.52		
100	QPSK	1	137	20.47	20.59	20.57	22.2	0.0
100	QPSK	1	271	20.43	20.63	20.54		
100	QPSK	135	0	20.46	20.60	20.60	22.2	0.0
100	QPSK	135	69	20.52	20.67	20.57	22.2	0.0
100	QPSK	135	138	20.53	20.66	20.59		
100	QPSK	270	0	20.47	20.69	20.62	22.2	0.0
100	16QAM	1	1	20.49	20.63	20.54	22.2	0.0
100	64QAM	1	1	20.51	20.63	20.56	22.2	0.0
100	256QAM	1	1	19.48	19.51	19.54	21.2	1.0
Channel				649668	650000	652334		
Frequency (MHz)				3745.02	3840	3935.01		
90	QPSK	1	1	20.26	20.55	20.38	22.2	0.0
Channel				649334	650000	662668		
Frequency (MHz)				3740.01	3840	3940.02		
80	QPSK	1	1	20.25	20.56	20.38	22.2	0.0
Channel				649000	650000	663000		
Frequency (MHz)				3735	3840	3945		
70	QPSK	1	1	20.21	20.54	20.47	22.2	0.0
Channel				648668	650000	663334		
Frequency (MHz)				3730.02	3840	3950.01		
60	QPSK	1	1	20.21	20.48	20.41	22.2	0.0
Channel				648334	650000	663668		
Frequency (MHz)				3725.01	3840	3955.02		
50	QPSK	1	1	20.28	20.54	20.43	22.2	0.0
Channel				648000	650000	664000		
Frequency (MHz)				3720	3840	3960		
40	QPSK	1	1	20.24	20.49	20.37	22.2	0.0
Channel				647668	650000	664334		
Frequency (MHz)				3715.02	3840	3965.01		
30	QPSK	1	1	20.27	20.49	20.47	22.2	0.0
Channel				647500	650000	664500		
Frequency (MHz)				3712.5	3840	3967.5		
25	QPSK	1	1	20.31	20.47	20.46	22.2	0.0
Channel				647334	650000	664668		
Frequency (MHz)				3710.01	3840	3970.02		
20	QPSK	1	1	20.28	20.54	20.39	22.2	0.0
Channel				647168	650000	664834		
Frequency (MHz)				3707.52	3840	3972.51		
15	QPSK	1	1	20.26	20.48	20.43	22.2	0.0
Channel				647000	650000	665000		
Frequency (MHz)				3705	3840	3975		
10	QPSK	1	1	20.22	20.54	20.43	22.2	0.0

Part270 n77 PC2 Ant10 DSI5

BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				65000	65000	65000		
Frequency (MHz)				3750	3840	3930		
100	1/2 BPSK	1	1	23.39	23.70	23.58		
100	1/2 BPSK	1	137	23.52	23.56	23.61	25.2	0.0
100	1/2 BPSK	1	271	23.53	23.64	23.54		
100	1/2 BPSK	135	0	23.39	23.60	23.49	25.2	0.0
100	1/2 BPSK	135	69	23.51	23.62	23.64	25.2	0.0
100	1/2 BPSK	135	138	23.45	23.64	23.61	25.2	0.0
100	1/2 BPSK	270	0	23.45	23.59	23.52		
100	QPSK	1	1	23.40	23.75	23.50		
100	QPSK	1	137	23.50	23.59	23.52	25.2	0.0
100	QPSK	1	271	23.38	23.65	23.56		
100	QPSK	135	0	23.49	23.64	23.57	25.2	0.0
100	QPSK	135	69	23.55	23.72	23.61	25.2	0.0
100	QPSK	135	138	23.58	23.61	23.64		
100	QPSK	270	0	23.44	23.66	23.65	25.2	0.0
100	16QAM	1	1	23.51	23.61	23.56	25.2	0.0
100	64QAM	1	1	23.25	23.46	23.36	25.0	0.2
100	256QAM	1	1	21.26	21.50	21.28	23.0	2.2
Channel				649668	650000	662334		
Frequency (MHz)				3745.02	3840	3935.01		
90	QPSK	1	1	23.36	23.61	23.45	25.2	0.0
Channel				649334	650000	662668		
Frequency (MHz)				3740.01	3840	3940.02		
80	QPSK	1	1	23.28	23.57	23.35	25.2	0.0
Channel				649000	650000	663000		
Frequency (MHz)				3735	3840	3945		
70	QPSK	1	1	23.32	23.57	23.42	25.2	0.0
Channel				648668	650000	663334		
Frequency (MHz)				3730.02	3840	3950.01		
60	QPSK	1	1	23.26	23.56	23.35	25.2	0.0
Channel				648334	650000	663668		
Frequency (MHz)				3725.01	3840	3955.02		
50	QPSK	1	1	23.33	23.60	23.45	25.2	0.0
Channel				648000	650000	664000		
Frequency (MHz)				3720	3840	3960		
40	QPSK	1	1	23.25	23.54	23.43	25.2	0.0
Channel				647668	650000	664334		
Frequency (MHz)				3715.02	3840	3965.01		
30	QPSK	1	1	23.33	23.62	23.43	25.2	0.0
Channel				647500	650000	664500		
Frequency (MHz)				3712.5	3840	3967.5		
25	QPSK	1	1	23.33	23.63	23.41	25.2	0.0
Channel				647334	650000	664668		
Frequency (MHz)				3710.01	3840	3970.02		
20	QPSK	1	1	23.30	23.59	23.45	25.2	0.0
Channel				647168	650000	664834		
Frequency (MHz)				3707.52	3840	3972.51		
15	QPSK	1	1	23.25	23.62	23.44	25.2	0.0
Channel				647000	650000	665000		
Frequency (MHz)				3705	3840	3975		
10	QPSK	1	1	23.26	23.53	23.37	25.2	0.0

Part27Q n77 Ant10 DSI5

BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				633334	633334	633334		
Frequency (MHz)				3500.01				
100	1/2 BPSK	1	1		20.44			
100	1/2 BPSK	1	137		20.40		22.2	0.0
100	1/2 BPSK	1	271		20.46			
100	1/2 BPSK	135	0		20.41		22.2	0.0
100	1/2 BPSK	135	69		20.38		22.2	0.0
100	1/2 BPSK	135	138		20.41		22.2	0.0
100	1/2 BPSK	270	0		20.50			
100	QPSK	1	1		20.53			
100	QPSK	1	137		20.40		22.2	0.0
100	QPSK	1	271		20.43			
100	QPSK	135	0		20.47		22.2	0.0
100	QPSK	135	69		20.41		22.2	0.0
100	QPSK	135	138		20.43			
100	QPSK	270	0		20.46		22.2	0.0
100	16QAM	1	1		20.47		22.2	0.0
100	64QAM	1	1		20.42		22.2	0.0
100	256QAM	1	1		19.36		21.2	1.0
Channel				633000	633334	633668		
Frequency (MHz)				3495	3500.01	3505.02		
90	QPSK	1	1	20.37	20.34	20.33	22.2	0.0
Channel				632668	633334	634000		
Frequency (MHz)				3490.02	3500.01	3510		
80	QPSK	1	1	20.39	20.29	20.34	22.2	0.0
Channel				632334	633334	634334		
Frequency (MHz)				3485.01	3500.01	3515.01		
70	QPSK	1	1	20.30	20.32	20.31	22.2	0.0
Channel				632000	633334	634668		
Frequency (MHz)				3480	3500.01	3520.02		
60	QPSK	1	1	20.40	20.34	20.32	22.2	0.0
Channel				631668	633334	635000		
Frequency (MHz)				3475.02	3500.01	3525		
50	QPSK	1	1	20.35	20.37	20.30	22.2	0.0
Channel				631334	633334	635334		
Frequency (MHz)				3470.01	3500.01	3530.01		
40	QPSK	1	1	20.36	20.39	20.34	22.2	0.0
Channel				631000	633334	635668		
Frequency (MHz)				3465	3500.01	3535.02		
30	QPSK	1	1	20.37	20.37	20.39	22.2	0.0
Channel				630834	633334	635834		
Frequency (MHz)				3462.51	3500.01	3537.51		
25	QPSK	1	1	20.35	20.38	20.30	22.2	0.0

Part270 n78 Ant10 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750					
100	1/2 BPSK	1	1		21.68				
100	1/2 BPSK	1	137		21.57		22.4	0.0	
100	1/2 BPSK	1	271		21.66				
100	1/2 BPSK	135	0		21.64		22.4	0.0	
100	1/2 BPSK	135	69		21.66		22.4	0.0	
100	1/2 BPSK	135	138		21.57		22.4	0.0	
100	1/2 BPSK	270	0		21.61				
100	QPSK	1	1		21.71				
100	QPSK	1	137		21.66		22.4	0.0	
100	QPSK	1	271		21.69				
100	QPSK	135	0		21.65		22.4	0.0	
100	QPSK	135	69		21.66		22.4	0.0	
100	QPSK	135	138		21.64		22.4	0.0	
100	QPSK	270	0		21.63				
100	16QAM	1	1		21.63		22.4	0.0	
100	64QAM	1	1		21.67		22.4	0.0	
100	256QAM	1	1		19.61		20.4	2.0	
Channel				649668	650000	650334	up	MPR	
Frequency (MHz)				3745.02	3750	3755.01	up	(dB)	
90	QPSK	1	1	21.61	21.56	21.54	22.4	0.0	
Channel				649334	650000	650668	up	MPR	
Frequency (MHz)				3740.01	3750	3760.02	up	(dB)	
80	QPSK	1	1	21.52	21.54	21.55	22.4	0.0	
Channel				649200	650000	651000	up	MPR	
Frequency (MHz)				3735	3750	3765	up	(dB)	
70	QPSK	1	1	21.61	21.60	21.61	22.4	0.0	
Channel				648668	650000	651334	up	MPR	
Frequency (MHz)				3730.02	3750	3770.01	up	(dB)	
60	QPSK	1	1	21.58	21.59	21.61	22.4	0.0	
Channel				648334	650000	651668	up	MPR	
Frequency (MHz)				3725.01	3750	3775.02	up	(dB)	
50	QPSK	1	1	21.61	21.63	21.53	22.4	0.0	
Channel				648000	650000	652000	up	MPR	
Frequency (MHz)				3720	3750	3780	up	(dB)	
40	QPSK	1	1	21.53	21.58	21.54	22.4	0.0	
Channel				647650	650000	652334	up	MPR	
Frequency (MHz)				3715.02	3750	3785.01	up	(dB)	
30	QPSK	1	1	21.52	21.55	21.55	22.4	0.0	
Channel				647500	650000	652500	up	MPR	
Frequency (MHz)				3712.5	3750	3787.5	up	(dB)	
25	QPSK	1	1	21.54	21.57	21.61	22.4	0.0	
Channel				647334	650000	652668	up	MPR	
Frequency (MHz)				3710.01	3750	3790.02	up	(dB)	
20	QPSK	1	1	21.55	21.62	21.53	22.4	0.0	
Channel				647168	650000	652834	up	MPR	
Frequency (MHz)				3707.52	3750	3792.51	up	(dB)	
15	QPSK	1	1	21.63	21.60	21.56	22.4	0.0	
Channel				647000	650000	653000	up	MPR	
Frequency (MHz)				3705	3750	3795	up	(dB)	
10	QPSK	1	1	21.60	21.57	21.61	22.4	0.0	

Part270 n78 PC2 Ant10 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)		
Channel									
Frequency (MHz)				650000					
100	1/2 BPSK	1	1		24.73				
100	1/2 BPSK	1	137		24.58	25.4	0.0		
100	1/2 BPSK	1	271		24.69				
100	1/2 BPSK	135	0		24.69	25.4	0.0		
100	1/2 BPSK	135	69		24.71	25.4	0.0		
100	1/2 BPSK	135	138		24.54				
100	1/2 BPSK	270	0		24.57	25.4	0.0		
100	QPSK	1	1		24.75				
100	QPSK	1	137		24.61	25.4	0.0		
100	QPSK	1	271		24.76				
100	QPSK	135	0		24.69	25.4	0.0		
100	QPSK	135	69		24.66	25.4	0.0		
100	QPSK	135	138		24.64				
100	QPSK	270	0		24.63	25.4	0.0		
100	16QAM	1	1		24.62	25.4	0.0		
100	64QAM	1	1		23.51	24.3	1.1		
100	256QAM	1	1		21.50	22.3	3.1		
Channel				648668	650000	650334	up	MPR	
Frequency (MHz)				3745.02	3750	3755.01	up	(dB)	
90	QPSK	1	1	24.50	24.48	24.56	25.4	0.0	
Channel				649334	650000	650668	up	MPR	
Frequency (MHz)				3740.01	3750	3760.02	up	(dB)	
80	QPSK	1	1	24.55	24.51	24.57	25.4	0.0	
Channel				649000	650000	651000	up	MPR	
Frequency (MHz)				3735	3750	3765	up	(dB)	
70	QPSK	1	1	24.50	24.47	24.58	25.4	0.0	
Channel				648668	650000	651334	up	MPR	
Frequency (MHz)				3730.02	3750	3770.01	up	(dB)	
60	QPSK	1	1	24.52	24.56	24.52	25.4	0.0	
Channel				648334	650000	651668	up	MPR	
Frequency (MHz)				3725.01	3750	3775.02	up	(dB)	
50	QPSK	1	1	24.48	24.50	24.57	25.4	0.0	
Channel				648000	650000	652000	up	MPR	
Frequency (MHz)				3720	3750	3780	up	(dB)	
40	QPSK	1	1	24.51	24.50	24.57	25.4	0.0	
Channel				647650	650000	652334	up	MPR	
Frequency (MHz)				3715.02	3750	3785.01	up	(dB)	
30	QPSK	1	1	24.54	24.52	24.48	25.4	0.0	
Channel				647500	650000	652500	up	MPR	
Frequency (MHz)				3712.5	3750	3787.5	up	(dB)	
25	QPSK	1	1	24.54	24.49	24.54	25.4	0.0	
Channel				647334	650000	652668	up	MPR	
Frequency (MHz)				3710.01	3750	3790.02	up	(dB)	
20	QPSK	1	1	24.57	24.54	24.51	25.4	0.0	
Channel				647168	650000	652834	up	MPR	
Frequency (MHz)				3707.52	3750	3792.51	up	(dB)	
15	QPSK	1	1	24.57	24.48	24.56	25.4	0.0	
Channel				647000	650000	653000	up	MPR	
Frequency (MHz)				3705	3750	3795	up	(dB)	
10	QPSK	1	1	24.59	24.49	24.49	25.4	0.0	

Part27Q n78 Ant10 DSI5									
BW (MHz)	Modulat ion	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune- up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3500.01					
100	1/2 BPSK	1	1		21.27				
100	1/2 BPSK	1	137		21.26		22.4	0.0	
100	1/2 BPSK	1	271		21.20				
100	1/2 BPSK	135	0		21.26		22.4	0.0	
100	1/2 BPSK	135	69		21.21		22.4	0.0	
100	1/2 BPSK	135	138		21.27		22.4	0.0	
100	1/2 BPSK	270	0		21.24				
100	QPSK	1	1		21.31				
100	QPSK	1	137		21.19		22.4	0.0	
100	QPSK	1	271		21.20				
100	QPSK	135	0		21.23		22.4	0.0	
100	QPSK	135	69		21.28		22.4	0.0	
100	QPSK	135	138		21.20		22.4	0.0	
100	QPSK	270	0		21.20				
100	16QAM	1	1		21.21		22.4	0.0	
100	64QAM	1	1		21.21		22.4	0.0	
100	256QAM	1	1		19.21		20.4	2.0	
Channel				633000	633334	633668	up	MPR	
Frequency (MHz)				3495	3500.01	3505.02	up	(dB)	
90	QPSK	1	1	21.10	21.15	21.16	22.4	0.0	
Channel				632668	633334	634000	up	MPR	
Frequency (MHz)				3490.02	3500.01	3510	up	(dB)	
80	QPSK	1	1	21.08	21.15	21.17	22.4	0.0	
Channel				632334	633334	634334	up	MPR	
Frequency (MHz)				3485.01	3500.01	3515.01	up	(dB)	
70	QPSK	1	1	21.06	21.06	21.09	22.4	0.0	
Channel				632000	633334	634668	up	MPR	
Frequency (MHz)				3480	3500.01	3520.02	up	(dB)	
60	QPSK	1	1	21.08	21.13	21.10	22.4	0.0	
Channel				631668	633334	635000	up	MPR	
Frequency (MHz)				3475.02	3500.01	3525	up	(dB)	
50	QPSK	1	1	21.16	21.11	21.15	22.4	0.0	
Channel				631334	633334	635334	up	MPR	
Frequency (MHz)				3470.01	3500.01	3530.01	up	(dB)	
40	QPSK	1	1	21.08	21.07	21.10	22.4	0.0	
Channel				631000	633334	635668	up	MPR	
Frequency (MHz)				3465	3500.01	3535.02	up	(dB)	
30	QPSK	1	1	21.14	21.16	21.10	22.4	0.0	
Channel				630834	633334	635834	up	MPR	
Frequency (MHz)				3462.51	3500.01	3537.51	up	(dB)	
25	QPSK	1	1	21.08	21.06	21.17	22.4	0.0	
Channel				630668	633334	636000	up	MPR	
Frequency (MHz)				3460.02	3500.01	3540	up	(dB)	
20	QPSK	1	1	21.15	21.13	21.06	22.4	0.0	
Channel				630500	633334	636168	up	MPR	
Frequency (MHz)				3457.5	3500.01	3542.52	up	(dB)	
15	QPSK	1	1	21.13	21.19	21.13	22.4	0.0	
Channel				630334	633334	636334	up	MPR	
Frequency (MHz)				3455.01	3500.01	3545.01	up	(dB)	
10	QPSK	1	1	21.10	21.11	21.07	22.4	0.0	

2.4GHz WLAN				Ant 15 Full power Body-worn Standalone Hotspot Standalone Extremity Standalone		Ant 7 Full power Body-worn Standalone Hotspot Standalone Extremity Standalone		Ant15+7 Full power Body-worn Standalone Hotspot Standalone Extremity Standalone		Ant 15 Head Standalone		Ant 7 Head Standalone		Ant 15+7 Head Standalone		Duty Cycle %
Mode	Channel	Frequency (MHz)	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit
2.4GHz WLAN	802.11b 1Mbps	1	2412	19.39	20.00	19.66	20.00	22.54	23.00	17.98	18.50	18.25	18.50	21.12	21.50	97.04
		6	2437	19.42	20.00	19.48	20.00	22.46	23.00	18.00	18.50	18.06	18.50	21.06	21.50	
		11	2462	19.35	20.00	19.46	20.00	22.42	23.00	17.94	18.50	17.95	18.50	20.94	21.50	
	802.11g 6Mbps	1	2412	19.39	20.00	19.25	20.00	22.33	23.00	Not Required	18.50	Not Required	18.50	Not Required	21.50	99.40
		6	2437	19.34	20.00	19.09	20.00	22.23	23.00		18.50		18.50		21.50	
		11	2462	19.20	20.00	19.05	20.00	22.14	23.00		18.50		18.50		21.50	
	802.11n-HT20 MCS0	1	2412	17.71	18.50	17.72	18.50	20.73	21.50		18.50		18.50		21.50	100
		6	2437	17.79	18.50	17.59	18.50	20.70	21.50		18.50		18.50		21.50	
		11	2462	17.83	18.50	17.55	18.50	20.70	21.50		18.50		18.50		21.50	
	802.11n-HT40 MCS0	3	2422	17.08	18.00	17.25	18.00	20.18	21.00		18.00		18.00		21.00	100
		6	2437	17.05	18.00	16.97	17.50	20.02	21.00		18.00		17.50		21.00	
		9	2452	16.99	17.50	17.07	18.00	20.04	21.00		17.50		18.00		21.00	
	802.11ax-HE20 MCS0	1	2412	18.29	19.00	18.18	19.00	21.25	22.00		18.50		18.50		21.50	100
		6	2437	18.21	19.00	18.11	19.00	21.17	22.00		18.50		18.50		21.50	
		11	2462	18.05	19.00	18.09	19.00	21.08	22.00		18.50		18.50		21.50	
	802.11ax-HE40 MCS0	3	2422	17.13	18.00	17.33	18.00	20.24	21.00		18.00		18.00		21.00	100
		6	2437	17.11	18.00	17.01	18.00	20.07	21.00		18.00		18.00		21.00	
		9	2452	17.05	18.00	17.15	18.00	20.11	21.00		18.00		18.00		21.00	
	802.11be-ET20 MCS0	1	2412	18.34	19.00	18.26	19.00	21.31	22.00		18.50		18.50		21.50	100
		6	2437	18.27	19.00	18.19	19.00	21.24	22.00		18.50		18.50		21.50	
		11	2462	18.14	19.00	18.16	19.00	21.16	22.00		18.50		18.50		21.50	
	802.11be-ET40 MCS0	3	2422	17.19	18.00	17.39	18.00	20.30	21.00		18.00		18.00		21.00	100
		6	2437	17.17	18.00	17.07	18.00	20.13	21.00		18.00		18.00		21.00	
		9	2452	17.13	18.00	17.22	18.00	20.19	21.00		18.00		18.00		21.00	

5.2GHz WLAN				Ant 17 Full power Body-worn Standalone Hotspot Standalone Extremity Standalone		Ant 16 Full power Body-worn Standalone Hotspot Standalone Extremity Standalone		Ant 17+16 Full power Body-worn Standalone Hotspot Standalone Extremity Standalone		Ant 17 Head Standalone		Ant 16 Head Standalone		Ant 17+16 Head Standalone		
	Mode	Channel	Frequency (MHz)	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Duty Cycle
5.2GHz WLAN	802.11a 6Mbps	36	5180	19.44	19.50	18.51	19.50	22.01	22.50		16.00		16.00		19.00	99.32
		40	5200	19.30	19.50	18.63	19.50	21.99	22.50		16.00		16.00		19.00	
		44	5220	19.65	20.00	18.97	19.00	22.34	22.50		16.00		16.00		19.00	
		48	5240	19.09	19.50	18.52	19.50	21.83	22.50		16.00		16.00		19.00	
	802.11n-HT20 MCS0	36	5180	19.30	20.00	18.24	19.00	21.81	22.50		16.00		16.00		19.00	100
		40	5200	19.07	20.00	18.30	19.00	21.71	22.50		16.00		16.00		19.00	
		44	5220	18.93	19.50	18.17	19.00	21.58	22.50		16.00		16.00		19.00	
		48	5240	18.93	19.50	18.20	19.00	21.59	22.50		16.00		16.00		19.00	
	802.11n-HT40 MCS0	38	5190	18.13	19.00	17.22	18.00	20.71	21.50	Not Required	16.00	Not Required	16.00	Not Required	19.00	100
		46	5230	17.83	18.50	17.13	18.00	20.50	21.00		16.00		16.00		19.00	
	802.11ac-VHT20 MCS0	36	5180	19.39	20.00	18.28	19.00	21.88	22.50		16.00		16.00		19.00	100
		40	5200	19.13	20.00	18.36	19.00	21.77	22.50		16.00		16.00		19.00	
		44	5220	19.02	20.00	18.26	19.00	21.67	22.50		16.00		16.00		19.00	
		48	5240	19.02	20.00	18.27	19.00	21.67	22.50		16.00		16.00		19.00	
	802.11ac-VHT40 MCS0	38	5190	18.21	19.00	17.27	18.00	20.78	21.50		16.00		16.00		19.00	100
		46	5230	17.89	18.50	17.16	18.00	20.55	21.50		16.00		16.00		19.00	
	802.11ac-VHT80 MCS0	42	5210	16.67	17.50	16.12	17.00	19.41	20.00	15.50	16.00	15.21	16.00	18.48	19.00	100
	802.11ax-HE20 MCS0	36	5180	19.45	20.00	18.33	19.00	21.94	22.50		16.00		16.00		19.00	100
		40	5200	19.20	20.00	18.41	19.00	21.83	22.50		16.00		16.00		19.00	
		44	5220	19.07	20.00	18.33	19.00	21.73	22.50		16.00		16.00		19.00	
		48	5240	19.05	20.00	18.33	19.00	21.72	22.50		16.00		16.00		19.00	
	802.11ax-HE40 MCS0	38	5190	18.24	19.00	17.30	18.00	20.81	21.50		16.00		16.00		19.00	100
		46	5230	17.97	18.50	17.22	18.00	20.62	21.50		16.00		16.00		19.00	
	802.11ax-HE80 MCS0	42	5210	16.72	17.50	16.19	17.00	19.47	20.00	Not Required	16.00	Not Required	16.00	Not Required	19.00	100
	802.11be-EHT20 MCS0	36	5180	19.52	20.00	18.38	19.00	22.00	22.50		16.00		16.00		19.00	100
		40	5200	19.25	20.00	18.47	19.00	21.89	22.50		16.00		16.00		19.00	
		44	5220	19.12	20.00	18.37	19.00	21.77	22.50		16.00		16.00		19.00	
		48	5240	19.11	20.00	18.38	19.00	21.77	22.50		16.00		16.00		19.00	
802.11be-EHT40 MCS0	38	5190	18.27	19.00	17.33	18.00	20.84	21.50		16.00		16.00		19.00	100	
	46	5230	18.04	19.00	17.29	18.00	20.69	21.50		16.00		16.00		19.00		
802.11be-EHT80 MCS0	42	5210	16.79	17.50	16.23	17.00	19.53	20.50		16.00		16.00		19.00	100	

5.5GHz WLAN				Ant 17 Full power Body-worn Standalone Extremity Standalone		Ant 16 Full power Body-worn Standalone Extremity Standalone		Ant 17+16 Full power Body-worn Standalone Extremity Standalone		Ant 17 Head Standalone		Ant 16 Head Standalone		Ant 17+16 Head Standalone		
	Mode	Channel	Frequency (MHz)	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Duty Cycle
5.5GHz WLAN	802.11a 6Mbps	100	5500	18.89	19.50	18.45	19.00	21.69	22.50		16.50		16.50		19.50	99.32
		116	5580	18.90	19.50	18.65	19.50	21.79	22.50		16.50		16.50		19.50	
		124	5620	18.95	19.50	18.62	19.50	21.80	22.50		16.50		16.50		19.50	
		132	5660	19.00	19.50	18.70	19.50	21.87	22.50		16.50		16.50		19.50	
		140	5700	18.91	19.50	18.51	19.50	21.73	22.50		16.50		16.50		19.50	
		144	5720	19.07	20.00	18.46	19.00	21.79	22.50		16.50		16.50		19.50	
	802.11n-HT20 MCS0	100	5500	19.08	20.00	18.57	19.50	21.84	22.50		16.50		16.50		19.50	100
		116	5580	18.79	19.50	18.34	19.00	21.58	22.50		16.50		16.50		19.50	
		124	5620	18.88	19.50	18.26	19.00	21.59	22.50		16.50		16.50		19.50	
		132	5660	18.84	19.50	18.47	19.00	21.67	22.50		16.50		16.50		19.50	
		140	5700	18.81	19.50	18.34	19.00	21.59	22.50		16.50		16.50		19.50	
		144	5720	18.38	19.00	17.73	18.50	21.08	22.00		16.50		16.50		19.50	
	802.11n-HT40 MCS0	102	5510	18.12	19.00	17.56	18.50	20.86	21.50		16.50		16.50		19.50	100
		110	5550	18.05	19.00	17.67	18.50	20.87	21.50	Not Required	16.50	Not Required	16.50	Not Required	19.50	
		126	5630	18.05	19.00	17.47	18.00	20.78	21.50		16.50		16.50		19.50	
		134	5670	18.04	19.00	17.52	18.50	20.80	21.50		16.50		16.50		19.50	
		142	5710	17.52	18.50	17.00	17.50	20.28	21.00		16.50		16.50		19.50	
		100	5500	19.17	20.00	18.63	19.50	21.92	22.50		16.50		16.50		19.50	
	802.11ac-VHT20 MCS0	116	5580	18.85	19.50	18.41	19.00	21.65	22.50		16.50		16.50		19.50	100
		124	5620	18.95	19.50	18.34	19.00	21.67	22.50		16.50		16.50		19.50	
		132	5660	18.89	19.50	18.51	19.50	21.71	22.50		16.50		16.50		19.50	
		140	5700	18.87	19.50	18.39	19.00	21.65	22.50		16.50		16.50		19.50	
		144	5720	18.45	19.00	17.82	18.50	21.16	22.00		16.50		16.50		19.50	
		102	5510	18.18	19.00	17.63	18.15	20.92	21.50		16.50		16.50		19.50	
	802.11ac-VHT40 MCS0	110	5550	18.09	19.00	17.73	18.50	20.92	21.50		16.50		16.50		19.50	100
		126	5630	18.10	19.00	17.52	18.50	20.83	21.50		16.50		16.50		19.50	
		134	5670	18.08	19.00	17.58	18.50	20.85	21.50		16.50		16.50		19.50	
		142	5710	17.57	18.50	17.07	18.00	20.34	21.00		16.50		16.50		19.50	
		106	5530	16.94	17.50	16.73	17.50	19.85	20.50	15.87	16.50	15.77	16.50	18.80	19.50	
		122	5610	16.67	17.50	16.48	17.00	19.59	20.50	15.77	16.50	16.02	16.50	18.58	19.50	
	802.11ac-VHT80 MCS0	138	5690	16.78	17.50	16.41	17.00	19.61	20.50	15.82	16.50	15.97	16.50	18.65	19.50	100
	802.11ac-VHT160 MCS0	114	5570	15.54	16.50	15.28	16.00	18.42	19.00		16.50		16.00		19.00	
		100	5500	19.23	20.00	18.70	19.50	21.98	22.50		16.50		16.50		19.50	
		116	5580	18.91	19.50	18.47	19.00	21.71	22.50		16.50		16.50		19.50	
		124	5620	18.99	19.50	18.41	19.00	21.72	22.50		16.50		16.50		19.50	
		132	5660	18.95	19.50	18.55	19.50	21.76	22.50		16.50		16.50		19.50	
		140	5700	18.94	19.50	18.43	19.00	21.70	22.50		16.50		16.50		19.50	
	802.11ax-HE20 MCS0	144	5720	18.51	19.50	17.88	18.50	21.22	22.00		16.50		16.50		19.50	
		102	5510	18.22	19.00	17.71	18.50	20.98	21.50		16.50		16.50		19.50	
		110	5550	18.12	19.00	17.79	18.50	20.97	21.50		16.50		16.50		19.50	
		126	5630	18.18	19.00	17.60	18.50	20.91	21.50		16.50		16.50		19.50	
		134	5670	18.14	19.00	17.64	18.50	20.91	21.50		16.50		16.50		19.50	
		142	5710	17.65	18.50	17.15	18.00	20.42	21.00		16.50		16.50		19.50	
	802.11ax-HE80 MCS0	106	5530	16.97	17.50	16.77	17.50	19.88	20.50		16.50		16.50		19.50	
		122	5610	16.72	17.50	16.51	17.50	19.63	20.50		16.50		16.50		19.50	
		138	5690	16.82	17.50	16.48	17.00	19.66	20.50		16.50		16.50		19.50	
		114	5570	15.58	16.50	15.32	16.00	18.46	19.00	Not Required	16.50	Not Required	16.00	Not Required	19.00	
	802.11ax-HE160 MCS0	100	5500	19.27	20.00	18.74	19.50	22.02	22.50		16.50		16.50		19.50	
		116	5580	18.98	19.50	18.53	19.50	21.77	22.50		16.50		16.50		19.50	
		124	5620	19.06	20.00	18.45	19.00	21.78	22.50		16.50		16.50		19.50	
		132	5660	19.02	20.00	18.62	19.50	21.83	22.50		16.50		16.50		19.50	
		140	5700	18.99	19.50	18.47	19.00	21.75	22.50		16.50		16.50		19.50	
		144	5720	18.58	19.50	17.94	18.50	21.28	22.00		16.50		16.50		19.50	
	802.11be-EHT20 MCS0	102	5510	18.27	19.00	17.78	18.50	21.04	22.00		16.50		16.50		19.50	
		110	5550	18.19	19.00	17.84	18.50	21.03	22.00		16.50		16.50		19.50	
		126	5630	18.25	19.00	17.64	18.50	20.97	21.50		16.50		16.50		19.50	
		134	5670	18.17	19.00	17.69	18.50	20.95	21.50		16.50		16.50		19.50	
		142	5710	17.72	18.50	17.18	18.00	20.47	21.00		16.50		16.50		19.50	
		106	5530	17.02	18.00	16.81	17.50	19.93	20.50		16.50		16.50		19.50	
	802.11be-EHT80 MCS0	122	5610	16.79	17.50	16.54	17.50	19.68	20.50		16.50		16.50		19.50	
		138	5690	16.85	17.50	16.51	17.50	19.69	20.50		16.50		16.50		19.50	
		114	5570	15.63	16.50	15.37	16.00	18.51	19.00		16.50		16.00		19.00	
		114	5570	15.63	16.50	15.37	16.00	18.51	19.00		16.50		16.00		19.00	

5.8GHz WLAN				Ant 17 Full power Body-worn Standalone Extremity Standalone		Ant 16 Full power Body-worn Standalone Extremity Standalone		Ant 17+16 Full power Body-worn Standalone Extremity Standalone		Ant 17 Head Standalone		Ant 16 Head Standalone		Ant 17+16 Head Standalone		Ant 17 Hotspot Standalone		Ant 16 Hotspot Standalone		Ant 17+16 Hotspot Standalone			
	Mode	Channel	Frequency (MHz)	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Duty Cycle %	
5.8GHz WLAN	802.11a 6Mbps	149	5745	19.52	20.00	18.98	19.50	22.27	23.00		17.00		16.50		20.00	18.51	19.00	17.98	18.50	21.22	22.00	99.32	
		157	5785	19.45	20.00	18.96	19.50	22.22	23.00		17.00		16.50		20.00	18.46	19.00	17.93	18.50	21.17	22.00		
		165	5825	19.49	20.00	19.09	19.50	22.31	23.00		17.00		16.50		20.00	18.49	19.00	18.04	18.50	21.23	22.00		
	802.11n-HT20 MCS0	149	5745	18.37	19.00	17.74	18.50	21.06	22.00		17.00		16.50		20.00		19.00			18.50	22.00	100	
		157	5785	18.36	19.00	17.81	18.50	21.10	22.00		17.00		16.50		20.00		19.00			18.50	22.00		
		165	5825	18.39	19.00	17.80	18.50	21.12	22.00		17.00		16.50		20.00		19.00			18.50	22.00		
	802.11n-HT40 MCS0	151	5755	17.58	18.50	16.98	17.50	20.30	21.00	Not Required	17.00	Not Required	16.50	Not Required	20.00	18.50	17.50			18.50	21.00	100	
		159	5795	17.48	18.00	17.02	18.00	20.27	21.00		17.00		16.50		20.00	18.00	18.00			18.50	21.00		
		149	5745	18.42	19.00	17.81	18.50	21.14	22.00		17.00		16.50		20.00	19.00	18.50			18.50	22.00		
	802.11ac-VHT20 MCS0	157	5785	18.44	19.00	17.90	18.50	21.19	22.00		17.00		16.50		20.00	19.00	18.50			18.50	22.00	100	
		165	5825	18.43	19.00	17.88	18.50	21.17	22.00		17.00		16.50		20.00	19.00	18.50			18.50	22.00		
		151	5755	17.63	18.50	17.03	18.00	20.35	21.00		17.00		16.50		20.00	18.50	18.00			18.50	21.00		
	802.11ac-VHT40 MCS0	159	5795	17.54	18.50	17.05	18.00	20.31	21.00		17.00		16.50		20.00	18.50	18.00			18.50	21.00	100	
	802.11ac-VHT80 MCS0	155	5775	16.33	17.00	15.92	16.50	19.14	20.00	16.33	17.00	15.92	16.50	19.14	20.00		17.00			16.50	20.00	100	
	802.11ax-HE20 MCS0	149	5745	18.50	19.00	17.88	18.50	21.21	22.00		17.00		16.50		20.00	Not Required	19.00	Not Required		18.50	Not Required	22.00	100
		157	5785	18.47	19.00	17.96	18.50	21.23	22.00		17.00		16.50		20.00		19.00			18.50	22.00		
		165	5825	18.46	19.00	17.93	18.50	21.21	22.00		17.00		16.50		20.00		19.00			18.50	22.00		
	802.11ax-HE40 MCS0	151	5755	17.70	18.50	17.07	18.00	20.41	21.00		17.00		16.50		20.00	18.50	18.00			18.50	21.00	100	
		159	5795	17.60	18.50	17.08	18.00	20.36	21.00		17.00		16.50		20.00	18.50	18.00			18.50	21.00		
	802.11ax-HE80 MCS0	155	5775	16.37	17.00	15.94	16.50	19.17	20.00		17.00		16.50		20.00	17.00	16.50			18.50	20.00	100	
802.11be-EHT20 MCS0	149	5745	18.54	19.50	17.95	18.50	21.27	22.00		17.00	Not Required	16.50	Not Required	20.00	19.00	18.50			18.50	22.00	100		
	157	5785	18.51	19.50	18.01	19.00	21.28	22.00		17.00		16.50		20.00	19.00	18.50			18.50	22.00			
	165	5825	18.51	19.50	17.98	18.50	21.26	22.00		17.00		16.50		20.00	19.00	18.50			18.50	22.00			
802.11be-EHT40 MCS0	151	5755	17.75	18.50	17.14	18.00	20.47	21.00		17.00		16.50		20.00	18.50	18.00			18.50	21.00	100		
	159	5795	17.67	18.50	17.12	18.00	20.41	21.00		17.00		16.50		20.00	18.50	18.00			18.50	21.00			
802.11be-EHT80 MCS0	155	5775	16.43	17.00	15.96	16.50	19.21	20.00		17.00		16.50		20.00	17.00	16.50			18.50	20.00	100		

BT BR/EDR

Mode	Channel	Frequency (MHz)	Ant15 Full power			
			Average power (dBm)			Tune-up Limit
BR / EDR	CH 00	2402	15.73	13.28	13.28	17.50
	CH 39	2441	16.22	13.99	13.97	17.50
	CH 76	2480	15.70	13.58	13.44	17.50

BLE_1M

Mode	Channel	Frequency (MHz)	Ant15 Full power	
			Average power (dBm)	
LE	CH 00	2402	8.07	
	CH 19	2440	8.34	
	CH 39	2480	8.08	
Tune-up Limit			10.00	

BLE_2M

Mode	Channel	Frequency (MHz)	Ant15 Full power	
			Average power (dBm)	
LE	CH 00	2402	8.18	
	CH 19	2440	8.44	
	CH 39	2480	8.16	
Tune-up Limit			10.00	

BT BR/EDR

Mode	Channel	Frequency (MHz)	Ant15 Full power			
			Average power (dBm)			Tune-up Limit
BR / EDR	CH 00	2402	11.08	7.34	7.30	12.50
	CH 39	2441	11.78	8.17	8.15	12.50
	CH 76	2480	11.50	7.67	7.60	12.50

BT BR/EDR

Mode	Channel	Frequency (MHz)	Ant15+7 Full power			
			Average power (dBm)			Tune-up Limit
BR / EDR	CH 00	2402	14.81	11.45	11.38	16.50
	CH 39	2441	14.90	11.23	20.00	16.50
	CH 76	2480	14.80	11.05	11.09	16.50

BT BR/EDR

Mode	Channel	Frequency (MHz)	Ant7 Full power			
			Average power (dBm)			Tune-up Limit
BR / EDR	CH 00	2402	15.77	13.26	13.39	17.00
	CH 39	2441	15.61	12.79	12.88	17.00
	CH 76	2480	14.97	12.67	12.73	16.50

BLE_1M

Mode	Channel	Frequency (MHz)	Ant7 Full power	
			Average power (dBm)	
LE	CH 00	2402	9.39	
	CH 19	2440	8.48	
	CH 39	2480	8.26	
Tune-up Limit			10.00	

BLE_2M

Mode	Channel	Frequency (MHz)	Ant7 Full power	
			Average power (dBm)	
LE	CH 00	2402	9.31	
	CH 19	2440	8.55	
	CH 39	2480	8.36	
Tune-up Limit			10.00	

BT

BT BR/EDR

Mode	Channel	Frequency (MHz)	Ant7 Full power			
			Average power (dBm)			Tune-up Limit
BR / EDR	CH 00	2402	12.41	9.32	9.24	13.50
	CH 39	2441	12.00	8.27	8.20	13.50
	CH 76	2480	12.06	8.38	8.51	13.50