



REPORT No.: SZ24090048S01

Annex H SAR Test Results List

Plot No.	Band	Modulation	RB Size	RB offset	Mode	Test Position	Gap (mm)	Sensor on or off	Power Reduction	Ch.	Average Power (dBm)	Time-Up (dBm)	Time-up (dBm)	Duty Cycle Factor	Power (dBm)	Measured 1g SAR (W/kg)	Reported 1g SAR (W/kg)	ANT	Note
18	WCDMA Band II	-	-	-	RMC 12.2Kbps	Bottom Face	16mm	Sensor off	Full Power	6062	23.88	25.00	1.294	1.000	-0.09	0.358	0.463	ANT 4	
	WCDMA Band II	-	-	-	RMC 12.2Kbps	Edge 1	16mm	Sensor off	Full Power	6062	23.88	25.00	1.294	1.000	0.01	0.169	0.219	ANT 4	
	WCDMA Band II	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	6062	16.88	18.00	1.294	1.000	0.09	0.730	0.845	ANT 4	
	WCDMA Band II	-	-	-	RMC 12.2Kbps	Edge 1	0mm	Sensor on	Reduced Power Level 1	6062	16.88	18.00	1.294	1.000	0.05	0.312	0.404	ANT 4	
	WCDMA Band II	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	9400	16.64	18.00	1.368	1.000	0.02	0.602	0.905	ANT 4	
28	WCDMA Band IV	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	9538	16.51	18.00	1.409	1.000	0.05	0.645	0.909	ANT 4	
	WCDMA Band IV	-	-	-	RMC 12.2Kbps	Edge 1	16mm	Sensor off	Full Power	1513	23.65	25.00	1.365	1.000	0.06	0.462	0.630	ANT 4	
	WCDMA Band IV	-	-	-	RMC 12.2Kbps	Edge 1	16mm	Sensor off	Full Power	1513	23.65	25.00	1.365	1.000	0.03	0.251	0.343	ANT 4	
	WCDMA Band IV	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	1513	16.15	17.50	1.365	1.000	0.02	0.843	1.180	ANT 4	
	WCDMA Band IV	-	-	-	RMC 12.2Kbps	Edge 1	0mm	Sensor on	Reduced Power Level 1	1513	16.15	17.50	1.365	1.000	0.01	0.425	0.580	ANT 4	
32	WCDMA Band IV	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	1312	15.89	17.50	1.449	1.000	0.03	0.744	1.076	ANT 4	
	WCDMA Band IV	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	1413	15.97	17.50	1.422	1.000	0.03	0.752	1.070	ANT 4	
	WCDMA Band V	-	-	-	RMC 12.2Kbps	Bottom Face	31mm	Sensor off	Full Power	4182	23.73	24.50	1.194	1.000	-0.05	0.128	0.153	ANT 1	
	WCDMA Band V	-	-	-	RMC 12.2Kbps	Edge 3	31mm	Sensor off	Full Power	4182	23.73	24.50	1.194	1.000	0.02	0.077	0.092	ANT 1	
	WCDMA Band V	-	-	-	RMC 12.2Kbps	Edge 4	31mm	Sensor off	Full Power	4182	23.73	24.50	1.194	1.000	0.03	0.089	0.106	ANT 1	
33	WCDMA Band V	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	4182	21.23	22.00	1.194	1.000	0	0.931	1.112	ANT 1	
	WCDMA Band V	-	-	-	RMC 12.2Kbps	Edge 3	0mm	Sensor on	Reduced Power Level 1	4182	21.23	22.00	1.194	1.000	0.05	0.611	0.730	ANT 1	
	WCDMA Band V	-	-	-	RMC 12.2Kbps	Edge 4	0mm	Sensor on	Reduced Power Level 1	4182	21.23	22.00	1.194	1.000	0.02	0.634	0.757	ANT 1	
	WCDMA Band V	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	4132	21.18	22.00	1.208	1.000	0.04	0.865	1.045	ANT 1	
	WCDMA Band V	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	4233	21.21	22.00	1.199	1.000	0.03	0.852	1.022	ANT 1	
44	WCDMA Band XIX	-	-	-	RMC 12.2Kbps	Bottom Face	31mm	Sensor off	Full Power	387	23.70	24.50	1.202	1.000	0.03	0.136	0.164	ANT 1	
	WCDMA Band XIX	-	-	-	RMC 12.2Kbps	Edge 3	31mm	Sensor off	Full Power	387	23.70	24.50	1.202	1.000	0.02	0.080	0.096	ANT 1	
	WCDMA Band XIX	-	-	-	RMC 12.2Kbps	Edge 4	31mm	Sensor off	Full Power	387	23.70	24.50	1.202	1.000	0.01	0.092	0.111	ANT 1	
	WCDMA Band XIX	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	387	21.20	22.00	1.202	1.000	0	0.939	1.129	ANT 1	
	WCDMA Band XIX	-	-	-	RMC 12.2Kbps	Edge 3	0mm	Sensor on	Reduced Power Level 1	387	21.20	22.00	1.202	1.000	0.01	0.622	0.748	ANT 1	
45	WCDMA Band XIX	-	-	-	RMC 12.2Kbps	Edge 4	0mm	Sensor on	Reduced Power Level 1	387	21.20	22.00	1.202	1.000	0.02	0.655	0.847	ANT 1	
	WCDMA Band XIX	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	412	21.15	22.00	1.216	1.000	0.05	0.844	1.026	ANT 1	
	WCDMA Band XIX	-	-	-	RMC 12.2Kbps	Bottom Face	0mm	Sensor on	Reduced Power Level 1	437	21.09	22.00	1.233	1.000	0.06	0.859	1.059	ANT 1	
	LTE Band 7	QPSK	1	0	-	Bottom Face	16mm	Sensor off	Full Power	21350	23.86	25.00	1.300	1.000	-0.06	0.387	0.484	ANT 3 ENDC	
	LTE Band 7	QPSK	1	0	-	Edge 3	16mm	Sensor off	Full Power	21350	23.86	25.00	1.300	1.000	0.1	0.162	0.211	ANT 3 ENDC	
46	LTE Band 7	QPSK	1	0	-	Edge 4	16mm	Sensor off	Full Power	21350	23.86	25.00	1.300	1.000	0.08	0.101	0.131	ANT 3 ENDC	
	LTE Band 7	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	21350	5.86	7.00	1.300	1.000	0.12	0.284	0.369	ANT 3 ENDC	
	LTE Band 7	QPSK	1	0	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	21350	5.86	7.00	1.300	1.000	0.09	0.100	0.130	ANT 3 ENDC	
	LTE Band 7	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	20850	9.71	7.00	1.346	1.000	-0.01	0.390	0.525	ANT 3 ENDC	
	LTE Band 7	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	21100	5.74	7.00	1.337	1.000	0.06	0.387	0.517	ANT 3 ENDC	
47	LTE Band 7	QPSK	50	0	-	Bottom Face	16mm	Sensor off	Full Power	21350	23.04	24.00	1.247	1.000	0.03	0.286	0.387	ANT 3 ENDC	
	LTE Band 7	QPSK	50	0	-	Edge 3	16mm	Sensor off	Full Power	21350	23.04	24.00	1.247	1.000	-0.14	0.130	0.162	ANT 3 ENDC	
	LTE Band 7	QPSK	50	0	-	Edge 4	16mm	Sensor off	Full Power	21350	23.04	24.00	1.247	1.000	0.08	0.099	0.123	ANT 3 ENDC	
	LTE Band 7	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	21350	5.04	6.00	1.247	1.000	0.07	0.280	0.350	ANT 3 ENDC	
	LTE Band 7	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	20850	4.94	6.00	1.276	1.000	-0.08	0.312	0.398	ANT 3 ENDC	
48	LTE Band 7	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	21100	4.96	6.00	1.271	1.000	0.16	0.310	0.394	ANT 3 ENDC	
	LTE Band 7	QPSK	1	0	-	Bottom Face	22mm	Sensor off	Full Power	21350	23.86	25.00	1.300	1.000	-0.08	0.410	0.533	ANT 3	
	LTE Band 7	QPSK	1	0	-	Edge 1	21mm	Sensor off	Full Power	21350	23.86	25.00	1.300	1.000	0.09	0.146	0.186	ANT 3	
	LTE Band 7	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	21350	13.86	15.00	1.300	1.000	-0.09	0.914	1.081	ANT 3	
	LTE Band 7	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	20850	13.71	15.00	1.346	1.000	0.09	0.763	1.027	ANT 3	Repeat SAR
49	LTE Band 7	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	21100	13.74	15.00	1.337	1.000	0.03	0.860	1.149	ANT 3	
	LTE Band 7	QPSK	50	0	-	Bottom Face	22mm	Sensor off	Full Power	21350	23.04	24.00	1.247	1.000	-0.06	0.320	0.399	ANT 3	
	LTE Band 7	QPSK	50	0	-	Edge 1	21mm	Sensor off	Full Power	21350	23.04	24.00	1.247	1.000	0.19	0.328	0.332	ANT 3	
	LTE Band 7	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	21350	13.04	14.00	1.247	1.000	-0.15	0.895	1.116	ANT 3	
	LTE Band 7	QPSK	50	0	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	21350	13.04	14.00	1.247	1.000	0.05	0.290	0.362	ANT 3	
50	LTE Band 7	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	20850	12.94	14.00	1.276	1.000	0.11	0.744	0.950	ANT 3	
	LTE Band 7	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	21100	12.96	14.00	1.271	1.000	0.1	0.840	1.067	ANT 3	
	LTE Band 7	QPSK	100	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	21350	12.99	14.00	1.262	1.000	0.03	0.832	1.050	ANT 3	
	LTE Band 7	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	21350	9.86	11.00	1.300	1.000	-0.19	0.384	0.499	ANT 3	Simultaneous Transmission
	LTE Band 7	QPSK	1	0	-	Edge 1	0mm	Sensor on	Reduced Power Level 2	21350	9.86	11.00	1.300	1.000	-0.18	0.126	0.164	ANT 3	Simultaneous Transmission
51	LTE Band 7	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	20850	9.71	11.00	1.346	1.000	-0.14	0.320	0.431	ANT 3	Simultaneous Transmission
	LTE Band 7	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	21100	9.74	11.00	1.337	1.000	-0.06	0.361	0.483	ANT 3	Simultaneous Transmission
	LTE Band 7	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	21350	9.04	10.00	1.247	1.000	-0.04	0.376	0.469	ANT 3	Simultaneous Transmission
	LTE Band 7	QPSK	50	0	-	Edge 1	0mm	Sensor on	Reduced Power Level 2	21350	9.04	10.00	1.247	1.000	0.15	0.122	0.152	ANT 3	Simultaneous Transmission
	LTE Band 7	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	20850	8.84	10.00	1.276	1.000	0.07	0.313	0.400	ANT 3	Simultaneous Transmission
52	LTE Band 12	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	21100	8.96	10.00	1.271	1.000	0	0.353	0.449	ANT 3	Simultaneous Transmission
	LTE Band 12	QPSK	1	0	-	Bottom Face	31mm	Sensor off	Full Power	23095	23.92	25.00	1.282	1.000	-0.				

		LTE Band 25	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26590	8.71	10.00	1.346	1.000	0.14	0.369	0.487	ANT 3, ENDC
		LTE Band 25	QPSK	50	0	-	Bottom Face	16mm	Sensor off	Full Power	26140	22.95	24.00	1.274	1.000	-0.18	0.282	0.359	ANT 3, ENDC
		LTE Band 25	QPSK	50	0	-	Edge 3	16mm	Sensor off	Full Power	26140	22.95	24.00	1.274	1.000	0.16	0.210	0.267	ANT 3, ENDC
		LTE Band 25	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Full Power	26140	22.95	24.00	1.274	1.000	-0.07	0.135	0.172	ANT 3, ENDC
		LTE Band 25	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26140	17.35	9.00	1.274	1.000	0.09	0.309	0.394	ANT 3, ENDC
		LTE Band 25	QPSK	50	0	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	26140	7.95	9.00	1.274	1.000	-0.05	0.128	0.163	ANT 3, ENDC
		LTE Band 25	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26365	7.88	9.00	1.284	1.000	0.17	0.307	0.397	ANT 3, ENDC
		LTE Band 25	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26590	7.79	9.00	1.321	1.000	0.07	0.317	0.419	ANT 3, ENDC
		LTE Band 25	QPSK	1	0	-	Bottom Face	16mm	Sensor off	Full Power	26140	23.80	25.00	1.318	1.000	-0.01	0.317	0.418	ANT 4
		LTE Band 25	QPSK	1	0	-	Edge 1	16mm	Sensor off	Full Power	26140	23.80	25.00	1.318	1.000	-0.08	0.151	0.199	ANT 4
		LTE Band 25	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26140	17.30	18.50	1.318	1.000	0.09	0.735	0.960	ANT 4
		LTE Band 25	QPSK	1	0	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	26140	17.30	18.50	1.318	1.000	0.17	0.384	0.507	ANT 4
		LTE Band 25	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26365	17.28	18.50	1.324	1.000	0.08	0.725	0.960	ANT 4
		LTE Band 25	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26590	17.21	18.50	1.346	1.000	0.05	0.744	1.001	ANT 4
58		LTE Band 25	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26590	17.21	18.50	1.346	1.000	0.05	0.744	1.001	ANT 4
		LTE Band 25	QPSK	50	0	-	Bottom Face	16mm	Sensor off	Full Power	26140	22.95	24.00	1.274	1.000	0.01	0.254	0.323	ANT 4
		LTE Band 25	QPSK	50	0	-	Edge 1	16mm	Sensor off	Full Power	26140	22.95	24.00	1.274	1.000	-0.03	0.121	0.154	ANT 4
		LTE Band 25	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26140	16.45	17.50	1.274	1.000	0.12	0.722	0.919	ANT 4
		LTE Band 25	QPSK	50	0	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	26140	16.45	17.50	1.274	1.000	0.16	0.377	0.480	ANT 4
		LTE Band 25	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26365	16.38	17.50	1.294	1.000	0.05	0.712	0.921	ANT 4
		LTE Band 25	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26590	16.29	17.50	1.321	1.000	0.02	0.731	0.966	ANT 4
		LTE Band 25	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26140	14.30	15.50	1.318	1.000	0.19	0.380	0.501	ANT 4
		LTE Band 25	QPSK	1	0	-	Edge 1	0mm	Sensor on	Reduced Power Level 2	26140	14.30	15.50	1.318	1.000	0.13	0.200	0.264	ANT 4
		LTE Band 25	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26365	14.18	15.50	1.305	1.000	0.03	0.375	0.508	ANT 4
		LTE Band 25	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26590	14.11	15.50	1.377	1.000	-0.03	0.382	0.626	ANT 4
		LTE Band 25	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26140	13.45	14.50	1.274	1.000	0.14	0.368	0.489	ANT 4
		LTE Band 25	QPSK	50	0	-	Edge 1	0mm	Sensor on	Reduced Power Level 2	26140	13.45	14.50	1.274	1.000	-0.12	0.192	0.245	ANT 4
		LTE Band 25	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26365	13.38	14.50	1.294	1.000	-0.18	0.364	0.471	ANT 4
		LTE Band 25	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26590	13.29	14.50	1.321	1.000	0.08	0.375	0.495	ANT 4
		LTE Band 26	QPSK	1	0	-	Bottom Face	31mm	Sensor off	Full Power	26865	23.82	25.00	1.312	1.000	-0.02	0.136	0.178	ANT 1
		LTE Band 26	QPSK	1	0	-	Edge 3	31mm	Sensor off	Full Power	26865	23.82	25.00	1.312	1.000	-0.11	0.074	0.097	ANT 1
		LTE Band 26	QPSK	1	0	-	Edge 4	31mm	Sensor off	Full Power	26865	23.82	25.00	1.312	1.000	-0.16	0.085	0.112	ANT 1
		LTE Band 26	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26865	20.82	22.00	1.312	1.000	0.05	0.784	1.003	ANT 1
		LTE Band 26	QPSK	1	0	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	26865	20.82	22.00	1.312	1.000	0.03	0.370	0.748	ANT 1
		LTE Band 26	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	26865	20.82	22.00	1.312	1.000	0.04	0.557	0.731	ANT 1
		LTE Band 26	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26765	20.75	22.00	1.334	1.000	-0.09	0.756	1.008	ANT 1
		LTE Band 26	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26865	20.73	22.00	1.340	1.000	0.05	0.776	1.040	ANT 1
		LTE Band 26	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26965	20.73	22.00	1.340	1.000	0.03	0.357	0.476	ANT 1
		LTE Band 26	QPSK	36	0	-	Bottom Face	31mm	Sensor off	Full Power	26865	23.01	24.00	1.256	1.000	-0.09	0.107	0.134	ANT 1
		LTE Band 26	QPSK	36	0	-	Edge 3	31mm	Sensor off	Full Power	26865	23.01	24.00	1.256	1.000	-0.05	0.060	0.075	ANT 1
		LTE Band 26	QPSK	36	0	-	Edge 4	31mm	Sensor off	Full Power	26865	23.01	24.00	1.256	1.000	-0.17	0.069	0.087	ANT 1
		LTE Band 26	QPSK	36	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26865	20.01	21.00	1.256	1.000	-0.11	0.711	0.863	ANT 1
		LTE Band 26	QPSK	36	0	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	26865	20.01	21.00	1.256	1.000	-0.14	0.530	0.666	ANT 1
		LTE Band 26	QPSK	36	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	26865	20.01	21.00	1.256	1.000	-0.07	0.518	0.651	ANT 1
		LTE Band 26	QPSK	36	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26765	19.89	21.00	1.297	1.000	0.15	0.703	0.868	ANT 1
		LTE Band 26	QPSK	36	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26965	19.87	21.00	1.297	1.000	0.12	0.722	0.937	ANT 1
		LTE Band 26	QPSK	76	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	26865	20.03	21.00	1.250	1.000	0.04	0.701	0.876	ANT 1
		LTE Band 26	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26865	17.82	19.00	1.312	1.000	0.07	0.351	0.461	ANT 1
		LTE Band 26	QPSK	1	0	-	Edge 3	0mm	Sensor on	Reduced Power Level 2	26865	17.82	19.00	1.312	1.000	0.06	0.282	0.344	ANT 1
		LTE Band 26	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	26865	17.82	19.00	1.312	1.000	-0.05	0.256	0.336	ANT 1
		LTE Band 26	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26765	17.75	19.00	1.334	1.000	-0.17	0.348	0.464	ANT 1
		LTE Band 26	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26965	17.73	19.00	1.340	1.000	-0.19	0.357	0.478	ANT 1
		LTE Band 26	QPSK	36	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26865	17.01	18.00	1.256	1.000	-0.08	0.327	0.411	ANT 1
		LTE Band 26	QPSK	36	0	-	Edge 3	0mm	Sensor on	Reduced Power Level 2	26865	17.01	18.00	1.256	1.000	0.06	0.244	0.306	ANT 1
		LTE Band 26	QPSK	36	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	26865	17.01	18.00	1.256	1.000	-0.11	0.238	0.299	ANT 1
		LTE Band 26	QPSK	36	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26765	16.89	18.00	1.291	1.000	-0.09	0.323	0.407	ANT 1
		LTE Band 26	QPSK	36	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	26965	16.87	18.00	1.297	1.000	0.06	0.333	0.432	ANT 1
		LTE Band 30	QPSK	1	0	-	Bottom Face	16mm	Sensor off	Full Power	27710	23.61	25.00	1.377	1.000	-0.17	0.315	0.434	ANT 3, ENDC
		LTE Band 30	QPSK	1	0	-	Edge 1	16mm	Sensor off	Full Power	27710	23.61	25.00	1.377	1.000	0.12	0.373	0.515	ANT 3, ENDC
		LTE Band 30	QPSK	1	0	-	Edge 4	0mm	Sensor off	Full Power	27710	23.61	25.00	1.377	1.000	0.1	0.168	0.231	ANT 3, ENDC
		LTE Band 30	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	27710	6.61	8.00	1.377	1.000	0.07	0.362	0.499	ANT 3, ENDC
		LTE Band 30	QPSK	1	0	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	27710	6.61	8.00	1.377	1.000	0.14	0.116	0.160	ANT 3, ENDC
		LTE Band 30	QPSK	25	0	-	Bottom Face	16mm	Sensor off	Full Power	27710	22.67	24.00	1.358	1.000	0.13	0.268	0.364	ANT 3, ENDC
		LTE Band 30	QPSK	25	0	-	Edge 3	16mm	Sensor off	Full Power	27710	22.67	24.00	1.358	1.000	-0.06	0.195	0.265	ANT 3, ENDC
		LTE Band 30	QPSK	25	0	-	Edge 4	0mm	Sensor off	Full Power	27710	22.67	24.00	1.358	1.000	-0.11	0.134	0.182	ANT 3, ENDC
		LTE Band 30	QPSK	25	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	27710	5.67	7.00	1.358	1.000	-0.15	0.303	0.418	ANT 3, ENDC
		LTE Band 30	QPSK	25	0	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	27710	5.67	7.00	1.358	1.000	-0.11	0.099	0.134	ANT 3, ENDC
		LTE Band 30	QPSK	1	0	-	Bottom Face	22mm	Sensor off	Full Power	27710	23.61	25.00	1.377	1.000	-0.14	0.210	0.289	ANT 3
		LTE Band 30	QPSK	1	0	-	Edge 1	21mm	Sensor off	Full Power	27710	23.61	25.00	1.377	1.000	-0.04	0.194	0.264	ANT 3
		LTE Band 30	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	27710	15.11	16.50	1.377	1.000	-0.14	0.785	1.081	ANT 3
		LTE Band 30	QPSK	1	0	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	27710	15.11	16.50	1.377	1.000	-0.04	0.336	0.465	ANT 3
		LTE Band 30	QPSK	25	0	-	Bottom Face	22mm	Sensor off	Full Power	27710	22.67	24.00	1.358	1.000	-0.19	0.169	0.230	ANT 3
		LTE Band 30	QPSK	25	0	-	Edge 1	21mm	Sensor off	Full Power	27710	22.67	24.00	1.358	1.000	-0.15	0.112	0.152	ANT 3
		LTE Band 30	QPSK	25	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	27710	14.17	15.50	1.358	1.000	0.06	0.746	1.013	ANT 3
		LTE Band 30	QPSK	25															

	LTE Band 41	QPSK	1	0	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	40620	13.48	14.50	1.205	1.006	0.04	0.247	0.314	ANT 5	Simultaneous Transmission
	CA 41C	QPSK	1	0	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	40621	12.64	13.50	1.219	1.006	0.09	0.202	0.248	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	1	0	PC2	Edge 1	0mm	Sensor on	Reduced Power Level 2	40620	13.48	14.50	1.265	1.006	-0.05	0.093	0.118	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	1	0	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	39750	13.36	14.50	1.300	1.006	-0.1	0.183	0.239	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	40185	12.51	13.50	1.256	1.006	-0.12	0.187	0.253	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	1	0	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	41055	13.43	14.50	1.279	1.006	0.15	0.226	0.291	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	1	0	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	41490	13.31	14.50	1.315	1.006	0.01	0.232	0.307	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	40620	12.55	13.50	1.245	1.006	-0.04	0.230	0.288	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC2	Edge 1	0mm	Sensor on	Reduced Power Level 2	40620	12.55	13.50	1.245	1.006	0.06	0.089	0.111	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	39750	12.45	13.50	1.274	1.006	0.12	0.172	0.220	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	40185	12.51	13.50	1.256	1.006	-0.12	0.186	0.235	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	41055	12.51	13.50	1.256	1.006	0.14	0.214	0.270	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	41490	12.49	13.50	1.262	1.006	-0.01	0.219	0.278	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	1	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	40620	11.38	12.50	1.294	1.006	-0.09	0.375	0.468	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	1	0	PC3	Edge 1	0mm	Sensor on	Reduced Power Level 2	40620	11.38	12.50	1.294	1.006	0.18	0.144	0.187	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	1	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	39750	11.09	12.50	1.384	1.006	0.1	0.317	0.441	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	1	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	40185	11.26	12.50	1.330	1.006	0.16	0.350	0.468	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	1	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	41055	11.35	12.50	1.350	1.006	-0.02	0.361	0.473	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	1	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	41490	11.20	12.50	1.340	1.006	0.18	0.370	0.502	ANT 5	Simultaneous Transmission
	CA 41C	QPSK	1	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	41292	10.40	11.50	1.288	1.006	0.02	0.267	0.346	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	40620	10.63	11.50	1.222	1.006	0.14	0.352	0.433	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC3	Edge 1	0mm	Sensor on	Reduced Power Level 2	40620	10.63	11.50	1.222	1.006	0.15	0.136	0.167	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	39750	10.32	11.50	1.312	1.006	0.15	0.350	0.396	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	40185	10.42	11.50	1.250	1.006	0.02	0.358	0.413	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	41055	10.60	11.50	1.230	1.006	-0.05	0.359	0.420	ANT 5	Simultaneous Transmission
	LTE Band 41	QPSK	50	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	41490	10.50	11.50	1.259	1.006	-0.15	0.348	0.441	ANT 5	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Bottom Face	20mm	Sensor off	Full Power	59990	23.94	25.00	1.276	1.006	0.09	0.192	0.247	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Edge 3	0mm	Sensor off	Full Power	59990	23.94	25.00	1.276	1.006	0.05	0.123	0.158	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Edge 4	20mm	Sensor off	Full Power	59990	23.94	25.00	1.276	1.006	-0.11	0.401	0.515	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59990	12.84	14.00	1.276	1.006	-0.03	0.716	0.919	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59990	12.84	14.00	1.276	1.006	0.09	0.850	1.091	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59340	12.89	14.00	1.291	1.006	0.02	0.833	1.082	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59340	12.89	14.00	1.291	1.006	0.04	0.319	0.414	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59830	12.91	14.00	1.295	1.006	0.1	0.702	0.908	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59150	12.79	14.00	1.321	1.006	0.04	0.715	0.960	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59640	12.82	14.00	1.312	1.006	0.17	0.774	1.022	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	59340	12.89	14.00	1.291	1.006	0.03	0.824	1.070	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	59830	12.91	14.00	1.295	1.006	0.05	0.833	1.077	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	59150	12.79	14.00	1.321	1.006	0.12	0.846	1.125	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	59640	12.92	14.00	1.292	1.006	0.01	0.923	1.191	ANT 6	Simultaneous Transmission
139	LTE Band 48	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	59640	12.92	14.00	1.292	1.006	0.05	0.913	1.178	ANT 6	Repeat SAR
	CA 48C	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	59442	11.94	13.00	1.276	1.006	-0.04	0.751	0.964	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Bottom Face	20mm	Sensor off	Full Power	59990	23.18	24.00	1.208	1.006	-0.05	0.156	0.190	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Edge 3	0mm	Sensor off	Full Power	59990	23.18	24.00	1.208	1.006	0.02	0.098	0.119	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Edge 4	20mm	Sensor off	Full Power	59990	23.18	24.00	1.208	1.006	0.06	0.324	0.394	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59990	12.18	13.00	1.208	1.006	0.19	0.887	0.855	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59990	12.18	13.00	1.208	1.006	-0.09	0.816	0.991	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59340	12.01	13.00	1.256	1.006	-0.14	0.800	1.011	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59830	12.07	13.00	1.239	1.006	-0.13	0.674	0.840	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59150	11.84	13.00	1.276	1.006	-0.16	0.686	0.841	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	59640	11.95	13.00	1.274	1.006	-0.01	0.743	0.952	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	59340	12.01	13.00	1.256	1.006	-0.02	0.751	0.969	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	59830	12.07	13.00	1.239	1.006	0.04	0.800	0.997	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	59150	11.84	13.00	1.276	1.006	0.04	0.812	1.043	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	59640	11.95	13.00	1.274	1.006	0.09	0.889	1.191	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	100	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	59990	12.11	13.00	1.227	1.006	0.07	0.802	0.960	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	59990	8.94	10.00	1.276	1.006	-0.17	0.274	0.352	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Edge 3	0mm	Sensor on	Reduced Power Level 2	59150	10.00	10.00	1.276	1.006	-0.02	0.355	0.417	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	59340	8.89	10.00	1.291	1.006	-0.09	0.315	0.409	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	59830	8.91	10.00	1.285	1.006	0.06	0.319	0.412	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	59150	7.94	9.00	1.321	1.006	0.19	0.324	0.431	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	59640	8.95	10.00	1.292	1.006	0.12	0.353	0.455	ANT 6	Simultaneous Transmission
	CA 48C	QPSK	1	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	59442	7.94	9.00	1.276	1.006	0.01	0.263	0.338	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	59990	8.18	9.00	1.208	1.006	-0.13	0.263	0.320	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Edge 3	0mm	Sensor on	Reduced Power Level 2	59990	8.18	9.00	1.208	1.006	-0.12	0.312	0.379	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	59340	8.01	9.00	1.256	1.006	0.12	0.303	0.383	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	59830	8.07	9.00	1.239	1.006	0	0.306	0.381	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	59150	7.94	9.00	1.276	1.006	0.16	0.311	0.399	ANT 6	Simultaneous Transmission
	LTE Band 48	QPSK	50	0	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	59640	7.95	9.00	1.274	1.006	-0.15	0.344	0.441	ANT 6	Simultaneous Transmission
	LTE Band 66	QPSK	1	0	-	Bottom Face	16mm	Sensor off	Full Power	132572	23.94	25.00	1.276	1.006	0.11	0.391	0.499	ANT 3 ENDC	Simultaneous Transmission
	LTE Band 66	QPSK	1	0	-	Edge 3	16mm	Sensor off	Full Power	132572	23.94	25.00	1.276	1.006	-0.02	0.242	0.309	ANT 3 ENDC	Simultaneous Transmission
	LTE Band 66	QPSK	1	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	132572	23.94	25.00	1.276	1.006	-0.06	0.301			

	5G NR n2	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	380000	6.38	8.00	1.452	1.000	0.03	0.162	0.235	ANT 3, ENDC	
	5G NR n2	DFT-S-QPSK	1	1	-	Bottom Face	16mm	Sensor off	Full Power	376000	23.75	25.00	1.334	1.000	0.03	0.301	0.401	ANT 4	
	5G NR n2	DFT-S-QPSK	1	1	-	Edge 1	16mm	Sensor off	Full Power	376000	23.75	25.00	1.334	1.000	0.04	0.155	0.207	ANT 4	
	5G NR n2	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	376000	15.73	17.00	1.334	1.000	0	0.793	1.087	ANT 4	
	5G NR n2	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	376000	15.73	17.00	1.334	1.000	0.03	0.338	0.435	ANT 4	
	5G NR n2	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	372000	15.65	17.00	1.365	1.000	0.04	0.745	1.017	ANT 4	
	5G NR n2	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	380000	15.41	17.00	1.442	1.000	0.02	0.723	1.043	ANT 4	
	5G NR n2	DFT-S-QPSK	50	1	-	Bottom Face	16mm	Sensor off	Full Power	376000	23.73	25.00	1.340	1.000	0.01	0.234	0.313	ANT 4	
	5G NR n2	DFT-S-QPSK	50	1	-	Edge 1	16mm	Sensor off	Full Power	376000	23.73	25.00	1.340	1.000	0.03	0.111	0.149	ANT 4	
	5G NR n2	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	376000	15.73	17.00	1.340	1.000	0.04	0.512	0.686	ANT 4	
	5G NR n2	DFT-S-QPSK	50	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	376000	15.73	17.00	1.340	1.000	0.05	0.241	0.323	ANT 4	
	5G NR n2	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	372000	15.65	17.00	1.368	1.000	0.06	0.637	0.857	ANT 4	
	5G NR n2	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	380000	15.38	17.00	1.452	1.000	0.02	0.471	0.684	ANT 4	
	5G NR n2	DFT-S-QPSK	100	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	376000	15.62	17.00	1.374	1.000	0.09	0.485	0.666	ANT 4	
	5G NR n2	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	376000	11.75	13.00	1.334	1.000	0.09	0.309	0.412	ANT 4	Simultaneous Transmission
	5G NR n2	DFT-S-QPSK	1	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 2	376000	11.75	13.00	1.334	1.000	-0.05	0.134	0.179	ANT 4	Simultaneous Transmission
	5G NR n2	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	372000	11.65	13.00	1.365	1.000	0.02	0.259	0.353	ANT 4	Simultaneous Transmission
	5G NR n2	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	380000	11.41	13.00	1.442	1.000	-0.11	0.288	0.386	ANT 4	Simultaneous Transmission
	5G NR n2	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	376000	11.73	13.00	1.340	1.000	0.03	0.212	0.284	ANT 4	Simultaneous Transmission
	5G NR n2	DFT-S-QPSK	50	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 2	376000	11.73	13.00	1.340	1.000	0.04	0.071	0.095	ANT 4	Simultaneous Transmission
	5G NR n2	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	372000	11.64	13.00	1.368	1.000	0.04	0.189	0.258	ANT 4	Simultaneous Transmission
	5G NR n2	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	380000	11.38	13.00	1.452	1.000	0.02	0.192	0.279	ANT 4	Simultaneous Transmission
	5G NR n5	DFT-S-QPSK	1	1	-	Bottom Face	31mm	Sensor off	Full Power	167300	23.68	25.00	1.355	1.000	0.02	0.258	0.350	ANT 1	
	5G NR n5	DFT-S-QPSK	1	1	-	Edge 3	31mm	Sensor off	Full Power	167300	23.68	25.00	1.355	1.000	0.01	0.122	0.165	ANT 1	
	5G NR n5	DFT-S-QPSK	1	1	-	Edge 1	31mm	Sensor off	Full Power	167200	23.65	25.00	1.356	1.000	0.04	0.129	0.175	ANT 1	
	5G NR n5	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	167200	18.68	20.00	1.355	1.000	0.02	0.897	1.203	ANT 1	
	5G NR n5	DFT-S-QPSK	1	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	167300	18.68	20.00	1.355	1.000	0.03	0.321	0.435	ANT 1	
	5G NR n5	DFT-S-QPSK	1	1	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	167300	18.68	20.00	1.355	1.000	0.03	0.342	0.463	ANT 1	
	5G NR n5	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	166800	18.65	20.00	1.360	1.000	-0.08	0.834	1.085	ANT 1	
	5G NR n5	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	167600	18.62	20.00	1.374	1.000	0.04	0.845	1.086	ANT 1	
	5G NR n5	DFT-S-QPSK	50	1	-	Bottom Face	31mm	Sensor off	Full Power	167300	23.62	25.00	1.374	1.000	0.03	0.177	0.243	ANT 1	
	5G NR n5	DFT-S-QPSK	50	1	-	Edge 3	31mm	Sensor off	Full Power	167300	23.62	25.00	1.374	1.000	0.09	0.085	0.117	ANT 1	
	5G NR n5	DFT-S-QPSK	50	1	-	Edge 1	31mm	Sensor off	Full Power	167300	23.62	25.00	1.374	1.000	0.07	0.089	0.122	ANT 1	
	5G NR n5	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	167300	18.62	20.00	1.374	1.000	0.05	0.425	0.584	ANT 1	
	5G NR n5	DFT-S-QPSK	50	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	167300	18.62	20.00	1.374	1.000	0.03	0.211	0.290	ANT 1	
	5G NR n5	DFT-S-QPSK	50	1	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	167300	18.62	20.00	1.374	1.000	0.02	0.234	0.322	ANT 1	
	5G NR n5	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	166800	18.60	20.00	1.380	1.000	-0.02	0.379	0.523	ANT 1	
	5G NR n5	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	167600	18.54	20.00	1.400	1.000	0.06	0.386	0.540	ANT 1	
	5G NR n5	DFT-S-QPSK	100	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	167300	18.60	20.00	1.380	1.000	-0.02	0.420	0.580	ANT 1	
	5G NR n5	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	167200	15.68	17.00	1.355	1.000	0	0.403	0.546	ANT 1	Simultaneous Transmission
	5G NR n5	DFT-S-QPSK	1	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 2	167300	15.68	17.00	1.355	1.000	0.05	0.130	0.176	ANT 1	Simultaneous Transmission
	5G NR n5	DFT-S-QPSK	1	1	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	167300	15.68	17.00	1.355	1.000	0.06	0.136	0.187	ANT 1	Simultaneous Transmission
	5G NR n5	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	166800	15.65	17.00	1.365	1.000	0.02	0.372	0.508	ANT 1	Simultaneous Transmission
	5G NR n5	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	167600	15.62	17.00	1.374	1.000	0.03	0.385	0.529	ANT 1	Simultaneous Transmission
	5G NR n5	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	167300	15.62	17.00	1.374	1.000	0.07	0.266	0.365	ANT 1	Simultaneous Transmission
	5G NR n5	DFT-S-QPSK	50	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 2	167300	15.62	17.00	1.374	1.000	0	0.102	0.140	ANT 1	Simultaneous Transmission
	5G NR n5	DFT-S-QPSK	50	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 2	167200	15.65	17.00	1.374	1.000	-0.04	0.111	0.153	ANT 1	Simultaneous Transmission
	5G NR n5	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	166800	15.60	17.00	1.380	1.000	0.03	0.245	0.338	ANT 1	Simultaneous Transmission
	5G NR n5	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	167600	15.54	17.00	1.400	1.000	0.04	0.247	0.346	ANT 1	Simultaneous Transmission
	5G NR n7	DFT-S-QPSK	50	1	-	Bottom Face	16mm	Sensor off	Full Power	512000	23.68	25.00	1.355	1.000	0.04	0.407	0.552	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	1	1	-	Edge 3	16mm	Sensor off	Full Power	512000	23.68	25.00	1.355	1.000	0.03	0.202	0.274	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	1	1	-	Edge 4	0mm	Sensor off	Full Power	512000	23.68	25.00	1.355	1.000	0.06	0.165	0.224	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	512000	6.68	8.00	1.355	1.000	0	0.300	0.407	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	1	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	512000	6.68	8.00	1.355	1.000	0.03	0.086	0.119	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	502000	6.42	8.00	1.439	1.000	0.02	0.245	0.353	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	507000	6.53	8.00	1.403	1.000	0.04	0.262	0.368	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	50	1	-	Bottom Face	16mm	Sensor off	Full Power	512000	23.65	25.00	1.365	1.000	0.01	0.289	0.387	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	50	1	-	Edge 3	16mm	Sensor off	Full Power	512000	23.65	25.00	1.365	1.000	0.07	0.111	0.151	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	50	1	-	Edge 4	0mm	Sensor off	Full Power	512000	23.65	25.00	1.365	1.000	0.03	0.082	0.112	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	512000	6.65	8.00	1.365	1.000	0.05	0.202	0.276	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	50	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	512000	6.65	8.00	1.365	1.000	0.03	0.082	0.088	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	502000	6.41	8.00	1.442	1.000	0.04	0.267	0.375	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	507000	6.50	8.00	1.413	1.000	0.06	0.192	0.271	ANT 3, ENDC	
	5G NR n7	DFT-S-QPSK	1	1	-	Bottom Face	22mm	Sensor off	Full Power	512000	23.68	25.00	1.355	1.000	0.05	0.230	0.312	ANT 3	
	5G NR n7	DFT-S-QPSK	1	1	-	Edge 3	22mm	Sensor off	Full Power	512000	23.68	25.00	1.355	1.000	0.03	0.081	0.110	ANT 3	
	5G NR n7	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	512000	11.68	13.00	1.355	1.000	0.09	0.615	0.833	ANT 3	
	5G NR n7	DFT-S-QPSK	1	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	512000	11.68	13.00	1.355	1.000	0.03	0.311	0.421	ANT 3	
	5G NR n7	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	502000	11.42	13.00	1.439	1.000	0.05	0.561	0.807	ANT 3	
	5G NR n7	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	507000	11.53	13.00	1.403	1.000	0.01	0.545	0.765	ANT 3	
	5G NR n7	DFT-S-QPSK	50	1	-	Bottom Face	22mm	Sensor off	Full Power	512000	23.65	25.00	1.365	1.000	0.06	0.192	0.262	ANT 3	
	5G NR n7	DFT-S-QPSK	50	1	-	Edge 1	21mm	Sensor off	Full Power	512000	23.65	25.00	1.365	1.000	0.07	0.075	0.102	ANT 3	
	5G NR n7	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	512000	11.65	13.00	1.365	1.000	0.03	0.453	0.677	ANT 3	
	5G NR n7	DFT-S-QPSK	50	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	51									

	SG NR n03	DFT-S-QPSK	25	1	-	Edge 3	10mm	Sensor off	Full Power	462000	23.52	25.00	1406	1000	0.04	0.085	0.120	ANT 3 ENDC
	SG NR n03	DFT-S-QPSK	25	1	-	Edge 4	10mm	Sensor off	Full Power	462000	23.52	25.00	1406	1000	0.02	0.080	0.084	ANT 3 ENDC
	SG NR n03	DFT-S-QPSK	25	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	462000	6.52	8.00	1406	1000	0.02	0.226	0.318	ANT 3 ENDC
	SG NR n03	DFT-S-QPSK	25	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	462000	6.52	8.00	1406	1000	0.06	0.088	0.124	ANT 3 ENDC
	SG NR n03	DFT-S-QPSK	1	1	-	Bottom Face	22mm	Sensor off	Full Power	462000	23.56	25.00	1393	1000	0.05	0.203	0.283	ANT 3
	SG NR n03	DFT-S-QPSK	1	1	-	Edge 1	21mm	Sensor off	Full Power	462000	23.56	25.00	1393	1000	-0.09	0.101	0.141	ANT 3
218	SG NR n03	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	462000	13.56	15.00	1393	1000	0.03	0.838	1.167	ANT 3
	SG NR n03	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	462000	13.56	15.00	1393	1000	0.07	0.830	1.156	ANT 3
	SG NR n03	DFT-S-QPSK	1	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	462000	13.56	15.00	1393	1000	0.03	0.407	0.567	ANT 3
	SG NR n03	DFT-S-QPSK	25	1	-	Bottom Face	22mm	Sensor off	Full Power	462000	23.52	25.00	1406	1000	-0.01	0.162	0.228	ANT 3
	SG NR n03	DFT-S-QPSK	25	1	-	Edge 1	21mm	Sensor off	Full Power	462000	23.52	25.00	1406	1000	-0.04	0.081	0.114	ANT 3
	SG NR n03	DFT-S-QPSK	25	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	462000	13.52	15.00	1406	1000	0.01	0.702	0.987	ANT 3
	SG NR n03	DFT-S-QPSK	25	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	462000	13.52	15.00	1406	1000	-0.04	0.336	0.472	ANT 3
	SG NR n03	DFT-S-QPSK	25	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	462000	13.47	15.00	1422	1000	0.14	0.688	0.979	ANT 3
	SG NR n03	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	462000	9.56	11.00	1393	1000	0.05	0.354	0.493	ANT 3
	SG NR n03	DFT-S-QPSK	1	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 2	462000	9.56	11.00	1393	1000	0.08	0.065	0.091	ANT 3
	SG NR n03	DFT-S-QPSK	25	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	462000	9.52	11.00	1406	1000	0.02	0.202	0.284	ANT 3
	SG NR n03	DFT-S-QPSK	25	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 2	462000	9.52	11.00	1406	1000	0.07	0.044	0.062	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	16mm	Sensor off	Full Power	518598	26.69	28.00	1352	1000	0	0.264	0.367	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC2	Edge 3	16mm	Sensor off	Full Power	518598	26.69	28.00	1352	1000	0.01	0.133	0.180	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	6.69	8.00	1352	1000	0.06	0.266	0.368	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	6.69	8.00	1352	1000	0	0.423	0.572	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC2	Edge 3	0mm	Sensor on	Reduced Power Level 1	518598	6.69	8.00	1352	1000	0.05	0.222	0.300	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	509202	6.13	8.00	1338	1000	0.06	0.366	0.563	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	513900	6.26	8.00	1400	1000	0.02	0.389	0.530	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	523300	6.43	8.00	1430	1000	0.02	0.372	0.524	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	528000	6.48	8.00	1419	1000	0.07	0.377	0.535	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	16mm	Sensor off	Full Power	518598	26.62	28.00	1374	1000	0.05	0.182	0.250	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC2	Edge 3	16mm	Sensor off	Full Power	518598	26.62	28.00	1374	1000	0.04	0.108	0.148	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	26.62	28.00	1374	1000	0.07	0.088	0.121	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	6.62	8.00	1374	1000	0.05	0.266	0.365	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC2	Edge 3	0mm	Sensor on	Reduced Power Level 1	518598	6.62	8.00	1374	1000	0.06	0.123	0.169	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	509202	6.06	8.00	1350	1000	0.03	0.271	0.313	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	513900	6.54	8.00	1400	1000	0.02	0.234	0.328	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	523300	6.58	8.00	1387	1000	0.03	0.216	0.300	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	528000	6.58	8.00	1387	1000	0.05	0.229	0.318	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC3	Bottom Face	16mm	Sensor off	Full Power	518598	23.98	25.00	1265	1000	0.03	0.229	0.290	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC3	Edge 3	16mm	Sensor off	Full Power	518598	23.98	25.00	1265	1000	0.06	0.077	0.087	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC3	Edge 4	0mm	Sensor off	Full Power	518598	23.98	25.00	1265	1000	0.09	0.052	0.066	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	6.98	8.00	1265	1000	0.02	0.13	0.183	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	6.98	8.00	1265	1000	0.08	0.086	0.109	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	509202	6.79	8.00	1321	1000	0.09	0.286	0.381	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	513900	6.90	8.00	1288	1000	0.04	0.289	0.334	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	523300	6.90	8.00	1288	1000	0.07	0.243	0.313	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	528000	6.92	8.00	1282	1000	0.07	0.277	0.355	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC3	Bottom Face	16mm	Sensor off	Full Power	518598	23.97	25.00	1268	1000	0.01	0.156	0.198	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC3	Edge 3	16mm	Sensor off	Full Power	518598	23.97	25.00	1268	1000	0.04	0.084	0.088	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	6.97	8.00	1268	1000	0.02	0.037	0.047	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	6.97	8.00	1268	1000	0.05	0.224	0.284	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC3	Edge 3	0mm	Sensor on	Reduced Power Level 1	518598	6.97	8.00	1268	1000	0.03	0.069	0.087	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	509202	6.88	8.00	1294	1000	0.04	0.189	0.245	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	513900	6.88	8.00	1294	1000	0.02	0.196	0.249	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	523300	6.85	8.00	1303	1000	0.03	0.177	0.231	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	137	67	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	528000	6.83	8.00	1309	1000	0.06	0.210	0.275	ANT 3 ENDC
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	22mm	Sensor off	Full Power	518598	26.69	28.00	1352	1000	-0.11	0.567	0.767	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC2	Edge 1	21mm	Sensor off	Full Power	518598	26.69	28.00	1352	1000	0.04	0.281	0.380	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	11.19	12.50	1352	1000	0.08	0.676	0.914	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC2	Edge 1	0mm	Sensor on	Reduced Power Level 1	518598	11.19	12.50	1352	1000	0.07	0.248	0.333	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	509202	10.53	12.50	1338	1000	0.03	0.583	0.807	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	513900	10.76	12.50	1493	1000	0.09	0.816	0.920	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	523300	10.93	12.50	1435	1000	0.05	0.746	1.071	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	528000	10.98	12.50	1419	1000	0.01	0.790	1.121	ANT 3
228	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	22mm	Sensor off	Full Power	518598	26.62	28.00	1374	1000	0.16	0.454	0.624	ANT 3
	SG NR n41	DFT-S-QPSK	137	67	PC2	Edge 1	21mm	Sensor off	Full Power	518598	26.62	28.00	1374	1000	-0.12	0.225	0.309	ANT 3
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	11.12	12.50	1374	1000	0.08	0.608	0.835	ANT 3
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	11.12	12.50	1374	1000	0.06	0.221	0.304	ANT 3
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	509202	10.99	12.50	1416	1000	-0.15	0.525	0.743	ANT 3
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	513900	11.04	12.50	1400	1000	0.04	0.554	0.775	ANT 3
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	523300	11.08	12.50	1387	1000	-0.05	0.671	0.931	ANT 3
	SG NR n41	DFT-S-QPSK	137	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	528000	11.08	12.50	1387	1000	0.17	0.711	0.986	ANT 3
	SG NR n41	DFT-S-QPSK	270	0	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	11.07	12.50	1350	1000	-0.12	0.555	0.807	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC3	Bottom Face	22mm	Sensor off	Full Power	518598	23.98	25.00	1265	1000	0.15	0.370	0.468	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC3	Edge 1	21mm	Sensor off	Full Power	518598	23.98	25.00	1265	1000	-0.12	0.183	0.231	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	518598	6.48	8.00	1265	1000	0.05	0.258	0.350	ANT 3
	SG NR n41	DFT-S-QPSK	1	1	PC3	Edge 1	0mm	Sensor on	Reduced Power Level 1	518598								

	SG NR #66	DFT-S-QPSK	1	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	354000	6.80	8.00	1.288	1.000	0.03	0.105	0.135	ANT 3 ENDC	
	SG NR #66	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	344000	6.75	8.00	1.334	1.000	0.01	0.333	0.400	ANT 3 ENDC	
	SG NR #66	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	348000	6.76	8.00	1.330	1.000	0.03	0.342	0.485	ANT 3 ENDC	
	SG NR #66	DFT-S-QPSK	50	1	-	Bottom Face	16mm	Sensor off	Full Power	354000	23.86	25.00	1.300	1.000	0.03	0.175	0.228	ANT 3 ENDC	
	SG NR #66	DFT-S-QPSK	50	1	-	Edge 3	0mm	Sensor off	Full Power	354000	23.76	25.00	1.300	1.000	0.03	0.091	0.066	ANT 3 ENDC	
	SG NR #66	DFT-S-QPSK	50	1	-	Edge 4	0mm	Sensor off	Full Power	354000	23.86	25.00	1.300	1.000	0.12	0.033	0.043	ANT 3 ENDC	
	SG NR #66	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	354000	6.86	8.00	1.300	1.000	0.07	0.268	0.348	ANT 3 ENDC	
	SG NR #66	DFT-S-QPSK	50	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	354000	6.86	8.00	1.300	1.000	0.02	0.062	0.081	ANT 3 ENDC	
	SG NR #66	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	344000	6.71	8.00	1.346	1.000	0.06	0.291	0.391	ANT 3 ENDC	
	SG NR #66	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	348000	6.79	8.00	1.321	1.000	0.06	0.229	0.303	ANT 3 ENDC	
	SG NR #66	DFT-S-QPSK	1	1	-	Bottom Face	16mm	Sensor off	Full Power	354000	24.00	25.00	1.299	1.000	0.05	0.216	0.272	ANT 1	
	SG NR #66	DFT-S-QPSK	1	1	-	Edge 1	0mm	Sensor off	Full Power	354000	24.00	25.00	1.299	1.000	-0.1	0.111	0.140	ANT 4	
	SG NR #66	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	354000	15.50	16.50	1.259	1.000	0.08	0.889	1.094	ANT 4	
	SG NR #66	DFT-S-QPSK	1	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	354000	15.50	16.50	1.259	1.000	-0.01	0.360	0.453	ANT 4	
	SG NR #66	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	344000	15.35	16.50	1.303	1.000	0.02	0.891	1.141	ANT 4	
	SG NR #66	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	344000	15.35	16.50	1.303	1.000	0.02	0.885	1.13	ANT 4	
	SG NR #66	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	348000	15.36	16.50	1.300	1.000	0.05	0.732	0.952	ANT 4	Repeat SDR
	SG NR #66	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor off	Full Power	354000	23.96	25.00	1.271	1.000	0.09	0.190	0.241	ANT 4	
	SG NR #66	DFT-S-QPSK	50	1	-	Edge 1	0mm	Sensor off	Full Power	354000	23.96	25.00	1.271	1.000	0.02	0.096	0.125	ANT 4	
	SG NR #66	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	354000	15.46	16.50	1.271	1.000	-0.06	0.730	0.928	ANT 4	
	SG NR #66	DFT-S-QPSK	50	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	354000	15.46	16.50	1.271	1.000	-0.04	0.302	0.384	ANT 4	
	SG NR #66	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	344000	15.31	16.50	1.315	1.000	-0.01	0.748	0.984	ANT 4	
	SG NR #66	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	348000	15.32	16.50	1.291	1.000	0.02	0.615	0.794	ANT 4	
	SG NR #66	DFT-S-QPSK	100	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	354000	15.45	16.50	1.274	1.000	0.03	0.719	0.916	ANT 4	
	SG NR #66	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	354000	11.50	12.50	1.259	1.000	0.09	0.392	0.493	ANT 4	Simultaneous Transmission
	SG NR #66	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	354000	11.50	12.50	1.259	1.000	0.02	0.072	0.091	ANT 4	Simultaneous Transmission
	SG NR #66	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	344000	11.35	12.50	1.303	1.000	-0.01	0.342	0.446	ANT 4	Simultaneous Transmission
	SG NR #66	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	348000	11.36	12.50	1.300	1.000	-0.06	0.311	0.404	ANT 4	Simultaneous Transmission
	SG NR #66	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	354000	11.48	12.50	1.271	1.000	0.03	0.226	0.287	ANT 4	Simultaneous Transmission
	SG NR #66	DFT-S-QPSK	50	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 2	354000	11.48	12.50	1.271	1.000	0.04	0.050	0.064	ANT 4	Simultaneous Transmission
	SG NR #66	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	344000	11.31	12.50	1.315	1.000	0.04	0.202	0.266	ANT 4	Simultaneous Transmission
	SG NR #66	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	348000	11.39	12.50	1.291	1.000	0	0.190	0.245	ANT 4	Simultaneous Transmission
	SG NR #71	DFT-S-QPSK	1	1	-	Bottom Face	31mm	Sensor off	Full Power	137600	23.79	25.00	1.321	1.000	0.05	0.022	0.029	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Edge 3	31mm	Sensor off	Full Power	137600	23.79	25.00	1.321	1.000	0.06	0.032	0.042	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Edge 4	31mm	Sensor off	Full Power	137600	23.79	25.00	1.321	1.000	0.02	0.025	0.033	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	137600	19.79	21.00	1.321	1.000	0.05	0.730	0.965	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	137600	19.79	21.00	1.321	1.000	-0.02	0.146	0.187	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	137600	19.79	21.00	1.321	1.000	-0.06	0.747	0.987	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	134600	19.73	21.00	1.334	1.000	-0.11	0.675	0.900	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	136100	19.73	21.00	1.340	1.000	-0.11	0.694	0.930	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	134600	19.73	21.00	1.334	1.000	0.12	0.735	0.980	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	136100	19.73	21.00	1.340	1.000	-0.05	0.755	1.011	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	134600	19.75	21.00	1.334	1.000	-0.01	0.694	1.139	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	136100	19.73	21.00	1.340	1.000	0.06	0.875	1.172	ANT 1	
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	136100	19.73	21.00	1.340	1.000	0.01	0.862	1.155	ANT 1	Repeat SDR
	SG NR #71	DFT-S-QPSK	50	1	-	Bottom Face	31mm	Sensor off	Full Power	137600	23.72	25.00	1.343	1.000	-0.04	0.616	0.824	ANT 1	
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 3	31mm	Sensor off	Full Power	137600	23.72	25.00	1.343	1.000	-0.02	0.029	0.038	ANT 1	
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 3	31mm	Sensor off	Full Power	137600	23.72	25.00	1.343	1.000	0.09	0.021	0.028	ANT 1	
	SG NR #71	DFT-S-QPSK	50	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 1	137600	19.72	21.00	1.343	1.000	0.17	0.584	0.794	ANT 1	
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	137600	19.72	21.00	1.343	1.000	0.12	0.737	0.980	ANT 1	
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	137600	19.72	21.00	1.343	1.000	0.14	0.635	0.853	ANT 1	
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 1	0mm	Sensor on	Reduced Power Level 1	134600	19.67	21.00	1.350	1.000	0.08	0.622	0.865	ANT 1	
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 4	0mm	Sensor on	Reduced Power Level 1	136100	19.63	21.00	1.371	1.000	-0.12	0.643	0.881	ANT 1	
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	134600	19.57	21.00	1.390	1.000	0.03	0.726	1.009	ANT 1	
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	136100	19.63	21.00	1.371	1.000	-0.13	0.744	1.020	ANT 1	
	SG NR #71	DFT-S-QPSK	100	0	-	Edge 3	0mm	Sensor on	Reduced Power Level 1	137600	19.67	21.00	1.358	1.000	0.06	0.719	0.977	ANT 1	
	SG NR #71	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	137600	15.79	17.00	1.321	1.000	5	0.303	0.400	ANT 1	Simultaneous Transmission
	SG NR #71	DFT-S-QPSK	1	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 2	137600	15.79	17.00	1.321	1.000	0.02	0.313	0.414	ANT 1	Simultaneous Transmission
	SG NR #71	DFT-S-QPSK	1	1	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	137600	15.79	17.00	1.321	1.000	0.08	0.300	0.396	ANT 1	Simultaneous Transmission
	SG NR #71	DFT-S-QPSK	1	1	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	134600	15.75	17.00	1.334	1.000	0.05	0.289	0.385	ANT 1	Simultaneous Transmission
	SG NR #71	DFT-S-QPSK	1	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 2	136100	15.73	17.00	1.340	1.000	0.01	0.291	0.390	ANT 1	Simultaneous Transmission
	SG NR #71	DFT-S-QPSK	50	0	-	Bottom Face	0mm	Sensor on	Reduced Power Level 2	137600	15.72	17.00	1.343	1.000	0.04	0.211	0.283	ANT 1	Simultaneous Transmission
	SG NR #71	DFT-S-QPSK	50	0	-	Edge 1	0mm	Sensor on	Reduced Power Level 2	137600	15.72	17.00	1.343	1.000	0.03	0.226	0.303	ANT 1	Simultaneous Transmission
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 4	0mm	Sensor on	Reduced Power Level 2	137600	15.72	17.00	1.343	1.000	-0.05	0.208	0.279	ANT 1	Simultaneous Transmission
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 2	134600	15.57	17.00	1.390	1.000	0.05	0.192	0.267	ANT 1	Simultaneous Transmission
	SG NR #71	DFT-S-QPSK	50	1	-	Edge 3	0mm	Sensor on	Reduced Power Level 2	136100	15.63	17.00	1.371	1.000	0.01	0.185	0.254	ANT 1	Simultaneous Transmission
	SG NR #77	DFT-S-QPSK	1	1	PC2	Bottom Face	29mm	Sensor off	Full Power	633334	25.60	26.50	1.230	1.000	0.03	0.411	0.506	ANT 6	
	SG NR #77	DFT-S-QPSK	1	1	PC2	Edge 3	0mm	Sensor off	Full Power	633334	25.60	26.50	1.230	1.000	0.02	0.235	0.289	ANT 6	
	SG NR #77	DFT-S-QPSK	1	1	PC2	Edge 4	29mm	Sensor off	Full Power	633334	25.60	26.50	1.230	1.000	-0.04	0.569	0.700	ANT 6	
	SG NR #77	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	633334	6.50	7.50	1.230	1.000	-0.14	0.608	0.748	ANT 6	
	SG NR #77	DFT-S-QPSK	1	1	PC2	Edge 4	0mm	Sensor on	Reduced Power Level 1	633334	6.60	7.50	1.230	1.000	0.1	0.502	1.132	ANT 6	
	SG NR #77	DFT-S-QPSK	135	67	PC2	Bottom Face	29mm	Sensor off	Full Power	633334	25.51	26.50	1.256	1.000	0.01	0.269	0.338	ANT 6	
	SG NR #77	DFT-S-QPSK	135	67	PC2	Edge 3	0mm	Sensor											

	SG NR #77	DFT-S-QPSK	1	1	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 2	650000	2.42	3.50	1.262	1.000	0.07	0.395	0.507	ANT 6	Simultaneous Transmission
	SG NR #77	DFT-S-QPSK	1	1	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 2	662000	2.35	3.50	1.303	1.000	-0.09	0.356	0.464	ANT 6	Simultaneous Transmission
	SG NR #77	DFT-S-QPSK	135	67	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	653000	2.51	3.50	1.256	1.000	-0.01	0.216	0.271	ANT 6	Simultaneous Transmission
	SG NR #77	DFT-S-QPSK	135	67	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 2	653000	2.51	3.50	1.256	1.000	-0.13	0.337	0.423	ANT 6	Simultaneous Transmission
	SG NR #77	DFT-S-QPSK	135	67	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 2	656000	2.23	3.50	1.340	1.000	-0.04	0.243	0.306	ANT 6	Simultaneous Transmission
	SG NR #77	DFT-S-QPSK	135	67	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 2	660000	2.38	3.50	1.294	1.000	0.17	0.242	0.313	ANT 6	Simultaneous Transmission
	SG NR #77	DFT-S-QPSK	135	67	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 2	660000	2.28	3.50	1.324	1.000	-0.1	0.053	0.070	ANT 6	Simultaneous Transmission
	SG NR #77	DFT-S-QPSK	135	67	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 2	662000	2.24	3.50	1.337	1.000	0.17	0.321	0.429	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	1	1	PC2	Bottom Face	20mm	Sensor off	Full Power	633334	25.51	26.50	1.256	1.000	0.03	0.371	0.466	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC2	Edge 3	0mm	Sensor off	Full Power	633334	25.51	26.50	1.256	1.000	0.02	0.195	0.245	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC2	Edge 4	20mm	Sensor on	Full Power	633334	25.51	26.50	1.256	1.000	0	0.486	0.610	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	633334	6.51	7.50	1.256	1.000	-0.02	0.056	0.068	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC2	Edge 4	0mm	Sensor on	Reduced Power Level 1	633334	6.51	7.50	1.256	1.000	0.08	0.813	1.021	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC2	Bottom Face	20mm	Sensor off	Full Power	633334	25.46	26.50	1.271	1.000	0.01	0.255	0.324	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC2	Edge 3	0mm	Sensor off	Full Power	633334	25.46	26.50	1.271	1.000	0.07	0.132	0.155	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC2	Edge 4	20mm	Sensor off	Full Power	633334	25.46	26.50	1.271	1.000	0.02	0.323	0.410	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	633334	6.46	7.50	1.271	1.000	0.08	0.500	0.635	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC2	Edge 4	0mm	Sensor on	Reduced Power Level 1	633334	6.46	7.50	1.271	1.000	-0.03	0.732	0.930	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC3	Bottom Face	20mm	Sensor off	Full Power	633334	22.45	23.50	1.274	1.000	0.01	0.315	0.401	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC3	Edge 3	0mm	Sensor off	Full Power	633334	22.45	23.50	1.274	1.000	0.06	0.144	0.183	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC3	Edge 4	20mm	Sensor off	Full Power	633334	22.45	23.50	1.274	1.000	0.13	0.363	0.468	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	633334	6.45	7.50	1.274	1.000	0.13	0.830	0.975	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 1	633334	6.45	7.50	1.274	1.000	-0.1	0.772	0.983	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC3	Bottom Face	20mm	Sensor off	Full Power	633334	22.41	23.50	1.285	1.000	0.02	0.202	0.260	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC3	Edge 3	0mm	Sensor off	Full Power	633334	22.42	23.50	1.285	1.000	0.14	0.091	0.117	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC3	Edge 4	20mm	Sensor on	Reduced Power Level 2	633334	2.41	3.50	1.285	1.000	0.05	0.256	0.342	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	633334	6.41	7.50	1.285	1.000	0.01	0.475	0.611	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 1	633334	6.41	7.50	1.285	1.000	-0.1	0.695	0.893	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	633334	2.51	3.50	1.256	1.000	-0.11	0.235	0.295	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	1	1	PC2	Edge 4	0mm	Sensor on	Reduced Power Level 2	633334	2.51	3.50	1.256	1.000	-0.19	0.344	0.432	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	135	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	633334	2.46	3.50	1.271	1.000	0.13	0.212	0.269	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	135	67	PC2	Edge 4	0mm	Sensor on	Reduced Power Level 2	633334	2.46	3.50	1.271	1.000	0.07	0.310	0.394	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	1	1	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	633334	2.45	3.50	1.274	1.000	-0.19	0.224	0.285	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	1	1	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 2	633334	2.45	3.50	1.274	1.000	-0.02	0.327	0.416	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	135	67	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	633334	2.41	3.50	1.285	1.000	0.09	0.201	0.258	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	135	67	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 2	633334	2.41	3.50	1.285	1.000	0.08	0.294	0.378	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	1	1	PC2	Bottom Face	20mm	Sensor off	Full Power	650000	25.41	26.50	1.285	1.000	0.06	0.391	0.503	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC2	Edge 3	0mm	Sensor off	Full Power	650000	25.41	26.50	1.285	1.000	0.05	0.188	0.242	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC2	Edge 4	20mm	Sensor off	Full Power	650000	25.41	26.50	1.285	1.000	-0.16	0.556	0.715	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	650000	6.41	7.50	1.285	1.000	0.01	0.564	0.725	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC2	Edge 4	0mm	Sensor on	Reduced Power Level 1	650000	6.41	7.50	1.285	1.000	0.04	0.846	1.105	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC2	Edge 4	0mm	Sensor on	Reduced Power Level 1	650000	6.41	7.50	1.285	1.000	0.08	0.884	1.136	ANT 6	Repeat SAR
	SG NR #78	DFT-S-QPSK	135	67	PC2	Bottom Face	20mm	Sensor off	Full Power	650000	25.38	26.50	1.294	1.000	0.07	0.313	0.405	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC2	Edge 3	0mm	Sensor off	Full Power	650000	25.38	26.50	1.294	1.000	0.13	0.142	0.184	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC2	Edge 4	20mm	Sensor off	Full Power	650000	25.38	26.50	1.294	1.000	0.06	0.597	0.773	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 1	650000	6.38	7.50	1.294	1.000	0.1	0.508	0.657	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC2	Edge 4	0mm	Sensor on	Reduced Power Level 1	650000	6.38	7.50	1.294	1.000	-0.01	0.803	1.038	ANT 6	
	SG NR #78	DFT-S-QPSK	270	0	PC2	Edge 4	0mm	Sensor on	Reduced Power Level 1	650000	6.25	7.50	1.321	1.000	0.04	0.775	1.029	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC3	Bottom Face	20mm	Sensor off	Full Power	650000	22.49	23.50	1.262	1.000	0.03	0.352	0.444	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC3	Edge 3	0mm	Sensor off	Full Power	650000	22.49	23.50	1.262	1.000	0.09	0.145	0.183	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC3	Edge 4	20mm	Sensor off	Full Power	650000	22.49	23.50	1.262	1.000	0.05	0.432	0.545	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	650000	6.49	7.50	1.262	1.000	0.16	0.336	0.426	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 1	650000	6.49	7.50	1.262	1.000	-0.18	0.850	1.073	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC3	Bottom Face	20mm	Sensor off	Full Power	650000	22.40	23.50	1.288	1.000	0.02	0.282	0.363	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC3	Edge 3	0mm	Sensor off	Full Power	650000	22.40	23.50	1.288	1.000	0.07	0.130	0.155	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC3	Edge 4	20mm	Sensor off	Full Power	650000	22.40	23.50	1.288	1.000	0.05	0.366	0.471	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 1	650000	6.40	7.50	1.288	1.000	-0.15	0.483	0.622	ANT 6	
	SG NR #78	DFT-S-QPSK	135	67	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 1	650000	6.40	7.50	1.288	1.000	-0.1	0.763	0.983	ANT 6	
	SG NR #78	DFT-S-QPSK	1	1	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	650000	2.41	3.50	1.285	1.000	0.12	0.240	0.308	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	1	1	PC2	Edge 4	0mm	Sensor on	Reduced Power Level 2	650000	2.41	3.50	1.285	1.000	-0.04	0.379	0.487	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	135	67	PC2	Bottom Face	0mm	Sensor on	Reduced Power Level 2	650000	2.38	3.50	1.294	1.000	-0.13	0.216	0.280	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	135	67	PC2	Edge 4	0mm	Sensor on	Reduced Power Level 2	650000	2.38	3.50	1.294	1.000	-0.1	0.341	0.441	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	1	1	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	650000	2.49	3.50	1.262	1.000	0.19	0.228	0.288	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	1	1	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 2	650000	2.49	3.50	1.262	1.000	-0.08	0.361	0.456	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	135	67	PC3	Bottom Face	0mm	Sensor on	Reduced Power Level 2	650000	2.40	3.50	1.288	1.000	-0.09	0.205	0.264	ANT 6	Simultaneous Transmission
	SG NR #78	DFT-S-QPSK	135	67	PC3	Edge 4	0mm	Sensor on	Reduced Power Level 2	650000	2.40	3.50	1.288	1.000	-0.18	0.324	0.417	ANT 6	Simultaneous Transmission
	WLANS2 4GHz	-	-	-	802.11b	Bottom Face	20mm	Sensor off	Full Power	1	16.23	17.00	1.194	1.011	-0.09	0.100	0.121	Ant 0	
	WLANS2 4GHz	-	-	-	802.11b	Edge 4	20mm	Sensor off	Full Power	1	16.23	17.00	1.194	1.011	0.05	0.046	0.058	Ant 0	
	WLANS2 4GHz	-	-	-	802.11b	Bottom Face	0mm	Sensor on	Reduced Power Level 1	1	11.73	12.50	1.194	1.011	0.03	0.088	0.108	Ant 0	
	WLANS2 4GHz	-	-	-	802.11b	Bottom Face	0mm	Sensor on	Reduced Power Level 1	1	11.73	12.50	1.194	1.011	0.01	0.081	0.101	Ant 0	Repeat SAR
	WLANS2 4GHz	-	-	-	802.11b	Edge 4	0mm	Sensor on	Reduced Power Level 1	1	11.73	12.50	1.194	1.011	0.12	0.839	1.013	Ant 0	
	WLANS2 4GHz	-	-	-	802.11b	Edge 4	0mm	Sensor on	Reduced Power Level 1	7	9.80	10.50	1.175	1.011	-0.15	0.464	0.551		