

User Guide

Wireless Presentation Button

1 LED Indicator

Indicator	EShare Button Status
Off	Not inserted into any PC or endpoints.
Blinking green	Pairing or connecting to the large display.
Solid green	Ready for screen sharing.
Solid blue	Pairing complete or sharing screen.
Blinking red	Failed to pair or connect to the large display.
Blinking yellow	The EShare button is upgrading.

2 Pairing

REQUIREMENT: ESharePro is installed and activated on the large display.

You can pair the EShare Button with the large display in the following ways.

① AUTO-PAIRING

Be sure that the Wi-Fi hotspot is enabled on the display, launch ESharePro, plug EShare Button into the USB/USB-C port of the display, wait for the pairing complete message to appear on the screen, then unplug it.

② MANUALLY PAIRING

If the Wi-Fi hotspot is not available on your display, please launch ESharePro, plug EShare Button into the USB/USB-C port of the display, a manual pairing window will pop up, enter the Wi-Fi SSID and password, then click OK to complete the pairing.

3 Share Screen

① Plug the EShare Button into the laptop via Type-C port and wait for LED from flash to solid blue. Tap the button to start screen


② Extend display mode

For Windows, press “Win+P” to switch the display mode to PC screen only, Duplicate, Extend, Second screen only.

For macOS, launch System Preferences> Displays>Display settings (EShare 4K), choose the projection mode according to your needs, e.g. Use As Separate Display, Mirror Built-in Retina Display.

4 Specifications

Item	Specifications
Power supply	5V DC from USB
Power consumption	3W(Typical)
Ambient temperature	<ul style="list-style-type: none">• Operating: 0℃ ~ 40℃• Storage: - 15℃ ~ +60℃
Relative humidity (non-condensing)	<ul style="list-style-type: none">• Operating: 5% ~ 95%• Storage: 0% ~ 95%
Package dimensions (H x W x D)	213mm × 100mm × 30.3mm
Product dimensions (H x W x D)	835mm × 58mm × 16.5mm
Gross weight	226.5g
Net weight	110g
Wi-Fi	2.4GHz and 5GHz
Wi-Fi operating frequency bands	2412MHz ~ 2472MHz 5180MHz ~ 5240MHz
Maximum Wi-Fi power	1.6mW/MHz
Actual Wi-Fi power	2.4GHz: 1.6mW/MHz 5GHz: 0.7mW/MHz
Resolution	Up to 4K 30 fps
OS	Windows 7/8/10/11 macOS, Chrome OS, Linux OS, Android OS, Any device supports full featuredType-C (DP Alt mode).

 Note: The actual power of Wi-Fi is measured data, and the test results of different laboratories

Statement on a Class A Product

Warning: Operation of this equipment in a residential environment could cause radio interference.

Angaben zu einem Produkt der Klasse A

eräts bzw. dieser Einrichtung

kann im Wohnbereich Funkstörungen verursachen.

Disposal and Recycling Information



This symbol on the device and any included batteries indicates that they should not be disposed of as normal household garbage. Do not dispose of your

device or batteries as unsorted municipal waste. They should be handed over to a certified collection point for recycling or proper disposal when they can no longer be used.

For more detailed information about the recycling of the device or batteries, contact your local city office, the household waste disposal service, or the retail store where you purchased this device.

The disposal of this device is subject to the Waste from Electrical and Electronic Equipment (WEEE) Directive of the European Union. The purpose for separating WEEE and batteries from other waste is to minimize any environmental impact and health hazards due to the presence of hazardous substances.

Reduction of Hazardous Substances

This device is compliant with the EU Registration, Evaluation, Authorization and Restriction of Chemicals (REACH) Regulation (Regulation No 1907/2006/EC of the European Parliament and of the Council) and the EU Restriction of Hazardous Substances (RoHS) Directive (Directive 2011/65/EU of the European Parliament and of the Council).

FCC WARNING

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To maintain compliance with FCC's RF Exposure guidelines, This equipment should be installed and operated with minimum 20cm distance between the radiator and your body: Use only the supplied antenna.

Warranty Card

Thank you for choosing our products. Please read this warranty card carefully and fill in the required information. Keep the card in a safe place. If lost it cannot be replaced.

Registry

Your Name (or Company Name): _____

Contact		Invoice Number	
Address		Expiration Date	
Telephone		Dealer's Name	
Product Model		Dealer's Address	
Serial Number		Dealer's Telephone	

Dealer's Seal: _____

Limited Warranty

We warrant the products that are purchased from authorized dealers to be free from defects in materials and workmanship, under proper use and in normal conditions, during the expressed warranty period.

Special Notice

1. The terms of warranty expressed in the purchase contract enjoy higher validity than the terms expressed within this card. This card is intended to be used solely as a warranty certificate.
2. The warranty card must be preserved in good condition and free of any scratch or alterations.
3. The warranty card must be presented to the authorized service technician when the product is being returned for repairs.

This warranty card does not cover defects caused by:

1. Modifications and alterations performed on the warranted product by parties other than authorized dealers.
2. Damage caused by using the product under inadequate operating environments.
3. Force majeure including but not limited to fires, earthquakes, lightning storms, and tsunamis.
4. Operations performed on the product unexpressed within User Guide.
5. Normal wear and tear of components, including but not limited to the shell and the power module.
6. The warranty card is altered or rendered illegible, or the product serial number recorded on the warranty card is inconsistent with the serial number imprinted or labeled on the product.

For cases not included within this limited warranty, not applicable, or where the warranty is rendered void or expired, we reserve the right to charge for the repair services should the said products be capable of being repaired.

We reserve the right to interpret this limited warranty.