

## RF Exposure evaluation

According to 447498 D04 Interim General RF Exposure Guidance v01

$$P_{th} (\text{mW}) = \begin{cases} ERP_{20\text{ cm}}(d/20\text{ cm})^x & d \leq 20\text{ cm} \\ ERP_{20\text{ cm}} & 20\text{ cm} < d \leq 40\text{ cm} \end{cases} \quad (\text{B.2})$$

where

$$x = -\log_{10}\left(\frac{eo}{ERP_{20\text{ cm}}f}\right)$$

and  $f$  is in GHz,  $d$  is the separation distance (cm), and  $ERP_{20\text{ cm}}$  is per Formula (B.1). The example values shown in Table B.2 are for illustration only.

$$P_{th} (\text{mW}) = ERP_{20\text{ cm}} (\text{mW}) = \begin{cases} 2040f & 0.3\text{ GHz} \leq f < 1.5\text{ GHz} \\ 3060 & 1.5\text{ GHz} \leq f \leq 6\text{ GHz} \end{cases} \quad (\text{B.1})$$

Table B.2—Example Power Thresholds (mW)

| Frequency (MHz) | Distance (mm) |    |    |     |     |     |     |     |     |     |
|-----------------|---------------|----|----|-----|-----|-----|-----|-----|-----|-----|
|                 | 5             | 10 | 15 | 20  | 25  | 30  | 35  | 40  | 45  | 50  |
| 300             | 39            | 65 | 88 | 110 | 129 | 148 | 166 | 184 | 201 | 217 |
| 450             | 22            | 44 | 67 | 89  | 112 | 135 | 158 | 180 | 203 | 226 |
| 835             | 9             | 25 | 44 | 66  | 90  | 116 | 145 | 175 | 207 | 240 |
| 1900            | 3             | 12 | 26 | 44  | 66  | 92  | 122 | 157 | 195 | 236 |
| 2450            | 3             | 10 | 22 | 38  | 59  | 83  | 111 | 143 | 179 | 219 |
| 3600            | 2             | 8  | 18 | 32  | 49  | 71  | 96  | 125 | 158 | 195 |
| 5800            | 1             | 6  | 14 | 25  | 40  | 58  | 80  | 106 | 136 | 169 |

$$eirp = pt \times gt = (Exd)^2/30$$

where:

pt = transmitter output power in watts,

gt = numeric gain of the transmitting antenna (unitless),

E = electric field strength in V/m, ---  $10^{(dBuV/m)/20}/10^6$

d = measurement distance in meters (m)---3m

$$Sopt = (Exd)^2/30 \times gt$$

$$\text{Ant gain} = -0.58\text{dBi} \text{ so Ant numeric gain} = 0.875$$

$$\text{Field strength} = 76.81\text{dB}\mu\text{V/m} @ 3\text{m} @ 2480\text{MHz}$$

$$\text{So Pt} = \{[10^{(76.81/20)/10^6} \times 3]^2 / (30 \times 0.875)\} \times 1000\text{mW} = 0.016\text{mW} < 2.76\text{mW}$$

$$\text{ERP} = 0.016 \times 0.53 = 0.0085$$

Worst case is recorded

Then SAR evaluation is not required