



849 NW STATE ROAD 45
NEWBERRY, FL 32669 USA
PH: 888.472.2424 OR 352.472.5500
FAX: 352.472.2030
EMAIL: INFO@TIMCOENGR.COM
[HTTP://WWW.TIMCOENGR.COM](http://WWW.TIMCOENGR.COM)

FCC PART 90 AND IC RSS-119, RSS-GEN TEST REPORT

APPLICANT	MOTOROLA, INC.
	1301 EAST ALGONQUIN RD. SCHAUMBURG IL 60196
FCC ID	ABZ99FT4089
IC CERTIFICATION	109AB-99FT4089
MODEL NUMBER	AAH02RDH9JA2AN
PRODUCT DESCRIPTION	HANDHELD UHF TRANSCEIVER
DATE SAMPLE RECEIVED	3/9/2012
DATE TESTED	3/13/2012
TESTED BY	Nam Nguyen
APPROVED BY	Mario de Aranzeta
TIMCO REPORT NO.	1715CZT11TestReport_Rev.doc
TEST RESULTS	<input checked="" type="checkbox"/> PASS <input type="checkbox"/> FAIL

THE ATTACHED REPORT SHALL NOT BE REPRODUCED EXCEPT IN FULL
WITHOUT THE WRITTEN APPROVAL OF TIMCO ENGINEERING, INC.





TABLE OF CONTENTS

GENERAL REMARKS.....	3
GENERAL INFORMATION	4
TEST PROCEDURES	5
RF POWER OUTPUT	6
OCCUPIED BANDWIDTH	7
EMC EQUIPMENT LIST	15

Applicant: MOTOROLA, INC.
FCC ID: ABZ99FT4089
IC CERT #: 109AB-99FT4089
Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

GENERAL REMARKS

The attached report shall not be reproduced except in full without the written permission of Timco Engineering Inc.

The test results relate only to the items tested.

Summary

The device under test does:

fulfill the general approval requirements as identified in this test report
 not fulfill the general approval requirements as identified in this test report

Attestations

This equipment has been tested in accordance with the standards identified in this test report. To the best of my knowledge and belief, these tests were performed using the measurement procedures described in this report.

All instrumentation and accessories used to test products for compliance to the indicated standards are calibrated regularly in accordance with ISO 17025: 2005 requirements.



Testing Certificate # 0955-01

I attest that the necessary measurements were made, under my supervision, at:

Timco Engineering Inc.
849 NW State Road 45
Newberry, FL 32669



Authorized Signatory Name:

Mario de Aranzeta C.E.T.
Compliance Engineer/ Lab. Supervisor

Date: 3/15/2012

Applicant: MOTOROLA, INC.
FCC ID: ABZ99FT4089
IC CERT #: 109AB-99FT4089
Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

GENERAL INFORMATION
DUT Specification

DUT Description	HANDHELD UHF TRANSCEIVER
FCC ID	ABZ99FT4089
IC Certification	109AB-99FT4089
Model Number	AAH02RDH9JA2AN
Serial Number	867TMR001 1331, Vintage P2A
Operating Frequency	(403.00 – 520.00) MHz
Test Frequencies	(406.125, 429.9875, and 469.9875) MHz
Type of Emission	11K0F3E , 7K60F1D, 7K60F1E, 7K60F1W, 7K60FXD, 7K60FXE
Modulation	FM
DUT Power Source	<input type="checkbox"/> 110–120Vac/50– 60Hz
	<input type="checkbox"/> DC Power 12V
	<input checked="" type="checkbox"/> Battery Operated Exclusively
Test Item	<input type="checkbox"/> Prototype
	<input checked="" type="checkbox"/> Pre-Production
	<input type="checkbox"/> Production
Type of Equipment	<input type="checkbox"/> Fixed
	<input type="checkbox"/> Mobile
	<input checked="" type="checkbox"/> Portable
Test Conditions	The temperature was 26°C with a relative humidity of 50%.
Modification to the DUT	None
Test Exercise	The DUT was placed in continuous transmit mode.
Applicable Standards	ANSI/TIA 603-C:2004, FCC CFR 47 Part 90, IC RSS-119, RSS-GEN
Test Facility	Timco Engineering Inc. at 849 NW State Road 45 Newberry, FL 32669 USA.

Applicant: MOTOROLA, INC.
 FCC ID: ABZ99FT4089
 IC CERT #: 109AB-99FT4089
 Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
 LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc



TEST PROCEDURES

Bandwidth 20 dB: The measurements were made with the spectrum analyzer's resolution bandwidth (RBW) = 1 MHz and the video bandwidth (VBW) = 3 MHz and the span set as shown on plot.

Applicant: MOTOROLA, INC.
FCC ID: ABZ99FT4089
IC CERT #: 109AB-99FT4089
Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

RF POWER OUTPUT

Rule Part No.: FCC Part 2.1046(a), IC RSS-119 4.1 and 5.4, RSS-GEN 4.8

Test Requirements:

Method of Measurement: RF power is measured by connecting a 50-ohm, resistive wattmeter to the RF output connector. With a nominal battery voltage, and the transmitter properly adjusted the RF output measures:

Test Setup Diagram:



Test Data:

OUTPUT POWER: HIGH – 4.2 Watts
LOW - 1.2 Watts

Part 2.1033 (C)(8) DC Input into the final amplifier

FOR LOW POWER SETTING INPUT POWER: $(7.2V)(0.98A) = 7.06$ Watts
FOR HIGH POWER SETTING INPUT POWER: $(7.2V)(1.75A) = 12.60$ Watts

Applicant: MOTOROLA, INC.
FCC ID: ABZ99FT4089
IC CERT #: 109AB-99FT4089
Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

OCCUPIED BANDWIDTH

FCC Part 2.1049(c), RSS-GEN 4.6 EMISSION BANDWIDTH **FCC Part 90.210(b) RSS-119 4.2 25kHz Channel Spacing**

Data in the plots show that on any frequency removed from the assigned frequency by more than 50%, but not more than 100%: At least 25dB. On any frequency removed from the assigned frequency by more than 100%, but not more than 250%: At least 35 dB. On any frequency removed from the assigned frequency by more than 250%, of the authorized bandwidth: At least $43 + 10\log(P)$ dB.

Part 90.210(c) 12.5kHz Channel Spacing Not Equipped with a Low Pass Filter

For transmitters that are not equipped with an audio low pass filter pursuant to S90.211 (b), the power of any emission must be attenuated below the un-modulated carrier output power as follows; (1) On any frequency removed from the center of the authorized bandwidth by a displacement frequency (fd in kHz) of more than 5 kHz but not more than 10 kHz: At least $83 \log(fd/5)$ dB; (2) On any frequency removed from the center of the authorized bandwidth by a displacement frequency (fd in kHz) of more than 10 kHz, but not more than 250% of the authorized bandwidth: At least $29 \log(fd/2/11)$ dB or 50 dB, whichever is the lesser attenuation; (3) On any frequency removed from the center of the authorized bandwidth by more than 250% of the authorized bandwidth: At least $43 + 10 \log(Po)$ dB.

Part 90.210(d) Emission Mask D - 12.5 kHz channel BW equipment.

For transmitters designed to operate with a 12.5 kHz channel bandwidth, any emission must be attenuated below the power (P) of the highest emission contained within the authorized bandwidth as follows:

- (1) On any frequency from the center of the authorized bandwidth f_0 to 5.625 kHz removed from f_0 : Zero dB.
- (2) On any frequency from the center of the authorized bandwidth by a displacement frequency (fd in kHz) of more than 5.625 kHz but no more than 12.5 kHz: At least $7.27(fd - 2.88)$ dB.
- (3) On any frequency removed from the center of the authorized bandwidth by a displacement frequency (fd in kHz) of more than 12.5 kHz: At least $50 + 10\log(P)$ dB or 70 dB, whichever is the lesser attenuation.

Part 90.210(e) Emission Mask E - 6.25 kHz channel BW equipment.

For transmitters designed to operate with a 6.25 kHz bandwidth, any emission must be attenuated below the power (P) of the highest emission contained within the authorized bandwidth as follows:

- (1) On any frequency from the center of the authorized bandwidth f_0 to 3.0 kHz removed from f_0 : Zero dB.
- (2) On any frequency from the center of the authorized bandwidth by a displacement frequency (fd in kHz) of more than 3.0 kHz but no more than 4.6 kHz: At least $30 + 16.67(fd - 3.0)$ dB or $55 + 10 \log(P)$ or 65, whichever is the lesser attenuation.
- (3) On any frequency removed from the center of the authorized bandwidth by more than 4.6 kHz: At least $55 + 10\log(P)$ dB or 65 dB, whichever is the lesser attenuation.


Applicant: MOTOROLA, INC.
FCC ID: ABZ99FT4089
IC CERT #: 109AB-99FT4089
Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

OCCUPIED BANDWIDTH MEASUREMENT

Test procedure: ANSI/TIA-603-C:2004 para 2.2.11.

Test Setup Diagram:

OCCUPIED BANDWIDTH MEASUREMENT



Test Data: See the plots below


Applicant: MOTOROLA, INC.
FCC ID: ABZ99FT4089
IC CERT #: 109AB-99FT4089
Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

**Analog 12.5 kHz channel spacing (11K0F3E)
 (406.125 MHz)**

NOTES:

MOTOROLA, INC. - UHF TRANSCEIVER (ANDORRA UHF)
 OCCUPIED BANDWIDTH PLOT - ANALOG 12.5 kHz

FCC 90.210 Mask D




Applicant: MOTOROLA, INC.
 FCC ID: ABZ99FT4089
 IC CERT #: 109AB-99FT4089
 Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
 LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

**Analog 12.5 kHz channel spacing (11K0F3E)
 (429.9875 MHz)**

NOTES:

MOTOROLA, INC. - UHF TRANSCEIVER (ANDORRA UHF)
 OCCUPIED BANDWIDTH PLOT - ANALOG 12.5 kHz

FCC 90.210 Mask D




Applicant: MOTOROLA, INC.
 FCC ID: ABZ99FT4089
 IC CERT #: 109AB-99FT4089
 Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
 LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

**Analog 12.5 kHz channel spacing (11K0F3E)
 (469.9875 MHz)**

NOTES:

MOTOROLA, INC. - UHF TRANSCEIVER (ANDORRA UHF)
 OCCUPIED BANDWIDTH PLOT - ANALOG 12.5 kHz

FCC 90.210 Mask D




Applicant: MOTOROLA, INC.
 FCC ID: ABZ99FT4089
 IC CERT #: 109AB-99FT4089
 Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
 LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

**Digital 12.5 kHz channel spacing
(406.125 MHz)**

NOTES:

MOTOROLA, INC. - HANDHELD UHF TRANSCEIVER (ANDORRA UHF1)
 OCCUPIED BANDWIDTH PLOT - DIGITAL

FCC 90.210 Mask D




Applicant: MOTOROLA, INC.
 FCC ID: ABZ99FT4089
 IC CERT #: 109AB-99FT4089
 Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
 LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

**Digital 12.5 kHz channel spacing
(429.9875 MHz)**

NOTES:

MOTOROLA, INC. - HANDHELD UHF TRANSCEIVER (ANDORRA UHF1)
 OCCUPIED BANDWIDTH PLOT - DIGITAL

FCC 90.210 Mask D




Applicant: MOTOROLA, INC.
 FCC ID: ABZ99FT4089
 IC CERT #: 109AB-99FT4089
 Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
 LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

**Digital 12.5 kHz channel spacing
(469.9875 MHz)**

NOTES:

MOTOROLA, INC. - HANDHELD UHF TRANSCEIVER (ANDORRA UHF1)
 OCCUPIED BANDWIDTH PLOT - DIGITAL

FCC 90.210 Mask D



Applicant: MOTOROLA, INC.
 FCC ID: ABZ99FT4089
 IC CERT #: 109AB-99FT4089
 Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
 LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc

EMC EQUIPMENT LIST

Device	Manufacturer	Model	Serial Number	Cal/Char Date	Due Date
3-Meter Semi-Anechoic Chamber	Panashield	N/A	N/A	Listed 5/10/10	5/10/12
AC Voltmeter	HP	400FL	2213A14499	CAL 6/12/11	6/12/13
Antenna: Active Loop	ETS-Lindgren	6502	00062529	CAL 9/23/10	9/23/12
Frequency Counter	HP	5385A	2730A03025	CAL 8/17/11	8/17/13
Hygro-Thermometer	Extech	445703	0602	CAL 6/15/11	6/15/13
Modulation Analyzer	HP	8901A	3435A06868	CAL 7/18/11	7/18/13
Digital Multimeter	Fluke	FLUKE-77	35053830	CAL 9/9/11	9/9/13
Analyzer Tan Tower Preamplifier	HP	8449B-H02	3008A00372	CAL 10/28/11	10/28/13
Analyzer Tan Tower Quasi-Peak Adapter	HP	85650A	3303A01690	CAL 10/28/11	10/28/13
Analyzer Tan Tower RF Preselector	HP	85685A	3221A01400	CAL 10/28/11	10/28/13
Analyzer Tan Tower Spectrum Analyzer	HP	8566B Opt 462	3138A07786 3144A20661	CAL 10/28/11	10/28/13
Temperature Chamber	Tenney Engineering	TTRC	11717-7	CHAR 4/25/10	4/25/12
Antenna	ETS	3117	35923	12/7/2011	12/7/2013
Antenna	Electro metrics	LPA-25	1122	5/04/2011	5/04/2013
Antenna	Electro metrics	BIA-25	1096	5/04/2011	5/04/2013

Applicant: MOTOROLA, INC.

FCC ID: ABZ99FT4089

IC CERT #: 109AB-99FT4089

 Report: O:\M\MOTOROLA_SCHAUMBURG LARRY
 LARSEN\1715CZT11\1715CZT11TestReport_Rev.doc