

RF Exposure / MPE Calculation

No. : 12079942H
Applicant : Sony Interactive Entertainment Inc.
Type of Equipment : Wireless communication module
Model No. : J20H096
 *Bluetooth part
FCC ID : AK8M18DFT1

Sony Interactive Entertainment Inc. declares that Model: J20H096 complies with FCC radiation exposure requirement specified in the FCC Rule 2.1091 (for mobile).

RF Exposure Calculations:

The following information provides the minimum separation distance for the highest gain antenna provided with the “J20H096” as calculated from (B) Limits for General Population / Uncontrolled Exposure of TABLE 1- LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE) of §1.1310 Radiofrequency radiation exposure limits.

[Bluetooth part]

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1mW/cm² uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

P = 1.40 mW (Maximum average output power)

☒ Time average was used for the above value in consideration of 6-minutes time-averaging

☐ Burst power average was used for the above value in consideration of worst condition.

G = 4.365 Numerical Antenna gain; equal to 6.4 dBi

r = 20 cm (Separation distance)

Power Density Result $S = 0.00122 \text{ mW/cm}^2$

UL Japan, Inc.

Ise EMC Lab.

4383-326 Asama-cho, Ise-shi, Mie-ken 516-0021 JAPAN

Telephone : +81 596 24 8999

Facsimile : +81 596 24 8124

Reference:**[WLAN (2.4 GHz) part]**

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1mW/cm² uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

$P =$ 13.19 mW (Maximum average output power)

☐ Time average was used for the above value in consideration of 6-minutes time-averaging

☒ Burst power average was used for the above value in consideration of worst condition.

$G =$ 5.140 Numerical Antenna gain; equal to 7.11dBi

$r =$ 20 cm (Separation distance)

Power Density Result $S = 0.01349 \text{ mW/cm}^2$

Reference:**[WLAN (5 GHz) part]**

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1mW/cm² uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

$P =$ 15.28 mW (Maximum average output power)

☐ Time average was used for the above value in consideration of 6-minutes time-averaging

☒ Burst power average was used for the above value in consideration of worst condition.

$G =$ 5.358 Numerical Antenna gain; equal to 7.29 dBi

$r =$ 20 cm (Separation distance)

Power Density Result $S = 0.01629 \text{ mW/cm}^2$

Therefore, if Bluetooth and WLAN 2.4GHz transmit simultaneously,

$$\begin{aligned} S &= 0.00122 \text{ mW/cm}^2 + 0.01349 \text{ mW/cm}^2 \\ &= 0.01471 \text{ mW/cm}^2 \end{aligned}$$

Therefore, if Bluetooth and WLAN 5GHz transmit simultaneously,

$$\begin{aligned} S &= 0.00122 \text{ mW/cm}^2 + 0.01629 \text{ mW/cm}^2 \\ &= 0.01751 \text{ mW/cm}^2 \end{aligned}$$

Even taking into account the tolerance, this device can be satisfied with the limits.

UL Japan, Inc.

Ise EMC Lab.

4383-326 Asama-cho, Ise-shi, Mie-ken 516-0021 JAPAN

Telephone : +81 596 24 8999

Facsimile : +81 596 24 8124