

Client

CCS, USA

## CALIBRATION CERTIFICATE

Object(s)

D1450V2 - SN:1020

Calibration procedure(s)

QA CAL-05.v2  
Calibration procedure for dipole validation kits

Calibration date:

October 2, 2003

Condition of the calibrated item

In Tolerance (according to the specific calibration document)


This calibration statement documents traceability of M&TE used in the calibration procedures and conformity of the procedures with the ISO/IEC 17025 international standard.

All calibrations have been conducted in the closed laboratory facility: environment temperature 22 +/- 2 degrees Celsius and humidity < 75%.

Calibration Equipment used (M&TE critical for calibration)

Model Type	ID #	Cal Date (Calibrated by, Certificate No.)	Scheduled Calibration
Power sensor HP 8481A	MY41092317	18-Oct-02 (Agilent, No. 20021018)	Oct-04
Power sensor HP 8481A	US37292783	30-Oct-02 (METAS, No. 252-0236)	Oct-03
Power meter EPM E442	GB37480704	30-Oct-02 (METAS, No. 252-0236)	Oct-03
RF generator R&S SML-03	100698	27-Mar-2002 (R&S, No. 20-92389)	In house check: Mar-05
Network Analyzer HP 8753E	US37390585	18-Oct-01 (Agilent, No. 24BR1033101)	In house check: Oct 03

	Name	Function	Signature
Calibrated by:	Judith Mueller	Technician	

	Name	Function	Signature
Approved by:	Katja Pokovic	Laboratory Director	

Date issued: October 3, 2003

This calibration certificate is issued as an intermediate solution until the accreditation process (based on ISO/IEC 17025 International Standard) for Calibration Laboratory of Schmid & Partner Engineering AG is completed.

# DASY

## Dipole Validation Kit

Type: D1450V2

Serial: 1020

Manufactured: December 17, 2002

Calibrated: October 2, 2003

## 1. Measurement Conditions

The measurements were performed in the flat section of the SAM twin phantom filled with **head simulating solution** of the following electrical parameters at 1450 MHz:

Relative Dielectricity	<b>42.1</b>	$\pm 5\%$
Conductivity	<b>1.20 mho/m</b>	$\pm 5\%$

The DASY4 System with a dosimetric E-field probe ET3DV6 (SN:1507, Conversion factor 5.9) was used for the measurements.

The dipole was mounted on the small tripod so that the dipole feedpoint was positioned below the center marking of the flat phantom section and the dipole was oriented parallel to the body axis (the long side of the phantom). The standard measuring distance was 10mm from dipole center to the solution surface. The included distance spacer was used during measurements for accurate distance positioning.

The coarse grid with a grid spacing of 15mm was aligned with the dipole. The 7x7x7 fine cube was chosen for cube integration.

The dipole input power (forward power) was  $250\text{mW} \pm 3\%$ . The results are normalized to 1W input power.

## 2. SAR Measurement with DASY4 System

Standard SAR-measurements were performed according to the measurement conditions described in section 1. The results (see figure supplied) have been normalized to a dipole input power of 1W (forward power). The resulting averaged SAR-values measured with the dosimetric probe ET3DV6 SN:1507 and applying the advanced extrapolation are:

averaged over $1\text{ cm}^3$ (1 g) of tissue:	<b>27.6 mW/g <math>\pm 16.8\%</math> (k=2)<sup>1</sup></b>
averaged over $10\text{ cm}^3$ (10 g) of tissue:	<b>15.6 mW/g <math>\pm 16.2\%</math> (k=2)<sup>1</sup></b>

---

<sup>1</sup> validation uncertainty

### 3. Dipole Impedance and Return Loss

The impedance was measured at the SMA-connector with a network analyzer and numerically transformed to the dipole feedpoint. The transformation parameters from the SMA-connector to the dipole feedpoint are:

Electrical delay:	<b>1.260 ns</b>	(one direction)
Transmission factor:	<b>0.983</b>	(voltage transmission, one direction)

The dipole was positioned at the flat phantom sections according to section 1 and the distance holder was in place during impedance measurements.

Feedpoint impedance at 1450 MHz:	$\text{Re}\{Z\} = \mathbf{52.4\ \Omega}$
	$\text{Im}\{Z\} = \mathbf{1.5\ \Omega}$
Return Loss at 1450 MHz	<b>-31.0 dB</b>

### 4. Handling

Do not apply excessive force to the dipole arms, because they might bend. Bending of the dipole arms stresses the soldered connections near the feedpoint leading to a damage of the dipole.

### 5. Design

The dipole is made of standard semirigid coaxial cable. The center conductor of the feeding line is directly connected to the second arm of the dipole. The antenna is therefore short-circuited for DC-signals.

Small end open caps have been added to the dipole arms in order to improve matching when loaded according to the position as explained in Section 1. The SAR data are not affected by this change.

### 6. Power Test

After long term use with 100W radiated power, only a slight warming of the dipole near the feedpoint can be measured.

Test Laboratory: SPEAG, Zurich, Switzerland

**DUT: Dipole 1450 MHz; Type: D1450V2; Serial: D1450V2 - SN1020**

Communication System: CW-1450; Frequency: 1450 MHz; Duty Cycle: 1:1

Medium: HSL 1450 MHz ( $\sigma = 1.2 \text{ mho/m}$ ,  $\epsilon_r = 42.13$ ,  $\rho = 1000 \text{ kg/m}^3$ )

Phantom section: Flat Section

Measurement Standard: DASY4 (High Precision Assessment)

DASY4 Configuration:

- Probe: ET3DV6 - SN1507; ConvF(5.9, 5.9, 5.9); Calibrated: 1/18/2003
- Sensor-Surface: 4mm (Mechanical Surface Detection)
- Electronics: DAE3 - SN411; Calibrated: 1/16/2003
- Phantom: SAM with CRP - TP1006; Type: SAM 4.0; Serial: TP:1006
- Measurement SW: DASY4, V4.1 Build 47; Postprocessing SW: SEMCAD, V1.8 Build 60

**Pin = 250 mW; d = 10 mm/Area Scan (81x81x1):** Measurement grid: dx=15mm, dy=15mm

Reference Value = 84.1 V/m

Power Drift = -0.0 dB

Maximum value of SAR = 7.61 mW/g

**Pin = 250 mW; d = 10 mm/Zoom Scan (7x7x7)/Cube 0:** Measurement grid: dx=5mm, dy=5mm, dz=5mm



Peak SAR (extrapolated) = 11.5 W/kg

SAR(1 g) = 6.89 mW/g; SAR(10 g) = 3.9 mW/g

Reference Value = 84.1 V/m

Power Drift = -0.0 dB

Maximum value of SAR = 7.66 mW/g



0 dB = 7.66mW/g

2 Oct 2003 14:07:38

CH1 S11 1 U FS

1: 52.396  $\Omega$  1.5449  $\Omega$  169.57  $\text{pH}$ 


1 450.000 000 MHz

De1

Cor

Avg  
16

↑




CH2 S11 LOG

5 dB/REF -20 dB

1: -31.032 dB 1 450.000 000 MHz

Cor

↑



CENTER 1 450.000 000 MHz

SPAN 400.000 000 MHz