

Shure Incorporated
5800 West Touhy Ave
Niles, IL 60714-4608

T 847 600 2000
F 847 600 1212
shure.com



Measurements of Shure Axient Digital ADX1 UHF and 2.4 GHz Antennas For Regulatory Approval

Shure Incorporated
August 19, 2024

Prepared by
Adem Celebi, Ph.D.



Table of Contents

1. Shure ADX1 – Body Pack Transmitter	3
1.1 Design Overview and Reference Angles	3
1.2 Test Setup.....	5
2. Test Results	7
2.1 ADX1 UHF Antenna (Dipole/Monopole Type)	7
2.1.1 ADX1 G56 (operating band 470-636MHz).....	7
2.1.2 ADX1 G57 (operating band 470-616MHz).....	8
2.1.3 ADX1 G62 (operating band 510-530MHz).....	9
2.1.4 ADX1 K54 (operating band 606-663MHz)	10
2.1.5 ADX1 K55 (operating band 606-694MHz)	11
2.1.6 ADX1 K57 (operating band 606-790MHz)	12
2.1.7 ADX1 JB (operating band 806-810MHz)	13
2.1.8 ADX1 X55 (operating band 941-960MHz)	14
2.1.9 ADX1 X56 (operating band 960-1000MHz)	15
2.2 ADX1 Zigbee Antenna (Conformal Custom Type).....	16
2.2.1 Antenna A - SMA Side (operating band 2405-2483.5MHz).....	16
2.2.2 Antenna B - SMA Side (operating band 2405-2483.5MHz).....	17



1. Shure ADX1 – Bodypack Transmitter

1.1 Design Overview and Reference Angles




Figure 1 Shure ADX1 UHF and Zigbee Antennas Overview




Figure 2 Shure ADX1 UHF and Zigbee Antennas Block Diagram

1.2 Test Setup




Figure 3 Shure ADX1 Reference Angles




Figure 4 Photo of Shure ADX1 in Antenna Chamber

Supporting Test Equipment List and Software:

- E5071C ENA series Vector Network Analyzer 100kHz-8.5GHz
- ETS Model 2090 Multi Device Controller
- ETS Lindgren Model 3164-10 3164-10 Open Boundary Quad-Ridged Horn 400MHz-10GHz
- ETS Lindgren Model 3126-2450 Precision Sleeve Dipole
- ETS Lindgren Model 3122D-DB4 Tuned Dipole Antenna
- EMQuest Data Acquisition and Analysis Software



2. Test Results

2.1 ADX1 UHF Antenna (Dipole/Monopole Type)

2.1.1 ADX1 G56 (operating band 470-636MHz, Antenna Model: 95D9043)

Peak Gain					
Parameter	Type	Pattern	470 MHz	553 MHz	636 MHz
UHF Antenna	Dipole	Omni	-3.0 dBi	0 dBi	-0.2 dBi




Figure 5 – ADX1 (G56) 3D radiation patterns and scale at max peak gain



2.1.2 ADX1 G57 (operating band 470-616MHz, Antenna Model: 95D9043)

Peak Gain					
Parameter	Type	Pattern	470 MHz	543 MHz	616 MHz
UHF Antenna	Dipole	Omni	-3.0 dBi	-0.2 dBi	0.4 dBi




Figure 6 – ADX1 (G57) 3D radiation patterns and scale at max peak gain



2.1.3 **ADX1 G62 (operating band 510-530MHz, Antenna Model: 95G9043)**

Peak Gain					
Parameter	Type	Pattern	510 MHz	520 MHz	530 MHz
UHF Antenna	Dipole	Omni	0	0.2 dBi	-0.4 dBi




Figure 7 – ADX1 (G62) 3D radiation patterns and scale at max peak gain

2.1.10 ADX1 K54 (operating band 606-663MHz, Antenna Model: 95E9043)

Peak Gain					
Parameter	Type	Pattern	606 MHz	650 MHz	663 MHz
UHF Antenna	Dipole	Omni	0.3 dBi	0.5 dBi	0.6 dBi




Figure 8 – ADX1 (K54) 3D radiation patterns and scale at max peak gain