



FCC RADIO TEST REPORT

FCC ID : H8N-CTX0800
Equipment : OBU
Brand Name : ASKEY
Model Name : CTX0800-RoHS-US
Applicant : ASKEY COMPUTER CORPORATION
10F, No.119, Jiankang Rd., Zhonghe
Dist., New Taipei City, Taiwan
Manufacturer : ASKEY COMPUTER CORPORATION
10F, No.119, Jiankang Rd., Zhonghe
Dist., New Taipei City, Taiwan
Standard : FCC Part 15 Subpart C §15.247

The product was received on Aug. 01, 2024 and testing was performed from Aug. 14, 2024 to Sep. 11, 2024. We, Sporton International Inc. Wensan Laboratory, would like to declare that the tested sample has been evaluated in accordance with the test procedures and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval from Sporton International Inc. Wensan Laboratory, the test report shall not be reproduced except in full.

Approved by: Louis Wu

Sportun International Inc. Wensan Laboratory

No.58, Aly. 75, Ln. 564, Wenhua 3rd, Rd., Guishan Dist., Taoyuan City 333010, Taiwan (R.O.C.)



Table of Contents

History of this test report.....	3
Summary of Test Result.....	4
1 General Description.....	5
1.1 Product Feature of Equipment Under Test.....	5
1.2 Modification of EUT	5
1.3 Testing Location	5
1.4 Applicable Standards.....	6
2 Test Configuration of Equipment Under Test.....	7
2.1 Carrier Frequency Channel	7
2.2 Test Mode.....	8
2.3 Connection Diagram of Test System.....	9
2.4 Support Unit used in test configuration and system	9
2.5 EUT Operation Test Setup	10
2.6 Measurement Results Explanation Example.....	10
3 Test Result.....	11
3.1 Number of Channel Measurement	11
3.2 Hopping Channel Separation Measurement	12
3.3 Dwell Time Measurement	13
3.4 20dB and 99% Bandwidth Measurement	14
3.5 Output Power Measurement.....	15
3.6 Conducted Band Edges Measurement.....	16
3.7 Conducted Spurious Emission Measurement	17
3.8 Radiated Band Edges and Spurious Emission Measurement	18
3.9 Antenna Requirements	22
4 List of Measuring Equipment	23
5 Measurement Uncertainty	25
Appendix A. Conducted Test Results	
Appendix B. Radiated Spurious Emission Test Data	
Appendix C. Duty Cycle Plots	
Appendix D. Setup Photographs	



History of this test report



Summary of Test Result

Report Clause	Ref Std. Clause	Test Items	Result (PASS/FAIL)	Remark
3.1	15.247(a)(1)	Number of Channels	Pass	-
3.2	15.247(a)(1)	Hopping Channel Separation	Pass	-
3.3	15.247(a)(1)	Dwell Time of Each Channel	Pass	-
3.4	15.247(a)(1)	20dB Bandwidth	Pass	-
3.4	2.1049	99% Occupied Bandwidth	Pass	-
3.5	15.247(b)(1) 15.247(b)(4)	Peak Output Power	Pass	-
3.6	15.247(d)	Conducted Band Edges	Pass	-
3.7	15.247(d)	Conducted Spurious Emission	Pass	-
3.8	15.247(d)	Radiated Band Edges and Radiated Spurious Emission	Pass	11.43 dB under the limit at 35.82 MHz
-	15.207	AC Conducted Emission	Not Required	-
3.9	15.203	Antenna Requirement	Pass	-

Note:

1. Not required means after assessing, test items are not necessary to carry out.
2. The device is for vehicular use.

Conformity Assessment Condition:

1. The test results (PASS/FAIL) with all measurement uncertainty excluded are presented against the regulation limits or in accordance with the requirements stipulated by the applicant/manufacturer who shall bear all the risks of non-compliance that may potentially occur if measurement uncertainty is taken into account.
2. The measurement uncertainty please refer to each test result in the section "Measurement Uncertainty".

Disclaimer:

The product specifications of the EUT presented in the test report that may affect the test assessments are declared by the manufacturer who shall take full responsibility for the authenticity.

Reviewed by: Keven Cheng

Report Producer: Wilda Wei



1 General Description

1.1 Product Feature of Equipment Under Test

Product Feature	
General Specs GSM/WCDMA/LTE/5G NR, Bluetooth, Wi-Fi 2.4GHz 802.11b/g/n, Wi-Fi 5GHz 802.11a/n/ac and GNSS.	
Antenna Type WWAN: Combination Antenna WLAN: <Ant.10>: Combination Antenna <Ant.11>: Combination Antenna Bluetooth: Combination Antenna GPS / Glonass / BDS / Galileo: Combination Antenna	
Integrated WWAN Module	Brand Name: ALPS ALPINE CO., LTD Model Name: UMNZ1A2 FCC ID: CWTUMNZ1A2
Antenna information	
2400 MHz ~ 2483.5 MHz	Peak Gain (dBi) 1.15

Remark: The EUT's information above is declared by manufacturer. Please refer to Disclaimer in report summary.

1.2 Modification of EUT

No modifications made to the EUT during the testing.

1.3 Testing Location

Test Site	Sporton International Inc. Wensan Laboratory
Test Site Location	No.58, Aly. 75, Ln. 564, Wenhua 3rd, Rd., Guishan Dist., Taoyuan City 333010, Taiwan (R.O.C.) TEL: +886-3-327-0868 FAX: +886-3-327-0855
Test Site No.	Sporton Site No. TH05-HY, 03CH16-HY

Note: The test site complies with ANSI C63.4 2014 requirement.

FCC designation No.: TW3786



1.4 Applicable Standards

According to the specifications declared by the manufacturer, the EUT must comply with the requirements of the following standards:

- ♦ FCC Part 15 Subpart C §15.247
- ♦ FCC KDB Publication No. 558074 D01 15.247 Meas Guidance v05r02
- ♦ FCC KDB 414788 D01 Radiated Test Site v01r01
- ♦ ANSI C63.10-2013

Remark:

1. All the test items were validated and recorded in accordance with the standards without any modification during the testing.
2. The TAF code is not including all the FCC KDB listed without accreditation.
3. This EUT has also been tested and complied with the requirements of FCC Part 15, Subpart B, recorded in a separate test report.



2 Test Configuration of Equipment Under Test

2.1 Carrier Frequency Channel

Frequency Band	Channel	Freq. (MHz)	Channel	Freq. (MHz)	Channel	Freq. (MHz)
2400-2483.5 MHz	0	2402	27	2429	54	2456
	1	2403	28	2430	55	2457
	2	2404	29	2431	56	2458
	3	2405	30	2432	57	2459
	4	2406	31	2433	58	2460
	5	2407	32	2434	59	2461
	6	2408	33	2435	60	2462
	7	2409	34	2436	61	2463
	8	2410	35	2437	62	2464
	9	2411	36	2438	63	2465
	10	2412	37	2439	64	2466
	11	2413	38	2440	65	2467
	12	2414	39	2441	66	2468
	13	2415	40	2442	67	2469
	14	2416	41	2443	68	2470
	15	2417	42	2444	69	2471
	16	2418	43	2445	70	2472
	17	2419	44	2446	71	2473
	18	2420	45	2447	72	2474
	19	2421	46	2448	73	2475
	20	2422	47	2449	74	2476
	21	2423	48	2450	75	2477
	22	2424	49	2451	76	2478
	23	2425	50	2452	77	2479
	24	2426	51	2453	78	2480
	25	2427	52	2454	-	-
	26	2428	53	2455	-	-




2.2 Test Mode

a. The EUT has been associated with peripherals and configuration operated in a manner tended to maximize its emission characteristics in a typical application. Frequency range investigated: radiation emission (9 kHz to the 10th harmonic of the highest fundamental frequency or to 40 GHz, whichever is lower). For radiated measurement, the measured emission level of the EUT was maximized by rotating the EUT on a turntable, adjusting the orientation of the EUT and EUT antenna in three orthogonal axis (X: flat, Y: portrait, Z: landscape), and adjusting the measurement antenna orientation, following C63.10 exploratory test procedures and only the worst plane, and the worst mode of radiated spurious emissions is Bluetooth 1Mbps mode, and recorded in this report.

The following summary table is showing all test modes to demonstrate in compliance with the standard.

Summary table of Test Cases			
Test Item	Data Rate / Modulation		
Conducted Test Cases	Bluetooth BR 1Mbps GFSK	Bluetooth EDR 2Mbps $\pi/4$-DQPSK	Bluetooth EDR 3Mbps 8-DPSK
	Mode 1: CH00_2402 MHz	Mode 4: CH00_2402 MHz	Mode 7: CH00_2402 MHz
	Mode 2: CH39_2441 MHz	Mode 5: CH39_2441 MHz	Mode 8: CH39_2441 MHz
	Mode 3: CH78_2480 MHz	Mode 6: CH78_2480 MHz	Mode 9: CH78_2480 MHz
Radiated Test Cases	Bluetooth BR 1Mbps GFSK		
	Mode 1: CH00_2402 MHz		
	Mode 2: CH39_2441 MHz		
	Mode 3: CH78_2480 MHz		
Remark: For Radiated Test Cases, the worst mode data rate 1Mbps was reported only since the highest RF output power in the preliminary tests. The conducted spurious emissions and conducted band edge measurement for other data rates were not worse than 1Mbps, and no other significantly frequencies found in conducted spurious emission.			

2.3 Connection Diagram of Test System



2.4 Support Unit used in test configuration and system

Item	Equipment	Brand Name	Model Name	FCC ID	Data Cable	Power Cord
1.	DC Power Supply	GW Insteck	GEU810968	GPE-2323	N/A	N/A
2.	System Simulator	Anritsu	6272278353	MT8821C	N/A	Unshielded, 1.8 m



2.5 EUT Operation Test Setup

The RF test items, utility “Tera Term 4.95” was installed in Notebook which was programmed in order to make the EUT get into the engineering modes to provide channel selection, power level, data rate and the application type and for continuous transmitting signals.

2.6 Measurement Results Explanation Example

For all conducted test items:

The offset level is set in the spectrum analyzer to compensate the RF cable loss and attenuator factor between EUT conducted output port and spectrum analyzer. With the offset compensation, the spectrum analyzer reading level is exactly the EUT RF output level.

Example:

The spectrum analyzer offset is derived from RF cable loss and attenuator factor.

Offset = RF cable loss + attenuator factor.

Following shows an offset computation example with cable loss 4.2 dB and 10 dB attenuator.

Offset(dB) = RF cable loss(dB) + attenuator factor(dB).

$$= 4.2 + 10 = 14.2 \text{ (dB)}$$

3 Test Result

3.1 Number of Channel Measurement

3.1.1 Limits of Number of Hopping Frequency

Frequency hopping systems in the 2400-2483.5 MHz band shall use at least 15 channels.


3.1.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.1.3 Test Procedure

1. The testing follows ANSI C63.10-2013 clause 7.8.3.
2. The RF output of EUT is connected to the spectrum analyzer by RF cable and attenuator. The path loss is compensated to the results for each measurement.
3. Set the maximum power setting and enable the EUT to transmit continuously.
4. Enable the EUT hopping function.
5. Use the following spectrum analyzer settings: Span = the frequency band of operation; RBW = 300 kHz; VBW \geq RBW; Sweep = auto; Detector function = peak; Trace = max hold.
6. The number of hopping frequency used is defined as the number of total channel.
7. Record the measurement data derived from spectrum analyzer.

3.1.4 Test Setup



3.1.5 Test Result of Number of Hopping Frequency

Please refer to Appendix A.

3.2 Hopping Channel Separation Measurement

3.2.1 Limit of Hopping Channel Separation

Frequency hopping systems operating in the 2400-2483.5 MHz band may have hopping channel carrier frequencies that are separated by 25 kHz or two-thirds of the 20 dB bandwidth of the hopping channel, whichever is greater.


3.2.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.2.3 Test Procedures

1. The testing follows ANSI C63.10-2013 clause 7.8.2.
2. The RF output of EUT is connected to the spectrum analyzer by RF cable and attenuator. The path loss is compensated to the results for each measurement.
3. Set the maximum power setting and enable the EUT to transmit continuously.
4. Enable the EUT hopping function.
5. Use the following spectrum analyzer settings:
Span = wide enough to capture the peaks of two adjacent channels;
RBW = 300 kHz; VBW \geq RBW; Sweep = auto; Detector function = peak; Trace = max hold.
6. Measure and record the results in the test report.

3.2.4 Test Setup



3.2.5 Test Result of Hopping Channel Separation

Please refer to Appendix A.

3.3 Dwell Time Measurement

3.3.1 Limit of Dwell Time

The average time of occupancy on any channel shall not be greater than 0.4 seconds within a period of 0.4 seconds multiplied by the number of hopping channels employed.


3.3.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.3.3 Test Procedures

1. The testing follows ANSI C63.10-2013 clause 7.8.4.
2. The RF output of EUT is connected to the spectrum analyzer by RF cable and attenuator. The path loss is compensated to the results for each measurement.
3. Set the maximum power setting and enable the EUT to transmit continuously.
4. Enable the EUT hopping function.
5. Use the following spectrum analyzer settings: Span = zero span, centered on a hopping channel; RBW = 1 MHz; VBW \geq RBW; Sweep = as necessary to capture the entire dwell time per hopping channel; Detector function = peak; Trace = max hold.
6. Measure and record the results in the test report.

3.3.4 Test Setup



3.3.5 Test Result of Dwell Time

Please refer to Appendix A.

3.4 20dB and 99% Bandwidth Measurement

3.4.1 Limit of 20dB and 99% Bandwidth

Reporting only


3.4.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.4.3 Test Procedures

1. The testing follows ANSI C63.10-2013 clause 6.9.2 and 6.9.3.
2. The RF output of EUT is connected to the spectrum analyzer by RF cable and attenuator. The path loss is compensated to the results for each measurement.
3. Set the maximum power setting and enable the EUT to transmit continuously.
4. Use the following spectrum analyzer settings for 20 dB Bandwidth measurement.
Span = approximately 2 to 5 times the 20 dB bandwidth, centered on a hopping channel;
RBW \geq 1% of the 20 dB bandwidth; VBW \geq RBW; Sweep = auto; Detector function = peak;
Trace = max hold.
5. Use the following spectrum analyzer settings for 99 % Bandwidth measurement.
Span = approximately 1.5 to 5 times the 99% bandwidth, centered on a hopping channel;
RBW \geq 1-5% of the 99% bandwidth; VBW \geq 3 * RBW; Sweep = auto; Detector function = peak;
Trace = max hold.
6. Measure and record the results in the test report.

3.4.4 Test Setup



3.4.5 Test Result of 20dB Bandwidth

Please refer to Appendix A.

3.4.6 Test Result of 99% Occupied Bandwidth

Please refer to Appendix A.

3.5 Output Power Measurement

3.5.1 Limit of Output Power

The maximum peak conducted output power of the intentional radiator shall not exceed the following:

For frequency hopping systems operating in the 2400-2483.5 MHz band employing at least 75 non-overlapping hopping channels, and all frequency hopping systems in the 5725-5850 MHz band: 1 watt. For all other frequency hopping systems in the 2400-2483.5 MHz band 0.125 watts.

If directional gain of transmitting antennas is greater than 6 dBi, the power shall be reduced by the same level in dB comparing to gain minus 6 dBi.


3.5.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.5.3 Test Procedures

1. The testing follows ANSI C63.10-2013 clause 7.8.5.
2. The RF output of EUT is connected to the power meter by RF cable and attenuator. The path loss is compensated to the results for each measurement.
3. Set the maximum power setting and enable the EUT to transmit continuously.
4. Measure the conducted output power with cable loss and record the results in the test report.
5. Measure and record the results in the test report.

3.5.4 Test Setup



3.5.5 Test Result of Peak Output Power

Please refer to Appendix A.

3.5.6 Test Result of Average Output Power (Reporting Only)

Please refer to Appendix A.

3.6 Conducted Band Edges Measurement

3.6.1 Limit of Band Edges

In any 100 kHz bandwidth outside the intentional radiation frequency band, the radio frequency power shall be at least 20 dB below the highest level of the radiated power. In addition, radiated emissions which fall in the restricted bands must also comply with the radiated emission limits.


3.6.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.6.3 Test Procedures

1. The testing follows ANSI C63.10-2013 clause 7.8.6.
2. Set the maximum power setting and enable the EUT to transmit continuously.
3. Set RBW = 100 kHz, VBW = 300 kHz. Band edge emissions must be at least 20 dB down from the highest emission level within the authorized band as measured with a 100 kHz RBW. The attenuation shall be 30 dB instead of 20 dB when RMS conducted output power procedure is used.
4. Enable hopping function of the EUT and then repeat step 2 and 3.
5. Measure and record the results in the test report.

3.6.4 Test Setup



3.6.5 Test Result of Conducted Band Edges

Please refer to Appendix A.

3.6.6 Test Result of Conducted Hopping Mode Band Edges

Please refer to Appendix A.

3.7 Conducted Spurious Emission Measurement

3.7.1 Limit of Spurious Emission Measurement

In any 100 kHz bandwidth outside the intentional radiation frequency band, the radio frequency power shall be at least 20 dB below the highest level of the radiated power. In addition, radiated emissions which fall in the restricted bands must also comply with the radiated emission limits.


3.7.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.7.3 Test Procedure

1. The testing follows ANSI C63.10-2013 clause 7.8.8.
2. The RF output of EUT is connected to the spectrum analyzer by RF cable and attenuator. The path loss is compensated to the results for each measurement.
3. Set the maximum power setting and enable the EUT to transmit continuously.
4. Set RBW = 100 kHz, VBW = 300 kHz, scan up through 10th harmonic. All harmonics / spurious must be at least 20 dB down from the highest emission level within the authorized band as measured with a 100 kHz RBW.
5. Measure and record the results in the test report.
6. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.

3.7.4 Test Setup



3.7.5 Test Result of Conducted Spurious Emission

Please refer to Appendix A.



3.8 Radiated Band Edges and Spurious Emission Measurement

3.8.1 Limit of Radiated Band Edges and Spurious Emission

In any 100 kHz bandwidth outside the intentional radiator frequency band, all harmonics / spurious must be at least 20 dB below the highest emission level within the authorized band. In addition, radiated emissions which fall in the restricted bands must also comply with the limits as below.

Frequency (MHz)	Field Strength (microvolts/meter)	Measurement Distance (meters)
0.009 – 0.490	2400/F(kHz)	300
0.490 – 1.705	24000/F(kHz)	30
1.705 – 30.0	30	30
30 – 88	100	3
88 – 216	150	3
216 - 960	200	3
Above 960	500	3

3.8.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.




3.8.3 Test Procedures

1. The EUT is placed on a turntable with 0.8 meter for frequency below 1 GHz and 1.5 meter for frequency above 1 GHz respectively above ground.
2. The EUT is set 3 meters away from the receiving antenna, which is mounted on the top of a variable height antenna tower.
3. For each suspected emission, the EUT is arranged to its worst case and then tune the Antenna tower (from 1 m to 4 m) and turntable (from 0 degree to 360 degrees) to find the maximum reading. A pre-amp and a high pass filter are used for the test in order to get better signal level to comply with the guidelines.
4. Set the maximum power setting and enable the EUT to transmit continuously.
5. Use the following spectrum analyzer settings:
 - (1) Span shall wide enough to fully capture the emission being measured;
 - (2) Set RBW = 100 kHz for $f < 1$ GHz, RBW = 1 MHz for $f > 1$ GHz ; VBW \geq RBW; Sweep = auto; Detector function = peak; Trace = max hold for peak
 - (3) For average measurement: use duty cycle correction factor method per 15.35(c).
Duty cycle = On time/100 milliseconds
On time = $N_1 \cdot L_1 + N_2 \cdot L_2 + \dots + N_{n-1} \cdot L_{n-1} + N_n \cdot L_n$
Where N_1 is number of type 1 pulses, L_1 is length of type 1 pulses, etc.
Average Emission Level = Peak Emission Level + $20 \cdot \log_{10}$ (Duty cycle)
6. Corrected Reading: Antenna Factor + Cable Loss + Read Level - Preamp Factor = Level
7. Radiated testing below 1 GHz is performed by adjusting the antenna tower from 1 m to 4 m and by rotating the turn table from 0 degree to 360 degrees to find the peak maximum hold reading. When there is no suspected emission found and the emission level is with at least 6 dB margin against QP limit line, the position is marked as “-”.
8. Radiated testing above 1 GHz is performed by adjusting the antenna tower from 1 m to 4 m and by rotating the turn table from 0 degree to 360 degrees to find the peak maximum hold reading for scanning all frequencies. When there is no suspected emission found and the harmonic emission level is with at least 6 dB margin against average limit line, the position is marked as “-”.


Note: The average levels are calculated from the peak level corrected with duty cycle correction factor (-24.76dB) derived from $20 \cdot \log_{10}$ (dwell time/100ms). This correction is only for signals that hop with the fundamental signal, such as band-edge and harmonic. Other spurious signals that are independent of the hopping signal would not use this correction.

3.8.4 Test Setup


For radiated test below 30MHz




For radiated test from 30MHz to 1GHz



For radiated test from 1GHz to 18GHz



For radiated test above 18GHz



3.8.5 Test Results of Radiated Spurious Emissions (9 kHz ~ 30 MHz)

The low frequency, which starts from 9 kHz to 30 MHz, is pre-scanned and the result which is 20 dB lower than the limit line is not reported.

There is adequate comparison measurement of both open-field test site and alternative test site - semi-Anechoic chamber according to 414788 D01 Radiated Test Site v01r01, and the result comes out very similar.

3.8.6 Test Result of Radiated Spurious at Band Edges

Please refer to Appendix B.

3.8.7 Duty Cycle

Please refer to Appendix C.

3.8.8 Test Result of Radiated Spurious Emission (30MHz ~ 10th Harmonic)

Please refer to Appendix B.



3.9 Antenna Requirements

3.9.1 Standard Applicable

An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator shall be considered sufficient to comply with the provisions of this section. The manufacturer may design the unit so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited. This requirement does not apply to carrier current devices or to devices operated under the provisions of §§ 15.211, 15.213, 15.217, 15.219, 15.221, or § 15.236. Further, this requirement does not apply to intentional radiators that must be professionally installed, such as perimeter protection systems and some field disturbance sensors, or to other intentional radiators which, in accordance with § 15.31(d), must be measured at the installation site. However, the installer shall be responsible for ensuring that the proper antenna is employed so that the limits in this part are not exceeded.

3.9.2 Antenna Anti-Replacement Construction

Unique (non-standard) antenna connector.



4 List of Measuring Equipment

Instrument	Brand Name	Model No.	Serial No.	Characteristics	Calibration Date	Test Date	Due Date	Remark
Loop Antenna	Rohde & Schwarz	HFH2-Z2	100315	9 kHz~30 MHz	Feb. 23, 2024	Aug. 26, 2024~Sep. 11, 2024	Feb. 22, 2025	Radiation (03CH16-HY)
SHF-EHF Horn Antenna	SCHWARZBECK	BBHA9170	1223	18GHz-40GHz	Jun. 24, 2024	Aug. 26, 2024~Sep. 11, 2024	Jun. 23, 2025	Radiation (03CH16-HY)
EMI Test Receiver	Keysight	N9038A(MXE)	MY57290111	3Hz~26.5GHz	Dec. 04, 2023	Aug. 26, 2024~Sep. 11, 2024	Dec. 03, 2024	Radiation (03CH16-HY)
Bilog Antenna	TESEQ	CBL 6111D & 00802N1D01N-06	47020 & 06	30MHz to 1GHz	Oct. 07, 2023	Aug. 26, 2024~Sep. 11, 2024	Oct. 06, 2024	Radiation (03CH16-HY)
Horn Antenna	SCHWARZBECK	BBHA 9120 D	9120D-1522	1G~18GHz	Mar. 28, 2024	Aug. 26, 2024~Sep. 11, 2024	Mar. 27, 2025	Radiation (03CH16-HY)
Amplifier	SONOMA	310N	371607	9kHz~1GHz	Jul. 02, 2024	Aug. 26, 2024~Sep. 11, 2024	Jul. 01, 2025	Radiation (03CH16-HY)
DC Power Supply	GW Instek	GPE-2323	GEU810968	0V~64V ; 0A~6A	Apr. 29, 2024	Aug. 26, 2024~Sep. 11, 2024	Apr. 28, 2025	Radiation (03CH16-HY)
Preamplifier	Keysight	83017A	MY53270264	1GHz~26.5GHz	Dec. 07, 2023	Aug. 26, 2024~Sep. 11, 2024	Dec. 06, 2024	Radiation (03CH16-HY)
Preamplifier	EMEC	EM1G18G	060812	1GHz~18GHz	Dec. 25, 2023	Aug. 26, 2024~Sep. 11, 2024	Dec. 24, 2024	Radiation (03CH16-HY)
Preamplifier	EMEC	EM18G40G	060801	18GHz~40GHz	May 27, 2024	Aug. 26, 2024~Sep. 11, 2024	May 26, 2025	Radiation (03CH16-HY)
Filter	Wainwright	WLK4-1000-15 30-8000-40SS	SN17	1.53GHz Low Pass Filter	Jan. 15, 2024	Aug. 26, 2024~Sep. 11, 2024	Jan. 14, 2025	Radiation (03CH16-HY)
Filter	Wainwright	WFKX12-2700-3000-18000-60ST	SN3	3GHz High Pass Filter	Jun. 28, 2024	Aug. 26, 2024~Sep. 11, 2024	Jun. 27, 2025	Radiation (03CH16-HY)
Filter	Wainwright	WFKX8-5872.5-6750-18000-40ST	SN27	6.75GHz High Pass Filter	Nov. 13, 2023	Aug. 26, 2024~Sep. 11, 2024	Nov. 12, 2024	Radiation (03CH16-HY)
RF Cable	HUBER + SUHNER	SUCOFLEX 102	803951/2	9K~30M	Mar. 06, 2024	Aug. 26, 2024~Sep. 11, 2024	Mar. 05, 2025	Radiation (03CH16-HY)
RF Cable	HUBER + SUHNER	SUCOFLEX 102/SUCOFLEX 104	EC-A5-300-5 757,805935/4 ,802434/4	30MHz~18GHz	Aug. 07, 2024	Aug. 26, 2024~Sep. 11, 2024	Aug. 06, 2025	Radiation (03CH16-HY)
RF Cable	HUBER + SUHNER	SUCOFLEX 102	804011/2,804012/2	18-40GHz	Jan. 02, 2024	Aug. 26, 2024~Sep. 11, 2024	Jan. 01, 2025	Radiation (03CH16-HY)
Software	Audix	E3 230621 V9	RK-002393	N/A	N/A	Aug. 26, 2024~Sep. 11, 2024	N/A	Radiation (03CH16-HY)
Controller	ChainTek	3000-1	N/A	Control Turn table & Ant Mast	N/A	Aug. 26, 2024~Sep. 11, 2024	N/A	Radiation (03CH16-HY)
Antenna Mast	ChainTek	MBS-520-1	N/A	1m~4m	N/A	Aug. 26, 2024~Sep. 11, 2024	N/A	Radiation (03CH16-HY)
Turn Table	ChainTek	T-200-S-1	N/A	0~360 Degree	N/A	Aug. 26, 2024~Sep. 11, 2024	N/A	Radiation (03CH16-HY)



Instrument	Brand Name	Model No.	Serial No.	Characteristics	Calibration Date	Test Date	Due Date	Remark
Hygrometer	TECPEL	DTM-303A	TP201996	N/A	Nov. 07, 2023	Aug. 14, 2024~Sep. 04, 2024	Nov. 06, 2024	Conducted (TH05-HY)
Power Meter	Agilent	E4416A	GB41292344	N/A	Jun. 26, 2024	Aug. 14, 2024~Sep. 04, 2024	Jun. 25, 2025	Conducted (TH05-HY)
Power Sensor	Agilent	E9327A	US40441548	50MHz~18GHz	Jun. 25, 2024	Aug. 14, 2024~Sep. 04, 2024	Jun. 24, 2025	Conducted (TH05-HY)
Signal Analyzer	Rohde & Schwarz	FSV3044	101466	10HZ~44GHZ	Jan. 24, 2024	Aug. 14, 2024~Sep. 04, 2024	Jan. 23, 2025	Conducted (TH05-HY)
Switch Control Mainframe	EM Electronics	EMSW18SE	SW200302 (BOX9)	N/A	Mar. 08, 2024	Aug. 14, 2024~Sep. 04, 2024	Mar. 07, 2025	Conducted (TH05-HY)
Software	Sporton	BTWIFI_Final_version:1.0(2024-04-11)	N/A	Conducted Items	N/A	Aug. 14, 2024~Sep. 04, 2024	N/A	Conducted (TH05-HY)



5 Measurement Uncertainty

Uncertainty of Radiated Emission Measurement (30 MHz ~ 1000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2U_{c(y)}$)	6.50 dB
---	---------

Uncertainty of Radiated Emission Measurement (1000 MHz ~ 6000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2U_{c(y)}$)	4.50 dB
---	---------

Uncertainty of Radiated Emission Measurement (6000 MHz ~ 18000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2U_{c(y)}$)	4.50 dB
---	---------

Uncertainty of Radiated Emission Measurement (18000 MHz ~ 40000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2U_{c(y)}$)	5.50 dB
---	---------

Appendix A. Test Result of Conducted Test Items

Test Engineer:	Shiming Liu	Temperature:	21~25	°C
Test Date:	2024/08/14~2024/09/04	Relative Humidity:	51~54	%

TEST RESULTS DATA									
20dB and 99% Occupied Bandwidth and Hopping Channel Separation									
Mod.	Data Rate	NTX	CH.	Freq. (MHz)	20db BW (MHz)	99% Bandwidth (MHz)	Hopping Channel Separation Measurement (MHz)	Hopping Channel Separation Measurement Limit (MHz)	Pass/Fail
DH	1Mbps	1	0	2402	1.034	0.953	0.994	0.6894	Pass
DH	1Mbps	1	39	2441	1.033	0.953	0.999	0.6888	Pass
DH	1Mbps	1	78	2480	1.037	0.952	1.007	0.6916	Pass
2DH	2Mbps	1	0	2402	1.340	1.197	1.003	0.8936	Pass
2DH	2Mbps	1	39	2441	1.342	1.197	1.003	0.8948	Pass
2DH	2Mbps	1	78	2480	1.344	1.197	1.003	0.8962	Pass
3DH	3Mbps	1	0	2402	1.292	1.181	1.016	0.8614	Pass
3DH	3Mbps	1	39	2441	1.281	1.180	1.012	0.8538	Pass
3DH	3Mbps	1	78	2480	1.266	1.181	1.007	0.8440	Pass

TEST RESULTS DATA						
Dwell Time						
Mod.	Hopping Channel Number Rate	Hops Over Occupancy Time (hops)	Package Transfer Time (msec)	Dwell Time (sec)	Limits (sec)	Pass/Fail
2DH5	79	106.670	2.90	0.31	0.4	Pass
2DH5 (AFH)	20	53.330	2.90	0.15	0.4	Pass


TEST RESULTS DATA					
Peak Power Table					
DH	CH.	NTX	Peak Power (dBm)	Power Limit (dBm)	Test Result
DH1	0	1	2.95	20.97	Pass
	39	1	2.56	20.97	Pass
	78	1	2.36	20.97	Pass
2DH1	0	1	1.54	20.97	Pass
	39	1	1.01	20.97	Pass
	78	1	0.84	20.97	Pass
3DH1	0	1	1.55	20.97	Pass
	39	1	1.08	20.97	Pass
	78	1	0.87	20.97	Pass

TEST RESULTS DATA				
Average Power Table				
(Reporting Only)				
DH	CH.	NTX	Average Power (dBm)	Duty Factor (dB)
DH1	0	1	2.49	5.17
	39	1	2.02	5.17
	78	1	1.88	5.17
2DH1	0	1	-1.49	5.06
	39	1	-2.01	5.06
	78	1	-2.06	5.06
3DH1	0	1	-1.48	5.06
	39	1	-2.00	5.06
	78	1	-2.05	5.06

TEST RESULTS DATA			
Number of Hopping Frequency			
Number of Hopping (Channel)	Adaptive Frequency Hopping (Channel)	Limits (Channel)	Pass/Fail
79	20	> 15	Pass




Number of Hopping Frequency






Hopping Channel Separation

<1Mbps>






<2Mbps>






<3Mbps>





Dwell Time


**Remark:**

1. In normal mode, hopping rate is 1600 hops/s with 6 slots in 79 hopping channels. With channel hopping rate (1600 / 6 / 79) in Occupancy Time Limit (0.4 x 79) (s), Hops Over Occupancy Time comes to (1600 / 6 / 79) x (0.4 x 79) = 106.67 hops.
2. In AFH mode, hopping rate is 800 hops/s with 6 slots in 20 hopping channels. With channel hopping rate (800 / 6 / 20) in Occupancy Time Limit (0.4 x 20) (s), Hops Over Occupancy Time comes to (800 / 6 / 20) x (0.4 x 20) = 53.33 hops.
3. Dwell Time(s) = Hops Over Occupancy Time (hops) x Package Transfer Time




20dB Bandwidth

<1Mbps>






<2Mbps>






<3Mbps>






99% Occupied Bandwidth

<1Mbps>






<2Mbps>






<3Mbps>






Band Edges

<1Mbps>




<2Mbps>






<3Mbps>






Hopping Mode Band Edges

<1Mbps>




<2Mbps>






<3Mbps>






Conducted Spurious Emission

<1Mbps>






<2Mbps>





<3Mbps>





Appendix B. Radiated Spurious Emission Test Data


Test Engineer :	Bill Chang, Gary Guo and Steven Wu	Temperature :	18.2~20.2°C
		Relative Humidity :	54.2~56.1%

C1. Radiated Spurious Emission Test Modes



Mode	Band (MHz)	Antenna	Modulation	Channel	Frequency	Data Rate	RU	Remark
Mode 1	2400-2483.5	10	Bluetooth BR_GFSK	00	2402	1Mbps	-	-
Mode 2	2400-2483.5	10	Bluetooth BR_GFSK	39	2441	1Mbps	-	-
Mode 3	2400-2483.5	10	Bluetooth BR_GFSK	78	2480	1Mbps	-	-
Mode 4	2400-2483.5	10	Bluetooth BR_GFSK	39	2441	1Mbps	-	LF
Mode 9	2400-2483.5	10	Bluetooth BR_GFSK	39	2441	1Mbps	-	SHF


C2. Summary of each worse mode

Mode	Modulation	Ch.	Freq. (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Pol.	Peak Avg.	Result	RU	Remark
1	Bluetooth BR_GFSK	00	2368.42	46.27	74.00	-27.73	V	Peak	Pass	-	Band Edge
			4804.00	40.70	74.00	-33.30	V	Peak	Pass	-	Harmonic
2	Bluetooth BR_GFSK	39	2484.34	47.81	74.00	-26.19	H	Peak	Pass	-	Band Edge
			7323.00	45.01	74.00	-28.99	V	Peak	Pass	-	Harmonic
3	Bluetooth BR_GFSK	78	2486.28	47.47	74.00	-26.53	V	Peak	Pass	-	Band Edge
			7440.00	44.21	74.00	-29.79	H	Peak	Pass	-	Harmonic
4	LF	39	35.82	28.57	40.00	-11.43	V	Peak	Pass	-	LF
9	SHF	39	25384.23	40.86	74.00	-33.14	V	Peak	Pass	-	SHF











Mode	1																																																																																	
	Band Edge																																																																																	
	2400-2483.5_Bluetooth BR_GFSK_CH00_2402MHz																																																																																	
ANT	10																																																																																	
Pol.	Vertical	Fundamental																																																																																
Peak	 <p>Site : 03CH16-HY Condition: PEAK_BE_74 3m 91200-1522_240328 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr></thead><tbody><tr><td>1</td><td>2368.42</td><td>46.27</td><td>74.00</td><td>-27.73</td><td>41.31</td><td>27.20</td><td>7.68</td><td>29.92</td><td>0.00 100 187 PEAK</td></tr><tr><td>2</td><td>2368.42</td><td>21.51</td><td>54.00</td><td>-32.49</td><td>--</td><td>--</td><td>--</td><td>--</td><td>100 187 AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor		1	2368.42	46.27	74.00	-27.73	41.31	27.20	7.68	29.92	0.00 100 187 PEAK	2	2368.42	21.51	54.00	-32.49	--	--	--	--	100 187 AVERAGE	 <p>Site : 03CH16-HY Condition: PEAK_74 3m 91200-1522_240328 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr></thead><tbody><tr><td>1</td><td>2402.00</td><td>89.82</td><td>-----</td><td>-----</td><td>84.60</td><td>27.40</td><td>7.73</td><td>29.91</td><td>0.00 100 187 PEAK</td></tr><tr><td>2</td><td>2402.00</td><td>65.06</td><td>-----</td><td>-----</td><td>--</td><td>--</td><td>--</td><td>--</td><td>100 187 AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor		1	2402.00	89.82	-----	-----	84.60	27.40	7.73	29.91	0.00 100 187 PEAK	2	2402.00	65.06	-----	-----	--	--	--	--	100 187 AVERAGE
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																									
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor																																																																										
1	2368.42	46.27	74.00	-27.73	41.31	27.20	7.68	29.92	0.00 100 187 PEAK																																																																									
2	2368.42	21.51	54.00	-32.49	--	--	--	--	100 187 AVERAGE																																																																									
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																									
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor																																																																										
1	2402.00	89.82	-----	-----	84.60	27.40	7.73	29.91	0.00 100 187 PEAK																																																																									
2	2402.00	65.06	-----	-----	--	--	--	--	100 187 AVERAGE																																																																									






Mode	1	
	Harmonic	
	2400-2483.5_Bluetooth BR_GFSK_CH00_2402MHz	
ANT	10	
Pol.	Horizontal	Vertical
14.47G ~14.5G Avg	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 HORIZONTAL	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 VERTICAL
17.7G ~18G Avg	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 HORIZONTAL	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 VERTICAL





Mode	2																																																																																	
	Band Edge - L																																																																																	
	2400-2483.5_Bluetooth BR_GFSK_CH39_2441MHz																																																																																	
ANT	10																																																																																	
Pol.	Horizontal	Fundamental																																																																																
Peak	 <p>Site : 03CH16-HY Condition: PEAK_BE_74 3m 91200-1522_240328 HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr></thead><tbody><tr><td>1</td><td>2376.02</td><td>46.36</td><td>74.00</td><td>-27.64</td><td>41.39</td><td>27.20</td><td>7.69</td><td>29.92</td><td>0.00</td></tr><tr><td>2</td><td>2376.02</td><td>21.60</td><td>54.00</td><td>-32.40</td><td>--</td><td>--</td><td>--</td><td>--</td><td>245</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor		1	2376.02	46.36	74.00	-27.64	41.39	27.20	7.69	29.92	0.00	2	2376.02	21.60	54.00	-32.40	--	--	--	--	245	 <p>Site : 03CH16-HY Condition: PEAK_74 3m 91200-1522_240328 HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr></thead><tbody><tr><td>1</td><td>2441.00</td><td>86.18</td><td>-----</td><td>-----</td><td>80.68</td><td>27.60</td><td>7.80</td><td>29.90</td><td>0.00</td></tr><tr><td>2</td><td>2441.00</td><td>61.42</td><td>-----</td><td>-----</td><td>--</td><td>--</td><td>--</td><td>--</td><td>245</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor		1	2441.00	86.18	-----	-----	80.68	27.60	7.80	29.90	0.00	2	2441.00	61.42	-----	-----	--	--	--	--	245
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																									
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor																																																																										
1	2376.02	46.36	74.00	-27.64	41.39	27.20	7.69	29.92	0.00																																																																									
2	2376.02	21.60	54.00	-32.40	--	--	--	--	245																																																																									
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																									
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor																																																																										
1	2441.00	86.18	-----	-----	80.68	27.60	7.80	29.90	0.00																																																																									
2	2441.00	61.42	-----	-----	--	--	--	--	245																																																																									





Mode	2	
	Band Edge - R	
	2400-2483.5_Bluetooth BR_GFSK_CH39_2441MHz	
ANT	10	
Pol.	Horizontal	Fundamental
Peak	 <p>Site : 03CH16-HY Condition: PEAK_BE_74 3m 91200-1522_248328 HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto Limit Read Ant Cable Preamp Aux APos TPos Freq Level Line Margin Level Factor Loss Factor Factor Remark MHz dBuV/m dBuV/m dB dBuV dB/m dB dB dB cm deg 1 2484.34 47.81 74.00 -26.19 42.13 27.70 7.86 29.88 0.00 245 0 PEAK 2 2484.34 23.05 54.00 -30.95 -- -- -- -- -- 245 0 AVERAGE</p> <p>Blank</p>	







Mode	2																																																																																	
	Band Edge - L																																																																																	
	2400-2483.5_Bluetooth BR_GFSK_CH39_2441MHz																																																																																	
ANT	10																																																																																	
Pol.	Vertical	Fundamental																																																																																
Peak	 <p>Site : 03CH16-HY Condition: PEAK_BE_74 3m 91200-1522_240328 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr></thead><tbody><tr><td>1</td><td>2388.99</td><td>46.00</td><td>74.00</td><td>-28.00</td><td>48.91</td><td>27.29</td><td>7.71</td><td>29.91</td><td>0.00 2 PEAK</td></tr><tr><td>2</td><td>2388.99</td><td>21.24</td><td>54.00</td><td>-32.76</td><td>--</td><td>--</td><td>--</td><td>--</td><td>200 2 AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor		1	2388.99	46.00	74.00	-28.00	48.91	27.29	7.71	29.91	0.00 2 PEAK	2	2388.99	21.24	54.00	-32.76	--	--	--	--	200 2 AVERAGE	 <p>Site : 03CH16-HY Condition: PEAK_74 3m 91200-1522_240328 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr></thead><tbody><tr><td>1</td><td>2441.00</td><td>90.63</td><td>-----</td><td>-----</td><td>85.13</td><td>27.60</td><td>7.80</td><td>29.90</td><td>0.00 2 PEAK</td></tr><tr><td>2</td><td>2441.00</td><td>65.87</td><td>-----</td><td>-----</td><td>--</td><td>--</td><td>--</td><td>--</td><td>200 2 AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor		1	2441.00	90.63	-----	-----	85.13	27.60	7.80	29.90	0.00 2 PEAK	2	2441.00	65.87	-----	-----	--	--	--	--	200 2 AVERAGE
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																									
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor																																																																										
1	2388.99	46.00	74.00	-28.00	48.91	27.29	7.71	29.91	0.00 2 PEAK																																																																									
2	2388.99	21.24	54.00	-32.76	--	--	--	--	200 2 AVERAGE																																																																									
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																									
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor																																																																										
1	2441.00	90.63	-----	-----	85.13	27.60	7.80	29.90	0.00 2 PEAK																																																																									
2	2441.00	65.87	-----	-----	--	--	--	--	200 2 AVERAGE																																																																									





Mode	2	
	Band Edge - R	
	2400-2483.5_Bluetooth BR_GFSK_CH39_2441MHz	
ANT	10	
Pol.	Vertical	Fundamental
Peak	 <p>Site : 03CH16-HY Condition: PEAK_BE_74 3m 91200-1522_248328 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto Limit Read Ant Cable Preamp Aux APos TPos Freq Level Line Margin Level Factor Loss Factor Factor Remark MHz dBuV/m dBuV/m dB dB/m dB dB dB cm deg 1 2498.08 46.96 74.00 -27.04 41.26 27.70 7.88 29.88 0.00 200 2 PEAK 2 2498.08 22.20 54.00 -31.88 -- -- -- -- -- 200 2 AVERAGE</p>	Blank







Mode	2	
	Harmonic	
	2400-2483.5_Bluetooth BR_GFSK_CH39_2441MHz	
ANT	10	
Pol.	Horizontal	Vertical
14.47G ~14.5G Avg	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 HORIZONTAL	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 VERTICAL
17.7G ~18G Avg	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 HORIZONTAL	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 VERTICAL



Mode	3																																																																																	
	Band Edge																																																																																	
	2400-2483.5_Bluetooth BR_GFSK_CH78_2480MHz																																																																																	
ANT	10																																																																																	
Pol.	Horizontal	Fundamental																																																																																
Peak	 <p>Site : 03CH16-HY Condition: PEAK_BE_74 3m 91200-1522_248328 HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr></thead><tbody><tr><td>1</td><td>2491.06</td><td>47.14</td><td>74.00</td><td>-26.86</td><td>41.45</td><td>27.70</td><td>7.87</td><td>29.88</td><td>0.00 193 15 PEAK</td></tr><tr><td>2</td><td>2491.06</td><td>22.38</td><td>54.00</td><td>-31.62</td><td>--</td><td>--</td><td>--</td><td>--</td><td>193 15 AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor		1	2491.06	47.14	74.00	-26.86	41.45	27.70	7.87	29.88	0.00 193 15 PEAK	2	2491.06	22.38	54.00	-31.62	--	--	--	--	193 15 AVERAGE	 <p>Site : 03CH16-HY Condition: PEAK_74 3m 91200-1522_248328 HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr></thead><tbody><tr><td>1</td><td>2480.00</td><td>90.49</td><td>-----</td><td>-----</td><td>84.83</td><td>27.70</td><td>7.85</td><td>29.89</td><td>0.00 193 15 PEAK</td></tr><tr><td>2</td><td>2480.00</td><td>65.73</td><td>-----</td><td>-----</td><td>--</td><td>--</td><td>--</td><td>--</td><td>193 15 AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor		1	2480.00	90.49	-----	-----	84.83	27.70	7.85	29.89	0.00 193 15 PEAK	2	2480.00	65.73	-----	-----	--	--	--	--	193 15 AVERAGE
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																									
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor																																																																										
1	2491.06	47.14	74.00	-26.86	41.45	27.70	7.87	29.88	0.00 193 15 PEAK																																																																									
2	2491.06	22.38	54.00	-31.62	--	--	--	--	193 15 AVERAGE																																																																									
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																									
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor																																																																										
1	2480.00	90.49	-----	-----	84.83	27.70	7.85	29.89	0.00 193 15 PEAK																																																																									
2	2480.00	65.73	-----	-----	--	--	--	--	193 15 AVERAGE																																																																									







Mode	3																																																																																																					
	Band Edge																																																																																																					
	2400-2483.5_Bluetooth BR_GFSK_CH78_2480MHz																																																																																																					
ANT	10																																																																																																					
Pol.	Vertical	Fundamental																																																																																																				
Peak	 <p>Site : 03CH16-HY Condition: PEAK_BE_74 3m 91200-1522_248328 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th></th> <th>Limit</th> <th>Read</th> <th>Ant</th> <th>Cable</th> <th>Preamp</th> <th>Aux</th> <th>APos</th> <th>TPos</th> <th>Remark</th> </tr> <tr> <th>Freq</th> <th>Level</th> <th>Line Margin</th> <th>Level</th> <th>Factor</th> <th>Loss</th> <th>Factor</th> <th>Factor</th> <th>Factor</th> <th></th> </tr> </thead> <tbody> <tr> <td>1</td> <td>2486.28</td> <td>47.47</td> <td>74.00</td> <td>-26.53</td> <td>41.79</td> <td>27.70</td> <td>7.86</td> <td>29.88</td> <td>0.00</td> </tr> <tr> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>100 280 PEAK</td> </tr> <tr> <td>2</td> <td>2486.28</td> <td>22.71</td> <td>54.00</td> <td>-31.29</td> <td>--</td> <td>--</td> <td>--</td> <td>--</td> <td>100 280 AVERAGE</td> </tr> </tbody> </table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor		1	2486.28	47.47	74.00	-26.53	41.79	27.70	7.86	29.88	0.00										100 280 PEAK	2	2486.28	22.71	54.00	-31.29	--	--	--	--	100 280 AVERAGE	 <p>Site : 03CH16-HY Condition: PEAK_74 3m 91200-1522_248328 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th></th> <th>Limit</th> <th>Read</th> <th>Ant</th> <th>Cable</th> <th>Preamp</th> <th>Aux</th> <th>APos</th> <th>TPos</th> <th>Remark</th> </tr> <tr> <th>Freq</th> <th>Level</th> <th>Line Margin</th> <th>Level</th> <th>Factor</th> <th>Loss</th> <th>Factor</th> <th>Factor</th> <th>Factor</th> <th></th> </tr> </thead> <tbody> <tr> <td>1</td> <td>2480.00</td> <td>95.57</td> <td>-----</td> <td>-----</td> <td>89.91</td> <td>27.70</td> <td>7.85</td> <td>29.89</td> <td>0.00</td> </tr> <tr> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>100 280 PEAK</td> </tr> <tr> <td>2</td> <td>2480.00</td> <td>70.81</td> <td>-----</td> <td>-----</td> <td>--</td> <td>--</td> <td>--</td> <td>--</td> <td>100 280 AVERAGE</td> </tr> </tbody> </table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor		1	2480.00	95.57	-----	-----	89.91	27.70	7.85	29.89	0.00										100 280 PEAK	2	2480.00	70.81	-----	-----	--	--	--	--	100 280 AVERAGE
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																													
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor																																																																																														
1	2486.28	47.47	74.00	-26.53	41.79	27.70	7.86	29.88	0.00																																																																																													
									100 280 PEAK																																																																																													
2	2486.28	22.71	54.00	-31.29	--	--	--	--	100 280 AVERAGE																																																																																													
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																													
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor	Factor																																																																																														
1	2480.00	95.57	-----	-----	89.91	27.70	7.85	29.89	0.00																																																																																													
									100 280 PEAK																																																																																													
2	2480.00	70.81	-----	-----	--	--	--	--	100 280 AVERAGE																																																																																													




Mode	3																																																																																																																									
	Harmonic																																																																																																																									
	2400-2483.5_Bluetooth BR_GFSK_CH78_2480MHz																																																																																																																									
ANT	10																																																																																																																									
Pol.	Horizontal																																																																																																																									
Peak	<p>Site : 03CH16-HY Condition: PEAK_74 3m 91200-1522 240328 HORIZONTAL</p> <table border="1"> <thead> <tr> <th></th> <th>Limit</th> <th>Read</th> <th>Ant</th> <th>Cable</th> <th>Preamp</th> <th>Aux</th> <th>APos</th> <th>TPos</th> <th>Remark</th> </tr> <tr> <th>Freq</th> <th>Level</th> <th>Line Margin</th> <th>Level Factor</th> <th>Loss Factor</th> <th>Factor</th> <th></th> <th></th> <th></th> <th></th> </tr> </thead> <tbody> <tr> <td>1</td> <td>4960.00</td> <td>42.03</td> <td>74.00</td> <td>-31.97</td> <td>63.29</td> <td>33.02</td> <td>11.06</td> <td>65.87</td> <td>0.53</td> </tr> <tr> <td>2</td> <td>4960.00</td> <td>17.27</td> <td>54.00</td> <td>-36.73</td> <td>--</td> <td>--</td> <td>--</td> <td>--</td> <td>--</td> </tr> <tr> <td>3</td> <td>7440.00</td> <td>44.21</td> <td>74.00</td> <td>-29.79</td> <td>59.47</td> <td>36.32</td> <td>13.38</td> <td>65.47</td> <td>0.51</td> </tr> <tr> <td>4</td> <td>7440.00</td> <td>19.45</td> <td>54.00</td> <td>-34.55</td> <td>--</td> <td>--</td> <td>--</td> <td>--</td> <td>--</td> </tr> </tbody> </table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor					1	4960.00	42.03	74.00	-31.97	63.29	33.02	11.06	65.87	0.53	2	4960.00	17.27	54.00	-36.73	--	--	--	--	--	3	7440.00	44.21	74.00	-29.79	59.47	36.32	13.38	65.47	0.51	4	7440.00	19.45	54.00	-34.55	--	--	--	--	--	<p>Site : 03CH16-HY Condition: PEAK_74 3m 91200-1522 240328 VERTICAL</p> <table border="1"> <thead> <tr> <th></th> <th>Limit</th> <th>Read</th> <th>Ant</th> <th>Cable</th> <th>Preamp</th> <th>Aux</th> <th>APos</th> <th>TPos</th> <th>Remark</th> </tr> <tr> <th>Freq</th> <th>Level</th> <th>Line Margin</th> <th>Level Factor</th> <th>Loss Factor</th> <th>Factor</th> <th></th> <th></th> <th></th> <th></th> </tr> </thead> <tbody> <tr> <td>1</td> <td>4960.00</td> <td>41.61</td> <td>74.00</td> <td>-32.39</td> <td>62.87</td> <td>33.02</td> <td>11.06</td> <td>65.87</td> <td>0.53</td> </tr> <tr> <td>2</td> <td>4960.00</td> <td>16.85</td> <td>54.00</td> <td>-37.15</td> <td>--</td> <td>--</td> <td>--</td> <td>--</td> <td>--</td> </tr> <tr> <td>3</td> <td>7440.00</td> <td>43.83</td> <td>74.00</td> <td>-30.17</td> <td>59.09</td> <td>36.32</td> <td>13.38</td> <td>65.47</td> <td>0.51</td> </tr> <tr> <td>4</td> <td>7440.00</td> <td>19.07</td> <td>54.00</td> <td>-34.93</td> <td>--</td> <td>--</td> <td>--</td> <td>--</td> <td>--</td> </tr> </tbody> </table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor					1	4960.00	41.61	74.00	-32.39	62.87	33.02	11.06	65.87	0.53	2	4960.00	16.85	54.00	-37.15	--	--	--	--	--	3	7440.00	43.83	74.00	-30.17	59.09	36.32	13.38	65.47	0.51	4	7440.00	19.07	54.00	-34.93	--	--	--	--	--
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																	
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																																																																					
1	4960.00	42.03	74.00	-31.97	63.29	33.02	11.06	65.87	0.53																																																																																																																	
2	4960.00	17.27	54.00	-36.73	--	--	--	--	--																																																																																																																	
3	7440.00	44.21	74.00	-29.79	59.47	36.32	13.38	65.47	0.51																																																																																																																	
4	7440.00	19.45	54.00	-34.55	--	--	--	--	--																																																																																																																	
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																	
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																																																																					
1	4960.00	41.61	74.00	-32.39	62.87	33.02	11.06	65.87	0.53																																																																																																																	
2	4960.00	16.85	54.00	-37.15	--	--	--	--	--																																																																																																																	
3	7440.00	43.83	74.00	-30.17	59.09	36.32	13.38	65.47	0.51																																																																																																																	
4	7440.00	19.07	54.00	-34.93	--	--	--	--	--																																																																																																																	
Avg																																																																																																																										




Mode	3	
	Harmonic	
	2400-2483.5_Bluetooth BR_GFSK_CH78_2480MHz	
ANT	10	
Pol.	Horizontal	Vertical
14.47G ~14.5G Avg	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 HORIZONTAL	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 VERTICAL
17.7G ~18G Avg	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 HORIZONTAL	 Site : 03CH16-HY Condition: AVG_54 3m 91200-1522_240328 VERTICAL



Mode	4																																																																																																																																																																	
	LF																																																																																																																																																																	
	2400-2483.5_Bluetooth BR_GFSK_CH39_2441MHz																																																																																																																																																																	
ANT	10																																																																																																																																																																	
Pol.	Horizontal 																																																																																																																																																																	
QP/ Peak	<p>Site : 03CH16-HY Condition: QP 3m CBL6111D&00802NID01N-06 _47920 & 06 HORIZONTAL</p> <table border="1"> <thead> <tr> <th>Freq</th> <th>Limit</th> <th>Read</th> <th>Ant</th> <th>Cable</th> <th>Preamp</th> <th>Aux</th> <th>APos</th> <th>TPos</th> <th>Remark</th> </tr> <tr> <th>MHz</th> <th>dBuV/m</th> <th>dBuV/m</th> <th>dB</th> <th>dB</th> <th>dB</th> <th>dB</th> <th>cm</th> <th>deg</th> <th></th> </tr> </thead> <tbody> <tr><td>1</td><td>81.41</td><td>22.83</td><td>40.00</td><td>-17.17</td><td>40.40</td><td>13.55</td><td>1.42</td><td>32.54</td><td>0.00</td></tr> <tr><td>2</td><td>187.14</td><td>21.35</td><td>43.50</td><td>-22.15</td><td>36.63</td><td>14.93</td><td>2.13</td><td>32.34</td><td>0.00</td></tr> <tr><td>3</td><td>265.71</td><td>20.48</td><td>46.00</td><td>-25.52</td><td>30.62</td><td>19.68</td><td>2.52</td><td>32.34</td><td>0.00</td></tr> <tr><td>4</td><td>514.03</td><td>23.82</td><td>46.00</td><td>-22.18</td><td>29.32</td><td>23.92</td><td>3.52</td><td>32.94</td><td>0.00</td></tr> <tr><td>5</td><td>705.12</td><td>31.94</td><td>46.00</td><td>-14.06</td><td>33.39</td><td>26.60</td><td>4.13</td><td>32.18</td><td>0.00</td></tr> <tr><td>6</td><td>947.62</td><td>31.65</td><td>46.00</td><td>-14.35</td><td>27.89</td><td>30.73</td><td>4.80</td><td>31.77</td><td>0.00</td></tr> </tbody> </table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dB	dB	dB	cm	deg		1	81.41	22.83	40.00	-17.17	40.40	13.55	1.42	32.54	0.00	2	187.14	21.35	43.50	-22.15	36.63	14.93	2.13	32.34	0.00	3	265.71	20.48	46.00	-25.52	30.62	19.68	2.52	32.34	0.00	4	514.03	23.82	46.00	-22.18	29.32	23.92	3.52	32.94	0.00	5	705.12	31.94	46.00	-14.06	33.39	26.60	4.13	32.18	0.00	6	947.62	31.65	46.00	-14.35	27.89	30.73	4.80	31.77	0.00	Vertical <p>Site : 03CH16-HY Condition: QP 3m CBL6111D&00802NID01N-06 _47920 & 06 VERTICAL</p> <table border="1"> <thead> <tr> <th>Freq</th> <th>Limit</th> <th>Read</th> <th>Ant</th> <th>Cable</th> <th>Preamp</th> <th>Aux</th> <th>APos</th> <th>TPos</th> <th>Remark</th> </tr> <tr> <th>MHz</th> <th>dBuV/m</th> <th>dBuV/m</th> <th>dB</th> <th>dB</th> <th>dB</th> <th>dB</th> <th>cm</th> <th>deg</th> <th></th> </tr> </thead> <tbody> <tr><td>1</td><td>35.82</td><td>28.57</td><td>40.00</td><td>-11.43</td><td>38.45</td><td>21.75</td><td>0.94</td><td>32.57</td><td>0.00</td></tr> <tr><td>2</td><td>188.11</td><td>27.71</td><td>43.50</td><td>-15.79</td><td>43.03</td><td>14.91</td><td>2.13</td><td>32.36</td><td>0.00</td></tr> <tr><td>3</td><td>239.52</td><td>23.62</td><td>46.00</td><td>-22.38</td><td>36.47</td><td>17.21</td><td>2.40</td><td>32.46</td><td>0.00</td></tr> <tr><td>4</td><td>494.63</td><td>24.90</td><td>46.00</td><td>-21.10</td><td>30.47</td><td>23.82</td><td>3.44</td><td>32.83</td><td>0.00</td></tr> <tr><td>5</td><td>709.97</td><td>30.93</td><td>46.00</td><td>-15.07</td><td>32.25</td><td>26.71</td><td>4.14</td><td>32.17</td><td>0.00</td></tr> <tr><td>6</td><td>942.77</td><td>32.99</td><td>46.00</td><td>-13.01</td><td>29.54</td><td>30.49</td><td>4.79</td><td>31.83</td><td>0.00</td></tr> </tbody> </table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dB	dB	dB	cm	deg		1	35.82	28.57	40.00	-11.43	38.45	21.75	0.94	32.57	0.00	2	188.11	27.71	43.50	-15.79	43.03	14.91	2.13	32.36	0.00	3	239.52	23.62	46.00	-22.38	36.47	17.21	2.40	32.46	0.00	4	494.63	24.90	46.00	-21.10	30.47	23.82	3.44	32.83	0.00	5	709.97	30.93	46.00	-15.07	32.25	26.71	4.14	32.17	0.00	6	942.77	32.99	46.00	-13.01	29.54	30.49	4.79	31.83	0.00
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																																																									
MHz	dBuV/m	dBuV/m	dB	dB	dB	dB	cm	deg																																																																																																																																																										
1	81.41	22.83	40.00	-17.17	40.40	13.55	1.42	32.54	0.00																																																																																																																																																									
2	187.14	21.35	43.50	-22.15	36.63	14.93	2.13	32.34	0.00																																																																																																																																																									
3	265.71	20.48	46.00	-25.52	30.62	19.68	2.52	32.34	0.00																																																																																																																																																									
4	514.03	23.82	46.00	-22.18	29.32	23.92	3.52	32.94	0.00																																																																																																																																																									
5	705.12	31.94	46.00	-14.06	33.39	26.60	4.13	32.18	0.00																																																																																																																																																									
6	947.62	31.65	46.00	-14.35	27.89	30.73	4.80	31.77	0.00																																																																																																																																																									
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																																																									
MHz	dBuV/m	dBuV/m	dB	dB	dB	dB	cm	deg																																																																																																																																																										
1	35.82	28.57	40.00	-11.43	38.45	21.75	0.94	32.57	0.00																																																																																																																																																									
2	188.11	27.71	43.50	-15.79	43.03	14.91	2.13	32.36	0.00																																																																																																																																																									
3	239.52	23.62	46.00	-22.38	36.47	17.21	2.40	32.46	0.00																																																																																																																																																									
4	494.63	24.90	46.00	-21.10	30.47	23.82	3.44	32.83	0.00																																																																																																																																																									
5	709.97	30.93	46.00	-15.07	32.25	26.71	4.14	32.17	0.00																																																																																																																																																									
6	942.77	32.99	46.00	-13.01	29.54	30.49	4.79	31.83	0.00																																																																																																																																																									



Appendix C. Duty Cycle Plots



Note:

1. Worst case Duty cycle = on time/100 milliseconds = $2 * 2.89 / 100 = 5.78 \%$
2. Worst case Duty cycle correction factor = $20 * \log(\text{Duty cycle}) = -24.76 \text{ dB}$
3. **DH5** has the highest duty cycle worst case and is reported.

Duty Cycle Correction Factor Consideration for AFH mode:

Bluetooth normal hopping rate is 1600Hz and reduced to 800Hz in AFH mode; due to the reduced number of hopping frequencies, with the same packet configuration the dwell time in each channel frequency within 100msec period is longer in AFH mode than normal mode.

In AFH mode, the minimum hopping frequencies are 20, to get the longest dwell time DH5 packet is observed; the on time period to have DH5 packet completing one hopping sequence is

$$2.89 \text{ ms} \times 20 \text{ channels} = 57.8 \text{ ms}$$

There cannot be 2 complete hopping sequences within 100ms period, considering the random hopping behavior, maximum 2 hops can be possibly observed within the period. $[100 \text{ ms} / 57.8 \text{ ms}] = 2 \text{ hops}$
Thus, the maximum possible ON time:

$$2.89 \text{ ms} \times 2 = 5.78 \text{ ms}$$

Worst case Duty Cycle Correction factor, which is derived from the maximum possible ON time,

$$20 \times \log(5.78 \text{ ms}/100 \text{ ms}) = -24.76 \text{ dB}$$