

Model: A03875		Test Number: 200715			
MPE Calculator	RF Exposure uses EIRP for calculation. EIRP is based on TX power added to the antenna gain in dBi.				
	dBi = dB gain compared to an isotropic radiator.				
	S = power density in mW/cm ²				
	Transmitter Output power (mW)	26.8			
	Transmitter Output power (W)	0.027			
Output Power for % duty Cycle operation (Watts)	100	0.027	Antenna Gain (dBi)	5.91	
Output Power for 100% duty Cycle operation (Watts)		0.027	Antenna Gain (Numeric)	3.90	
Tx Frequency (MHz)	2437	Calculation power (Watts)	0.027	dBd + 2.17 = dBi	dBi to dBd
				Antenna Gain (dBd)	3.74
Cable Loss (dB)	0.0	Adjusted Power (dBm)	14.28	Antenna minus cable (dBi)	5.91
				Antenna Gain (Numeric)	3.90
	Calculated ERP (mw)	63.387	EIRP = Po(dBm) + Gain (dB)		
	Calculated EIRP (mw)	104.472	Radiated (EIRP) dBm	20.190	
			ERP = EIRP - 2.17 dB		
			Radiated (ERP) dBm	18.020	
	<div style="border: 1px solid black; padding: 5px; width: fit-content;"> $\text{Power density (S) mW/cm}^2 = \frac{\text{EIRP}}{4\pi r^2}$ <p>r (cm) EIRP (mW)</p> </div>				
	Occupational Limit				
	FCC radio frequency radiation exposure limits per 1.1310				
		Frequency (MHz)	Occupational Limit (mW/cm ²)	Public Limit (mW/cm ²)	
5	mW/cm ²	30-300	1	0.2	
50	W/m ²				
	General Public Limit	300-1,500	ƒ/300	ƒ/1500	
1	mW/cm ²	1,500-10,000	5	1	
10	W/m ²				
	Occupational Limit				
	IC radio frequency radiation exposure limits per RSS-102				
		Frequency (MHz)	Occupational Limit (W/m ²)	Public Limit (W/m ²)	
0.6455f ^{0.5}	W/m ²	100-6,000	0.6455f ^{0.5}		
39.7	W/m ²				
	General Public Limit	100-6,000			
0.02619f ^{0.6834}	W/m ²	6,000-15,000	50		
5.4	W/m ²	48-300		1.291	
		300-6,000		0.02619f ^{0.6834}	
		6,000-15,000	50	10	
f = Transmit Frequency (MHz)			f (MHz) =	2437 MHz	
P _T = Power Input to Antenna (mW)			P _T (mW) =	26.7917 mW	
Duty cycle (percentage of operation)			% =	100 %	
P _A = Adjusted Power due to Duty cycle or Cable Loss (mW)			P _A (mW) =	26.79 mW	
G _N = Numeric Gain of the Antenna			G _N (numeric) =	3.90 numeric	
S ₂₀ = Power Density of device at 20cm (mW/m ²)		S ₂₀ =(P _A G _N)/(4πR ₂₀) ²	S ₂₀ (mW/m ²) =	0.02 mW/m ²	
S ₂₀ = Power Density of device at 20cm (W/m ²)		S ₂₀ =(P _A G _N)/(4πR ₂₀) ²	S ₂₀ (W/m ²) =	0.21 W/m ²	
S _L = Power Density Limit (W/m ²)			S _L (W/m ²) =	5.404 W/m ²	
R _C = Minimum distance to the Radiating Element for Compliance (cm)		R _C =√(P _A G _N /4πS _L)	R _C (cm) =	3.9 cm	
S _C = Power Density of the device at the Compliance Distance R _C (W/m ²)		S _C =(P _A G _N)/(4πR _C) ²	S _C (W/m ²) =	5.40 W/m ²	
R ₂₀ = 20cm			R ₂₀ =	20 cm	
	For Compliance with Canada General Population Limits, User Manual must indicate a minimum separation distance of				3.9 cm
	Or in Meters for Compliance with Canada General Population Limits, a minimum separation distance of				0.04 Meters

Rogers Labs, Inc.
4405 West 259th Terrace
Louisburg, KS 66053
Phone/Fax: (913) 837-3214
Revision 1

Garmin International, Inc.
Model: A03875
Test: 200715
Test to: CFR47 15.C, RSS-210, RSS-247
File: A03875 RFExp

SN's: 3336565130, 3327593326
FCC ID: IPH-03875
IC: 1792A-03875
Date: October 19, 2020
Page 1 of 1