

FCC SAR Test Report

APPLICANT : HTC Corporation
EQUIPMENT : Smartphone
MODEL NAME : PG05100
FCC ID : NM8PG05100
STANDARD : FCC 47 CFR Part 2 (2.1093)
IEEE C95.1-1991
IEEE 1528-2003
FCC OET Bulletin 65 Supplement C (Edition 01-01)

The product was received on Oct. 15, 2010 and completely tested on Jan. 08, 2011. We, SPORTON INTERNATIONAL INC., would like to declare that the tested sample has been evaluated in accordance with the procedures and shown the compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of SPORTON INTERNATIONAL INC., the test report shall not be reproduced except in full.

Reviewed by:



Roy Wu / Manager



SPORTON INTERNATIONAL INC.

No. 52, Hwa Ya 1st Rd., Hwa Ya Technology Park, Kwei-Shan Hsiang, Tao Yuan Hsien, Taiwan, R.O.C.

Table of Contents

| | |
|--|-----------|
| Revision History | 3 |
| 1. Statement of Compliance | 4 |
| 2. Administration Data | 5 |
| 2.1 Testing Laboratory | 5 |
| 2.2 Applicant | 5 |
| 2.3 Manufacturer | 5 |
| 2.4 Application Details | 5 |
| 3. General Information | 6 |
| 3.1 Description of Device Under Test (DUT) | 6 |
| 3.2 Applied Standards | 6 |
| 3.3 Device Category and SAR Limits | 6 |
| 3.4 Test Conditions | 7 |
| 3.4.1 Ambient Condition | 7 |
| 3.4.2 Test Configuration | 7 |
| 4. Specific Absorption Rate (SAR) | 10 |
| 4.1 Introduction | 10 |
| 4.2 SAR Definition | 10 |
| 5. SAR Measurement System | 11 |
| 5.1 E-Field Probe | 12 |
| 5.1.1 E-Field Probe Specification | 12 |
| 5.1.2 E-Field Probe Calibration | 13 |
| 5.2 Data Acquisition Electronics (DAE) | 13 |
| 5.3 Robot | 13 |
| 5.4 Measurement Server | 14 |
| 5.5 Phantom | 15 |
| 5.6 Device Holder | 16 |
| 5.7 Data Storage and Evaluation | 18 |
| 5.7.1 Data Storage | 18 |
| 5.7.2 Data Evaluation | 18 |
| 5.8 Test Equipment List | 20 |
| 6. Tissue Simulating Liquids | 21 |
| 7. Uncertainty Assessment | 24 |
| 8. SAR Measurement Evaluation | 26 |
| 8.1 Purpose of System Performance check | 26 |
| 8.2 System Setup | 26 |
| 8.3 Validation Results | 28 |
| 9. DUT Testing Position | 29 |
| 10. Measurement Procedures | 32 |
| 10.1 Spatial Peak SAR Evaluation | 32 |
| 10.2 Area & Zoom Scan Procedures | 33 |
| 10.3 Volume Scan Procedures | 33 |
| 10.4 SAR Averaged Methods | 33 |
| 10.5 Power Drift Monitoring | 33 |
| 11. SAR Test Results | 34 |
| 11.1 Conducted Power (Unit: dBm) | 34 |
| 11.1.1 Maximum Transmit Power Results with Power Reduction Enabled | 35 |
| 11.2 Test Records for Head SAR Test | 38 |
| 11.3 Test Records for Body SAR Test | 40 |
| 11.4 Simultaneous Transmission SAR Analysis and Measurements | 42 |
| 12. References | 59 |
| Appendix A. Plots of System Performance Check | |
| Appendix B. Plots of SAR Measurement | |
| Appendix C. DASY Calibration Certificate | |
| Appendix D. Test Setup Photos | |
| Appendix E. FCC 3G SAR Measurement Procedures | |



Revision History

| REPORT NO. | VERSION | DESCRIPTION | ISSUED DATE |
|------------|---------|--|---------------|
| FA001550A | Rev. 01 | Initial issue of report | Nov. 29, 2010 |
| FA001550A | Rev. 02 | Update report for retest the volume scan | Jan. 09, 2011 |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |

1. Statement of Compliance

The maximum results of Specific Absorption Rate (SAR) found during testing for **HTC Corporation Smartphone PG05100** are as follows (with expanded uncertainty 21.4 % for 300 MHz to 3 GHz).

<Standalone SAR>

| Band | | Position | SAR _{1g} (W/kg) |
|-----------------------|--------------|----------|-----------------------------|
| Ant-1 (1xRTT) | CDMA2000 BC0 | Head | 0.428 |
| | | Body | 0.545 |
| | CDMA2000 BC1 | Head | 1.19 |
| | | Body | 1.46 |
| Ant-2 (EVDO / LTE) | CDMA2000 BC0 | Head | 0.623 |
| | | Body | 0.395 |
| | CDMA2000 BC1 | Head | 1.20 |
| | | Body | 0.989 |
| | LTE Band 13 | Head | 0.455 |
| | | Body | 0.449 |

<Volume Scan SAR>

| Band | Test Position | Channel | Multi Band SAR _{1g} (W/kg) |
|--------------------|---------------|---------|--|
| CDMA2000 BC1 1xRTT | Left Check | 25 | 1.31 |
| LTE Band 13 | | 23230 | |
| 802.11b | | 11 | |

This device is in compliance with Specific Absorption Rate (SAR) for general population/uncontrolled exposure limits (1.6 W/kg) specified in FCC 47 CFR part 2 (2.1093) and ANSI/IEEE C95.1-1991, and had been tested in accordance with the measurement methods and procedures specified in IEEE 1528-2003 and FCC OET Bulletin 65 Supplement C (Edition 01-01).

2. Administration Data

2.1 Testing Laboratory

| | |
|--------------------|---|
| Test Site | SPORTON INTERNATIONAL INC. |
| Test Site Location | No. 52, Hwa Ya 1 st Rd., Hwa Ya Technology Park, Kwei-Shan Hsiang, Tao Yuan Hsien, Taiwan, R.O.C. TEL: +886-3-327-3456 FAX: +886-3-328-4978 |

2.2 Applicant

| | |
|--------------|---|
| Company Name | HTC Corporation |
| Address | No. 23, Xinghua Rd., Taoyuan City, Taiwan |

2.3 Manufacturer

| | |
|--------------|---|
| Company Name | HTC Corporation |
| Address | No. 23, Xinghua Rd., Taoyuan City, Taiwan |

2.4 Application Details

| | |
|--------------------------------|---------------|
| Date of Receipt of Application | Oct. 15, 2010 |
| Date of Start during the Test | Oct. 25, 2010 |
| Date of End during the Test | Jan. 08, 2011 |

3. General Information

3.1 Description of Device Under Test (DUT)

| Product Feature & Specification | |
|---------------------------------|---|
| DUT Type | Smartphone |
| Model Name | PG05100 |
| FCC ID | NM8PG05100 |
| Tx Frequency | CDMA2000 BC0 : 824 MHz ~ 849 MHz CDMA2000 BC1 : 1850 MHz ~ 1910 MHz LTE Band 13 : 777 MHz ~ 787 MHz |
| Rx Frequency | CDMA2000 BC0 : 869 MHz ~ 894 MHz CDMA2000 BC1 : 1930 MHz ~ 1990 MHz LTE Band 13 : 746 MHz ~ 756 MHz |
| LTE Bandwidth | 10MHz |
| Maximum Output Power to Antenna | CDMA2000 BC0 : 23.96 dBm CDMA2000 BC1 : 24.00 dBm LTE Band 13 : 23.00 dBm |
| Antenna Type | Fixed Internal Antenna |
| Type of Modulation | CDMA2000 : QPSK LTE : QPSK, 16QAM (Uplink) |
| DUT Stage | Production Unit |

Remark:

1. The above DUT's information was declared by manufacturer. Please refer to the specifications or user's manual for more detailed description.
2. This device supports WiFi hotspot function, so body SAR was tested under 1 cm separation distance for all 6 faces.

3.2 Applied Standards

The Specific Absorption Rate (SAR) testing specification, method and procedure for this device is in accordance with the following standards:

- FCC 47 CFR Part 2 (2.1093)
- IEEE C95.1-1991
- IEEE 1528-2003
- FCC OET Bulletin 65 Supplement C (Edition 01-01)
- FCC KDB 648474 D01 v01r05
- FCC KDB 941225 D01 v02

3.3 Device Category and SAR Limits

This device belongs to portable device category because its radiating structure is allowed to be used within 20 centimeters of the body of the user. Limit for General Population/Uncontrolled exposure should be applied for this device, it is 1.6 W/kg as averaged over any 1 gram of tissue.

3.4 Test Conditions

3.4.1 Ambient Condition

| | |
|---------------------|-------------|
| Ambient Temperature | 20 to 24 °C |
| Humidity | < 60 % |

3.4.2 Test Configuration

The EUT is a dual transmitter Simultaneous Voice and Data device that contains two independent WWAN transmitters with the capabilities listed in Table 3.1. The first transmitter supports a CDMA2000 1x call (e.g. voice, SMS) and the second transmitter supports a CDMA2000 EVDO or LTE data call. A simultaneous CDMA 1x voice and CDMA EVDO data connection is referred to as "SVDO" while a simultaneous CDMA 1x voice and LTE data connection is referred to as "SVLTE". The transmitters are independent in respect to the RF chains as each transmitter has dedicated RF circuitry (PA, RF filtering) and a unique transmit antenna. The device also contains an additional antenna associated with receiver diversity or unlicensed transmitters. The LTE UL MIMO configuration is 1x2 (1 UL antenna and 2 DL RX antennas).

Although the RF circuits are independent for both transmitters, the chipset solution incorporated SVDO/SVLTE implementation does include electrical connections between the voice and data transmitters such that the device can coordinate the transmit power of both transmitters. That said, the transmitters operate independently in the sense that they independently support voice or data connection without interaction between the modems or signaling from the WWAN network.

Table 3.1 EUT Technology Support

| Mode | WWAN Technology | Supported Frequency Band(s) (MHz) | Channel BW (MHz) |
|-------|----------------------|--|----------------------|
| Voice | CDMA2000 1x | Band Class 0: 824-848 Band Class I: 1850-1910 | 1.23 MHz 1.25 MHz |
| Data | CDMA2000 1xEvDO RevA | Band Class 0: 824-848 Band Class I: 1850-1910 | 1.23 MHz 1.25 MHz |
| Data | LTE | Band 13 (Upper 700 MHz): 777-787 | Max of 10 MHz |
| Data | 802.11b/g/n | 2.45 GHz | 40 MHz max |

Table 3.2 Definition of Antennas

| Antenna | Antenna Use | Technologies | TX Bands |
|---------|---|--------------------|--------------|
| 1 | Voice 1x TX/ RX+ DO/LTE diversity (RX only) | 1x TX/RX | 850/1900 |
| 2 | DO/LTE Data TX/RX | DO + LTE | 850/1900/700 |
| 3 | WLAN/BT | 802.11 + Bluetooth | 2400 MHz |

Confirming the LTE transmitter follows 3GPP standards, is category 3, 10MHz, Band 13, and supports QPSK / 16QAM modulations. Tested per 3GPP 36.521 maximum transmit procedures for both QPSK / 16QAM.

Table 3.3 Simultaneous Transmission Possibilities

| Simultaneous TX Combination | Configuration |
|-----------------------------|--|
| 1 | CDMA850 Voice + DO850 Data + WLAN/BT |
| 2 | CDMA850 Voice + DO1900 Data + WLAN/BT |
| 3 | CDMA850 Voice + LTE700 Data + WLAN/BT |
| 4 | CDMA1900 Voice + DO850 Data + WLAN/BT |
| 5 | CDMA1900 Voice + DO1900 Data + WLAN/BT |
| 6 | CDMA1900 Voice + LTE700 Data + WLAN/BT |
| 7 | CDMA850 Voice + DO850 Data |
| 8 | CDMA850 Voice + DO1900 Data |
| 9 | CDMA850 Voice + LTE700 Data |
| 10 | CDMA1900 Voice + DO850 Data |
| 11 | CDMA1900 Voice + DO1900 Data |
| 12 | CDMA1900 Voice + LTE700 Data |
| 13 | CDMA850 Voice + WLAN/BT |
| 14 | CDMA1900 Voice + WLAN/BT |
| 15 | DO850 Data + WLAN/BT |
| 16 | DO1900 Data + WLAN/BT |
| 17 | LTE700 Data + WLAN/BT |

SVDO/SVLTE Power Reduction

All standalone SAR was tested at individual mode maximum transmit power level. Simultaneous SAR of CDMA 1x 1900 + EV DO 850, and CDMA 1x 1900 + LTE was also tested at maximum individual mode transmit power level. Simultaneous SAR for CDMA 1x 1900 + EV DO 1900 was tested using SVDO power reduction. Additional simultaneous SAR configuration information is described in Note 2 of Table 11.7

The device also implements maximum power reduction per 3GPP 36.101 requirements where the MPR target is 1 dB for RB allocations > 12. Measured test results demonstrate the expected MPR variation for the product. Additional information is included in the technical description document. LTE MPR cannot be disabled by the end user or LTE network.

Table 3.4 Power Reduction Settings

| Mode | Voice Average Power 1x 850 MHz (dBm) | Maximum DO850 MHz Average Power (dBm) |
|-------|---------------------------------------|--|
| SVDO | $P < 15$ | 23 |
| | $P \geq 15$ | 18 |
| Mode | Voice Average Power 1x 850 MHz (dBm) | Maximum DO1900 MHz Average Power (dBm) |
| SVDO | $P < 15$ | 23 |
| | $P \geq 15$ | 18 |
| Mode | Voice Average Power 1x 1900 MHz (dBm) | Maximum DO850 MHz Average Power (dBm) |
| SVDO | $P < 15$ | 23 |
| | $P \geq 15$ | 18 |
| Mode | Voice Average Power 1x 1900 MHz (dBm) | Maximum DO1900 MHz Average Power (dBm) |
| SVDO | $P < 15$ | 23 |
| | $P \geq 15$ | 18 |
| Mode | Voice Average Power 1x850 MHz (dBm) | Maximum LTE700 MHz Average Power (dBm) |
| SVLTE | $P < 18$ | 23 |
| | $P \geq 18$ | 19 |
| Mode | Voice Average Power 1x 1900 MHz (dBm) | Maximum LTE700 MHz Average Power (dBm) |
| SVLTE | $P < 18$ | 23 |
| | $P \geq 18$ | 19 |

Note: Please see the technical description for additional details on the power reduction.

A-MPR was disabled by setting NS=01 on the R&S CMW500.

The WLAN and BT cannot transmit simultaneously, so there is no co-location test requirement for WLAN and BT.

According KDB 648474, the BT standalone SAR was not required, because the output power of Bluetooth (4.97 dBm) is less than P_{Ref} (10.8 dBm).

The device was controlled by using a base station emulator. Communication between the device and the emulator was established by air link. The distance between the DUT and the antenna of the emulator is larger than 50 cm and the output power radiated from the emulator antenna is at least 30 dB smaller than the output power of DUT. The DUT was set from the emulator to radiate maximum output power during all tests.

For WWAN SAR testing, the DUT is in CDMA2000 or LTE link mode, and the crest factor is 1.

This device supports WiFi hotspot function, so body SAR was tested under 1 cm for the surfaces/slide edges where a transmitting antenna is within 2.5 cm from the edge.

4. Specific Absorption Rate (SAR)

4.1 Introduction

SAR is related to the rate at which energy is absorbed per unit mass in an object exposed to a radio field. The SAR distribution in a biological body is complicated and is usually carried out by experimental techniques or numerical modeling. The standard recommends limits for two tiers of groups, occupational/controlled and general population/uncontrolled, based on a person's awareness and ability to exercise control over his or her exposure. In general, occupational/controlled exposure limits are higher than the limits for general population/uncontrolled.

4.2 SAR Definition

The SAR definition is the time derivative (rate) of the incremental energy (dW) absorbed by (dissipated in) an incremental mass (dm) contained in a volume element (dv) of a given density (ρ). The equation description is as below:

$$SAR = \frac{d}{dt} \left(\frac{dW}{dm} \right) = \frac{d}{dt} \left(\frac{dW}{\rho dv} \right)$$

SAR is expressed in units of Watts per kilogram (W/kg)

SAR measurement can be either related to the temperature elevation in tissue by

$$SAR = C \left(\frac{\delta T}{\delta t} \right)$$

Where: C is the specific heat capacity, δT is the temperature rise and δt is the exposure duration, or related to the electrical field in the tissue by

$$SAR = \frac{\sigma |E|^2}{\rho}$$

Where: σ is the conductivity of the tissue, ρ is the mass density of the tissue and E is the RMS electrical field strength.

However for evaluating SAR of low power transmitter, electrical field measurement is typically applied.

5. SAR Measurement System




Fig 5.1 SPEAG DASY4 or DASY5 System Configurations

The DASY4 or DASY5 system for performance compliance tests is illustrated above graphically. This system consists of the following items:

- A standard high precision 6-axis robot with controller, a teach pendant and software
- A data acquisition electronic (DAE) attached to the robot arm extension
- A dosimetric probe equipped with an optical surface detector system
- The electro-optical converter (ECO) performs the conversion between optical and electrical signals
- A measurement server performs the time critical tasks such as signal filtering, control of the robot operation and fast movement interrupts.
- A probe alignment unit which improves the accuracy of the probe positioning
- A computer operating Windows XP
- DASY4 or DASY5 software
- Remote control with teach pendant and additional circuitry for robot safety such as warning lamps, etc.
- The SAM twin phantom
- A device holder
- Tissue simulating liquid
- Dipole for evaluating the proper functioning of the system

Some of the components are described in details in the following sub-sections.

5.1 E-Field Probe

The SAR measurement is conducted with the dosimetric probe (manufactured by SPEAG). The probe is specially designed and calibrated for use in liquid with high permittivity. The dosimetric probe has special calibration in liquid at different frequency. This probe has a built in optical surface detection system to prevent from collision with phantom.

5.1.1 E-Field Probe Specification

<ET3DV6>


| | | |
|----------------------|--|--|
| Construction | Symmetrical design with triangular core Built-in optical fiber for surface detection system. Built-in shielding against static charges. PEEK enclosure material (resistant to organic solvents, e.g., DGBE) |  |
| Frequency | 10 MHz to 3 GHz; Linearity: ± 0.2 dB | |
| Directivity | ± 0.2 dB in HSL (rotation around probe axis) ± 0.4 dB in HSL (rotation normal to probe axis) | |
| Dynamic Range | 5 μ W/g to 100 mW/g; Linearity: ± 0.2 dB | |
| Dimensions | Overall length: 330 mm (Tip: 16 mm) Tip diameter: 6.8 mm (Body: 12 mm) Distance from probe tip to dipole centers: 2.7 mm | |

Fig 5.2 Photo of ET3DV6

<EX3DV4 Probe>


| | | |
|----------------------|---|---|
| Construction | Symmetrical design with triangular core Built-in shielding against static charges PEEK enclosure material (resistant to organic solvents, e.g., DGBE) |  |
| Frequency | 10 MHz to 6 GHz; Linearity: ± 0.2 dB | |
| Directivity | ± 0.3 dB in HSL (rotation around probe axis) ± 0.5 dB in tissue material (rotation normal to probe axis) | |
| Dynamic Range | 10 μ W/g to 100 mW/g; Linearity: ± 0.2 dB (noise: typically < 1 μ W/g) | |
| Dimensions | Overall length: 330 mm (Tip: 20 mm) Tip diameter: 2.5 mm (Body: 12 mm) Typical distance from probe tip to dipole centers: 1 mm | |

Fig 5.3 Photo of EX3DV4

5.1.2 E-Field Probe Calibration

Each probe needs to be calibrated according to a dosimetric assessment procedure with accuracy better than $\pm 10\%$. The spherical isotropy shall be evaluated and within ± 0.25 dB. The sensitivity parameters (NormX, NormY, and NormZ), the diode compression parameter (DCP) and the conversion factor (ConvF) of the probe are tested. The calibration data can be referred to appendix C of this report.

5.2 Data Acquisition Electronics (DAE)

The data acquisition electronics (DAE) consists of a highly sensitive electrometer-grade preamplifier with auto-zeroing, a channel and gain-switching multiplexer, a fast 16 bit AD-converter and a command decoder and control logic unit. Transmission to the measurement server is accomplished through an optical downlink for data and status information as well as an optical uplink for commands and the clock. The input impedance of the DAE is 200 MOhm; the inputs are symmetrical and floating. Common mode rejection is above 80 dB.



Fig 5.4 Photo of DAE

5.3 Robot

The SPEAG DASY system uses the high precision robots (DASY4: RX90BL; DASY5: TX90XL) type from Stäubli SA (France). For the 6-axis controller system, the robot controller version (DASY4: CS7MB; DASY5: CS8c) from Stäubli is used. The Stäubli robot series have many features that are important for our application:

- High precision (repeatability ± 0.035 mm)
- High reliability (industrial design)
- Jerk-free straight movements
- Low ELF interference (the closed metallic construction shields against motor control fields)




Fig 5.5 Photo of DASY4



Fig 5.6 Photo of DASY5

5.4 Measurement Server

The measurement server is based on a PC/104 CPU board with CPU (DASY4: 166 MHz, Intel Pentium; DASY5: 400 MHz, Intel Celeron), chipdisk (DASY4: 32 MB; DASY5: 128 MB), RAM (DASY4: 64 MB, DASY5: 128 MB). The necessary circuits for communication with the DAE electronic box, as well as the 16 bit AD converter system for optical detection and digital I/O interface are contained on the DASY I/O board, which is directly connected to the PC/104 bus of the CPU board.

The measurement server performs all the real-time data evaluation for field measurements and surface detection, controls robot movements and handles safety operations.



Fig 5.7 Photo of Server for DASY4



Fig 5.8 Photo of Server for DASY5

5.5 Phantom

<SAM Twin Phantom>

| | |
|--------------------------|--|
| Shell Thickness | 2 ± 0.2 mm; Center ear point: 6 ± 0.2 mm |
| Filling Volume | Approx. 25 liters |
| Dimensions | Length: 1000 mm; Width: 500 mm; Height: adjustable feet |
| Measurement Areas | Left Hand, Right Hand, Flat Phantom |




Fig 5.9 Photo of SAM Phantom

The bottom plate contains three pair of bolts for locking the device holder. The device holder positions are adjusted to the standard measurement positions in the three sections. A white cover is provided to tap the phantom during off-periods to prevent water evaporation and changes in the liquid parameters. On the phantom top, three reference markers are provided to identify the phantom position with respect to the robot.

<ELI4 Phantom>

| | |
|------------------------|--|
| Shell Thickness | 2 ± 0.2 mm (sagging: <1%) |
| Filling Volume | Approx. 30 liters |
| Dimensions | Major ellipse axis: 600 mm Minor axis: 400 mm |




Fig 5.10 Photo of ELI4 Phantom

The ELI4 phantom is intended for compliance testing of handheld and body-mounted wireless devices in the frequency range of 30 MHz to 6 GHz. ELI4 is fully compatible with standard and all known tissue simulating liquids.

5.6 Device Holder

<Device Holder for SAM Twin Phantom>

The SAR in the phantom is approximately inversely proportional to the square of the distance between the source and the liquid surface. For a source at 5 mm distance, a positioning uncertainty of ± 0.5 mm would produce a SAR uncertainty of ± 20 %. Accurate device positioning is therefore crucial for accurate and repeatable measurements. The positions in which the devices must be measured are defined by the standards.

The DASY device holder is designed to cope with different positions given in the standard. It has two scales for the device rotation (with respect to the body axis) and the device inclination (with respect to the line between the ear reference points). The rotation center for both scales is the ear reference point (EPR). Thus the device needs no repositioning when changing the angles.

The DASY device holder is constructed of low-loss POM material having the following dielectric parameters: relative permittivity $\epsilon = 3$ and loss tangent $\delta = 0.02$. The amount of dielectric material has been reduced in the closest vicinity of the device, since measurements have suggested that the influence of the clamp on the test results could thus be lowered.



Fig 5.11 Device Holder

<Laptop Extension Kit>

The extension is lightweight and made of POM, acrylic glass and foam. It fits easily on the upper part of the mounting device in place of the phone positioned. The extension is fully compatible with the SAM Twin and ELI phantoms.




Fig 5.12 Laptop Extension Kit

5.7 Data Storage and Evaluation

5.7.1 Data Storage

The DASY software stores the assessed data from the data acquisition electronics as raw data (in microvolt readings from the probe sensors), together with all the necessary software parameters for the data evaluation (probe calibration data, liquid parameters and device frequency and modulation data) in measurement files. The post-processing software evaluates the desired unit and format for output each time the data is visualized or exported. This allows verification of the complete software setup even after the measurement and allows correction of erroneous parameter settings. For example, if a measurement has been performed with an incorrect crest factor parameter in the device setup, the parameter can be corrected afterwards and the data can be reevaluated.

The measured data can be visualized or exported in different units or formats, depending on the selected probe type (e.g., [V/m], [A/m], [mW/g]). Some of these units are not available in certain situations or give meaningless results, e.g., a SAR-output in a non-lose media, will always be zero. Raw data can also be exported to perform the evaluation with other software packages.

5.7.2 Data Evaluation

The DASY post-processing software (SEMCAD) automatically executes the following procedures to calculate the field units from the microvolt readings at the probe connector. The parameters used in the evaluation are stored in the configuration modules of the software :

| | | |
|----------------------------|---------------------------|---|
| Probe parameters : | - Sensitivity | $\text{Norm}_i, a_{i0}, a_{i1}, a_{i2}$ |
| | - Conversion factor | ConvF_i |
| | - Diode compression point | dcp_i |
| Device parameters : | - Frequency | f |
| | - Crest factor | cf |
| Media parameters : | - Conductivity | σ |
| | - Density | ρ |

These parameters must be set correctly in the software. They can be found in the component documents or they can be imported into the software from the configuration files issued for the DASY components. In the direct measuring mode of the multi-meter option, the parameters of the actual system setup are used. In the scan visualization and export modes, the parameters stored in the corresponding document files are used.

The first step of the evaluation is a linearization of the filtered input signal to account for the compression characteristics of the detector diode. The compensation depends on the input signal, the diode type and the DC-transmission factor from the diode to the evaluation electronics. If the exciting field is pulsed, the crest factor of the signal must be known to correctly compensate for peak power.

The formula for each channel can be given as :

$$V_i = U_i + U_i^2 \cdot \frac{cf}{dcp_i}$$

with V_i = compensated signal of channel i, (i = x, y, z)
 U_i = input signal of channel i, (i = x, y, z)
 cf = crest factor of exciting field (DASY parameter)
 dcp_i = diode compression point (DASY parameter)

From the compensated input signals, the primary field data for each channel can be evaluated :

$$\text{E-field Probes : } E_i = \sqrt{\frac{V_i}{\text{Norm}_i \cdot \text{ConvF}}}$$

$$\text{H-field Probes : } H_i = \sqrt{V_i} \cdot \frac{a_{i0} + a_{i1}f + a_{i2}f^2}{f}$$

with V_i = compensated signal of channel i, (i = x, y, z)
 Norm_i = sensor sensitivity of channel i, (i = x, y, z), $\mu\text{V}/(\text{V/m})^2$ for E-field Probes
 ConvF = sensitivity enhancement in solution
 a_{ij} = sensor sensitivity factors for H-field probes
 f = carrier frequency [GHz]
 E_i = electric field strength of channel i in V/m
 H_i = magnetic field strength of channel i in A/m

The RSS value of the field components gives the total field strength (Hermitian magnitude) :

$$E_{\text{tot}} = \sqrt{E_x^2 + E_y^2 + E_z^2}$$

The primary field data are used to calculate the derived field units.

$$\text{SAR} = E_{\text{tot}}^2 \cdot \frac{\sigma}{\rho \cdot 1000}$$

with SAR = local specific absorption rate in mW/g
 E_{tot} = total field strength in V/m
 σ = conductivity in [mho/m] or [Siemens/m]
 ρ = equivalent tissue density in g/cm^3

Note that the density is set to 1, to account for actual head tissue density rather than the density of the tissue simulating liquid.

5.8 Test Equipment List

| Manufacturer | Name of Equipment | Type/Model | Serial Number | Calibration | |
|--------------|--------------------------------------|---------------|---------------|---------------|---------------|
| | | | | Last Cal. | Due Date |
| SPEAG | Dosimetric E-Field Probe | ET3DV6 | 1787 | May 18, 2010 | May 17, 2011 |
| SPEAG | Dosimetric E-Field Probe | ET3DV6 | 1788 | Sep. 21, 2010 | Sep. 20, 2011 |
| SPEAG | Dosimetric E-Field Probe | EX3DV4 | 3731 | Jul. 16, 2010 | Jul. 15, 2011 |
| SPEAG | 750MHz System Validation Kit | D750V3 | 1012 | Jun. 11, 2010 | Jun. 10, 2012 |
| SPEAG | 835MHz System Validation Kit | D835V2 | 499 | Mar. 22, 2010 | Mar. 21, 2012 |
| SPEAG | 900MHz System Validation Kit | D900V2 | 190 | Jul. 21, 2009 | Jul. 20, 2011 |
| SPEAG | 1800MHz System Validation Kit | D1800V2 | 2d076 | Jul. 20, 2009 | Jul. 19, 2011 |
| SPEAG | 1900MHz System Validation Kit | D1900V2 | 5d041 | Mar. 23, 2010 | Mar. 22, 2012 |
| SPEAG | 2000MHz System Validation Kit | D2000V2 | 1010 | Sep. 22, 2010 | Sep. 21, 2012 |
| SPEAG | 2300MHz System Validation Kit | D2300V2 | 1006 | Sep. 24, 2009 | Sep. 23, 2011 |
| SPEAG | 2450MHz System Validation Kit | D2450V2 | 736 | Jul. 20, 2009 | Jul. 19, 2011 |
| SPEAG | 2600MHz System Validation Kit | D2600V2 | 1008 | Sep. 24, 2009 | Sep. 23, 2011 |
| SPEAG | 3500MHz System Validation Kit | D3500V2 | 1014 | Sep. 17, 2009 | Sep. 16, 2011 |
| SPEAG | 5GHz System Validation Kit | D5GHzV2 | 1006 | Jan. 21, 2010 | Jan. 20, 2012 |
| SPEAG | Data Acquisition Electronics | DAE3 | 577 | Aug. 18, 2010 | Aug. 17, 2011 |
| SPEAG | Data Acquisition Electronics | DAE4 | 778 | Oct. 22, 2010 | Oct. 21, 2011 |
| SPEAG | Data Acquisition Electronics | DAE4 | 905 | Jun. 22, 2010 | Jun. 21, 2011 |
| SPEAG | Data Acquisition Electronics | DAE4 | 913 | Nov. 18, 2010 | Nov. 17, 2011 |
| SPEAG | Device Holder | N/A | N/A | NCR | NCR |
| SPEAG | SAM Phantom | QD 000 P40 C | TP-1303 | NCR | NCR |
| SPEAG | SAM Phantom | QD 000 P40 C | TP-1383 | NCR | NCR |
| SPEAG | SAM Phantom | QD 000 P40 C | TP-1446 | NCR | NCR |
| SPEAG | SAM Phantom | QD 000 P40 C | TP-1478 | NCR | NCR |
| SPEAG | ELI4 Phantom | QD 0VA 001 BB | 1026 | NCR | NCR |
| SPEAG | ELI4 Phantom | QD 0VA 001 BA | 1029 | NCR | NCR |
| Agilent | PNA Series Network Analyzer | E8358A | US40260131 | May 06, 2010 | May 05, 2011 |
| R&S | Wideb. Radio Comm. Tester | CMW500 | 102159 | Sep. 09, 2010 | Sep. 08, 2011 |
| Agilent | Wireless Communication Test Set | E5515C | MY48360820 | Jan. 12, 2010 | Jan. 11, 2012 |
| Agilent | Wireless Communication Test Set | E5515C | GB46311322 | Feb. 16, 2009 | Feb. 15, 2011 |
| R&S | Universal Radio Communication Tester | CMU200 | 117995 | Mar. 19, 2009 | Mar. 18, 2011 |
| Agilent | Dielectric Probe Kit | 85070D | US01440205 | NCR | NCR |
| Agilent | Dual Directional Coupler | 778D | 50422 | NCR | NCR |
| AR | Power Amplifier | 5S1G4M2 | 0328767 | NCR | NCR |
| R&S | Spectrum Analyzer | FSP7 | 101131 | Mar. 05, 2010 | Mar. 04, 2011 |

Table 5.1 Test Equipment List

Note: The calibration certificate of DASY can be referred to appendix C of this report.

6. Tissue Simulating Liquids

For the measurement of the field distribution inside the SAM phantom with DASY, the phantom must be filled with around 25 liters of homogeneous body tissue simulating liquid. For head SAR testing, the liquid height from the ear reference point (ERP) of the phantom to the liquid top surface is larger than 15 cm, which is shown in Fig. 6.1. For body SAR testing, the liquid height from the center of the flat phantom to the liquid top surface is larger than 15 cm, which is shown in Fig. 6.2.




Fig 6.1 Photo of Liquid Height for Head SAR



Fig 6.2 Photo of Liquid Height for Body SAR

The following table gives the recipes for tissue simulating liquid.

| Frequency (MHz) | Water (%) | Sugar (%) | Cellulose (%) | Salt (%) | Preventol (%) | DGBE (%) | Conductivity (σ) | Permittivity (ϵ_r) |
|--------------------|--------------|--------------|------------------|-------------|------------------|-------------|------------------------------|----------------------------------|
| For Head | | | | | | | | |
| 750 | 41.1 | 57.0 | 0.2 | 1.4 | 0.2 | 0 | 0.89 | 41.9 |
| 835 | 40.3 | 57.9 | 0.2 | 1.4 | 0.2 | 0 | 0.90 | 41.5 |
| 900 | 40.3 | 57.9 | 0.2 | 1.4 | 0.2 | 0 | 0.97 | 41.5 |
| 1800, 1900, 2000 | 55.2 | 0 | 0 | 0.3 | 0 | 44.5 | 1.40 | 40.0 |
| 2450 | 55.0 | 0 | 0 | 0 | 0 | 45.0 | 1.80 | 39.2 |
| For Body | | | | | | | | |
| 750 | 51.7 | 47.2 | 0 | 0.9 | 0.1 | 0 | 0.96 | 55.5 |
| 835 | 50.8 | 48.2 | 0 | 0.9 | 0.1 | 0 | 0.97 | 55.2 |
| 900 | 50.8 | 48.2 | 0 | 0.9 | 0.1 | 0 | 1.05 | 55.0 |
| 1800, 1900, 2000 | 70.2 | 0 | 0 | 0.4 | 0 | 29.4 | 1.52 | 53.3 |
| 2450 | 68.6 | 0 | 0 | 0 | 0 | 31.4 | 1.95 | 52.7 |

Table 6.1 Recipes of Tissue Simulating Liquid

The following table gives the targets for tissue simulating liquid.

| Frequency (MHz) | Liquid Type | Conductivity (σ) | $\pm 5\%$ Range | Permittivity (ϵ_r) | $\pm 5\%$ Range |
|------------------|-------------|---------------------------|-----------------|-------------------------------|-----------------|
| 750 | Head | 0.89 | 0.85 ~ 0.93 | 41.9 | 39.8 ~ 44.0 |
| 835 | Head | 0.90 | 0.86 ~ 0.95 | 41.5 | 39.4 ~ 43.6 |
| 900 | Head | 0.97 | 0.92 ~ 1.02 | 41.5 | 39.4 ~ 43.6 |
| 1800, 1900, 2000 | Head | 1.40 | 1.33 ~ 1.47 | 40.0 | 38.0 ~ 42.0 |
| 2450 | Head | 1.80 | 1.71 ~ 1.89 | 39.2 | 37.2 ~ 41.2 |
| 750 | Body | 0.96 | 0.91 ~ 1.01 | 55.5 | 52.7 ~ 58.3 |
| 835 | Body | 0.97 | 0.92 ~ 1.02 | 55.2 | 52.4 ~ 58.0 |
| 900 | Body | 1.05 | 1.00 ~ 1.10 | 55.0 | 52.3 ~ 57.8 |
| 1800, 1900, 2000 | Body | 1.52 | 1.44 ~ 1.60 | 53.3 | 50.6 ~ 56.0 |
| 2450 | Body | 1.95 | 1.85 ~ 2.05 | 52.7 | 50.1 ~ 55.3 |

Table 6.2 Targets of Tissue Simulating Liquid

The dielectric parameters of the liquids were verified prior to the SAR evaluation using an Agilent 85070D Dielectric Probe Kit and an Agilent Network Analyzer.

The following table shows the measuring results for simulating liquid.

| Frequency (MHz) | Liquid Type | Temperature (°C) | Conductivity (σ) | Deviation (%) | Permittivity (ϵ_r) | Deviation (%) | Measurement Date |
|-----------------|-------------|------------------|---------------------------|---------------|-------------------------------|---------------|------------------|
| 750 | Head | 21.5 | 0.855 | -3.9 | 40.8 | -2.6 | Oct. 27, 2010 |
| 777 | Head | | 0.855 | -3.9 | 40.5 | -3.3 | |
| 782 | Head | | 0.855 | -3.9 | 40.5 | -3.3 | |
| 787 | Head | | 0.851 | -4.4 | 40.4 | -3.6 | |
| 750 | Head | 21.2 | 0.85 | -4.5 | 41.0 | -2.1 | Nov. 23, 2010 |
| 777 | Head | | 0.855 | -3.9 | 40.7 | -2.9 | |
| 782 | Head | | 0.855 | -3.9 | 40.7 | -2.9 | |
| 787 | Head | | 0.856 | -3.8 | 40.6 | -3.1 | |
| 750 | Head | 21.4 | 0.852 | -4.3 | 41.1 | -1.9 | Jan. 08, 2011 |
| 777 | Head | | 0.855 | -3.9 | 40.8 | -2.6 | |
| 782 | Head | | 0.855 | -3.9 | 40.7 | -2.9 | |
| 787 | Head | | 0.860 | -3.4 | 40.7 | -2.9 | |
| 750 | Body | 21.4 | 0.911 | -5.0 | 54.1 | -2.5 | Nov. 09, 2010 |
| 777 | Body | | 0.915 | -4.7 | 53.8 | -3.1 | |
| 782 | Body | | 0.92 | -4.2 | 53.8 | -3.1 | |
| 787 | Body | | 0.924 | -3.7 | 53.7 | -3.2 | |
| 750 | Body | 21.4 | 0.91 | -5.0 | 56.5 | 1.8 | Nov. 23, 2010 |
| 777 | Body | | 0.932 | -2.9 | 56.3 | 1.4 | |
| 782 | Body | | 0.937 | -2.4 | 56.3 | 1.4 | |
| 787 | Body | | 0.942 | -1.9 | 56.2 | 1.3 | |
| 835 | Head | 21.5 | 0.918 | 2.0 | 41.1 | -1.0 | Oct. 26, 2010 |
| 835 | Head | 21.3 | 0.899 | -0.1 | 41.2 | -0.7 | Nov. 02, 2010 |
| 835 | Head | 21.5 | 0.895 | -0.5 | 41.1 | -1.0 | Jan. 08, 2011 |
| 835 | Body | 21.4 | 0.962 | -0.8 | 54.6 | -1.1 | Nov. 10, 2010 |
| 1900 | Head | 21.4 | 1.47 | 5.0 | 38.3 | -4.3 | Oct. 25, 2010 |
| 1900 | Head | 21.3 | 1.46 | 4.3 | 38.1 | -4.8 | Oct. 26, 2010 |
| 1900 | Head | 21.5 | 1.40 | 0.0 | 41.8 | 4.5 | Oct. 29, 2010 |
| 1900 | Head | 21.4 | 1.43 | 2.1 | 38.8 | -3.0 | Jan. 04, 2011 |
| 1900 | Body | 21.6 | 1.50 | -1.3 | 53.0 | -0.6 | Nov. 07, 2010 |
| 1900 | Body | 21.6 | 1.53 | 0.7 | 52.5 | -1.5 | Nov. 10, 2010 |

Table 6.3 Measuring Results for Simulating Liquid

7. Uncertainty Assessment

The component of uncertainty may generally be categorized according to the methods used to evaluate them. The evaluation of uncertainty by the statistical analysis of a series of observations is termed a Type A evaluation of uncertainty. The evaluation of uncertainty by means other than the statistical analysis of a series of observation is termed a Type B evaluation of uncertainty. Each component of uncertainty, however evaluated, is represented by an estimated standard deviation, termed standard uncertainty, which is determined by the positive square root of the estimated variance.

A Type A evaluation of standard uncertainty may be based on any valid statistical method for treating data. This includes calculating the standard deviation of the mean of a series of independent observations; using the method of least squares to fit a curve to the data in order to estimate the parameter of the curve and their standard deviations; or carrying out an analysis of variance in order to identify and quantify random effects in certain kinds of measurement.

A type B evaluation of standard uncertainty is typically based on scientific judgment using all of the relevant information available. These may include previous measurement data, experience and knowledge of the behavior and properties of relevant materials and instruments, manufacture's specification, data provided in calibration reports and uncertainties assigned to reference data taken from handbooks. Broadly speaking, the uncertainty is either obtained from an outdoor source or obtained from an assumed distribution, such as the normal distribution, rectangular or triangular distributions indicated in Table 7.1

| Uncertainty Distributions | Normal | Rectangular | Triangular | U-Shape |
|------------------------------------|--------------------|-------------|------------|---------|
| Multi-plying Factor ^(a) | 1/k ^(b) | 1/√3 | 1/√6 | 1/√2 |

(a) standard uncertainty is determined as the product of the multiplying factor and the estimated range of variations in the measured quantity

(b) k is the coverage factor

Table 7.1 Standard Uncertainty for Assumed Distribution

The combined standard uncertainty of the measurement result represents the estimated standard deviation of the result. It is obtained by combining the individual standard uncertainties of both Type A and Type B evaluation using the usual "root-sum-squares" (RSS) methods of combining standard deviations by taking the positive square root of the estimated variances.

Expanded uncertainty is a measure of uncertainty that defines an interval about the measurement result within which the measured value is confidently believed to lie. It is obtained by multiplying the combined standard uncertainty by a coverage factor. Typically, the coverage factor ranges from 2 to 3. Using a coverage factor allows the true value of a measured quantity to be specified with a defined probability within the specified uncertainty range. For purpose of this document, a coverage factor two is used, which corresponds to confidence interval of about 95 %. The DASY uncertainty Budget is showed in Table 7.2.

| Error Description | Uncertainty Value (±%) | Probability Distribution | Divisor | Ci (1g) | Standard Uncertainty (1g) |
|--------------------------------------|------------------------|--------------------------|---------|---------|---------------------------|
| Measurement System | | | | | |
| Probe Calibration | 5.5 | Normal | 1 | 1 | ± 5.5 % |
| Axial Isotropy | 4.7 | Rectangular | √3 | 0.7 | ± 1.9 % |
| Hemispherical Isotropy | 9.6 | Rectangular | √3 | 0.7 | ± 3.9 % |
| Boundary Effects | 1.0 | Rectangular | √3 | 1 | ± 0.6 % |
| Linearity | 4.7 | Rectangular | √3 | 1 | ± 2.7 % |
| System Detection Limits | 1.0 | Rectangular | √3 | 1 | ± 0.6 % |
| Readout Electronics | 0.3 | Normal | 1 | 1 | ± 0.3 % |
| Response Time | 0.8 | Rectangular | √3 | 1 | ± 0.5 % |
| Integration Time | 2.6 | Rectangular | √3 | 1 | ± 1.5 % |
| RF Ambient Noise | 3.0 | Rectangular | √3 | 1 | ± 1.7 % |
| RF Ambient Reflections | 3.0 | Rectangular | √3 | 1 | ± 1.7 % |
| Probe Positioner | 0.4 | Rectangular | √3 | 1 | ± 0.2 % |
| Probe Positioning | 2.9 | Rectangular | √3 | 1 | ± 1.7 % |
| Max. SAR Eval. | 1.0 | Rectangular | √3 | 1 | ± 0.6 % |
| Test Sample Related | | | | | |
| Device Positioning | 2.9 | Normal | 1 | 1 | ± 2.9 % |
| Device Holder | 3.6 | Normal | 1 | 1 | ± 3.6 % |
| Power Drift | 5.0 | Rectangular | √3 | 1 | ± 2.9 % |
| Phantom and Setup | | | | | |
| Phantom Uncertainty | 4.0 | Rectangular | √3 | 1 | ± 2.3 % |
| Liquid Conductivity (Target) | 5.0 | Rectangular | √3 | 0.64 | ± 1.8 % |
| Liquid Conductivity (Meas.) | 2.5 | Normal | 1 | 0.64 | ± 1.6 % |
| Liquid Permittivity (Target) | 5.0 | Rectangular | √3 | 0.6 | ± 1.7 % |
| Liquid Permittivity (Meas.) | 2.5 | Normal | 1 | 0.6 | ± 1.5 % |
| Combined Standard Uncertainty | | | | | ± 10.7 % |
| Coverage Factor for 95 % | | | | | K = 2 |
| Expanded Uncertainty | | | | | ± 21.4 % |

Table 7.2 Uncertainty Budget of DASY for frequency range 300 MHz to 3 GHz

8. SAR Measurement Evaluation

Each DASY system is equipped with one or more system validation kits. These units, together with the predefined measurement procedures within the DASY software, enable the user to conduct the system performance check and system validation. System validation kit includes a dipole, tripod holder to fix it underneath the flat phantom and a corresponding distance holder.

8.1 Purpose of System Performance check

The system performance check verifies that the system operates within its specifications. System and operator errors can be detected and corrected. It is recommended that the system performance check be performed prior to any usage of the system in order to guarantee reproducible results. The system performance check uses normal SAR measurements in a simplified setup with a well characterized source. This setup was selected to give a high sensitivity to all parameters that might fail or vary over time. The system check does not intend to replace the calibration of the components, but indicates situations where the system uncertainty is exceeded due to drift or failure.

8.2 System Setup

In the simplified setup for system evaluation, the DUT is replaced by a calibrated dipole and the power source is replaced by a continuous wave that comes from a signal generator. The calibrated dipole must be placed beneath the flat phantom section of the SAM twin phantom with the correct distance holder. The distance holder should touch the phantom surface with a light pressure at the reference marking and be oriented parallel to the long side of the phantom. The equipment setup is shown below:




Fig 8.1 System Setup for System Evaluation

1. Signal Generator
2. Amplifier
3. Directional Coupler
4. Power Meter
5. Calibrated Dipole

The output power on dipole port must be calibrated to 20 dBm (100 mW) before dipole is connected.




Fig 8.2 Photo of Dipole Setup

8.3 Validation Results

Comparing to the original SAR value provided by SPEAG, the validation data should be within its specification of 10 %. Table 8.1 shows the target SAR and measured SAR after normalized to 1W input power. The table below indicates the system performance check can meet the variation criterion and the plots can be referred to Appendix A of this report.

| Measurement Date | Frequency (MHz) | Targeted SAR _{1g} (W/kg) | Measured SAR _{1g} (W/kg) | Deviation (%) |
|------------------|-----------------|-----------------------------------|-----------------------------------|---------------|
| Oct. 27, 2010 | 750 | 8.28 | 8.32 | 0.48 |
| Nov. 23, 2010 | 750 | 8.28 | 8.57 | 3.50 |
| Jan. 08, 2011 | 750 | 8.28 | 8.41 | 1.57 |
| Nov. 09, 2010 | 750 | 8.86 | 8.51 | -3.95 |
| Nov. 23, 2010 | 750 | 8.86 | 8.66 | -2.26 |
| Oct. 26, 2010 | 835 | 9.71 | 10.20 | 5.05 |
| Nov. 02, 2010 | 835 | 9.71 | 9.60 | -1.13 |
| Jan. 08, 2011 | 835 | 9.71 | 9.59 | -1.24 |
| Nov. 10, 2010 | 835 | 9.82 | 9.85 | 0.31 |
| Oct. 25, 2010 | 1900 | 39.80 | 38.40 | -3.52 |
| Oct. 26, 2010 | 1900 | 39.80 | 38.30 | -3.77 |
| Oct. 29, 2010 | 1900 | 39.80 | 37.60 | -5.53 |
| Nov. 07, 2010 | 1900 | 40.00 | 41.60 | 4.00 |
| Nov. 10, 2010 | 1900 | 40.00 | 41.40 | 3.50 |
| Jan. 04, 2011 | 1900 | 39.80 | 39.50 | -0.75 |

Table 8.1 Target and Measurement SAR after Normalized

9. DUT Testing Position

This DUT was tested in ten different positions. They are right cheek, right tilted, left cheek, left tilted, front face of the DUT with phantom 1 cm gap, rear face of the DUT with phantom 1 cm gap, bottom side of the DUT with phantom 1 cm gap, top side of the DUT with phantom 1 cm gap, left side of the DUT with phantom 1 cm gap, and right side of the DUT with phantom 1 cm gap as illustrated below:

1. Define two imaginary lines on the handset

- The vertical centerline passes through two points on the front side of the handset - the midpoint of the width w_t of the handset at the level of the acoustic output, and the midpoint of the width w_b of the bottom of the handset.
- The horizontal line is perpendicular to the vertical centerline and passes through the center of the acoustic output. The horizontal line is also tangential to the face of the handset at point A.
- The two lines intersect at point A. Note that for many handsets, point A coincides with the center of the acoustic output; however, the acoustic output may be located elsewhere on the horizontal line. Also note that the vertical centerline is not necessarily parallel to the front face of the handset, especially for clamshell handsets, handsets with flip covers, and other irregularly shaped handsets.




Fig 9.1 Illustration for Handset Vertical and Horizontal Reference Lines

2. Cheek Position

- (a) To position the device with the vertical center line of the body of the device and the horizontal line crossing the center piece in a plane parallel to the sagittal plane of the phantom. While maintaining the device in this plane, align the vertical center line with the reference plane containing the three ear and mouth reference point (M: Mouth, RE: Right Ear, and LE: Left Ear) and align the center of the ear piece with the line RE-LE.
- (b) To move the device towards the phantom with the ear piece aligned with the line LE-RE until the phone touched the ear. While maintaining the device in the reference plane and maintaining the phone contact with the ear, move the bottom of the phone until any point on the front side is in contact with the cheek of the phantom or until contact with the ear is lost (see Fig. 9.2).




Fig 9.2 Illustration for Cheek Position

3. Tilted Position

- (a) To position the device in the “cheek” position described above.
- (b) While maintaining the device the reference plane described above and pivoting against the ear, moves it outward away from the mouth by an angle of 15 degrees or until contact with the ear is lost (see Fig. 9.3).



Fig 9.3 Illustration for Tilted Position

4. Body Worn Position

- (a) To position the device parallel to the phantom surface with DUT each edges.
- (b) To adjust the device parallel to the flat phantom.
- (c) To adjust the distance between the device surface and the flat phantom to 1 cm.




Fig 9.4 Illustration for Body Worn Position

5. DUT Setup Photos

Please refer to Appendix D for the test setup photos.

10. Measurement Procedures

The measurement procedures are as follows:

- (a) For WWAN function, link DUT with base station emulator in the highest power channel
- (b) Set base station emulator to allow DUT to radiate maximum output power
- (c) Measure output power through RF cable and power meter
- (d) Place the DUT in the positions described in the last section
- (e) Set scan area, grid size and other setting on the DASY software
- (f) Taking data for the middle channel on each testing position
- (g) Find out the largest SAR result on these testing positions of each band
- (h) Measure SAR results for other channels in worst SAR testing position if the SAR of highest power channel is larger than 0.8 W/kg

According to the test standard, the recommended procedure for assessing the peak spatial-average SAR value consists of the following steps:

- (a) Power reference measurement
- (b) Area scan
- (c) Zoom scan
- (d) Power drift measurement

10.1 Spatial Peak SAR Evaluation

The procedure for spatial peak SAR evaluation has been implemented according to the test standard. It can be conducted for 1g and 10g, as well as for user-specific masses. The DASY software includes all numerical procedures necessary to evaluate the spatial peak SAR value.

The base for the evaluation is a "cube" measurement. The measured volume must include the 1g and 10g cubes with the highest averaged SAR values. For that purpose, the center of the measured volume is aligned to the interpolated peak SAR value of a previously performed area scan.

The entire evaluation of the spatial peak values is performed within the post-processing engine (SEMCAD). The system always gives the maximum values for the 1g and 10g cubes. The algorithm to find the cube with highest averaged SAR is divided into the following stages:

- (a) Extraction of the measured data (grid and values) from the Zoom Scan
- (b) Calculation of the SAR value at every measurement point based on all stored data (A/D values and measurement parameters)
- (c) Generation of a high-resolution mesh within the measured volume
- (d) Interpolation of all measured values from the measurement grid to the high-resolution grid
- (e) Extrapolation of the entire 3-D field distribution to the phantom surface over the distance from sensor to surface
- (f) Calculation of the averaged SAR within masses of 1g and 10g

10.2 Area & Zoom Scan Procedures

First Area Scan is used to locate the approximate location(s) of the local peak SAR value(s). The measurement grid within an Area Scan is defined by the grid extent, grid step size and grid offset. Next, in order to determine the EM field distribution in a three-dimensional spatial extension, Zoom Scan is required. The Zoom Scan measures 5x5x7 points with step size 8, 8 and 5 mm for 300 MHz to 3 GHz, and 8x8x8 points with step size 4, 4 and 2.5 mm for 3 GHz to 6 GHz. The Zoom Scan is performed around the highest E-field value to determine the averaged SAR-distribution over 10 g.

10.3 Volume Scan Procedures

The volume scan is used for assess overlapping SAR distributions for antennas transmitting in different frequency bands. It is equivalent to an oversized zoom scan used in standalone measurements. The measurement volume will be used to enclose all the simultaneous transmitting antennas. For antennas transmitting simultaneously in different frequency bands, the volume scan is measured separately in each frequency band. In order to sum correctly to compute the 1g aggregate SAR, the DUT remain in the same test position for all measurements and all volume scan use the same spatial resolution and grid spacing (step-size is 4, 4 and 2.5 mm). When all volume scan were completed, the software, SEMCAD postprocessor can combine and subsequently superpose these measurement data to calculating the multiband SAR.

10.4 SAR Averaged Methods

In DASY, the interpolation and extrapolation are both based on the modified Quadratic Shepard's method. The interpolation scheme combines a least-square fitted function method and a weighted average method which are the two basic types of computational interpolation and approximation.

Extrapolation routines are used to obtain SAR values between the lowest measurement points and the inner phantom surface. The extrapolation distance is determined by the surface detection distance and the probe sensor offset. The uncertainty increases with the extrapolation distance. To keep the uncertainty within 1% for the 1 g and 10 g cubes, the extrapolation distance should not be larger than 5 mm.

10.5 Power Drift Monitoring

All SAR testing is under the DUT install full charged battery and transmit maximum output power. In DASY measurement software, the power reference measurement and power drift measurement procedures are used for monitoring the power drift of DUT during SAR test. Both these procedures measure the field at a specified reference position before and after the SAR testing. The software will calculate the field difference in dB. If the power drift more than 5%, the SAR will be retested.

11. SAR Test Results

11.1 Conducted Power (Unit: dBm)

| Band | CDMA2000 BC0 | | | CDMA2000 BC1 | | |
|----------------------|--------------|-----------|-------------|--------------|---|-------------|
| Channel | 1013 | 384 | 777 | 25 | 600 | 1175 |
| Frequency (MHz) | 824.70 | 836.52 | 848.31 | 1851.25 | 1880.00 | 1908.75 |
| Ant-1 RC1+SO55 | 23.79 | 23.96 | 23.90 | 23.85 | 23.93 | 23.91 |
| Ant-1 RC3+SO55 | 23.81 | 23.93 | 23.92 | 24.00 | 23.97 | 23.86 |
| Ant-1 RC3+SO32 (FCH) | 23.83 | 23.92 | 23.90 | 23.98 | 23.90 | 23.92 |
| Ant-1 RC3+SO32 (SCH) | 23.83 | 23.93 | 23.89 | 24.00 | 23.93 | 23.90 |
| Ant-2 RTAP 153.6 | 23.65 | 23.78 | 23.76 | 23.95 | 23.91 | 23.93 |
| Ant-2 RETAP 4096 | 23.71 | 23.80 | 23.81 | 23.82 | 23.81 | 23.82 |
| Band | LTE Band 13 | | | | | |
| Modulation | RB Size | RB Offset | Power (dBm) | MPR Target | Measured Reduction for 23 dBm Target (dB) | Note |
| Ant-2 QPSK | 1 | 0 | 22.51 | 0 | 0.49 | - |
| Ant-2 QPSK | 1 | 49 | 22.92 | 0 | 0.08 | - |
| Ant-2 QPSK | 25 | 13 | 21.47 | 1 | 1.53 | MPR Enabled |
| Ant-2 QPSK | 50 | 0 | 21.42 | 1 | 1.58 | MPR Enabled |
| Ant-2 16QAM | 1 | 0 | 22.49 | 0 | 0.51 | - |
| Ant-2 16QAM | 1 | 49 | 23.00 | 0 | 0.00 | - |
| Ant-2 16QAM | 25 | 13 | 21.46 | 1 | 1.54 | MPR Enabled |
| Ant-2 16QAM | 50 | 0 | 21.39 | 1 | 1.61 | MPR Enabled |

Note: Above EVDO power is measured on standalone mode which does not include 1 dB power reduction for SVDO operation.

**11.1.1 Maximum Transmit Power Results with Power Reduction Enabled**

The following tables show the maximum transmit power results at different voice transmit power levels.

| Voice Band | Voice Channel | Voice Power (dBm) | Expected Measured Data Transmit Power | | | | | | | | | | | | | |
|------------|---------------|-------------------|---------------------------------------|------|------|------------|------|------|-----------------------------------|-------------------|-----------------|-------------------|--------------------|-------------------|------------------|-------------------|
| | | | DO 850 MHz | | | DO1900 MHz | | | LTE 700 MHz (RB allocation / RB#) | | | | | | | |
| | | | Low | Mid | High | Low | Mid | High | RB=25, RB#13 QPSK | RB=49, RB#49 QPSK | RB=1, RB#0 QPSK | RB=50, RB#0, QPSQ | RB=25, RB#13 16QAM | RB=1, RB#49 16QAM | RB=1, RB#0 16QAM | RB=50, RB#0, QPSQ |
| 850 MHz | Low | 24 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Low | 23 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Low | 22 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Low | 21 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Low | 20 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Low | 19 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Low | 18 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Low | 17 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Low | 16 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Low | 15 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Low | 14 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Low | 13 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Low | 12 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Low | 11 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |

| Voice Band | Voice Channel | Voice Power (dBm) | Expected Measured Data Transmit Power | | | | | | | | | | | | | |
|------------|---------------|-------------------|---------------------------------------|------|------|------------|------|------|-----------------------------------|------------------|-----------------|-------------------|--------------------|-------------------|------------------|-------------------|
| | | | DO 850 MHz | | | DO1900 MHz | | | LTE 700 MHz (RB allocation / RB#) | | | | | | | |
| | | | Low | Mid | High | Low | Mid | High | RB=25, RB#13 QPSK | RB=1, RB#49 QPSK | RB=1, RB#0 QPSK | RB=50, RB#0, QPSQ | RB=25, RB#13 16QAM | RB=1, RB#49 16QAM | RB=1, RB#0 16QAM | RB=50, RB#0, QPSQ |
| 850 MHz | Mid | 24 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Mid | 23 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Mid | 22 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Mid | 21 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Mid | 20 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Mid | 19 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Mid | 18 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | Mid | 17 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Mid | 16 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Mid | 15 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Mid | 14 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Mid | 13 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Mid | 12 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | Mid | 11 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |



| Voice Band | Voice Channel | Voice Power (dBm) | Measured Data Transmit Power (call box) | | | | | | | | | | | | | |
|------------|---------------|-------------------|---|------|------|------------|------|------|-----------------------------------|------------------|-----------------|-------------------|--------------------|-------------------|------------------|-------------------|
| | | | DO 850 MHz | | | DO1900 MHz | | | LTE 700 MHz (RB allocation / RB#) | | | | | | | |
| | | | Low | Mid | High | Low | Mid | High | RB=25, RB#13 QPSK | RB=1, RB#49 QPSK | RB=1, RB#0 QPSK | RB=50, RB#0, QPSQ | RB=25, RB#13 16QAM | RB=1, RB#49 16QAM | RB=1, RB#0 16QAM | RB=50, RB#0, QPSQ |
| 850 MHz | High | 24 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | High | 23 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | High | 22 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | High | 21 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | High | 20 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | High | 19 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | High | 18 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 850 MHz | High | 17 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | High | 16 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | High | 15 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 17.8 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | High | 14 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | High | 13 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | High | 12 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 850 MHz | High | 11 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |

| Voice Band | Voice Channel | Voice Power (dBm) | Measured Data Transmit Power (call box) | | | | | | | | | | | | | |
|------------|---------------|-------------------|---|------|------|------------|------|------|-----------------------------------|------------------|-----------------|-------------------|--------------------|-------------------|------------------|-------------------|
| | | | DO 850 MHz | | | DO1900 MHz | | | LTE 700 MHz (RB allocation / RB#) | | | | | | | |
| | | | Low | Mid | High | Low | Mid | High | RB=25, RB#13 QPSK | RB=1, RB#49 QPSK | RB=1, RB#0 QPSK | RB=50, RB#0, QPSQ | RB=25, RB#13 16QAM | RB=1, RB#49 16QAM | RB=1, RB#0 16QAM | RB=50, RB#0, QPSQ |
| 1900 MHz | Low | 24 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Low | 23 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Low | 22 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Low | 21 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Low | 20 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Low | 19 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Low | 18 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Low | 17 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Low | 16 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Low | 15 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Low | 14 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Low | 13 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Low | 12 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Low | 11 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |



| Voice Band | Voice Channel | Voice Power (dBm) | Measured Data Transmit Power (call box) | | | | | | | | | | | | | |
|------------|---------------|-------------------|---|------|------|------------|------|------|-----------------------------------|------------------|-----------------|-------------------|--------------------|-------------------|------------------|-------------------|
| | | | DO 850 MHz | | | DO1900 MHz | | | LTE 700 MHz (RB allocation / RB#) | | | | | | | |
| | | | Low | Mid | High | Low | Mid | High | RB=25, RB#13 QPSK | RB=1, RB#49 QPSK | RB=1, RB#0 QPSK | RB=50, RB#0, QPSQ | RB=25, RB#13 16QAM | RB=1, RB#49 16QAM | RB=1, RB#0 16QAM | RB=50, RB#0, QPSQ |
| 1900 MHz | Mid | 24 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Mid | 23 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Mid | 22 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Mid | 21 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Mid | 20 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Mid | 19 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Mid | 18 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | Mid | 17 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Mid | 16 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Mid | 15 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Mid | 14 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Mid | 13 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Mid | 12 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | Mid | 11 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |

| Voice Band | Voice Channel | Voice Power (dBm) | Measured Data Transmit Power (call box) | | | | | | | | | | | | | |
|------------|---------------|-------------------|---|------|------|------------|------|------|-----------------------------------|------------------|-----------------|-------------------|--------------------|-------------------|------------------|-------------------|
| | | | DO 850 MHz | | | DO1900 MHz | | | LTE 700 MHz (RB allocation / RB#) | | | | | | | |
| | | | Low | Mid | High | Low | Mid | High | RB=25, RB#13 QPSK | RB=1, RB#49 QPSK | RB=1, RB#0 QPSK | RB=50, RB#0, QPSQ | RB=25, RB#13 16QAM | RB=1, RB#49 16QAM | RB=1, RB#0 16QAM | RB=50, RB#0, QPSQ |
| 1900 MHz | High | 24 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | High | 23 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | High | 22 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | High | 21 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | High | 20 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | High | 19 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | High | 18 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 19.1 | 19.2 | 19.1 | 19.1 | 19.1 | 19.0 | 19.1 | 19.1 |
| 1900 MHz | High | 17 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | High | 16 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | High | 15 | 18.1 | 18.2 | 18.1 | 18.0 | 17.9 | 18.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | High | 14 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | High | 13 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | High | 12 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |
| 1900 MHz | High | 11 | 23.1 | 23.2 | 23.2 | 22.9 | 23.0 | 23.0 | 21.5 | 22.8 | 22.5 | 21.6 | 21.5 | 23.1 | 22.6 | 21.5 |



11.2 Test Records for Head SAR Test

| Plot No. | Band | Mode | Test Position | Channel | Ant Status | Battery | RB | Offset | SAR _{1g} (W/kg) |
|----------|--------------|------------|---------------|---------|------------|---------|----|--------|--------------------------|
| #01 | CDMA2000 BC0 | RC3+SO55 | Right Cheek | 384 | 1(Voice) | 1(06M) | - | - | 0.428 |
| #02 | CDMA2000 BC0 | RC3+SO55 | Right Cheek | 384 | 1(Voice) | 2(07M) | - | - | 0.418 |
| #05 | CDMA2000 BC0 | RC3+SO55 | Right Tilted | 384 | 1(Voice) | 1(06M) | - | - | 0.256 |
| #06 | CDMA2000 BC0 | RC3+SO55 | Left Cheek | 384 | 1(Voice) | 1(06M) | - | - | 0.353 |
| #07 | CDMA2000 BC0 | RC3+SO55 | Left Tilted | 384 | 1(Voice) | 1(06M) | - | - | 0.216 |
| #08 | CDMA2000 BC0 | RTAP 153.6 | Right Cheek | 384 | 2(Data) | 1(06M) | - | - | 0.490 |
| #09 | CDMA2000 BC0 | RTAP 153.6 | Right Tilted | 384 | 2(Data) | 1(06M) | - | - | 0.368 |
| #10 | CDMA2000 BC0 | RTAP 153.6 | Left Cheek | 384 | 2(Data) | 1(06M) | - | - | 0.623 |
| #11 | CDMA2000 BC0 | RTAP 153.6 | Left Tilted | 384 | 2(Data) | 1(06M) | - | - | 0.475 |
| #12 | CDMA2000 BC1 | RC3+SO55 | Right Cheek | 25 | 1(Voice) | 1(06M) | - | - | 0.595 |
| #13 | CDMA2000 BC1 | RC3+SO55 | Right Tilted | 25 | 1(Voice) | 1(06M) | - | - | 0.379 |
| #14 | CDMA2000 BC1 | RC3+SO55 | Left Cheek | 25 | 1(Voice) | 1(06M) | - | - | 1.19 |
| #15 | CDMA2000 BC1 | RC3+SO55 | Left Tilted | 25 | 1(Voice) | 1(06M) | - | - | 0.380 |
| #25 | CDMA2000 BC1 | RC3+SO55 | Left Cheek | 600 | 1(Voice) | 1(06M) | - | - | 1.08 |
| #26 | CDMA2000 BC1 | RC3+SO55 | Left Cheek | 1175 | 1(Voice) | 1(06M) | - | - | 1.10 |
| #16 | CDMA2000 BC1 | RTAP 153.6 | Right Cheek | 25 | 2(Data) | 1(06M) | - | - | 0.687 |
| #17 | CDMA2000 BC1 | RTAP 153.6 | Right Tilted | 25 | 2(Data) | 1(06M) | - | - | 0.859 |
| #18 | CDMA2000 BC1 | RTAP 153.6 | Left Cheek | 25 | 2(Data) | 1(06M) | - | - | 1.20 |
| #19 | CDMA2000 BC1 | RTAP 153.6 | Left Tilted | 25 | 2(Data) | 1(06M) | - | - | 0.998 |
| #20 | CDMA2000 BC1 | RTAP 153.6 | Left Cheek | 600 | 2(Data) | 1(06M) | - | - | 0.770 |
| #21 | CDMA2000 BC1 | RTAP 153.6 | Left Cheek | 1175 | 2(Data) | 1(06M) | - | - | 0.619 |
| #22 | CDMA2000 BC1 | RTAP 153.6 | Left Tilted | 600 | 2(Data) | 1(06M) | - | - | 0.578 |
| #23 | CDMA2000 BC1 | RTAP 153.6 | Left Tilted | 1175 | 2(Data) | 1(06M) | - | - | 0.394 |
| #24 | CDMA2000 BC1 | RTAP 153.6 | Right Tilted | 600 | 2(Data) | 1(06M) | - | - | 0.508 |
| #33 | CDMA2000 BC1 | RTAP 153.6 | Right Tilted | 1175 | 2(Data) | 1(06M) | - | - | 0.354 |
| #43 | LTE Band 13 | QPSK | Right Cheek | 23230 | 2(Data) | 1(06M) | 25 | 13 | 0.183 |
| #44 | LTE Band 13 | QPSK | Right Tilted | 23230 | 2(Data) | 1(06M) | 25 | 13 | 0.143 |
| #45 | LTE Band 13 | QPSK | Left Cheek | 23230 | 2(Data) | 1(06M) | 25 | 13 | 0.348 |
| #46 | LTE Band 13 | QPSK | Left Tilted | 23230 | 2(Data) | 1(06M) | 25 | 13 | 0.335 |
| #48 | LTE Band 13 | QPSK | Left Cheek | 23230 | 2(Data) | 1(06M) | 1 | 0 | 0.432 |
| #50 | LTE Band 13 | QPSK | Left Cheek | 23230 | 2(Data) | 1(06M) | 1 | 49 | 0.455 |
| #155 | LTE Band 13 | 16QAM | Right Cheek | 23230 | 2(Data) | 1(06M) | 25 | 13 | 0.25 |
| #156 | LTE Band 13 | 16QAM | Right Tilted | 23230 | 2(Data) | 1(06M) | 25 | 13 | 0.192 |
| #51 | LTE Band 13 | 16QAM | Left Cheek | 23230 | 2(Data) | 1(06M) | 25 | 13 | 0.348 |
| #157 | LTE Band 13 | 16QAM | Left Tilted | 23230 | 2(Data) | 1(06M) | 25 | 13 | 0.293 |
| #47 | LTE Band 13 | 16QAM | Left Cheek | 23230 | 2(Data) | 1(06M) | 1 | 0 | 0.45 |
| #49 | LTE Band 13 | 16QAM | Left Cheek | 23230 | 2(Data) | 1(06M) | 1 | 49 | 0.453 |

Notes:

1. According to April 2010 TCB Workshop RF Exposure Procedures, the SAR testing is use the maximum power channel to determine test reduction.
2. LTE 100% BW was not tested since the SAR is < 1.45 W/kg.
3. The DASY4 system was used for CDMA2000 head SAR testing, and the DASY5 system was used for LTE.



| Plot No. | Band | Test Position | Channel | Battery | SAR _{1g} (W/kg) |
|----------|---------|---------------|---------|---------|--------------------------|
| #29 | 802.11b | Right Cheek | 11 | 1 | 0.114 |
| #30 | 802.11b | Right Tilted | 11 | 1 | 0.057 |
| #27 | 802.11b | Left Cheek | 11 | 1 | 0.079 |
| #28 | 802.11b | Left Tilted | 11 | 1 | 0.046 |

Notes:

1. According to KDB 248227, when the SAR of maximum power channel is less 0.8 W/kg the SAR for other channels is optional.
2. The battery 1 was used for WLAN SAR testing due to it is worse battery of WWAN SAR.
3. The DASY4 system was used for WLAN head SAR testing.



11.3 Test Records for Body SAR Test

| Plot No. | Band | Mode | Test Position | Separation Distance (cm) | Ch. | Ant Status | Battery | Ear-phone | RB | Offset | SAR _{1g} (W/kg) |
|----------|---------------------|-------------------|--------------------|--------------------------|------------|-----------------|---------------|------------|----|--------|--------------------------|
| #106 | CDMA2000 BC0 | RC3+SO32 | Front Face | 1.0 | 384 | 1(Voice) | 1(06M) | w/o | - | - | 0.526 |
| #107 | CDMA2000 BC0 | RC3+SO32 | Rear Face | 1.0 | 384 | 1(Voice) | 1(06M) | w/o | - | - | 0.545 |
| #134 | CDMA2000 BC0 | RC3+SO32 | Rear Face | 1.0 | 384 | 1(Voice) | 2(07M) | w/o | - | - | 0.516 |
| #108 | CDMA2000 BC0 | RC3+SO32 | Bottom Side | 1.0 | 384 | 1(Voice) | 1(06M) | w/o | - | - | 0.229 |
| #110 | CDMA2000 BC0 | RC3+SO32 | Left Side | 1.0 | 384 | 1(Voice) | 1(06M) | w/o | - | - | 0.463 |
| #111 | CDMA2000 BC0 | RC3+SO32 | Right Side | 1.0 | 384 | 1(Voice) | 1(06M) | w/o | - | - | 0.381 |
| #135 | CDMA2000 BC0 | RC3+SO32 | Rear Face | 1.0 | 384 | 1(Voice) | 1(06M) | w/ | - | - | 0.490 |
| #59 | CDMA2000 BC0 | RTAP 153.6 | Front Face | 1.0 | 384 | 2(Data) | 1(06M) | w/o | - | - | 0.232 |
| #60 | CDMA2000 BC0 | RTAP 153.6 | Rear Face | 1.0 | 384 | 2(Data) | 1(06M) | w/o | - | - | 0.395 |
| #62 | CDMA2000 BC0 | RTAP 153.6 | Top Side | 1.0 | 384 | 2(Data) | 1(06M) | w/o | - | - | 0.157 |
| #63 | CDMA2000 BC0 | RTAP 153.6 | Left Side | 1.0 | 384 | 2(Data) | 1(06M) | w/o | - | - | 0.392 |
| #65 | CDMA2000 BC0 | RTAP 153.6 | Rear Face | 1.0 | 384 | 2(Data) | 1(06M) | w/ | - | - | 0.270 |
| #136 | CDMA2000 BC1 | RC3+SO32 | Front Face | 1.0 | 25 | 1(Voice) | 1(06M) | w/o | - | - | 0.810 |
| #137 | CDMA2000 BC1 | RC3+SO32 | Rear Face | 1.0 | 25 | 1(Voice) | 1(06M) | w/o | - | - | 1.28 |
| #138 | CDMA2000 BC1 | RC3+SO32 | Bottom Side | 1.0 | 25 | 1(Voice) | 1(06M) | w/o | - | - | 1.46 |
| #140 | CDMA2000 BC1 | RC3+SO32 | Left Side | 1.0 | 25 | 1(Voice) | 1(06M) | w/o | - | - | 0.115 |
| #141 | CDMA2000 BC1 | RC3+SO32 | Right Side | 1.0 | 25 | 1(Voice) | 1(06M) | w/o | - | - | 0.893 |
| #144 | CDMA2000 BC1 | RC3+SO32 | Rear Face | 1.0 | 600 | 1(Voice) | 1(06M) | w/o | - | - | 0.969 |
| #145 | CDMA2000 BC1 | RC3+SO32 | Rear Face | 1.0 | 1175 | 1(Voice) | 1(06M) | w/o | - | - | 0.900 |
| #146 | CDMA2000 BC1 | RC3+SO32 | Bottom Side | 1.0 | 600 | 1(Voice) | 1(06M) | w/o | - | - | 1.23 |
| #147 | CDMA2000 BC1 | RC3+SO32 | Bottom Side | 1.0 | 1175 | 1(Voice) | 1(06M) | w/o | - | - | 1.22 |
| #150 | CDMA2000 BC1 | RC3+SO32 | Rear Face | 1.0 | 25 | 1(Voice) | 1(06M) | w/ | - | - | 1.27 |
| #155 | CDMA2000 BC1 | RC3+SO32 | Rear Face | 1.0 | 600 | 1(Voice) | 1(06M) | w/ | - | - | 0.763 |
| #156 | CDMA2000 BC1 | RC3+SO32 | Rear Face | 1.0 | 1175 | 1(Voice) | 1(06M) | w/ | - | - | 0.761 |
| #94 | CDMA2000 BC1 | RTAP 153.6 | Front Face | 1.0 | 25 | 2(Data) | 1(06M) | w/o | - | - | 0.344 |
| #95 | CDMA2000 BC1 | RTAP 153.6 | Rear Face | 1.0 | 25 | 2(Data) | 1(06M) | w/o | - | - | 0.989 |
| #97 | CDMA2000 BC1 | RTAP 153.6 | Top Side | 1.0 | 25 | 2(Data) | 1(06M) | w/o | - | - | 0.324 |
| #98 | CDMA2000 BC1 | RTAP 153.6 | Left Side | 1.0 | 25 | 2(Data) | 1(06M) | w/o | - | - | 0.290 |
| #100 | CDMA2000 BC1 | RTAP 153.6 | Rear Face | 1.0 | 600 | 2(Data) | 1(06M) | w/o | - | - | 0.868 |
| #101 | CDMA2000 BC1 | RTAP 153.6 | Rear Face | 1.0 | 1175 | 2(Data) | 1(06M) | w/o | - | - | 0.949 |
| #102 | CDMA2000 BC1 | RTAP 153.6 | Rear Face | 1.0 | 25 | 2(Data) | 1(06M) | w/ | - | - | 0.933 |
| #153 | CDMA2000 BC1 | RTAP 153.6 | Rear Face | 1.0 | 600 | 2(Data) | 1(06M) | w/ | - | - | 0.789 |
| #154 | CDMA2000 BC1 | RTAP 153.6 | Rear Face | 1.0 | 1175 | 2(Data) | 1(06M) | w/ | - | - | 0.860 |

Notes:

1. For EVDO body SAR testing, the device was set on standalone mode which does not include 1 dB power reduction for SVDO operation.
2. According to April 2010 TCB Workshop RF Exposure Procedures, the SAR testing is use the maximum power channel to determine test reduction.
3. According to October 2010 TCB Workshop RF Exposure Procedures Update, the Ant-1 (1xRTT) SAR for hotspot mode only Front Face, Rear Face, Bottom Side, Left Side, and Right Side are needed due to the antenna location is within 2.5 cm from the edge.
4. The Ant-2 (EVDO) SAR for hotspot mode only Front Face, Rear Face, Top Side, and Left Side are needed due to the antenna location is within 2.5 cm from the edge.
5. The DASY5 system was used for CDMA2000 body SAR testing.



| Plot No. | Band | Mode | Test Position | Separation Distance (cm) | Ch. | Ant Status | Battery | Ear-phone | RB | Offset | SAR _{1g} (W/kg) |
|----------|-------------|-------|---------------|--------------------------|-------|------------|---------|-----------|----|--------|--------------------------|
| #120 | LTE Band 13 | QPSK | Front Face | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 25 | 13 | 0.170 |
| #121 | LTE Band 13 | QPSK | Rear Face | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 25 | 13 | 0.304 |
| #123 | LTE Band 13 | QPSK | Top Side | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 25 | 13 | 0.138 |
| #124 | LTE Band 13 | QPSK | Left Side | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 25 | 13 | 0.301 |
| #127 | LTE Band 13 | QPSK | Rear Face | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 1 | 0 | 0.443 |
| #129 | LTE Band 13 | QPSK | Rear Face | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 1 | 49 | 0.396 |
| #158 | LTE Band 13 | 16QAM | Front Face | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 25 | 13 | 0.171 |
| #126 | LTE Band 13 | 16QAM | Rear Face | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 25 | 13 | 0.331 |
| #160 | LTE Band 13 | 16QAM | Top Side | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 25 | 13 | 0.127 |
| #161 | LTE Band 13 | 16QAM | Left Side | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 25 | 13 | 0.317 |
| #128 | LTE Band 13 | 16QAM | Rear Face | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 1 | 0 | 0.449 |
| #130 | LTE Band 13 | 16QAM | Rear Face | 1.0 | 23230 | 2(Data) | 1(06M) | w/o | 1 | 49 | 0.396 |
| #132 | LTE Band 13 | 16QAM | Rear Face | 1.0 | 23230 | 2(Data) | 1(06M) | w/ | 1 | 0 | 0.329 |

Notes:

1. LTE 100% BW was not tested since the SAR is < 1.45 W/kg.
2. According to October 2010 TCB Workshop RF Exposure Procedures Update, the Ant-2 (LTE) SAR for hotspot mode only Front Face, Rear Face, Top Side, and Left Side are needed due to the antenna location is within 2.5 cm from the edge.
3. The DASY5 system was used for LTE body SAR testing.

| Plot No. | Band | Test Position | Separation Distance (cm) | Channel | Battery | Earphone | SAR _{1g} (W/kg) |
|----------|---------|---------------|--------------------------|---------|---------|----------|--------------------------|
| #113 | 802.11b | Front Face | 1.0 | 11 | 1 | w/o | 0.046 |
| #114 | 802.11b | Rear Face | 1.0 | 11 | 1 | w/o | 0.154 |
| #118 | 802.11b | Right Side | 1.0 | 11 | 1 | w/o | 0.127 |
| #133 | 802.11b | Rear Face | 1.0 | 11 | 1 | w/ | 0.148 |

Notes:

1. According to KDB 248227, when the SAR of maximum power channel is less 0.8 W/kg the SAR for other channels is optional.
2. The battery 1 was used for WLAN SAR testing due to it is worse battery of WWAN SAR.
3. According to October 2010 TCB Workshop RF Exposure Procedures Update, the WLAN SAR for hotspot mode only Front Face, Rear Face, and Right Side are needed due to the antenna location is within 2.5 cm from the edge.
4. The DASY5 system was used for WLAN body SAR testing.

11.4 Simultaneous Transmission SAR Analysis and Measurements

Table 11.1 Co-located Simultaneous Transmission Analysis for CDMA850 Voice + DO850 Data + WLAN

| Position | Transmitter 1 CDMA 850 Voice | Transmitter 2 DO 850 Data | Transmitter 3 WLAN | All 3 SAR Summation | SPLSR T1&T2 | SPLSR T1&T3 | SPLSR T2&T3 | Note |
|-------------------|---------------------------------|------------------------------|-----------------------|------------------------|----------------|----------------|----------------|--|
| Head-Right Cheek | 0.428 | 0.49 | 0.114 | 1.032 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Right Tilted | 0.256 | 0.368 | 0.057 | 0.681 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Left Cheek | 0.353 | 0.623 | 0.079 | 1.055 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Left Tilted | 0.216 | 0.475 | 0.046 | 0.737 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Front Face | 0.526 | 0.232 | 0.046 | 0.804 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Rear Face | 0.545 | 0.395 | 0.154 | 1.094 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Bottom Side | 0.229 | 0 | 0 | 0.229 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Top Side | 0 | 0.157 | 0 | 0.157 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Left Side | 0.463 | 0.392 | 0 | 0.855 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Right Side | 0.381 | 0 | 0.127 | 0.508 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |

Table 11.2 Co-located Simultaneous Transmission Analysis for CDMA850 Voice + DO1900 Data + WLAN

| Position | Transmitter 1 CDMA 850 Voice | Transmitter 2 DO 1900 Data | Transmitter 3 WLAN | All 3 SAR Summation | SPLSR T1&T2 | SPLSR T1&T3 | SPLSR T2&T3 | Note |
|-------------------|---------------------------------|-------------------------------|-----------------------|------------------------|----------------|----------------|----------------|--|
| Head-Right Cheek | 0.428 | 0.687 | 0.114 | 1.229 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Right Tilted | 0.256 | 0.859 | 0.057 | 1.172 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Left Cheek | 0.353 | 1.2 | 0.079 | 1.632 | 0.23 | 0.24 | 0.18 | All SPLSR<0.3, Simul-TX SAR not required |
| Head-Left Tilted | 0.216 | 0.998 | 0.046 | 1.26 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Front Face | 0.526 | 0.344 | 0.046 | 0.916 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Rear Face | 0.545 | 0.989 | 0.154 | 1.688 | 0.21 | 0.16 | 0.20 | All SPLSR<0.3, Simul-TX SAR not required |
| Body-Bottom Side | 0.229 | 0 | 0 | 0.229 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Top Side | 0 | 0.324 | 0 | 0.324 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Left Side | 0.463 | 0.29 | 0 | 0.753 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Right Side | 0.381 | 0 | 0.127 | 0.508 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |


Note: The calculation of SPLSR is as follows.

<SPLSR calculation procedure>

- 1) Use DASY software to open SAR data file with zoom scan results.
- 2) Export data file to SEMCAD using 'Field Data Export' function.
- 3) Search for highest SAR based on the imported measured/interpolated data and identify the X, Y, and Z coordinates. Per the SAR system manufacture, DASY stores the individual coordinates of each measurement point in the measurement file where the center coordinate (x=0, y=0) is always the Grid Reference Point as set in DASY for a phantom section.
- 4) Calculate the peak SAR separation distances using the Pythagoras' theorem where

$$\text{Peak SAR separation distance} = \sqrt{(X_1 - X_2)^2 + (Y_1 - Y_2)^2 + (Z_1 - Z_2)^2}$$
- 5) Calculate SPLSR = (SAR1 + SAR2) / Peak SAR separation distance.
- 6) The SPLSR calculation plots shown in test report are for reference only as the images were generated in a separate software program to add the antenna and arrow references. The distance information in the calculations below each plot is derived from the DASY SAR zoom scan data as specified in this procedure.

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T1+T2) is as below:




Coordinate of Peak SAR Location (X, Y, Z) : T1(6.67, 26.1, -17.4), T2(3.53, 32.1, -17.5)

Peak Location Spacing = 6.8 cm

SPLSR (SAR to Peak Location Spacing Ratio) = (0.353 + 1.2) / 6.8 = 0.23

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T1+T3) is as below:

CDMA 850 Voice + WLAN Plot




Coordinate of Peak SAR Location (X, Y, Z) : T1(6.67, 26.1, -17.4), T3(5.06, 25.3, -17.5)

Peak Location Spacing = 1.8 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(0.353 + 0.079) / 1.8 = 0.24$

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T2+T3) is as below:

DO 1900 Data + WLAN Plot




Coordinate of Peak SAR Location (X, Y, Z) : T2(3.53, 32.1, -17.5), T3(5.06, 25.3, -17.5)

Peak Location Spacing = 7.0 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.2 + 0.079) / 7.0 = 0.18$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T1+T2) is as below:

CDMA 850 Voice + DO 1900 Data Plot




Coordinate of Peak SAR Location (X, Y, Z) : T1(-1.28, -8.44, -20.5), T2(-3.76, -1.4, -20.6)

Peak Location Spacing = 7.5 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(0.545 + 0.989) / 7.5 = 0.21$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T1+T3) is as below:

CDMA 850 Voice + WLAN Plot




Coordinate of Peak SAR Location (X, Y, Z) : T1(-1.28, -8.44, -20.5), T3(0.76, -4.7, -20.5)

Peak Location Spacing = 4.3 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(0.545 + 0.154) / 4.3 = 0.16$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T2+T3) is as below:



Coordinate of Peak SAR Location (X, Y, Z) : T2(-3.76, -1.4, -20.6), T3(0.76, -4.7, -20.5)

Peak Location Spacing = 5.6 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(0.989 + 0.154) / 5.6 = 0.20$

Table 11.3 Co-located Simultaneous Transmission Analysis for CDMA850 Voice + LTE700 Data + WLAN


| Position | Transmitter 1 CDMA 850 Voice | Transmitter 2 LTE 700 Data | Transmitter 3 WLAN | All 3 SAR Summation | SPLSR T1&T2 | SPLSR T1&T3 | SPLSR T2&T3 | Note |
|-------------------|---------------------------------|-------------------------------|-----------------------|------------------------|----------------|----------------|----------------|--|
| Head-Right Cheek | 0.428 | 0.25 | 0.114 | 0.792 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Right Tilted | 0.256 | 0.192 | 0.057 | 0.505 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Left Cheek | 0.353 | 0.455 | 0.079 | 0.887 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Left Tilted | 0.216 | 0.335 | 0.046 | 0.597 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Front Face | 0.526 | 0.171 | 0.046 | 0.743 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Rear Face | 0.545 | 0.449 | 0.154 | 1.148 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Bottom Side | 0.229 | 0 | 0 | 0.229 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Top Side | 0 | 0.138 | 0 | 0.138 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Left Side | 0.463 | 0.317 | 0 | 0.78 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Right Side | 0.381 | 0 | 0.127 | 0.508 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |

Table 11.4 Co-located Simultaneous Transmission Analysis for CDMA1900 Voice + DO850 Data + WLAN

| Position | Transmitter 1 CDMA 1900 Voice | Transmitter 2 DO 850 Data | Transmitter 3 WLAN | All 3 SAR Summation | SPLSR T1&T2 | SPLSR T1&T3 | SPLSR T2&T3 | Note |
|-------------------|----------------------------------|------------------------------|-----------------------|------------------------|----------------|----------------|----------------|--|
| Head-Right Cheek | 0.595 | 0.49 | 0.114 | 1.199 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Right Tilted | 0.379 | 0.368 | 0.057 | 0.804 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Left Cheek | 1.19 | 0.623 | 0.079 | 1.892 | 0.21 | 0.67 | 0.09 | T1+T3 SPLSR>0.3, Simul-TX SAR required |
| Head-Left Tilted | 0.38 | 0.475 | 0.046 | 0.901 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Front Face | 0.81 | 0.232 | 0.046 | 1.088 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Rear Face | 1.28 | 0.395 | 0.154 | 1.829 | 0.12 | 0.19 | 0.07 | All SPLSR<0.3, Simul-TX SAR not required |
| Body-Bottom Side | 1.46 | 0 | 0 | 1.46 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Top Side | 0 | 0.157 | 0 | 0.157 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Left Side | 0.115 | 0.392 | 0 | 0.507 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Right Side | 0.893 | 0 | 0.127 | 1.02 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |

Note: The calculation of SPLSR is as follows.

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T1+T2) is as below:




Coordinate of Peak SAR Location (X, Y, Z) : T1(6.93, 25.1, -17.3), T2(2.83, 32.5, -17.5)

Peak Location Spacing = 8.5 cm

SPLSR (SAR to Peak Location Spacing Ratio) = (1.19 + 0.623) / 8.5 = 0.21

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T1+T3) is as below:

CDMA 1900 Voice + WLAN Plot



**DUT Bottom Side
DUT Face Up**


Coordinate of Peak SAR Location (X, Y, Z) : T1(6.93, 25.1, -17.3), T3(5.06, 25.3, -17.5)

Peak Location Spacing = 1.9 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.19 + 0.079) / 1.9 = 0.67$

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T2+T3) is as below:

DO 850 Data + WLAN Plot



**DUT Bottom Side
DUT Face Up**


Coordinate of Peak SAR Location (X, Y, Z) : T2(2.83, 32.5, -17.5), T3(5.06, 25.3, -17.5)

Peak Location Spacing = 7.5 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(0.623 + 0.079) / 7.5 = 0.09$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T1+T2) is as below:

CDMA 1900 Voice + DO 850 Data Plot




Coordinate of Peak SAR Location (X, Y, Z) : T1(-0.72, -12.3, -20.5), T2(-2.98, 1.4, -18)

Peak Location Spacing = 14.1 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.28 + 0.395) / 14.1 = 0.12$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T1+T3) is as below:

CDMA 1900 Voice + WLAN Plot




Coordinate of Peak SAR Location (X, Y, Z) : T1(-0.72, -12.3, -20.5), T3(0.76, -4.7, -20.5)

Peak Location Spacing = 7.7 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.28 + 0.154) / 7.7 = 0.19$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T2+T3) is as below:



Coordinate of Peak SAR Location (X, Y, Z) : T2(-2.98, 1.4, -18), T3(0.76, -4.7, -20.5)

Peak Location Spacing = 7.6 cm


SPLSR (SAR to Peak Location Spacing Ratio) = $(0.395 + 0.154) / 7.6 = 0.07$

Table 11.5 Co-located Simultaneous Transmission Analysis for CDMA1900 Voice + DO1900 Data + WLAN

| Position | Transmitter 1 CDMA 1900 Voice | Transmitter 2 DO 1900 Data | Transmitter 3 WLAN | All 3 SAR Summation | SPLSR T1&T2 | SPLSR T1&T3 | SPLSR T2&T3 | Note |
|-------------------|----------------------------------|-------------------------------|-----------------------|------------------------|----------------|----------------|----------------|--|
| Head-Right Cheek | 0.595 | 0.687 | 0.114 | 1.396 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Right Tilted | 0.379 | 0.859 | 0.057 | 1.295 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Left Cheek | 1.19 | 1.2 | 0.079 | 2.469 | 0.31 | 0.67 | 0.18 | T1+T2 & T1+T3 SPLSR>0.3, Simul-TX SAR required |
| Head-Left Tilted | 0.38 | 0.998 | 0.046 | 1.424 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Front Face | 0.81 | 0.344 | 0.046 | 1.2 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Rear Face | 1.28 | 0.989 | 0.154 | 2.423 | 0.20 | 0.19 | 0.20 | All SPLSR<0.3, Simul-TX SAR not required |
| Body-Bottom Side | 1.46 | 0 | 0 | 1.46 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Top Side | 0 | 0.324 | 0 | 0.324 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Left Side | 0.115 | 0.29 | 0 | 0.405 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Right Side | 0.893 | 0 | 0.127 | 1.02 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |

Note: The calculation of SPLSR is as follows.

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T1+T2) is as below:




Coordinate of Peak SAR Location (X, Y, Z) : T1(6.93, 25.1, -17.3), T2(3.53, 32.1, -17.5)

Peak Location Spacing = 7.8 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.19 + 1.2) / 7.8 = 0.31$

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T1+T3) is as below:




Coordinate of Peak SAR Location (X, Y, Z) : T1(6.93, 25.1, -17.3), T3(5.06, 25.3, -17.5)

Peak Location Spacing = 1.9 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.19 + 0.079) / 1.9 = 0.67$

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T2+T3) is as below:

DO 1900 Data + WLAN Plot




Coordinate of Peak SAR Location (X, Y, Z) : T2(3.53, 32.1, -17.5), T3(5.06, 25.3, -17.5)

Peak Location Spacing = 7.0 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.2 + 0.079) / 7.0 = 0.18$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T1+T2) is as below:

CDMA 1900 Voice + DO 1900 Data Plot




Coordinate of Peak SAR Location (X, Y, Z) : T1(-0.72, -12.3, -20.5), T2(-3.76, -1.4, -20.6)

Peak Location Spacing = 11.3 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.28 + 0.989) / 11.3 = 0.20$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T1+T3) is as below:

CDMA 1900 Voice + WLAN Plot




Coordinate of Peak SAR Location (X, Y, Z) : T1(-0.72, -12.3, -20.5), T3(0.76, -4.7, -20.5)

Peak Location Spacing = 7.7 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.28 + 0.154) / 7.7 = 0.19$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T2+T3) is as below:

DO 1900 Data + WLAN Plot



Coordinate of Peak SAR Location (X, Y, Z) : T2(-3.76, -1.4, -20.6), T3(0.76, -4.7, -20.5)

Peak Location Spacing = 5.6 cm


SPLSR (SAR to Peak Location Spacing Ratio) = $(0.989 + 0.154) / 5.6 = 0.20$

Table 11.6 Co-located Simultaneous Transmission Analysis for CDMA1900 Voice + LTE700 Data + WLAN

| Position | Transmitter 1 CDMA 1900 Voice | Transmitter 2 LTE 700 Data | Transmitter 3 WLAN | All 3 SAR Summation | SPLSR T1&T2 | SPLSR T1&T3 | SPLSR T2&T3 | Note |
|-------------------|----------------------------------|-------------------------------|-----------------------|------------------------|----------------|----------------|----------------|--|
| Head-Right Cheek | 0.595 | 0.183 | 0.114 | 0.892 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Right Tilted | 0.379 | 0.143 | 0.057 | 0.579 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Head-Left Cheek | 1.19 | 0.455 | 0.079 | 1.724 | 0.18 | 0.67 | 0.07 | T1+T3 SPLSR>0.3, Simul-TX SAR required |
| Head-Left Tilted | 0.38 | 0.335 | 0.046 | 0.761 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Front Face | 0.81 | 0.171 | 0.046 | 1.027 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Rear Face | 1.28 | 0.449 | 0.154 | 1.883 | 0.16 | 0.19 | 0.14 | All SPLSR<0.3, Simul-TX SAR not required |
| Body-Bottom Side | 1.46 | 0 | 0 | 1.46 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Top Side | 0 | 0.138 | 0 | 0.138 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Left Side | 0.115 | 0.317 | 0 | 0.432 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |
| Body-Right Side | 0.893 | 0 | 0.127 | 1.02 | N/A | N/A | N/A | SUM SAR<1.6, Simul-TX SAR not required |

Note: The calculation of SPLSR is as follows.

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T1+T2) is as below:




Coordinate of Peak SAR Location (X, Y, Z) : T1(6.93, 25.1, -17.3), T2(3, 33.1, -17.3)

Peak Location Spacing = 8.9 cm

SPLSR (SAR to Peak Location Spacing Ratio) = (1.19 + 0.455) / 8.9 = 0.18

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T1+T3) is as below:

CDMA 1900 Voice + WLAN Plot




Coordinate of Peak SAR Location (X, Y, Z) : T1(6.93, 25.1, -17.3), T3(5.06, 25.3, -17.5)

Peak Location Spacing = 1.9 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.19 + 0.079) / 1.9 = 0.67$

The calculation of SAR to peak location separation ratio for (Head-Left Cheek, T2+T3) is as below:

LTE 700 Data + WLAN Plot




Coordinate of Peak SAR Location (X, Y, Z) : T2(3, 33.1, -17.3), T3(5.06, 25.3, -17.5)

Peak Location Spacing = 8.1 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(0.455 + 0.079) / 8.1 = 0.07$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T1+T2) is as below:

CDMA 1900 Voice + LTE 700 Data Plot




Coordinate of Peak SAR Location (X, Y, Z) : T1(-0.72, -12.3, -20.5), T2(-0.7, -1.8, -17.9)

Peak Location Spacing = 10.8 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.28 + 0.449) / 10.8 = 0.16$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T1+T3) is as below:

CDMA 1900 Voice + WLAN Plot




Coordinate of Peak SAR Location (X, Y, Z) : T1(-0.72, -12.3, -20.5), T3(0.76, -4.7, -20.5)

Peak Location Spacing = 7.7 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(1.28 + 0.154) / 7.7 = 0.19$

The calculation of SAR to peak location separation ratio for (Body-Rear Face, T2+T3) is as below:



Coordinate of Peak SAR Location (X, Y, Z) : T2(-0.7, -1.8, -17.9), T3(0.76, -4.7, -20.5)

Peak Location Spacing = 4.2 cm

SPLSR (SAR to Peak Location Spacing Ratio) = $(0.449 + 0.154) / 4.2 = 0.14$

Table 11.7 Volume Scan SAR Measurement Results


| Plot No. | Band | Mode | Test Position | Ch. | Ant Status | Battery | SAR _{1g} (W/kg) | Multi Band SAR _{1g} (W/kg) |
|----------|--------------|------------------------------|---------------|-------|------------|---------|--------------------------|-------------------------------------|
| #162 | CDMA2000 BC1 | RC3+SO55 (Pw: 24.00 dBm) | Left Cheek | 25 | 1(Voice) | 1(06M) | 1.2 | 1.23 |
| | CDMA2000 BC1 | RTAP 153.6 (Pw: 18.58 dBm) | Left Cheek | 25 | 2(Data) | 1(06M) | | |
| #81 | 802.11b | - | Left Cheek | 11 | - | 1(06M) | 0.09 | |
| #163 | CDMA2000 BC1 | RC3+SO55 (Pw: 14.73 dBm) | Left Cheek | 25 | 1(Voice) | 1(06M) | 1.12 | 1.13 |
| | CDMA2000 BC1 | RTAP 153.6 (Pw: 23.18 dBm) | Left Cheek | 25 | 2(Data) | 1(06M) | | |
| #81 | 802.11b | - | Left Cheek | 11 | - | 1(06M) | 0.09 | |
| #71 | CDMA2000 BC1 | RC3+SO55 (Pw: 24.00 dBm) | Left Cheek | 25 | 1(Voice) | 1(06M) | 1.19 | 1.3 |
| #164 | CDMA2000 BC0 | RTAP 153.6 (Pw: 23.78 dBm) | Left Cheek | 384 | 2(Data) | 1(06M) | 0.501 | |
| #81 | 802.11b | - | Left Cheek | 11 | - | 1(06M) | 0.09 | |
| #71 | CDMA2000 BC1 | RC3+SO55 (Pw: 24.00 dBm) | Left Cheek | 25 | 1(Voice) | 1(06M) | 1.19 | 1.31 |
| #165 | LTE Band 13 | QPSK (RB1, OS 49, 22.92 dBm) | Left Cheek | 23230 | 2(Data) | 1(06M) | 0.536 | |
| #81 | 802.11b | - | Left Cheek | 11 | - | 1(06M) | 0.09 | |

Notes:

1. Volume scan was performed on the SVDO mode and two conditions (#162 & #163). One is 1x power above reduce threshold, and the other one is 1x power below reduce threshold.
2. The 1x and EVDO are transmitting simultaneously during volume scan testing (#162 & #163). DUT was set up the co-transmission by system simulator and continuous Tx program (FTM). Test condition is shown as below.

| | |
|---------------------------------|--------------------------------|
| 1x power ABOVE reduce threshold | 1x via Simulator, EVDO via FTM |
| 1x power BELOW reduce threshold | 1x via FTM, EVDO via Simulator |

During simultaneous testing of this DUT when both the voice and transmitter operated in the same frequency band, the volume SAR scans were completed with both transmitters active and transmitting on the same RF channel (i.e. the same frequencies). It is impossible to sustain a simultaneous 1x and DO call on the same RF channel using call boxes and therefore test code, referred to as "FTM", was used to configure one transmitter to transmit at the desired transmit power. The 2nd transmitter used a call simulator box to operate in a live maximum transmit power call. The following figure illustrates the test setup.



FTM allows the transmitter to be manually tuned to a RF frequency and the transmitter adjusted to the desire transmit power. The average transmit power before and after the test is measured to verify the DUT is transmitter the appropriate maximum transmit power as desired per the power reduction settings in Table 3.4.

The maximum transmit power data in section 11.1.1 shows voice and data transmit measurements at different voice transmit power levels to validate the DUT performs as expected during a live call.

3. The worst configuration on each position is used for the volume scan.
4. The DASY5 system was used for volume scan testing.

Test Engineer : A-Rod Chen, Andy He, Robert Liu, and Eric Huang

12. References

- [1] FCC 47 CFR Part 2 "Frequency Allocations and Radio Treaty Matters; General Rules and Regulations"
- [2] IEEE Std. C95.1-1991, "IEEE Standard for Safety Levels with Respect to Human Exposure to Radio Frequency Electromagnetic Fields, 3 kHz to 300 GHz", 1991
- [3] IEEE Std. 1528-2003, "Recommended Practice for Determining the Peak Spatial-Average Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques", December 2003
- [4] FCC OET Bulletin 65 (Edition 97-01) Supplement C (Edition 01-01), "Evaluating Compliance with FCC Guidelines for Human Exposure to Radiofrequency Electromagnetic Fields", June 2001
- [5] SPEAG DASY System Handbook
- [6] FCC KDB 248227 D01 v01r02, "SAR Measurement Procedures for 802.11 a/b/g Transmitters", May 2007
- [7] FCC KDB 447498 D01 v04, "Mobile and Portable Device RF Exposure Procedures and Equipment Authorization Policies", November 2009
- [8] FCC KDB 447498 D02 v02, "SAR Measurement Procedures for USB Dongle Transmitters", November 2009
- [9] FCC KDB 616217 D01 v01r01, "SAR Evaluation Considerations for Laptop Computers with Antennas Built-in on Display Screens", November 2009
- [10] FCC KDB 616217 D03 v01, "SAR Evaluation Considerations for Laptop/Notebook/Netbook and Tablet Computers", November 2009
- [11] FCC KDB 648474 D01 v01r05, "SAR Evaluation Considerations for Handsets with Multiple Transmitters and Antennas", September 2008
- [12] FCC KDB 941225 D01 v02, "SAR Measurement Procedures for 3G Devices – CDMA 2000 / Ev-Do / WCDMA / HSDPA / HSPA", October 2007
- [13] FCC KDB 941225 D03 v01, "Recommended SAR Test Reduction Procedures for GSM / GPRS / EDGE", December 2008
- [14] FCC KDB 941225 D04 v01, "Evaluating SAR for GSM/(E)GPRS Dual Transfer Mode", January 27 2010



Appendix A. Plots of System Performance Check

The plots are shown as follows.



Appendix B. Plots of SAR Measurement

The plots are shown as follows.



Appendix C. DASY Calibration Certificate

The DASY calibration certificates are shown as follows.