



Intertek Testing Services  
ETL SEMKO

**Cirkisys Electronics Ltd.**

Application  
For  
Certification  
**(FCC ID: OBMALPHA-1-400-4)**

Superheterodyne Receiver

WO# 99033434  
WN/at  
3 May, 1999

**Intertek Testing Services Hong Kong Ltd.**  
2/F., Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong.  
Tel: (852) 2173 8888 Fax: (852) 2745 8306

# INTERTEK TESTING SERVICES

---

## LIST OF EXHIBITS

### *INTRODUCTION*

|                   |                           |
|-------------------|---------------------------|
| <i>EXHIBIT 1:</i> | General Description       |
| <i>EXHIBIT 2:</i> | System Test Configuration |
| <i>EXHIBIT 3:</i> | Emission Results          |
| <i>EXHIBIT 4:</i> | Equipment Photographs     |
| <i>EXHIBIT 5:</i> | Product Labelling         |
| <i>EXHIBIT 6:</i> | Technical Specifications  |
| <i>EXHIBIT 7:</i> | Instruction Manual        |
| <i>EXHIBIT 8:</i> | Miscellaneous Information |

# INTERTEK TESTING SERVICES

## MEASUREMENT/TECHNICAL REPORT

**Cirkisys Electronics Ltd. - MODEL: ALPHA - ONE 6015N**  
**FCC ID: OBMALPHA-1-400-4**

This report concerns (check one):      Original Grant X      Class II Change \_\_\_\_\_

Equipment Type: Superheterodyne Receiver (example: computer, printer, modem, etc.)

\_\_\_\_\_ Deferred grant  
requested per 47 CFR 0.457(d)(1)(ii)?      Yes \_\_\_\_\_ No X

If yes, defer until: \_\_\_\_\_  
date

Company Name agrees to notify the Commission by: \_\_\_\_\_  
date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37?      Yes \_\_\_\_\_ No X

If no, assumed Part 15, Subpart B for unintentional radiator - the new 47 CFR [10-1-96 Edition] provision.

Report prepared by:

Wilbur Ng  
Intertek Testing Services  
Hong Kong Ltd.  
2/F., Garment Centre,  
576, Castle Peak Road,  
Kowloon, Hong Kong  
Phone: 852-2173-8502  
Fax: 852-2745-8306

---

# INTERTEK TESTING SERVICES

---

## Table of Contents

|     |   |    |
|-----|---|----|
| 1.0 | <b><u>General Description</u></b> .....         | 1  |
| 1.1 | Product Description .....                       | 1  |
| 1.2 | Related Submittal(s) Grants .....               | 1  |
| 1.3 | Test Methodology .....                          | 2  |
| 1.4 | Test Facility.....                              | 2  |
| 2.0 | <b><u>System Test Configuration</u></b> .....   | 3  |
| 2.1 | Justification .....                             | 3  |
| 2.2 | EUT Exercising Software.....                    | 3  |
| 2.3 | Support Equipment List and Description .....    | 3  |
| 2.4 | Equipment Modification.....                     | 5  |
| 2.5 | Special Accessories.....                        | 5  |
| 3.0 | <b><u>Emission Results</u></b> .....            | 7  |
| 3.1 | Field Strength Calculation .....                | 8  |
| 3.2 | Radiated Emission Configuration Photograph..... | 9  |
| 3.3 | Radiated Emission Data.....                     | 11 |
| 4.0 | <b><u>Equipment Photographs</u></b> .....       | 14 |
| 5.0 | <b><u>Product Labelling</u></b> .....           | 16 |
| 6.0 | <b><u>Technical Specifications</u></b> .....    | 18 |
| 7.0 | <b><u>Instruction Manual</u></b> .....          | 20 |
| 8.0 | <b><u>Miscellaneous Information</u></b> .....   | 22 |
| 8.1 | Discussion of Pulse Desensitization.....        | 23 |
| 8.2 | Calculation of Average Factor.....              | 24 |
| 8.3 | Emissions Test Procedures .....                 | 25 |

---

## INTERTEK TESTING SERVICES

---

### List of attached file

| Exhibit type          | File Description           | filename                     |
|-----------------------|----------------------------|------------------------------|
| Cover Letter          | Letter of Agency           | letter.pdf                   |
| Test Report           | Test Report                | report.doc                   |
| Operation Description | Technical Description      | descri.pdf                   |
| Test Setup Photo      | Radiated Emission          | radiated1.jpg, radiated2.jpg |
| External Photo        | External Photo             | ophoto1.jpg to ophoto2.jpg   |
| Internal Photo        | Internal Photo             | iphoto1.jpg to iphoto4.jpg   |
| Block Diagram         | Block Diagram              | block.pdf                    |
| Schematics            | Circuit Diagram            | circuit.pdf                  |
| ID Label/Location     | Label Artwork and Location | label.pdf                    |
| User Manual           | User Manual                | manual.pdf                   |

# **INTERTEK TESTING SERVICES**

---

## **EXHIBIT 1**

### **GENERAL DESCRIPTION**

## INTERTEK TESTING SERVICES

---

### 1.0 **General Description**

#### 1.1 Product Description

The Equipment Under Test (EUT) is a POCSAG alpha-numeric pager. The EUT is powered by a 1.5V “AAA” battery. It can operate from 464 MHz to 468 MHz by choosing corresponding value of channel crystal X1. It has two buttons and 16-characters (14-segment type) LCD display. The message will be displayed on the LCD glass and will scroll if more than 16 characters. When a new user message is being received, the pager will give an alert signal, such as buzzing sound or vibration form vibrator.

For electronic filing, the brief circuit description is saved with filename: descri.pdf

#### 1.2 Related Submittal(s) Grants

This is an application for Certification of a receiver.

## INTERTEK TESTING SERVICES

---

### 1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.4 (1992). All radiated measurements were performed in an Open Area Test Site. Preliminary scans were performed in the Open Area Test Site only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

### 1.4 Test Facility

The open area test site and conducted measurement facility used to collect the radiated data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been placed on file with the FCC.



**EXHIBIT 2**  
**SYSTEM TEST CONFIGURATION**

## INTERTEK TESTING SERVICES

---

### 2.0 **System Test Configuration**

#### 2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSIC63.4 (1992).

The device was powered from 1 fully charged 1.5V "AAA" battery

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. The step by step procedure for maximizing emissions led to the data reported in Exhibit 3.0.

The unit was operated standalone and placed in the center of the turntable.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was mounted to a cardboard box, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes.

#### 2.2 EUT Exercising Software

There was no special software to exercise the device. Once the unit is powered up, it received continuously.

#### 2.3 Special Accessories

There are no special accessories necessary for compliance of this product.

## INTERTEK TESTING SERVICES

---

### 2.4 Equipment Modification

Any modifications installed previous to testing by Cirkisys Electronics Ltd. will be incorporated in each production model sold/leased in the United States.

No modifications were installed by Intertek Testing Services.

### 2.5 Support Equipment List and Description

This product was tested in standalone configuration.

All the items listed under section 2.0 of this report are

*Confirmed by:*

*Wilbur Ng  
Assistant Manager  
Intertek Testing Services Hong Kong Ltd.  
Agent for Cirkisys Electronics Ltd.*



\_\_\_\_\_  
Signature

\_\_\_\_\_  
3 May, 1999

\_\_\_\_\_  
Date

**EXHIBIT 3**  
**EMISSION RESULTS**

### 3.0 **Emission Results**

Data is included of the worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

---

## INTERTEK TESTING SERVICES

---

### 3.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CF - AG$$

where FS = Field Strength in dB $\mu$ V/m

RA = Receiver Amplitude (including preamplifier) in dB $\mu$ V

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB

AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows:

$$FS = RR + LF$$

where FS = Field Strength in dB $\mu$ V/m

RR = RA - AG in dB $\mu$ V

LF = CF + AF in dB

Assume a receiver reading of 52.0 dB $\mu$ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB are added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 dB $\mu$ V/m. This value in dB $\mu$ V/m was converted to its corresponding level in  $\mu$ V/m.

$$RA = 52.0 \text{ dB}\mu\text{V/m}$$

$$AF = 7.4 \text{ dB}$$

$$CF = 1.6 \text{ dB}$$

$$AG = 29.0 \text{ dB}$$

$$FS = RR + LF$$

$$FS = 23 + 9 = 32 \text{ dB}\mu\text{V/m}$$

$$RR = 23.0 \text{ dB}\mu\text{V}$$

$$LF = 9.0 \text{ dB}$$

$$\text{Level in mV/m} = \text{Common Antilogarithm} [(32 \text{ dB}\mu\text{V/m})/20] = 39.8 \mu\text{V/m}$$

## INTERTEK TESTING SERVICES

---

### 3.2 Radiated Emission Configuration Photograph

Worst Case Radiated Emission  
at  
893.236 MHz

For electronic filing, the front view and back view of the test configuration photographs are saved with filename: radiated1.jpg and radiated2.jpg respectively.

## INTERTEK TESTING SERVICES

---

### 3.3 Radiated Emission Data

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 5.8 dB

#### ***TEST PERSONNEL:***



---

*Signature*

Liza C. Y. Chan, Compliance Engineer  
*Typed/Printed Name*

3 May, 1999  
*Date*



---

## INTERTEK TESTING SERVICES

---

Company: Cirkisys Electronics Ltd.  
Model: ALPHA - ONE 6015N

Date of Test: 28 April, 1999

**Table 1**

**FCC Class B Radiated Emissions**

| Polarity | Frequency<br>(M H z) | Reading<br>(dB $\mu$ V ) | Antenna<br>Factor<br>(dB ) | Pre-Am p<br>Gain<br>(dB ) | Net<br>at 3m<br>(dB $\mu$ V /m ) | Lin it<br>at 3m<br>(dB $\mu$ V /m ) | M argin<br>(dB ) |
|----------|----------------------|--------------------------|----------------------------|---------------------------|----------------------------------|-------------------------------------|------------------|
| H        | 446.618              | 29.0                     | 25.0                       | 16                        | 38.0                             | 46.0                                | -8.0             |
| H        | 893.236              | 25.2                     | 31.0                       | 16                        | 40.2                             | 46.0                                | -5.8             |
| H        | 1339.854             | 50.4                     | 25.5                       | 34                        | 41.9                             | 54.0                                | -12.1            |

- NOTES:
1. Peak Detector Data unless otherwise stated.
  2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
  3. Negative sign in the column shows value below limit.
  4. Horn antenna and average detector are used for the emission over 1000MHz.
- \* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Liza C. Y. Chan

**EXHIBIT 4**  
**EQUIPMENT PHOTOGRAPHS**

## INTERTEK TESTING SERVICES

---

### 4.0 **Equipment Photographs**

For electronic filing, photographs of the tested EUT are saved with filename: ophoto1.jpg, ophoto2.jpg for external photo, and iphoto1.jpg, iphoto2.jpg, iphoto3.jpg and iphoto4.jpg for internal photo.

**EXHIBIT 5**

**PRODUCT LABELLING**

### 5.0 **Product Labelling**

For electronics filing, the FCC ID label artwork and the label location are saved with filename: label.pdf.

**EXHIBIT 6**  
**TECHNICAL SPECIFICATIONS**

### 6.0 **Technical Specifications**

For electronic filing, the block diagram and schematic of the tested EUT are saved with filename: block.pdf and circuit.pdf respectively.

**EXHIBIT 7**  
**INSTRUCTION MANUAL**



## INTERTEK TESTING SERVICES

---

### 7.0 **Instruction Manual**

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

This manual will be provided to the end-user with each unit sold/leased in the United States.

**EXHIBIT 8**

**MISCELLANEOUS INFORMATION**

### 8.0 **Miscellaneous Information**

This miscellaneous information includes the test procedure and calculation of factors such as pulse desensitization and averaging factor.

## INTERTEK TESTING SERVICES

---

### 8.1 Discussion of Pulse Desensitization

The determination of pulse desensitivity was made in accordance with Hewlett Packard Application Note 150-2, *Spectrum Analysis ... Pulsed RF*.

This device is a superheterodyne receiver. The stabilized signals are continuous, and no desensitization of the measurement equipment occurs.

### 8.2 Calculation of Average Factor

The emission limits are specified using spectrum analyzers or receivers which incorporate quasi-peak detectors. Typical measurements are made using peak detectors, however, emissions which approach the respective emission limit are measured using a quasi-peak detector.

For measurements above 1 GHz, spectrum analyzers or receivers using average detectors are employed, or the appropriate average factor can be applied.

Measurements using spectrum analyzers with filters other than peak detectors are recorded in the data table section of this report.

This device is a superheterodyne receiver.

It is not necessary to apply average factor to the measurement results.

### 8.3 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services Hong Kong Ltd. in the measurements of superheterodyne receivers operating under the Part 15, Subpart B rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 - 1992. Superheterodyne receivers are stabilized prior to measurement by generating a signal well above the receiver threshold whose frequency is tuned until the emissions stabilize into a line spectrum. The signal is usually generated as CW with a Marconi 2022D signal generator and a short whip antenna and is at a level of several hundred to several thousand mV/m. Plots of the stabilized signal will be shown. If a modulated signal is used, it will be noted.

The equipment under test (EUT) is placed on a wooden turntable which is four feet in diameter and approximately one meter in height above the groundplane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The EUT is adjusted through all three orthogonal axis to obtain maximum emission levels. The antenna height and polarization are also varied during the testing to search for maximum signal levels. The height of the antenna is varied from one to four meters.

Detector function for radiated emissions is in peak mode. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings. A detailed description for the calculation of the average factor can be found in Exhibit 8.2.

The frequency range scanned is from the lowest radio frequency signal generated in the device which is greater than 9 kHz to the tenth harmonic of the highest fundamental frequency or 40 GHz, whichever is lower. For line conducted emissions, the range scanned is 450 kHz to 30 MHz.

## INTERTEK TESTING SERVICES

---

### 8.3 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test.

AC power to the unit is varied from 85% to 115% nominal and variation in the fundamental emission field strength is recorded. If battery powered, a new, fully charged battery is used.

Conducted measurements were made as described in ANSI C63.4 - 1992.

The IF bandwidth used for measurement of radiated signal strength was 100 kHz or greater when frequency is below 1000 MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. A discussion of whether pulse desensitivity is applicable to this unit is included in this report (See Exhibit 8.1). Above 1000 MHz, a resolution bandwidth of 1 MHz is used.

Measurements are normally conducted at a measurement distance of three meters. All measurements are extrapolated to three meters using inverse scaling, unless otherwise reported. Measurements taken at a closer distance are so marked.