



RF EXPOSURE REPORT

REPORT NO.: SA940511L04

MODEL NO.: WAP54GX

ACCORDING: FCC Guidelines for Human Exposure
IEEE C95.1

APPLICANT: Cisco-Linksys LLC

ADDRESS: 121 Theory Drive Irvine, CA 92617, U.S.A.

ISSUED BY: Advance Data Technology Corporation

LAB LOCATION: 47 14th Lin, Chiapau Tsun, Linko, Taipei,
Taiwan, R.O.C.

TEST LOCATION: No. 19, Hwa Ya 2nd Rd., Wen Hwa Tsuen,
Kwei Shan Hsiang, Taoyuan Hsien 333,
Taiwan, R.O.C.



RF Exposure Measurement (Mobile Device)

1. Introduction

In this document, we try to prove the safety of radiation harmfulness to the human body for our product. The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The Gain of the antenna used in this product is measured in a Fully Anechoic Chamber (FAC) calibrated for antenna measurement in ADT, and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis transmission formula is a far field assumption, the calculated result of that is an over-prediction for near field power density. We will take that as the worst case to specify the safety range.

2. RF Exposure Limit

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of human exposure to radio-frequency (RF) radiation as specified in 1.1307(b)

LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
(A)Limits For Occupational / Control Exposures				
300-1500	F/300	6
1500-100,000	5	6
(B)Limits For General Population / Uncontrolled Exposure				
300-1500	F/1500	6
1500-100,000	1.0	30

F = Frequency in MHz



3. Friis Formula

Friis transmission formula : $P_d = (P_{out} \cdot G) / (4 \cdot \pi \cdot r^2)$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

If we know the maximum Gain of the antenna and the total power input to the antenna, through the calculation, we will know the MPE value at distance r .

Ref. : David K. Cheng, *Field and Wave Electromagnetics*, Second Edition,
Page 640, Eq. (11-133).

4 EUT Operating condition

The software provided by Manufacturer enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

5. Classification

This modular is specified to be installed in access point or router which is connected with host through wire. So it is easy to be re-located in the place where at least 20cm far away from the body of the user. Warning statement to the user for keeping at least 20cm or more separation distance with the antenna should be included in users manual. So, this device is classified as **Mobile Device**.



6 Test Results

6.1 Antenna Gain

The maximum Gain measured in Fully Anechoic Chamber is 2dBi or 1.585(numeric) and 7dBi or 5.012(numeric).

6.2 Output Power Into Antenna & RF Exposure value at distance 20cm:

Signal Chain

802.11b DSSS modulation

Gain: 2dBi

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	35.645	0.011	1.0
6	2437	70.958	0.022	1.0
11	2462	51.523	0.016	1.0

802.11g OFDM modulation

Gain: 2dBi

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	28.510	0.009	1.0
6	2437	71.121	0.022	1.0
11	2462	39.902	0.013	1.0

Dual Chain

Gain: 2dBi

CHANNEL	CHANNEL FREQUENCY (MHz)	PEAK POWER OUTPUT (mW)		PEAK POWER OUTPUT (dBm)		TOTAL PEAK POWER (mW)	TOTAL PEAK POWER (dBm)	POWER DENSITY (mW/CM2))	LIMIT OF POWER DENSITY (mW/CM2)
		CHAIN 0	CHAIN 1	CHAIN 0	CHAIN 1				
1	2412	28.510	28.249	14.55	14.51	56.759	17.54	0.018	1.0
6	2437	50.933	50.234	17.07	17.01	101.167	20.05	0.032	1.0
11	2462	40.365	40.272	16.06	16.05	80.637	19.07	0.025	1.0