

## Declaration of Electromagnetic Field Health Compliance

To whom it may concern,

As to the product **pRRU3901 PCS+2.6G** made by Huawei Technologies Co., Ltd., we declare that it complies with the Basic restrictions/Reference levels for electric, magnetic and electromagnetic fields as specified in following standards(s):

Nr.	Standard
1	47CFR FCC Part 1 & OET Bulletin 65

The compliance is demonstrated based on the following calculation model assessment:

- The power density according to far-field model is:

$$S = \frac{P \times G_{(\theta,\phi)}}{4 \times \pi \times R^2}$$

Where:

$P$  = input power of the antenna.

$G$  = antenna gain relative to an isotropic antenna.

$\theta, \phi$  = elevation and azimuth angles.

$R$  = distance from the antenna to the point of investigation.

- For single or multiple RF sources, the calculated power density should comply with following:

$$\sum_i \frac{S_i}{S_{Limit,i}} \leq 1$$

Where:

$S_i$  = the power density when the  $f$  is  $i$ .

$S_{Limit,i}$  = the reference level requirement for power density when  $f$  is  $i$ .

- The calculation of the power density or safe distance is:

NOTE 1: The RF exposure evaluation is base on the far-field and the radiation exposure is over-estimated.

NOTE 2: The maximum output power level is taken into account as a worst case for the purpose of the calculation of power density or safe distance.

NOTE 3: The minimum antenna feed cable loss (assumed no cable loss) is taken into account as a worst case for the purpose of the calculation of power density or safe distance.

NOTE 4: The maximum antenna radiation exposure orientation and maximum antenna gain is taken into account as a worst case for the purpose of the calculation of power density or safe distance.

**BRS&EBS Band:**

RF Source	Calculation for Individual Source		
RF Source #1	$f$	=	<u>2620</u> to <u>2690</u> MHz

$S_{Limit,i}$	=	<u>10</u> W/m <sup>2</sup>
$P, G_{(\theta,\phi)}$	=	<input type="checkbox"/> $EIRP(=P \times G_{(\theta,\phi)})$ : $EIRP^{(*)} =$ _____ W (=_____ dBm, all ports)  <input checked="" type="checkbox"/> $P \times G_{(\theta,\phi)}$ : $P^{(*)} =$ <u>0.355</u> W (=25.5 dBm) (two ports, total rated power: 23dBm, tolerance: +/-2.5dB) _____ W (calculated, two ports) $G_{(\theta,\phi)} =$ <u>2.51</u> (=4 dBi) (Integrated antenna)
$\theta, \phi$	=	The worst condition is considered, i.e. the max $G$ is used.
$S_i$	=	$\frac{P \times G_{(\theta,\phi)}}{4 \times \pi R^2} =$ <u>0.0709</u> / $R^2$ W/m <sup>2</sup>
$\frac{S_i}{S_{Limit,i}}$	=	<u>0.00709</u> / $R^2$

(\*) The value is from:  
 measured max (See relevant RF report),  
 rated + declared tolerance,  
 max allowed by RF standard.  
 And, the transmission duty cycle is:  
 ignored,  
 used, that is: 100 %.

PCS Band:

RF Source	Calculation for Individual Source	
RF Source #1	$f$	= <u>1930</u> to <u>1990</u> MHz
	$S_{Limit,i}$	= <u>10</u> W/m <sup>2</sup>
	$P, G_{(\theta,\phi)}$	= <input type="checkbox"/> $EIRP(=P \times G_{(\theta,\phi)})$ : $EIRP^{(*)} =$ _____ W (=_____ dBm, all ports)  <input checked="" type="checkbox"/> $P \times G_{(\theta,\phi)}$ : $P^{(*)} =$ <u>0.355</u> W (=25.5 dBm) (two ports, total rated power: 23dBm, tolerance: +/-2.5dB) _____ W (calculated, two ports) $G_{(\theta,\phi)} =$ <u>2.51</u> (=4 dBi) (Integrated antenna)
		(*) The value is from: <input type="checkbox"/> measured max (See relevant RF report), <input checked="" type="checkbox"/> rated + declared tolerance,

		<input type="checkbox"/> max allowed by RF standard. And, the transmission duty cycle is: <input type="checkbox"/> ignored, <input checked="" type="checkbox"/> used, that is: <u>100</u> %.
	$\theta, \phi$	= The worst condition is considered, i.e. the max $G$ is used.
	$S_i$	= $\frac{P \times G_{(\theta, \phi)}}{4 \times \pi} / R^2 = \underline{0.0709} / R^2 \text{ W/m}^2$
	$\frac{S_i}{S_{Limit,i}}$	= $\underline{0.00709} / R^2$
Whole Product	Calculation for Whole Product	
Whole Product	$\sum_i \frac{S_i}{S_{Limit,i}}$	= $\underline{0.01418} / R^2 \leq 1$
	$R$	$\geq \underline{0.119} \text{ m (the minimum Safe Distance)}$
	NOTE: The result is the worst case of each individual source and simultaneous transmission sources (if applicable).	

Note: If the practical maximum antenna gain exceeds the value as described above, the safe distance must be recalculated and estimated.

Beyond the specified distance: 0.119 m

Person responsible for making this declaration:

Hu Wei

Hu Wei

RF Engineer, EMC Lab

Reliability Laboratory of Huawei Technologies Co., Ltd.

June 30, 2015