



## Declaration of Electromagnetic Field Health Compliance

To whom it may concern,

As to the product **RU3261** made by Huawei Technologies Co., Ltd., we declare that it complies with the Basic restrictions/Reference levels for electric, magnetic and electromagnetic fields as specified in following standards(s):

Nr.	Standard
1	47CFR FCC Part 1 & OET Bulletin 65

The compliance is demonstrated based on the following calculation model assessment:

1. The power density according to far-field model is:

$$S = \frac{P \times G_{(\theta,\phi)}}{4 \times \pi \times R^2}$$

Where:

$P$  = input power of the antenna.

$G$  = antenna gain relative to an isotropic antenna.

$\theta, \phi$  = elevation and azimuth angles.

$R$  = distance from the antenna to the point of investigation.

2. For single or multiple RF sources, the calculated power density should comply with following:

$$\sum_i \frac{S_i}{S_{Limit,i}} \leq 1$$

Where:

$S_i$  = the power density when the  $f$  is  $i$ .

$S_{Limit,i}$  = the reference level requirement for power density when  $f$  is  $i$ .

3. The calculation of the power density or safe distance is:

NOTE 1: The RF exposure evaluation is base on the far-field and the radiation exposure is over-estimated.

NOTE 2: The maximum output power level is taken into account as a worst case for the purpose of the calculation of power density or safe distance.

NOTE 3: The minimum antenna feed cable loss (assumed no cable loss) is taken into account as a worst case for the purpose of the calculation of power density or safe distance.

NOTE 4: The maximum antenna radiation exposure orientation and maximum antenna gain is taken into account as a worst case for the purpose of the calculation of power density or safe distance.

BRS&EBS Band:

RF Source	Calculation for Individual Source	
RF Source #1	$f$	= 2620 to 2690 MHz



	$S_{Limit,i}$	=	<u>10</u> W/m <sup>2</sup>
			<input type="checkbox"/> EIRP (= $P \times G_{(\theta,\phi)}$ ): $EIRP^{(*)}$ = _____ W (= _____ dBm, all ports)  <input checked="" type="checkbox"/> $P \times G_{(\theta,\phi)}$ : $P^{(*)}$ = <u>134.59</u> W (= <u>51.29</u> dBm) (all ports, total rated power: 50.79dBm, tolerance: +/-0.5dB) $P, G_{(\theta,\phi)}$ = _____ W (calculated, all ports) $G_{(\theta,\phi)}$ = <u>70.307</u> (= <u>18.47</u> dBi)  <sup>(*)</sup> : The value is from: <input type="checkbox"/> measured max (See relevant RF report), <input checked="" type="checkbox"/> rated + declared tolerance, <input type="checkbox"/> max allowed by RF standard. And, the transmission duty cycle is: <input type="checkbox"/> ignored, <input checked="" type="checkbox"/> used, that is: <u>100</u> %.
	$\theta, \phi$	=	The worst condition is considered, i.e. the max $G$ is used.
	$S_i$	=	$\frac{P \times G_{(\theta,\phi)}}{4 \times \pi R^2} = \underline{753.01} / R^2$ W/m <sup>2</sup>
	$\frac{S_i}{S_{Limit,i}}$	=	<u>75.3</u> / $R^2$
Whole Product	Calculation for Whole Product		
Whole Product	$\sum_i \frac{S_i}{S_{Limit,i}}$	=	<u>53.68</u> / $R^2 \leq 1$
	$R$	$\geq$	<u>8.68</u> m (the minimum Safe Distance)
	NOTE: The result is the worst case of each individual source and simultaneous transmission sources (if applicable).		

Note: If the practical maximum antenna gain exceeds the value as described above, the safe distance must be recalculated and estimated.

Beyond the specified distance: 8.68 m

Person responsible for making this declaration:

*Liang Changguan*

\_\_\_\_\_  
 Liang Changguan  
 RF Engineer, EMC Lab  
 Reliability Laboratory of Huawei Technologies Co., Ltd.  
 July 31, 2015