






TEST REPORT

<p>KCTL Inc. 65, Sinwon-ro, Yeongtong-gu, Suwon-si, Gyeonggi-do, 16677, Korea TEL: 82-31-285-0894 FAX: 82-505-299-8311 www.kctl.co.kr</p>	<p>Report No.: KR20-SRF0040-A Page (1) of (19)</p>	
<p>1. Client</p> <ul style="list-style-type: none"> ◦ Name : HYUNDAI MOBIS CO., LTD. ◦ Address : 203, Teheran-ro, Gangnam-gu, Seoul, 06141, Korea ◦ Date of Receipt : 2019-09-20 <p>2. Use of Report : Certification</p> <p>3. Name of Product and Model : WIDE AVN / ATBA0HYAN</p> <p>4. Manufacturer and Country of Origin : Hyundai Mobis Co., Ltd. / Korea</p> <p>5. FCC ID : TQ8-ATBA0HYAN</p> <p>6. Date of Test : 2019-10-16 to 2020-02-20</p> <p>7. Test Standards : FCC Part 2 FCC Part 22 subpart H FCC Part 24 subpart E</p> <p>8. Test Results : Refer to the test result in the test report</p>		
Affirmation	<p>Tested by</p>  Name : Euijung Kim (Signature)	<p>Technical Manager</p>  Name : Heesu Ahn (Signature)
2020-02-21		
<h2>KCTL Inc.</h2>		
<p>As a test result of the sample which was submitted from the client, this report does not guarantee the whole product quality. This test report should not be used and copied without a written agreement by KCTL Inc.</p>		

Report revision history

Date	Revision	Page No
2020-02-09	Initial report	-
2020-02-21	Updated	3,6,16,17,18,19

This report shall not be reproduced except in full, without the written approval of KCTL Inc. This document may be altered or revised by KCTL Inc. personnel only, and shall be noted in the revision section of the document. Any alteration of this document not carried out by KCTL Inc. will constitute fraud and shall nullify the document. This test report is a General report that does not use the KOLAS accreditation mark and is not related to KOLAS accreditation.

Note. The report No. KR20-SRF0040 is superseded by the report No. KR20-SRF0040-A.



CONTENTS

1.	General information	4
2.	Device information	4
2.1.	Information about derivative model	5
2.2.	Frequency/channel operations.....	5
3.	Maximum ERP/EIRP power.....	5
4.	Summary of tests	6
5.	Measurement uncertainty	7
6.	Test results	8
6.1.	Radiated Power (ERP/EIRP)	8
6.2.	Radiated Spurious Emissions	12
7.	Measurement equipment	19



KCTL Inc.

65, Sinwon-ro, Yeongtong-gu,
Suwon-si, Gyeonggi-do, 16677, Korea
TEL: 82-31-285-0894 FAX: 82-505-299-8311
www.kctl.co.kr

Report No.:
KR20-SRF0040-A

Page (4) of (19)



1. General information

Client : HYUNDAI MOBIS CO., LTD.
Address : 203, Teheran-ro, Gangnam-gu, Seoul, 06141, Korea
Manufacturer : Hyundai Mobis Co., Ltd.
Address : 95, Sayang 2-Gil, Munbaek-Myeon, Jincheon-Gun, Chungcheongbuk-Do
27862 Korea
Laboratory : KCTL Inc.
Address : 65, Sinwon-ro, Yeongtong-gu, Suwon-si, Gyeonggi-do, 16677, Korea
Accreditations : FCC Site Designation No: KR0040, FCC Site Registration No: 687132
VCCI Registration No. : R-20080, G-20078, C-20059, T-20056
Industry Canada Registration No. : 8035A
KOLAS No.: KT231

2. Device information

Equipment under test : WIDE AVN
Model : ATBA0HYAN
Derivative model : ATBA0HCAN, ATBA3HCAN
Frequency range : 779.5 MHz ~ 784.5 MHz (LTE Band 13)
824.7 MHz ~ 848.3 MHz (LTE Band 5)
1 710.7 MHz ~ 1 754.3 MHz (LTE Band 4)
1 850.7 MHz ~ 1 909.3 MHz (LTE Band 2)
824.7 MHz ~ 848.31 MHz (CDMA BC0)
1 851.25 MHz ~ 1 908.75 MHz (CDMA BC1)
Modulation technique : QPSK, 16-QAM (LTE)
QPSK (CDMA)
Power source : DC 14.4 V
Antenna specification : C-PAD Antenna(LTE), Shark Antenna(CDMA)
Software version : MQ4.USA.0000.V028.001.190821
Hardware version : MQ4.USA.STD_AVN_G5_WIDE.004.001
Test device serial No. : N/A
Operation temperature : -20 °C ~ 70 °C

2.1. Information about derivative model

The difference between basic model and derivative models is:

The derivative models have a different product identification number.

ATBA0HCAN(96560 P4700), ATBA3HCAN(96560 P4900)

2.2. Frequency/channel operations

This device contains the following capabilities:

LTE Band 13, LTE Band 5, LTE Band 4, LTE Band 2, CDMA 850/1900(BC0, BC1)

CDMA 850

Ch.	Frequency (MHz)
1013	824.70
384	836.52
777	848.31

Table 2.2.1. BC0

CDMA1900

Ch.	Frequency (MHz)
25	1 851.25
600	1 880.00
1175	1 908.75

Table 2.2.2. BC1

3. Maximum ERP/EIRP power**CDMA 850**

Mode	Tx frequency (MHz)	Emission designator	ERP	
			Max. power (dBm)	Max. power (W)
BC0	824.70 ~ 848.31	1M28F9W	19.32	0.086

CDMA 1900

Mode	Tx frequency (MHz)	Emission designator	EIRP	
			Max. power (dBm)	Max. power (W)
BC1	1 851.25 ~ 1 908.75	1M27F9W	21.24	0.133

4. Summary of tests

FCC Part Section(s)	Parameter	Test results
2.1046	Conducted Output Power	N/T ^(note1)
2.1049	Occupied Bandwidth & 26 dB Bandwidth	N/T ^(note1)
2.1051	Band Edge Emissions at Antenna Terminal	N/T ^(note1)
22.917(a) 24.238(a)		N/T ^(note1)
22.913(d) 24.232(d)	Peak to Average Power Ratio	N/T ^(note1)
2.1055 22.355 24.235	Frequency stability	N/T ^(note1)
2.1046 22.913(a)(5) 24.232(c)	Effective Radiated Power & Equivalent Isotropic Radiated Power	Pass
2.1053 22.917(a) 24.238(a)	Radiated Spurious Emissions	Pass

Notes: (N/T: Not Tested, N/A: Not Applicable)

1. This test item was not performed by the request of manufacturer. Please refer to original test report no. F690501/RF-RTL011908-1 issued on Nov. 09, 2017 by SGS Korea Co., Ltd. (Gunpo Laboratory)
2. All modes of operation were investigated and the worst case emissions are reported with the EUT positioning, modulations and paging service configurations in the test data.
3. The fundamental of the EUT was investigated in three orthogonal orientations X, Y and Z. It was determined that X orientation was worst-case orientation. Therefore, all final radiated testing was performed with the EUT in X orientation.
4. The test procedure(s) in this report were performed in accordance as following.
 - ◆ ANSI C63.26-2015
 - ◆ ANSI/TIA-603-E-2016
 - ◆ KDB 971168 D01 v03r01

5. Measurement uncertainty

The measurement uncertainties shown below were calculated in accordance with the requirements of ANSI C63.4-2014.

All measurement uncertainty values are shown with a coverage factor of $k=2$ to indicate a 95 % level of confidence. The measurement data shown herein meets or exceeds the U_{CISPR} measurement uncertainty values specified in CISPR 16-4-2 and thus, can be compared directly to specified limits to determine compliance.

Parameter	Expanded uncertainty(±)	
Radiated spurious emissions	9 kHz ~ 30 MHz	2.28 dB
	30 MHz ~ 1 GHz	3.68 dB
	Above 1 GHz	5.72 dB




6. Test results


6.1. Radiated Power (ERP/EIRP)

Test setup


The diagram below shows the test setup that is utilized to make the measurements for emission from 30 MHz to 1 GHz emissions.



The diagram below shows the test setup that is utilized to make the measurements for emission from 1 GHz to the tenth harmonic of the highest fundamental frequency or to 40 GHz emissions, whichever is lower.



The diagram below shows the test setup for substituted method.



Limit

According to §22.913(a)(5), the ERP of transmitters in the cellular radiotelephone service must not exceed the limits in this section. The ERP of mobile transmitters and auxiliary test transmitters must not exceed 7 watts.

According to §24.232(c) mobile and portable stations are limited to 2 watts EIRP and the equipment must employ a means for limiting power to the minimum necessary for successful communications.

Test procedure

971168 D01 v03r01 - Section 5.2.2

ANSI 63.26-2015 – Section 5.2.4.4.1

ANSI/TIA-603-E-2016 - Section 2.2.17

Test settings

- 1) RBW = 1 % to 5 % of the OBW.
- 2) VBW $\geq 3 \times$ RBW.
- 3) SPAN = 2 \times to 3 \times the OBW.
- 4) Number of measurement points in sweep $\geq 2 \times$ span / RBW.
- 5) Sweep time :
 - 1) Auto couple, or
 - 2) $\geq [10 \times (\text{number of points in sweep}) \times (\text{transmission period})]$ for single sweep (automation-compatible) measurement. Transmission period is the on and off time of the transmitter.
- 6) Detector = RMS
- 7) If the EUT can be configured to transmit continuously, then set the trigger to free run.
- 8) If the EUT cannot be configured to transmit continuously, then use a sweep trigger with the level set to enable triggering only on full power bursts and configure the EUT to transmit at full power for the entire duration of each sweep. Verify that the sweep time is less than or equal to the transmission burst duration. Time gating can also be used under similar constraints (i.e., configured such that measurement data is collected only during active full-power transmissions).
- 9) Trace mode = trace averaging (RMS) over 100 sweeps.
- 10) Compute the power by integrating the spectrum across the OBW of the signal using the instrument's band or channel power measurement function, with the band/channel limits set equal to the OBW band edges. If the instrument does not have a band or channel power function, then sum the spectrum levels (in linear power units) at intervals equal to the RBW extending across the entire OBW of the spectrum.
- 11) Allow trace to fully stabilize.

Notes:

1. On a test site, the EUT shall be placed at 80 cm height on a turn table, and in the position close To normal use as declared by the applicant.
2. The test antenna shall be oriented initially for vertical polarization located 3 m from EUT to Correspond to the fundamental frequency of the transmitter.
3. The turntable is rotated through 360°, and the receiving antenna scans in order to determine the Level of the maximized emission.
4. The test antenna shall be raised and lowered again through the specified range of height until the maximum signal level is detected by the measuring receiver.
5. The maximum signal level detected by the measuring receiver shall be noted.
6. The EUT was replaced by half-wave dipole (1 GHz below) or horn antenna (1 GHz above) connected to a signal generator.
The power is calculated by the following formula;
$$Pd(\text{dBm}) = Pg(\text{dBm}) - \text{Cable loss (dB)} + \text{Antenna gain (dB)}$$
Note. Pd is the dipole equivalent power and Pg is the generator output power into the substitution antenna.
7. The test antenna shall be raised and lowered through the specified range of height to ensure that The maximum signal is received.
8. The input signal to the substitution antenna shall be adjusted to the level that produces a level Detected by the measuring corrected for the change of input attenuator setting of the measuring Receiver.
9. The input level to the substitution antenna shall be recorded as power level in dBm, corrected for Any change of input attenuator setting of the measuring receiver.
10. The measurement shall be repeated with the test antenna and the substitution antenna Orientated for horizontal polarization.

KCTL Inc.

65, Sinwon-ro, Yeongtong-gu,
Suwon-si, Gyeonggi-do, 16677, Korea
TEL: 82-31-285-0894 FAX: 82-505-299-8311
www.kctl.co.kr

Report No.:
KR20-SRF0040-A

Page (11) of (19)

**Test results****CDMA 850**

Mode	Channel	Frequency	Pol.	Antenna Gain	C.L	Substitute Level	ERP	
		[MHz]	[V/H]	[dBi]	[dB]	[dBm]	[dBm]	[W]
BC0	1013	824.70	H	-0.60	3.69	23.30	19.01	0.080
	384	836.52	H	-0.50	3.72	23.54	19.32	0.086
	777	848.31	H	-0.50	3.74	22.62	18.38	0.069

CDMA 1900

Mode	Channel	Frequency	Pol.	Antenna Gain	C.L	Substitute Level	ERP	
		[MHz]	[V/H]	[dBi]	[dB]	[dBm]	[dBm]	[W]
BC1	25	1 851.25	V	6.18	5.74	17.21	17.65	0.058
	600	1 880.00	V	6.14	5.78	19.53	19.89	0.097
	1175	1 908.75	V	6.11	5.81	20.94	21.24	0.133

Note.


1. E.R.P & E.I.R.P(dBm) = Substitute Level(dB) + Antenna gain(dBi) - C.L(Cable loss) (dB)




6.2. Radiated Spurious Emissions

Test setup


The diagram below shows the test setup that is utilized to make the measurements for emission from 30 MHz to 1 GHz emissions.



The diagram below shows the test setup that is utilized to make the measurements for emission from 1 GHz to the tenth harmonic of the highest fundamental frequency or to 40 GHz emissions, whichever is lower.



The diagram below shows the test setup for substituted method.



KCTL Inc.

65, Sinwon-ro, Yeongtong-gu,
Suwon-si, Gyeonggi-do, 16677, Korea
TEL: 82-31-285-0894 FAX: 82-505-299-8311
www.kctl.co.kr

Report No.:
KR20-SRF0040-A

Page (13) of (19)



Limit

According to §22.917(a), §24.238(a) the power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10\log(P_{\text{Watts}})$ dB.

Test procedure

971168 D01 v03r01 - Section 5.8

ANSI 63.26-2015 – Section 5.5

ANSI/TIA-603-E-2016 - Section 2.2.12

Test settings

- 1) RBW = 1 kHz for below 1 GHz and 1 MHz for above 1 GHz.
- 2) VBW $\geq 3 \times$ RBW.
- 3) Detector = RMS
- 4) Trace mode = Max hold
- 5) Sweep time = Auto couple
- 6) Number of sweep points $\geq 2 \times$ span / RBW
- 7) Allow trace to fully stabilize.

Notes:

1. On a test site, the EUT shall be placed at 80 cm height on a turn table, and in the position close To normal use as declared by the applicant.
2. The test antenna shall be oriented initially for vertical polarization located 3 m from EUT to Correspond to the fundamental frequency of the transmitter.
3. The turntable is rotated through 360° , and the receiving antenna scans in order to determine the Level of the maximized emission.
4. The test antenna shall be raised and lowered again through the specified range of height until the maximum signal level is detected by the measuring receiver.
5. The maximum signal level detected by the measuring receiver shall be noted.
6. The EUT was replaced by half-wave dipole (1 GHz below) or horn antenna (1 GHz above) connected to a signal generator.
7. The test antenna shall be raised and lowered through the specified range of height to ensure that The maximum signal is received.
8. The input signal to the substitution antenna shall be adjusted to the level that produces a level Detected by the measuring corrected for the change of input attenuator setting of the measuring Receiver.
9. The input level to the substitution antenna shall be recorded as power level in dBm, corrected for Any change of input attenuator setting of the measuring receiver.
10. The measurement shall be repeated with the test antenna and the substitution antenna Orientated for horizontal polarization.

KCTL Inc.

65, Sinwon-ro, Yeongtong-gu,
Suwon-si, Gyeonggi-do, 16677, Korea
TEL: 82-31-285-0894 FAX: 82-505-299-8311
www.kctl.co.kr

Report No.:
KR20-SRF0040-A

Page (14) of (19)

**Test results (Above 1 000 MHz)**

Test mode : CDMA 850

Frequency(MHz) : 824.70

Channel : 1013

Mode	Frequency	Pol.	Antenna Gain	Cable loss	Substitute Level	Level	Limit	Margin
	[MHz]	[V/H]	[dBi]	[dB]	[dBm]	[dBm]	[dBm]	[dB]
BC0	1 649.04	V	6.42	5.36	-50.06	-49.00	-13.00	36.00
	2 384.59	V	6.00	6.51	-50.29	-50.80	-13.00	37.80
	2 473.59	V	6.00	6.63	-48.37	-49.00	-13.00	36.00
	3 300.64	V	7.36	7.66	-58.50	-58.80	-13.00	45.80
	3 396.15	V	7.57	7.78	-54.39	-54.60	-13.00	41.60

Test mode : CDMA 850

Frequency(MHz) : 836.50

Channel : 384

Mode	Frequency	Pol.	Antenna Gain	Cable loss	Substitute Level	Level	Limit	Margin
	[MHz]	[V/H]	[dBi]	[dB]	[dBm]	[dBm]	[dBm]	[dB]
BC0	1 672.54	V	6.39	5.40	-51.69	-50.70	-13.00	37.70
	2 385.09	V	6.00	6.51	-51.19	-51.70	-13.00	38.70
	2 510.09	V	6.01	6.67	-47.84	-48.50	-13.00	35.50
	3 347.15	V	7.46	7.72	-58.54	-58.80	-13.00	45.80
	3 406.65	V	7.59	7.79	-53.90	-54.10	-13.00	41.10

Test mode : CDMA 850

Frequency(MHz) : 848.31

Channel : 777

Mode	Frequency	Pol.	Antenna Gain	Cable loss	Substitute Level	Level	Limit	Margin
	[MHz]	[V/H]	[dBi]	[dB]	[dBm]	[dBm]	[dBm]	[dB]
BC0	1 697.54	V	6.36	5.45	-52.21	-51.30	-13.00	38.30
	2 385.09	V	6.00	6.51	-49.09	-49.60	-13.00	36.60
	2 544.60	V	6.06	6.73	-50.23	-50.90	-13.00	37.90
	3 393.65	H	7.57	7.78	-59.09	-59.30	-13.00	46.30
	3 401.65	V	7.58	7.79	-52.79	-53.00	-13.00	40.00

Note.

1. Limit Calculation(dBm)= 43 + 10log(P[Watts])

This test report shall not be reproduced, except in full, without the written approval

KCTL-TIR001-003/2

KCTL Inc.

65, Sinwon-ro, Yeongtong-gu,
Suwon-si, Gyeonggi-do, 16677, Korea
TEL: 82-31-285-0894 FAX: 82-505-299-8311
www.kctl.co.kr

Report No.:
KR20-SRF0040-A

Page (15) of (19)



Test mode : CDMA 1900

Frequency(MHz) : 1 851.25

Channel : 25

Mode	Frequency	Pol.	Antenna Gain	Cable loss	Substitute Level	Level	Limit	Margin
	[MHz]	[V/H]	[dBi]	[dB]	[dBm]	[dBm]	[dBm]	[dB]
BC1	3 702.50	V	8.12	8.15	-31.67	-31.70	-13.00	18.70
	5 554.50	V	10.60	10.05	-45.65	-45.10	-13.00	32.10
	7 406.50	V	11.83	11.63	-54.00	-53.80	-13.00	40.80
	9 258.00	H	12.95	13.13	-53.02	-53.20	-13.00	40.20

Test mode : CDMA 1900

Frequency(MHz) : 1 880.00

Channel : 600

Mode	Frequency	Pol.	Antenna Gain	Cable loss	Substitute Level	Level	Limit	Margin
	[MHz]	[V/H]	[dBi]	[dB]	[dBm]	[dBm]	[dBm]	[dB]
BC1	3 759.50	V	8.22	8.24	-29.08	-29.10	-13.00	16.10
	5 639.50	V	10.60	10.18	-48.22	-47.80	-13.00	34.80
	7 521.00	V	12.02	11.83	-52.99	-52.80	-13.00	39.80
	9 400.50	H	13.04	13.31	-53.13	-53.40	-13.00	40.40

Test mode : CDMA 1900

Frequency(MHz) : 1 908.75

Channel : 1175

Mode	Frequency	Pol.	Antenna Gain	Cable loss	Substitute Level	Level	Limit	Margin
	[MHz]	[V/H]	[dBi]	[dB]	[dBm]	[dBm]	[dBm]	[dB]
BC1	3 818.00	V	8.31	8.21	-38.50	-38.40	-13.00	25.40
	5 726.50	V	10.60	10.45	-43.75	-43.60	-13.00	30.60
	7 633.50	H	12.13	11.92	-49.01	-48.80	-13.00	35.80
	9 544.00	V	13.06	13.31	-54.45	-54.70	-13.00	41.70

Note.

1. Limit Calculation(dBm)= 43 + 10log(P[Watts])

KCTL Inc.

65, Sinwon-ro, Yeongtong-gu,
Suwon-si, Gyeonggi-do, 16677, Korea
TEL: 82-31-285-0894 FAX: 82-505-299-8311
www.kctl.co.kr

Report No.:
KR20-SRF0040-A

Page (16) of (19)



Test mode : Simultaneously
CDMA 1900
+ 2.4G WIFI 802.11g
Frequency(MHz) : 1 851.25 + 2 412
Channel : 25, 1

Mode	Frequency	Pol.	Antenna Gain	Cable loss	Substitute Level	Level	Limit	Margin
	[MHz]	[V/H]	[dBi]	[dB]	[dBm]	[dBm]	[dBm]	[dB]
QPSK + OFDM	1 293.57	V	4.62	4.76	-18.76	-18.90	-13.00	5.90
	2 975.49	V	6.67	7.27	-29.50	-30.10	-13.00	17.10
	3 706.00	V	8.13	8.16	-33.77	-33.80	-13.00	20.80
	4 883.00	V	9.71	9.44	-56.67	-56.40	-13.00	43.40
	5 559.50	V	10.60	10.05	-42.55	-42.00	-13.00	29.00
	7 323.00	V	11.68	11.56	-55.12	-55.00	-13.00	42.00

Test mode : Simultaneously
CDMA 1900
+ 5G WIFI 802.11a
Frequency(MHz) : 1 851.25 + 5 320
Channel : 25, 64

Mode	Frequency	Pol.	Antenna Gain	Cable loss	Substitute Level	Level	Limit	Margin
	[MHz]	[V/H]	[dBi]	[dB]	[dBm]	[dBm]	[dBm]	[dB]
QPSK + OFDM	1 612.06	V	6.47	5.29	-18.97	-17.80	-13.00	4.80
	2 088.60	V	6.00	6.07	-19.93	-20.00	-13.00	7.00
	3 707.00	V	8.13	8.16	-32.57	-32.60	-13.00	19.60
	5 559.00	V	10.60	10.05	-42.65	-42.10	-13.00	29.10
	10 640.00	V	12.90	14.19	-51.51	-52.80	-13.00	39.80
	15 960.36	H	13.36	17.44	-45.51	-49.60	-13.00	36.60

Note.

1. Limit Calculation(dBm)= 43 + 10log(P[Watts])

KCTL Inc.

65, Sinwon-ro, Yeongtong-gu,
Suwon-si, Gyeonggi-do, 16677, Korea
TEL: 82-31-285-0894 FAX: 82-505-299-8311
www.kctl.co.kr

Report No.:
KR20-SRF0040-A

Page (17) of (19)



Test mode : Simultaneously
CDMA 1900 + BT
Frequency(MHz) : 1 851.25 + 2 480
Channel : 25, 78

Mode	Frequency [MHz]	Pol. [V/H]	Antenna Gain [dBi]	Cable loss [dB]	Substitute Level [dBm]	Level [dBm]	Limit [dBm]	Margin [dB]
QPSK + GFSK	1 223.06	V	3.94	4.63	-16.51	-17.20	-13.00	4.20
	3 707.00	V	8.13	8.16	-32.47	-32.50	-13.00	19.50
	4 960.50	H	9.84	9.48	-56.66	-56.30	-13.00	43.30
	5 554.00	V	10.60	10.05	-43.45	-42.90	-13.00	29.90
	7 441.00	H	11.89	11.66	-54.24	-54.00	-13.00	41.00

Test mode : Simultaneously
CDMA 1900 + BT
+ 2.4G WIFI 802.11g
Frequency(MHz) : 1 851.25 + 2 480
+ 2 412
Channel : 25, 78, 1

Mode	Frequency [MHz]	Pol. [V/H]	Antenna Gain [dBi]	Cable loss [dB]	Substitute Level [dBm]	Level [dBm]	Limit [dBm]	Margin [dB]
QPSK + GFSK + OFDM	1 226.56	V	3.97	4.64	-15.94	-16.60	-13.00	3.60
	1 296.07	V	4.64	4.76	-19.48	-19.60	-13.00	6.60
	2 974.99	H	6.66	7.27	-31.60	-32.20	-13.00	19.20
	3 703.00	V	8.12	8.15	-34.77	-34.80	-13.00	21.80
	4 882.00	V	9.71	9.44	-56.77	-56.50	-13.00	43.50
	4 959.50	H	9.84	9.48	-57.86	-57.50	-13.00	44.50
	5 555.00	V	10.60	10.05	-42.35	-41.80	-13.00	28.80
	7 323.50	V	11.68	11.56	-53.72	-53.60	-13.00	40.60
	7 440.00	V	11.89	11.66	-55.44	-55.20	-13.00	42.20

Note.

1. Limit Calculation(dBm)= 43 + 10log(P[Watts])

KCTL Inc.

65, Sinwon-ro, Yeongtong-gu,
Suwon-si, Gyeonggi-do, 16677, Korea
TEL: 82-31-285-0894 FAX: 82-505-299-8311
www.kctl.co.kr

Report No.:
KR20-SRF0040-A

Page (18) of (19)

KCTL

Test mode : Simultaneously
CDMA 1900 + BT
+ 5G WIFI 802.11a
Frequency(MHz) : 1 880.0 + 2 480
+ 5 320
Channel : 25, 78, 64

Mode	Frequency	Pol.	Antenna Gain	Cable loss	Substitute Level	Level	Limit	Margin
	[MHz]	[V/H]	[dBi]	[dB]	[dBm]	[dBm]	[dBm]	[dB]
QPSK + GFSK + OFDM	1 618.06	V	6.46	5.30	-18.25	-17.10	-13.00	4.10
	2 089.60	V	6.00	6.07	-20.33	-20.40	-13.00	7.40
	3 707.00	V	8.13	8.16	-31.87	-31.90	-13.00	18.90
	4 960.50	V	9.84	9.48	-55.46	-55.10	-13.00	42.10
	5 553.50	V	10.60	10.05	-41.05	-40.50	-13.00	27.50
	10 640.46	V	12.90	14.19	-51.61	-52.90	-13.00	39.90
	15 961.74	V	13.35	17.44	-46.41	-50.50	-13.00	37.50

Note.

1. Limit Calculation(dBm)= 43 + 10log(P[Watts])

KCTL

KCTL Inc.

65, Sinwon-ro, Yeongtong-gu,
Suwon-si, Gyeonggi-do, 16677, Korea
TEL: 82-31-285-0894 FAX: 82-505-299-8311
www.kctl.co.kr

Report No.:
KR20-SRF0040-A

Page (19) of (19)



7. Measurement equipment

Equipment Name	Manufacturer	Model No.	Serial No.	Cal. Date	Next Cal. Date
Biconical VHF-UHF Broadband Antenna	SCHWARZBECK	VUBA9117	275	19.04.13	20.04.13
Bilog Antenna	Teseq GmbH	CBL 6143A	35039	19.05.21	21.05.21
Horn Antenna	ETS.lindgren	3117	00161083	19.09.18	20.09.18
Horn Antenna	ETS.lindgren	3117	161225	19.05.22	20.05.22
Horn Antenna	Steatite Antennas	QMS-00225	17790	19.08.12	20.08.12
Horn Antenna	ETS.lindgren	3116	00086635	19.05.09	20.05.09
High pass Filter	Wainwright Instruments GmbH	WHKX3.0/18G-12SS	44	20.01.21	21.01.21
High pass Filter	Wainwright Instruments GmbH	WHKX1.0/1.5S-10SS	14	20.01.21	21.01.21
Attenuator	Weinschel ENGINEERING	10	AJ1239	19.05.14	20.05.14
Attenuator	API Inmet	40AH2W-10	12	19.05.15	20.05.15
Amplifier	SONOMA INSTRUMENT	310N	185799	20.01.21	21.01.21
Amplifier	L-3 Narda-MITEQ	AMF-7D-01001800-22-10P	2031196	20.02.12	21.02.12
Amplifier	L-3 Narda-MITEQ	JS44-18004000-33-8P	2000997	19.08.01	20.08.01
Spectrum Analyzer	AGILENT	N9040B	MY57010132	19.07.31	20.07.31
Signal Generator	R&S	SMB100A	176206	20.01.21	21.01.21
Wideband Radio Communication Tester	R & S	CMW500	141780	19.04.18	20.04.18
Antenna Mast	MATURO	EAS 1.5	042/8941211	N/A	N/A
Antenna Mast	MATURO	EAS 1.5	043/8941211	N/A	N/A
Turn Table	MATURO	TT 0.8 PF	041/8941211	N/A	N/A
Cable Assembly	Radiall	R286303620	1649.241	N/A	N/A
Cable Assembly	Radiall	TESTPRO 3	-	N/A	N/A

End of test report