

**Cover page:**

Medallion I™  
Bluetooth® Speakerphone  
User manual

Omni Laboratories, Inc.  
City of Industry, CA 91746  
[www.medallionspeakerphones.com](http://www.medallionspeakerphones.com)  
Copyrights 2007 – 2008, All rights reserved

**Page-1**

**General Information:** The following functions may vary if you are pairing the Medallion I with different equipment. Please read the user manual of your pairing equipment carefully before use.

- A. Multifunction Button.
- B. Switch Button.
- C. Vol.+
- D. Vol.-
- E. LED indicator
- F. Charging USB
- G. Microphone
- H. Speaker
- I. Clip

The use of wireless devices and their accessories may be prohibited or restricted by law in certain areas. Always obey the local laws and regulations on the use of these products.

Bluetooth® is the registered trademark of Bluetooth SIG, Inc.

**Page-2**

Medallion I™ User Manual  
Bluetooth® Speakerphone

**Note:** different environment, networks, and mobile phones may have different performance. We recommend this product to use either Verizon, Sprint, or T-Mobile mobile phone network. AT&T mobile phone network users are generally not recommended in this version of Medallion speakerphone.

**Page-3**

**Specification:**

Dimension: 75mm x 35mm x 18mm(with the clip)

Weight: 35g

Powered by Li-ion battery 350mAH

Charging duration: 2 hours, by mini USB-A

Standby duration: 150hours

Talking duration: 4 hours

Speaker driver: 1W/8Ohm

Microphone: -42dB Omni

#### Bluetooth Technical Parameters

Bluetooth Version: Bluetooth V1.2

Bluetooth Output Power: Class 2

Transmit distance: 10m

Frequency Range: 2402-2480MHz

#### Page-4

##### Important Safety Instruction

- Please ensure the unit is power off before placing it in your pocket to avoid unintentional dialing.
- Keep the unit away from water or moisture.
- Do not clean the unit with caustic liquid.
- Keep the unit from fire or heat to avoid explosion.
- Avoid leaving the unit inside a car during summer; exposing the unit at high temperature over 155 °F (or 75°C) will void the warranty.
- Do not disassemble the unit. For repairing, return your unit to our Service Center. Unauthorized disassembly will void warranty.
- If the unit is not to be used for an extended period of time, please keep it in ventilated and dry place.

##### Declaration in Law

This unit is BQB, CE, FCC, and RoHS compliant only. Please refer to local law and regulation for compliance.

#### Installation

There is a clip on the back of the unit that can be attached to your collar, shirt/blouse pocket, or belt.

#### Page-5

#### Operation

### First use and charging instruction

1. The unit is assembled with a built-in battery.
2. Please charge the unit fully before first use.
3. The red LED will light for 3-4 hours when charging. The LED goes off when fully charged.

If the unit is not used for an extended period of time, the built-in battery power will deplete. To charge again, the LED will take several minutes to light up when charging once the battery power has been depleted.

### Low Battery Power

When the battery power is too low, the red LED will flicker when used. There will also be a short beeping sound. Charge unit as soon as possible.

### Charger

Please use the attached charger with a DC 5V 500mA, standard USB cable to charge the unit.

## Page-6

### Power ON/OFF

- Ensure that the unit is fully charged.
- To power up the unit, press and hold the multifunction button for 3 seconds, wait for the beeping sound, and the blue LED will light up showing the unit is powered up.
- On standby mode, press and hold the multifunction button for 3 seconds wait for the long beeping sound, and the red LED will light up. Then the unit will power off.

### Initial pairing

- Make sure the unit is off, then, press and keep holding the multifunction button for 8 seconds and hear the second beep, the LED light will flash RED and BLUE alternatively, the Medallion I is in paring mode.
- Turn on the Bluetooth® function of the pairing device and search for the Medallion speakerphone. When your device displays "Medallion I", input the passcode "0000". Once pairing is successful, you will hear a long beep, and the blue LED will flash slowly.
- If the pairing fails, the unit will power off automatically in 2 minutes. Repeat "Initial pairing" steps as needed.

## Page-7

### Auto-Reconnection

-When the Medallion I is turn on again, it will automatically re-connect to the last cellular phone it was paired with prior to turning off Medallion I.

To pair with your cellular phone again, just power up the Medallion speakerphone, by holding the multifunction button for 3 seconds. Please refer to Power ON/OFF section above.

Answer a call

-Press the multifunction button to answer calls.

Volume control -

-Press "VOL+" or "VOL-" to adjust the volume during talking.

Ending a call

-Press the multifunction button one time to end a call during talking.

Redialing the last dialed number

-Press the multifunction button two times quickly to redial the last dialed number.

**Page-8**

Note: The operation of this step may vary from mobile phones to mobile phones. For example; some Samsung mobile phones, user may press the multifunction button twice quickly to redial the last dialed number. Please refer to your mobile phone user manual.

Turn speaker phone function on/off

Press and hold the Switch button for 1 second. The "talk" function will switch to the mobile phone. Press and hold the Switch button for 1 second again to recover the hands free "talk" function.

**Page-9**

Function of making calls

<u>Functions</u>	<u>Actions</u>
Answer a call	Tap the multifunction button
End a call	Tap the multifunction button
Reject a call	Tap the multifunction button twice
	When a call comes in
Redial last call	Press the multifunction button twice
	Fast

## Indicator lights

<u>Light</u>	<u>Status</u>
Steady Red	Charging
No light	Charging complete
Light off	Power off
Red and Blue	Pairing mode
Quick Red	Battery low
Quick Blue	Pairing successful
Slow Blue	Call connected
Rapid Blue	Incoming call

## Page-10

### Warranty

Omni warrants this product to be free from defects in materials and workmanship for 1 year from the date of purchase. If your Omni product is found to be defective within that time, we will promptly repair or replace it. This warranty does not cover accidental damage, wear and tear, or consequential or incidental loss. Under no conditions is Omni liable for loss of or damage to a mobile phone, even if Omni has been informed of their possibility. This warranty does not affect your statutory rights.

[www.medallionspeakerphones.com](http://www.medallionspeakerphones.com)

## Page-11

### Production Registration

First Name: \_\_\_\_\_ Last Name: \_\_\_\_\_

Address: \_\_\_\_\_

City: \_\_\_\_\_ State: \_\_\_\_\_ Zip: \_\_\_\_\_

Email: \_\_\_\_\_ Telephone #: \_\_\_\_\_

Date of Purchase: \_\_\_\_\_ Purchased from: \_\_\_\_\_

Product serial number: \_\_\_\_\_  
(Located on the back of the unit)

**Warning:**

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications to this unit not expressly approved by the party responsible for compliance will void the user's authority to operate the equipment. Any change to the equipment will void FCC grant.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

--Reorient or relocate the receiving antenna.

--Increase the separation between the equipment and receiver.

--Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

--Consult the dealer or an experienced radio/TV technician for help.

The equipment complies with FCC radiation exposure limit set forth for uncontrolled Environment