

# FCC Radio Test Report

## FCC ID: XMR2023RM520NGLM

**Report No.** : BTL-FCCP-18-2311T076  
**Equipment** : 5G Sub-6 GHz M.2 Module  
**Model Name** : RM520N-GL  
**Brand Name** : Quectel  
**Applicant** : Quectel Wireless Solutions Co., Ltd.  
**Address** : Building 5, Shanghai Business Park Phase III (Area B), No.1016 Tianlin Road, Minhang District, Shanghai, China 200233

**Radio Function** : NR Band n26

**FCC Rule Part(s)** : FCC CFR Title 47, Part 90, Subpart S

**Date of Receipt** : 2023/11/16  
**Date of Test** : 2023/11/27 ~ 2024/1/12  
**Issued Date** : 2024/3/19


The above equipment has been tested and found in compliance with the requirement of the above standards by BTL Inc.

**Prepared by**

:   
Jerry Chuang, Supervisor



**Approved by**

:   
Peter Chen, Manager

### **BTL Inc.**

No.18, Ln. 171, Sec. 2, Jiuzong Rd., Neihu Dist., Taipei City 114, Taiwan

Tel: +886-2-2657-3299 Fax: +886-2-2657-3331 Web: [www.newbtl.com](http://www.newbtl.com) Service mail: [btl\\_qa@newbtl.com](mailto:btl_qa@newbtl.com)

**Declaration**

**BTL** represents to the client that testing is done in accordance with standard procedures as applicable and that test instruments used has been calibrated with standards traceable to international standard(s) and/or national standard(s).

**BTL**'s reports apply only to the specific samples tested under conditions. It is manufacture's responsibility to ensure that additional production units of this model are manufactured with the identical electrical and mechanical components. **BTL** shall have no liability for any declarations, inferences or generalizations drawn by the client or others from **BTL** issued reports.

This report is the confidential property of the client. As a mutual protection to the clients, the public and ourselves, the test report shall not be reproduced, except in full, without our written approval.

**BTL**'s laboratory quality assurance procedures are in compliance with the **ISO/IEC 17025** requirements, and accredited by the conformity assessment authorities listed in this test report.

**BTL** is not responsible for the sampling stage, so the results only apply to the sample as received.

The information, data and test plan are provided by manufacturer which may affect the validity of results, so it is manufacturer's responsibility to ensure that the apparatus meets the essential requirements of applied standards and in all the possible configurations as representative of its intended use.

**Limitation**

For the use of the authority's logo is limited unless the Test Standard(s)/Scope(s)/Item(s) mentioned in this test report is (are) included in the conformity assessment authorities acceptance respective.

Please note that the measurement uncertainty is provided for informational purpose only and are not use in determining the Pass/Fail results.

**CONTENTS**

1	SUMMARY OF TEST RESULTS	5
1.1	REFERENCE TEST GUIDANCE	6
1.2	TEST FACILITY	6
1.3	MEASUREMENT UNCERTAINTY	6
1.4	TEST ENVIRONMENT CONDITIONS	6
2	GENERAL INFORMATION	7
2.1	DESCRIPTION OF EUT	7
2.2	TEST MODES	8
2.3	BLOCK DIAGRAM SHOWING THE CONFIGURATION OF SYSTEM TESTED	9
2.4	SUPPORT UNITS	9
3	EFFECTIVE RADIATED POWER MEASUREMENT	10
3.1	LIMIT	10
3.2	TEST PROCEDURE	10
3.3	DEVIATION FROM TEST STANDARD	10
3.4	TEST SETUP	10
3.5	EUT OPERATING CONDITIONS	10
3.6	TEST RESULT	10
4	RADIATED SPURIOUS EMISSIONS MEASUREMENT	11
4.1	LIMIT	11
4.2	TEST PROCEDURE	11
4.3	DEVIATION FROM TEST STANDARD	11
4.4	TEST SETUP	12
4.5	EUT OPERATING CONDITIONS	12
4.6	TEST RESULT	12
5	LIST OF MEASURING EQUIPMENTS	13
6	EUT TEST PHOTO	14
7	EUT PHOTOS	14
APPENDIX A	EFFECTIVE RADIATED POWER	15
APPENDIX B	RADIATED SPURIOUS EMISSIONS	18

**REVISION HISTORY**

Report No.	Version	Description	Issued Date	Note
BTL-FCCP-18-2311T076	R00	Original Report.	2024/1/31	Invalid
BTL-FCCP-18-2311T076	R01	Revised Typo.	2024/3/19	Valid

## 1 SUMMARY OF TEST RESULTS

Test procedures according to the technical standards.

Standard(s) Section	Description	Test Result	Judgement	Remark
2.1046 90.635 (b)	Effective Radiated Power	APPENDIX A	Pass	-----
2.1053 90.691	Radiated Spurious Emissions	APPENDIX B	Pass	-----

NOTE:

- (1) "N/A" denotes test is not applicable in this Test Report.
- (2) The report format version is TP.1.1.1.
- (3) This test report is issued for the RF module (FCCID: XMR2023RM520NGLM) to be incorporated to the host device (Model number: TP00160A), Product name: Notebook Computer.  
Since the RF module has been certificated, after evaluation, above test items were criticized and reconfirmed in this report.
- (4) After spot check, this revision does not change original radio parameters.

## 1.1 REFERENCE TEST GUIDANCE

ANSI C63.26-2015

ANSI/TIA-603-E-2016

FCC KDB 971168 D01 Power Meas License Digital Systems v03r01

## 1.2 TEST FACILITY

The test locations stated below are under the TAF Accreditation Number 0659.

The test location(s) used to collect the test data in this report are:

No. 68-1, Ln. 169, Sec. 2, Datong Rd., Xizhi Dist., New Taipei City 221, Taiwan  
(FCC DN: TW0659)

C05       SR10       SR11

No. 72, Ln. 169, Sec. 2, Datong Rd., Xizhi Dist., New Taipei City 221, Taiwan  
(FCC DN: TW0659)

C06       CB21       CB22

## 1.3 MEASUREMENT UNCERTAINTY

The reported uncertainty of measurement  $y \pm U$ , where expanded uncertainty  $U$  is based on a standard uncertainty multiplied by a coverage factor of  $k = 2$ , providing a level of confidence of approximately 95 %.

The measurement instrumentation uncertainty considerations contained in CISPR 16-4-2. The BTL measurement uncertainty is less than the CISPR 16-4-2  $U_{cisp}$  requirement.

A. Radiated emissions test :

Test Site	Measurement Frequency Range	$U_{cisp}$ (dB)
CB21	0.03 GHz ~ 0.2 GHz	4.17
	0.2 GHz ~ 1 GHz	4.72
	1 GHz ~ 6 GHz	5.21
	6 GHz ~ 18 GHz	5.51
	18 GHz ~ 26 GHz	3.69
	26 GHz ~ 40 GHz	4.23

NOTE:

Unless specifically mentioned, the uncertainty of measurement has not been taken into account to declare the compliance or non-compliance to the specification.

## 1.4 TEST ENVIRONMENT CONDITIONS

Test Item	Environment Condition	Test Voltage	Tested by
Effective Radiated Power	22.5 °C, 51 %	AC 120V	Cora Lin
Radiated Spurious Emissions	Refer to data	AC 120V	Kevin Zhen

## 2 GENERAL INFORMATION

### 2.1 DESCRIPTION OF EUT

Equipment	5G Sub-6 GHz M.2 Module			
Model Name	RM520N-GL			
Brand Name	Quectel			
Model Difference	N/A			
Power Source	Supplied from host system.			
Power Rating	3.3 Vdc			
Host device information				
Equipment	Notebook Computer			
Model Name	TP00160A			
Brand Name	Lenovo			
Model Difference	N/A			
Power Source	DC voltage supplied from External Power Supply. (Lenovo/ ADLX65YSDC2A)			
Power Rating	I/P: 100-240V~ 1.8A 50-60Hz O/P: 20.0VDC 3.25A 65.0W / 15.0VDC 3.0A / 9.0VDC 3.0A / 5.0VDC 3.0A 15.0W			
WIFI+BT Module	Intel® Wi-Fi 6E AX211 / AX211D2W Intel® BE200D2W / BE200D2W			
WWAN Module	Quectel / RM520N-GL Quectel / EM061K-GL			
NFC Module	FOXCONN / T77H747			
Operation Frequency	Band	UL Frequency (MHz)	DL Frequency (MHz)	
	NR n26	814 ~ 824	859 ~ 869	
Maximum ERP	Band	BW (MHz)	Mode	Power (W)
	NR n26	5	PI/2 BPSK	0.073
			QPSK	0.076
			16QAM	0.062
			64QAM	0.044
			256QAM	0.026
	NR n26	10	PI/2 BPSK	0.066
			QPSK	0.066
			16QAM	0.060
			64QAM	0.043
			256QAM	0.026
Test Model	RM520N-GL			
Sample Status	Engineering Sample			
EUT Modification(s)	N/A			

#### NOTE:

(1) The above EUT information is declared by manufacturer and for more detailed features description, please refers to the manufacturer's specifications or user's manual.

(2) Table for Filed Antenna:

Antenna	Manufacture	Parts Number	Type	Connector	Gain (dBi)	Note
Main	Luxshare-ICT	DC330022C00	PIFA	I-PEX	-2.97	NR Band n26
MIMO1	Luxshare-ICT	DC330022C00	PIFA	I-PEX	-	RX only

Antenna	Manufacture	Parts Number	Type	Connector	Gain (dBi)	Note
Main	SPEEDWIRE	DC330022J10	PIFA	I-PEX	-2.97	NR Band n26
MIMO1	SPEEDWIRE	DC330022J10	PIFA	I-PEX	-	RX only

(3) The above Antenna information are derived from the antenna data sheet provided by manufacturer and for more detailed features description, please refer to the manufacturer's specifications, the laboratory shall not be held responsible.

## 2.2 TEST MODES


Test Items	Band	Test Mode	Note
Effective Radiated Power	NR n26	Refer to APPENDIX A	-
Radiated Spurious Emissions (Below 1G)	NR n26	TX Mode (CH 163800)	-
Radiated Spurious Emissions (Above 1G)	NR n26	TX Mode (CH 163800)	-

**NOTE:**

- (1) All X, Y and Z axes are evaluated, but only the worst case (X axis) is recorded.
- (2) For Radiated Spurious Emissions both Pi/2 BPSK, QPSK, 16QAM, 64QAM and 256QAM are evaluated, but only the worst case (QPSK) is recorded.

## 2.3 BLOCK DIAGRAM SHOWING THE CONFIGURATION OF SYSTEM TESTED

Equipment letters and Cable numbers refer to item numbers described in the tables of clause 2.4.



## 2.4 SUPPORT UNITS

Item	Equipment	Brand	Model No.	Series No.	Remarks
A	NB	HP	TPN-I119	N/A	Furnished by test lab.
B	ADP	Lenovo	ADLX65YSDC2 A	N/A	Supplied by test requester.
C	USB 2.5" HDD	TOSIBA	XS700	483B60M9KQSS	Furnished by test lab.
D	27" 4K Monitor	DELL	U2720Q	CN-083VF-WSL0 0-0B7-332L	Furnished by test lab.
E	Mouse	Lenovo	SM-8823	N/A	Furnished by test lab.
F	Ear Phone	HTC	N/A	N/A	Furnished by test lab.
G	Keyboard	Bloody	KB-8	N/A	Furnished by test lab.

Item	Shielded	Ferrite Core	Length	Cable Type	Remarks
1	N/A	N/A	0.9m	Power Cord	Supplied by test requester.
2	N/A	N/A	1m	Type C to USB Cable	Furnished by test lab.
3	N/A	N/A	1.8m	HDMI	Furnished by test lab.
4	N/A	N/A	10m	RJ45 Cable	Furnished by test lab.

### 3 EFFECTIVE RADIATED POWER MEASUREMENT

#### 3.1 LIMIT

Mobile / Portable station are limited to 100 watts e.r.p.

#### 3.2 TEST PROCEDURE

The testing follows FCC KDB 971168 v03r01 Section 5.8.


- a. Substitution method is used for E.I.R.P measurement. In the semi-anechoic chamber, EUT placed on the 0.8m height of Turn Table, rotated the table around 360 degrees to search the maximum radiation power and receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum polar radiated power. The "Read Value" is the spectrum reading the maximum power value.
- b. The substitution horn antenna is substituted for EUT at the same position and signals generator export the CW signal to the substitution antenna via a TX cable. Rotated the Turn Table and moved receiving antenna to find the maximum radiation power. Adjust output power level of S.G to get a Value of spectrum reading equal to "Read Value " of step a. Record the power level of S.G
- c. EIRP = Output power level of S.G – TX cable loss + Antenna gain of substitution horn.
- d. ERP can be calculated from EIRP by subtracting the gain of dipole,  $ERP = EIRP - 2.15\text{dBi..}$
- e. The resolution bandwidth and video bandwidth of test receiver/spectrum analyzer is 1MHz/3MHz.

#### 3.3 DEVIATION FROM TEST STANDARD

No deviation.

#### 3.4 TEST SETUP

**Conducted Measurement:**



#### 3.5 EUT OPERATING CONDITIONS

The EUT was programmed to be in continuously transmitting mode.

#### 3.6 TEST RESULT

Please refer to the APPENDIX A.

## 4 RADIATED SPURIOUS EMISSIONS MEASUREMENT

### 4.1 LIMIT

The power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least  $43 + 10 \log(P)$  dB. The emission limit equal to -13dBm.

NOTE:

- (1) The measurements of emission power can be expressed in peak or average values, provided they are expressed in the same parameters as the transmitter power.
- (2) The test result calculated as following:

Measurement Value = Reading Level + Correct Factor

Correct Factor = Antenna Factor + Cable Loss - Amplifier Gain(if use)

Margin Level = Measurement Value - Limit Value

Calculation example:

Reading Level (dBm)		Correct Factor (dB/m)		Measurement Value (dBm)
-50.43	+	-2.11	=	-52.54

Measurement Value (dBm)		Limit Value (dBm)		Margin Level (dB)
-52.54	-	-13	=	-39.54

### 4.2 TEST PROCEDURE

The testing follows FCC KDB 971168 v03r01 Section 6.2.



- a. Substitution method is used for E.I.R.P measurement. In the semi-anechoic chamber, EUT placed on the 0.8m height of Turn Table, rotated the table around 360 degrees to search the maximum radiation power and receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum polar radiated power. The "Read Value" is the spectrum reading the maximum power value.
- b. The substitution horn antenna is substituted for EUT at the same position and signals generator export the CW signal to the substitution antenna via a TX cable. Rotated the Turn Table and moved receiving antenna to find the maximum radiation power. Adjust output power level of S.G to get a Value of spectrum reading equal to "Read Value" of step a. Record the power level of S.G
- c. EIRP = Output power level of S.G – TX cable loss + Antenna gain of substitution horn.
- d. ERP can be calculated from EIRP by subtracting the gain of dipole,  $ERP = EIRP - 2.15\text{dBi}$ .
- e. The resolution bandwidth and video bandwidth of test receiver/spectrum analyzer is 1MHz/3MHz.

### 4.3 DEVIATION FROM TEST STANDARD



No deviation.

#### 4.4 TEST SETUP

##### 30 MHz to 1 GHz



##### Above 1 GHz



#### 4.5 EUT OPERATING CONDITIONS

The EUT was programmed to be in continuously transmitting mode.

#### 4.6 TEST RESULT

Please refer to the APPENDIX B.

**5 LIST OF MEASURING EQUIPMENTS**

Effective Radiated Power						
Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated Date	Calibrated Until
1	WIRELESS COMMUNICATION TEST SET	Agilent	E5515C	GB47390193	2023/7/4	2024/7/3
2	Radio Communication Test Station	ANRITSU	MT8821C	6262044728	2023/11/22	2024/11/21
3	Radio Communication Analyzer	ANRITSU	MT8000A	6262036844	2023/11/22	2024/11/21
4	Radio Communication Analyzer	Keysight	E7515B	MY59020217	2023/7/6	2024/7/5

Radiated Emissions						
Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated Date	Calibrated Until
1	Preamplifier	EMCI	EMC330N	980850	2023/9/6	2024/9/5
2	Preamplifier	EMCI	EMC118A45SE	980819	2023/3/7	2024/3/6
3	Pre-Amplifier	EMCI	EMC184045SE	980907	2023/9/21	2024/9/20
4	Test Cable	EMCI	EMC104-SM-1000	180809	2023/7/10	2024/7/9
5	Test Cable	EMCI	EMC104-SM-SM-3000	220322	2023/3/14	2024/3/13
6	Test Cable	EMCI	EMC104-SM-SM-7000	220324	2023/3/14	2024/3/13
7	EXA Signal Analyzer	keysight	N9020B	MY57120120	2023/2/24	2024/2/23
8	Horn Antenna	RFSPIN	DRH18-E	211202A18EN	2023/5/12	2024/5/11
9	Horn Ant	Schwarzbeck	BBHA 9170D	1136	2023/5/12	2024/5/11
10	Log-bicon Antenna	Schwarzbeck	VULB9168	1369	2023/5/9	2024/5/8
11	6dB Attenuator	EMCI	EMCI-N-6-06	AT-06001	2023/5/9	2024/5/8
12	Test Cable	EMCI	EMC101G-KM-KM-3000	220329	2023/3/14	2024/3/13
13	Test Cable	EMCI	EMC102-KM-KM-1000	220327	2023/3/14	2024/3/13
14	WIRELESS COMMUNICATION TEST SET	Agilent	E5515C	GB47390193	2023/7/4	2024/7/3
15	Radio Communication Analyzer	ANRITSU	MT8820C	6201381608	2022/12/22	2023/12/21
16	Radio Communication Analyzer	Keysight	E7515B	MY59020217	2023/7/6	2024/7/5
17	Measurement Software	EZ	EZ_EMC (Version NB-03A1-01)	N/A	N/A	N/A

Remark: "N/A" denotes no model name, no serial no. or no calibration specified.  
All calibration period of equipment list is one year.

## **6 EUT TEST PHOTO**

Please refer to document Appendix No.: TP-2311T076-FCCP-1 (APPENDIX-TEST PHOTOS).

## **7 EUT PHOTOS**

Please refer to document Appendix No.: EP-2311T076-1(APPENDIX-EUT PHOTOS).

**APPENDIX A EFFECTIVE RADIATED POWER**

**NR Band n26 Power:**

Band	BW (MHz)	Channel	Frequency (MHz)	Mode	UL RB Allocation	UL RB Offset	MPR	Average power (dBm)	ERP power (dBm)	ERP power (W)
n26_SA	5	163300	816.5	PI/2 BPSK	1	1	0	23.72	18.60	0.072
					1	23	0	23.74	18.62	0.073
					25	0	0.5	23.29	18.17	0.066
				QPSK	1	1	0	23.70	18.58	0.072
					1	23	0	23.93	18.81	0.076
					25	0	1	22.89	17.77	0.060
		163800	819.0	16QAM	1	1	1	22.85	17.73	0.059
					1	23	1	23.01	17.89	0.062
					25	0	2	21.79	16.67	0.046
		164300	821.5	64QAM	1	1	2.5	21.44	16.32	0.043
					1	23	2.5	21.52	16.40	0.044
					25	0	2.5	21.42	16.30	0.043
		164300	821.5	256QAM	1	1	4.5	19.01	13.89	0.024
					1	23	4.5	19.07	13.95	0.025
					25	0	4.5	19.18	14.06	0.025
		164300	821.5	PI/2 BPSK	1	1	0	23.59	18.47	0.070
					1	23	0	23.59	18.47	0.070
					25	0	0.5	23.28	18.16	0.065
		164300	821.5	QPSK	1	1	0	23.73	18.61	0.073
					1	23	0	23.82	18.70	0.074
					25	0	1	22.82	17.70	0.059
		164300	821.5	16QAM	1	1	1	22.76	17.64	0.058
					1	23	1	22.85	17.73	0.059
					25	0	2	21.72	16.60	0.046
		164300	821.5	64QAM	1	1	2.5	21.36	16.24	0.042
					1	23	2.5	21.41	16.29	0.043
					25	0	2.5	21.35	16.23	0.042
		164300	821.5	256QAM	1	1	4.5	18.82	13.70	0.023
					1	23	4.5	19.10	13.98	0.025
					25	0	4.5	19.21	14.09	0.026

**NOTE:**

(1) EIRP = Average power + Antenna gain.

(2) ERP = EIRP - 2.15.

(3) P(W) = 1 W · 10<sup>(P(dBm) / 10)</sup> / 1000

Band	BW (MHz)	Channel	Frequency (MHz)	Mode	UL RB Allocation	UL RB Offset	MPR	Average power (dBm)	ERP power (dBm)	ERP power (W)
n26_SA	10	163800	819	PI/2 BPSK	1	1	0	22.47	17.35	0.054
					1	50	0	23.29	18.17	0.066
					50	0	0.5	23.32	18.20	0.066
				QPSK	1	1	0	23.29	18.17	0.066
					1	50	0	23.21	18.09	0.064
					50	0	1	22.86	17.74	0.059
				16QAM	1	1	1	22.81	17.69	0.059
					1	50	1	22.92	17.80	0.060
					50	0	2	21.78	16.66	0.046
				64QAM	1	1	2.5	21.41	16.29	0.043
					1	50	2.5	21.47	16.35	0.043
					50	0	2.5	21.43	16.31	0.043
				256QAM	1	1	4.5	18.87	13.75	0.024
					1	50	4.5	19.17	14.05	0.025
					50	0	4.5	19.27	14.15	0.026

**NOTE:**


(1) EIRP = Average power + Antenna gain.

(2) ERP = EIRP - 2.15.

 (3) P(W) = 1 W ·  $10^{(P(\text{dBm}) / 10)} / 1000$

**APPENDIX B RADIATED SPURIOUS EMISSIONS**

Test Mode	NR n26	Test Date	2023/12/4
Test Channel	CH163800	Polarization	Vertical
Temp	22°C	Hum.	58%




No.	Mk.	Freq.	Reading Level	Correct Factor	Measure- ment	Limit	Over	
		MHz	dBm	dB	dBm	dBm	dB	Detector Comment
1		42.9333	-67.44	-2.15	-69.59	-13.00	-56.59	peak
2	*	118.5287	-62.25	-2.15	-64.40	-13.00	-51.40	peak
3		178.0220	-71.16	-2.15	-73.31	-13.00	-60.31	peak
4		215.8197	-72.17	-2.15	-74.32	-13.00	-61.32	peak
5		321.0323	-69.78	-2.15	-71.93	-13.00	-58.93	peak
6		458.2873	-70.34	-2.15	-72.49	-13.00	-59.49	peak

## REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.  
 (2) Margin Level = Measurement Value - Limit Value.

Test Mode	NR n26	Test Date	2023/12/4
Test Channel	CH163800	Polarization	Horizontal
Temp	22°C	Hum.	58%




No.	Mk.	Freq.	Reading Level	Correct Factor	Measure-ment	Limit	Over	
		MHz	dBm	dB	dBm	dBm	dB	Detector Comment
1		83.4792	-63.74	-2.15	-65.89	-13.00	-52.89	peak
2	*	118.7227	-54.91	-2.15	-57.06	-13.00	-44.06	peak
3		178.0867	-61.06	-2.15	-63.21	-13.00	-50.21	peak
4		258.3703	-71.14	-2.15	-73.29	-13.00	-60.29	peak
5		317.4110	-71.33	-2.15	-73.48	-13.00	-60.48	peak
6		458.4490	-68.25	-2.15	-70.40	-13.00	-57.40	peak

## REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.  
 (2) Margin Level = Measurement Value - Limit Value.

Test Mode	NR n26	Test Date	2023/12/4
Test Channel	CH163800	Polarization	Vertical
Temp	22°C	Hum.	58%




No.	Mk.	Freq.	Reading Level	Correct Factor	Measure-ment	Limit	Over
		MHz	dBm	dB	dBm	dBm	Detector
1	*	1628.000	-63.69	5.26	-58.43	-13.00	-45.43 peak

## REMARKS:

- (1) Measurement Value = Reading Level + Correct Factor.
- (2) Margin Level = Measurement Value - Limit Value.

Test Mode	NR n26	Test Date	2023/12/4
Test Channel	CH163800	Polarization	Horizontal
Temp	22°C	Hum.	58%



No.	Mk.	Freq.	Reading Level	Correct Factor	Measure- ment	Limit	Over
		MHz	dBm	dB	dBm	dB	Detector
1	*	1628.000	-62.64	5.26	-57.38	-13.00	-44.38 peak

**REMARKS:**

(1) Measurement Value = Reading Level + Correct Factor.  
(2) Margin Level = Measurement Value - Limit Value.

**End of Test Report**