









11BE160MIMO_total_5570_Large RU 996+484_1




11BE160MIMO_total_5570_Large RU 996+484_4






11BE160MIMO_total_5570_Puncturing 40M_1




11BE160MIMO_total_5570_Puncturing 40M_4






11BE160MIMO_total_5570_Puncturing 20M_1




11BE160MIMO_total_5570_Puncturing 20M_8





Appendix B. AC Conducted Emission Test Results


Test Engineer :	Amos Zhang	Temperature :	25.3~26.2°C
		Relative Humidity :	38~40%
Test Voltage :	120Vac / 60Hz	Phase :	Line
Remark :	All emissions not reported here are more than 10 dB below the prescribed limit.		



Site : CO01-KS
Condition : 15E RSS247-QP LISN-060105-L 2023 LINE

	Freq	Level	Over	Limit	Read	LISN	Cable	Remark
	MHz	dBuV	Limit	Line	Level	Factor	Loss	
			dB	dBuV	dBuV	dB	dB	
1	0.151	46.37	-19.59	65.96	35.90	0.05	10.42	QP
2	0.151	38.07	-17.89	55.96	27.60	0.05	10.42	Average
3	0.238	43.71	-18.46	62.17	33.30	0.03	10.38	QP
4	0.238	33.91	-18.26	52.17	23.50	0.03	10.38	Average
5	0.318	39.85	-19.90	59.75	29.50	0.03	10.32	QP
6	0.318	30.25	-19.50	49.75	19.90	0.03	10.32	Average
7	0.354	39.52	-19.35	58.87	29.20	0.02	10.30	QP
8	0.354	29.82	-19.05	48.87	19.50	0.02	10.30	Average
9	0.385	39.89	-18.28	58.17	29.59	0.01	10.29	QP
10	0.385	30.59	-17.58	48.17	20.29	0.01	10.29	Average
11	0.426	38.55	-18.78	57.33	28.30	-0.01	10.26	QP
12 *	0.426	30.55	-16.78	47.33	20.30	-0.01	10.26	Average

Test Engineer :	Amos Zhang	Temperature :	25.3~26.2°C
		Relative Humidity :	38~40%
Test Voltage :	120Vac / 60Hz	Phase :	Neutral
Remark :	All emissions not reported here are more than 10 dB below the prescribed limit.		



Site : CO01-KS
Condition : 15E RSS247-QP LISN-060105-N 2023 NEUTRAL

	Freq	Level	Over	Limit	Read	LISN	Cable	Remark
	MHz	dBuV	Limit	Line	Level	Factor	Loss	
			dB	dBuV	dBuV	dB	dB	
1	0.163	46.76	-18.54	65.30	36.30	0.04	10.42	QP
2	0.163	37.16	-18.14	55.30	26.70	0.04	10.42	Average
3	0.234	43.99	-18.31	62.30	33.60	0.01	10.38	QP
4	0.234	33.89	-18.41	52.30	23.50	0.01	10.38	Average
5	0.267	41.54	-19.66	61.20	31.19	-0.01	10.36	QP
6	0.267	31.54	-19.66	51.20	21.19	-0.01	10.36	Average
7	0.297	44.40	-15.92	60.32	34.10	-0.04	10.34	QP
8 *	0.297	34.60	-15.72	50.32	24.30	-0.04	10.34	Average
9	0.385	39.83	-18.34	58.17	29.59	-0.05	10.29	QP
10	0.385	30.93	-17.24	48.17	20.69	-0.05	10.29	Average
11	0.497	36.75	-19.30	56.05	26.60	-0.07	10.22	QP
12	0.497	28.95	-17.10	46.05	18.80	-0.07	10.22	Average

Note:

1. Level(dBμV) = Read Level(dBμV) + LISN Factor(dB) + Cable Loss(dB)
2. Over Limit(dB) = Level(dBμV) – Limit Line(dBμV)



Appendix C. Radiated Spurious Emission Test Data

Test Engineer :	Zhang Xu	Relative Humidity :	50%
		Temperature :	20-22℃

Radiated Spurious Emission Test Modes

Mode	Band	Band (GHz)	Antenna	Modulation	Channel	Frequency	Data Rate	RU	Remark
Mode 1	U-NII-1	5.15-5.25	CDD	802.11a	36	5180	6Mbps	-	-
Mode 2	U-NII-1	5.15-5.25	CDD	802.11a	44	5220	6Mbps	-	-
Mode 3	U-NII-1	5.15-5.25	CDD	802.11a	48	5240	6Mbps	-	-
Mode 4	U-NII-2A	5.25-5.35	CDD	802.11a	52	5260	6Mbps	-	-
Mode 5	U-NII-2A	5.25-5.35	CDD	802.11a	60	5300	6Mbps	-	-
Mode 6	U-NII-2A	5.25-5.35	CDD	802.11a	64	5320	6Mbps	-	-
Mode 7	U-NII-2C	5.47-5.725	CDD	802.11a	100	5500	6Mbps	-	-
Mode 8	U-NII-2C	5.47-5.725	CDD	802.11a	116	5580	6Mbps	-	-
Mode 9	U-NII-2C	5.47-5.725	CDD	802.11a	140	5700	6Mbps	-	-
Mode 10	U-NII-1	5.15-5.25	CDD	802.11ac VHT20	36	5180	MCS0	-	-
Mode 11	U-NII-1	5.15-5.25	CDD	802.11ac VHT20	44	5220	MCS0	-	-
Mode 12	U-NII-1	5.15-5.25	CDD	802.11ac VHT20	48	5240	MCS0	-	-
Mode 13	U-NII-2A	5.25-5.35	CDD	802.11ac VHT20	52	5260	MCS0	-	-
Mode 14	U-NII-2A	5.25-5.35	CDD	802.11ac VHT20	60	5300	MCS0	-	-
Mode 15	U-NII-2A	5.25-5.35	CDD	802.11ac VHT20	64	5320	MCS0	-	-
Mode 16	U-NII-2C	5.47-5.725	CDD	802.11ac VHT20	100	5500	MCS0	-	-
Mode 17	U-NII-2C	5.47-5.725	CDD	802.11ac VHT20	116	5580	MCS0	-	-
Mode 18	U-NII-2C	5.47-5.725	CDD	802.11ac VHT20	140	5700	MCS0	-	-
Mode 19	U-NII-1	5.15-5.25	CDD	802.11ac VHT40	38	5190	MCS0	-	-
Mode 20	U-NII-1	5.15-5.25	CDD	802.11ac VHT40	46	5230	MCS0	-	-
Mode 21	U-NII-2A	5.25-5.35	CDD	802.11ac VHT40	54	5270	MCS0	-	-
Mode 22	U-NII-2A	5.25-5.35	CDD	802.11ac VHT40	62	5310	MCS0	-	-
Mode 23	U-NII-2C	5.47-5.725	CDD	802.11ac VHT40	102	5510	MCS0	-	-
Mode 24	U-NII-2C	5.47-5.725	CDD	802.11ac VHT40	110	5550	MCS0	-	-
Mode 25	U-NII-2C	5.47-5.725	CDD	802.11ac VHT40	134	5670	MCS0	-	-
Mode 26	U-NII-1	5.15-5.25	CDD	802.11ac VHT80	42	5210	MCS0	-	-
Mode 27	U-NII-2A	5.25-5.35	CDD	802.11ac VHT80	58	5290	MCS0	-	-
Mode 28	U-NII-2C	5.47-5.725	CDD	802.11ac VHT80	106	5530	MCS0	-	-
Mode 29	U-NII-2C	5.47-5.725	CDD	802.11ac VHT80	122	5610	MCS0	-	-
Mode 30	U-NII-2A	5.25-5.35	CDD	802.11ac VHT160	50	5250	MCS0	-	-
Mode 31	U-NII-2C	5.47-5.725	CDD	802.11ac VHT160	114	5570	MCS0	-	-
Mode 32	U-NII-1	5.15-5.25	CDD	802.11ax HE20	36	5180	MCS0	Full	-
Mode 33	U-NII-1	5.15-5.25	CDD	802.11ax HE20	44	5220	MCS0	Full	-
Mode 34	U-NII-1	5.15-5.25	CDD	802.11ax HE20	48	5240	MCS0	Full	-
Mode 35	U-NII-2A	5.25-5.35	CDD	802.11ax HE20	52	5260	MCS0	Full	-
Mode 36	U-NII-2A	5.25-5.35	CDD	802.11ax HE20	60	5300	MCS0	Full	-
Mode 37	U-NII-2A	5.25-5.35	CDD	802.11ax HE20	64	5320	MCS0	Full	-



Mode 38	U-NII-2C	5.47-5.725	CDD	802.11ax HE20	100	5500	MCS0	-	-
Mode 39	U-NII-2C	5.47-5.725	CDD	802.11ax HE20	116	5580	MCS0	-	-
Mode 40	U-NII-2C	5.47-5.725	CDD	802.11ax HE20	140	5700	MCS0	-	-
Mode 41	U-NII-1	5.15-5.25	CDD	802.11ax HE20	36	5180	MCS0	Partial RU26/0	-
Mode 44	U-NII-2A	5.25-5.35	CDD	802.11ax HE20	64	5320	MCS0	Partial RU26/8	-
Mode 45	U-NII-2C	5.47-5.725	CDD	802.11ax HE20	100	5500	MCS0	Partial RU26/0	-
Mode 46	U-NII-2C	5.47-5.725	CDD	802.11ax HE20	140	5700	MCS0	Partial RU26/8	-
Mode 47	U-NII-1	5.15-5.25	CDD	802.11ax HE20	36	5180	MCS0	Partial RU52/37	-
Mode 50	U-NII-2A	5.25-5.35	CDD	802.11ax HE20	64	5320	MCS0	Partial RU52/40	-
Mode 51	U-NII-2C	5.47-5.725	CDD	802.11ax HE20	100	5500	MCS0	Partial RU52/37	-
Mode 52	U-NII-2C	5.47-5.725	CDD	802.11ax HE20	140	5700	MCS0	Partial RU52/40	-
Mode 53	U-NII-1	5.15-5.25	CDD	802.11ax HE20	36	5180	MCS0	Partial RU106/53	-
Mode 56	U-NII-2A	5.25-5.35	CDD	802.11ax HE20	64	5320	MCS0	Partial RU106/54	-
Mode 57	U-NII-2C	5.47-5.725	CDD	802.11ax HE20	100	5500	MCS0	Partial RU106/53	-
Mode 58	U-NII-2C	5.47-5.725	CDD	802.11ax HE20	140	5700	MCS0	Partial RU106/54	-
Mode 59	U-NII-1	5.15-5.25	CDD	802.11ax HE40	38	5190	MCS0	Full	-
Mode 60	U-NII-1	5.15-5.25	CDD	802.11ax HE40	46	5230	MCS0	Full	-
Mode 61	U-NII-2A	5.25-5.35	CDD	802.11ax HE40	54	5270	MCS0	Full	-
Mode 62	U-NII-2A	5.25-5.35	CDD	802.11ax HE40	62	5310	MCS0	Full	-
Mode 63	U-NII-2C	5.47-5.725	CDD	802.11ax HE40	102	5510	MCS0	Full	-
Mode 64	U-NII-2C	5.47-5.725	CDD	802.11ax HE40	110	5550	MCS0	Full	-
Mode 65	U-NII-2C	5.47-5.725	CDD	802.11ax HE40	134	5670	MCS0	Full	-
Mode 66	U-NII-1	5.15-5.25	CDD	802.11ax HE80	42	5210	MCS0	Full	-
Mode 67	U-NII-2A	5.25-5.35	CDD	802.11ax HE80	58	5290	MCS0	Full	-
Mode 68	U-NII-2C	5.47-5.725	CDD	802.11ax HE80	106	5530	MCS0	Full	-
Mode 69	U-NII-2C	5.47-5.725	CDD	802.11ax HE80	122	5610	MCS0	Full	-
Mode 70	U-NII-2A	5.25-5.35	CDD	802.11ax HE160	50	5250	MCS0	Full	-
Mode 71	U-NII-2C	5.47-5.725	CDD	802.11ax HE160	114	5570	MCS0	Full	-
Mode 72	U-NII-1	5.15-5.25	CDD	802.11be EHT20	36	5180	MCS0	Full	-
Mode 73	U-NII-1	5.15-5.25	CDD	802.11be EHT20	44	5220	MCS0	Full	-
Mode 74	U-NII-1	5.15-5.25	CDD	802.11be EHT20	48	5240	MCS0	Full	-
Mode 75	U-NII-2A	5.25-5.35	CDD	802.11be EHT20	52	5260	MCS0	Full	-
Mode 76	U-NII-2A	5.25-5.35	CDD	802.11be EHT20	60	5300	MCS0	Full	-
Mode 77	U-NII-2A	5.25-5.35	CDD	802.11be EHT20	64	5320	MCS0	Full	-
Mode 78	U-NII-2C	5.47-5.725	CDD	802.11be EHT20	100	5500	MCS0	Full	-
Mode 79	U-NII-2C	5.47-5.725	CDD	802.11be EHT20	116	5580	MCS0	Full	-
Mode 80	U-NII-2C	5.47-5.725	CDD	802.11be EHT20	140	5700	MCS0	Full	-
Mode 81	U-NII-1	5.15-5.25	CDD	802.11be EHT40	38	5190	MCS0	Full	-



Mode 82	U-NII-1	5.15-5.25	CDD	802.11be EHT40	46	5230	MCS0	Full	-
Mode 83	U-NII-2A	5.25-5.35	CDD	802.11be EHT40	54	5270	MCS0	Full	-
Mode 84	U-NII-2A	5.25-5.35	CDD	802.11be EHT40	62	5310	MCS0	Full	-
Mode 85	U-NII-2C	5.47-5.725	CDD	802.11be EHT40	102	5510	MCS0	Full	-
Mode 86	U-NII-2C	5.47-5.725	CDD	802.11be EHT40	110	5550	MCS0	Full	-
Mode 87	U-NII-2C	5.47-5.725	CDD	802.11be EHT40	134	5670	MCS0	Full	-
Mode 88	U-NII-1	5.15-5.25	CDD	802.11be EHT80	42	5210	MCS0	Full	-
Mode 89	U-NII-2A	5.25-5.35	CDD	802.11be EHT80	58	5290	MCS0	Full	-
Mode 90	U-NII-2C	5.47-5.725	CDD	802.11be EHT80	106	5530	MCS0	Full	-
Mode 91	U-NII-2C	5.47-5.725	CDD	802.11be EHT80	122	5610	MCS0	Full	-
Mode 92	U-NII-2A	5.25-5.35	CDD	802.11be EHT160	50	5250	MCS0	Full	-
Mode 93	U-NII-2C	5.47-5.725	CDD	802.11be EHT160	114	5570	MCS0	Full	-
Mode 94	U-NII-3	5.725-5.85	CDD	802.11a	149	5745	6Mbps	-	-
Mode 95	U-NII-3	5.725-5.85	CDD	802.11a	157	5785	6Mbps	-	-
Mode 96	U-NII-3	5.725-5.85	CDD	802.11a	165	5825	6Mbps	-	-
Mode 97	U-NII-3	5.725-5.85	CDD	802.11ac VHT20	149	5745	MCS0	-	-
Mode 98	U-NII-3	5.725-5.85	CDD	802.11ac VHT20	157	5785	MCS0	-	-
Mode 99	U-NII-3	5.725-5.85	CDD	802.11ac VHT20	165	5825	MCS0	-	-
Mode 100	U-NII-3	5.725-5.85	CDD	802.11ac VHT40	151	5755	MCS0	-	-
Mode 101	U-NII-3	5.725-5.85	CDD	802.11ac VHT40	159	5795	MCS0	-	-
Mode 102	U-NII-3	5.725-5.85	CDD	802.11ac VHT80	155	5775	MCS0	-	-
Mode 103	U-NII-3	5.725-5.85	CDD	802.11ax HE20	149	5745	MCS0	Full	-
Mode 104	U-NII-3	5.725-5.85	CDD	802.11ax HE20	157	5785	MCS0	Full	-
Mode 105	U-NII-3	5.725-5.85	CDD	802.11ax HE20	165	5825	MCS0	Full	-
Mode 106	U-NII-3	5.725-5.85	CDD	802.11ax HE40	151	5755	MCS0	Full	-
Mode 107	U-NII-3	5.725-5.85	CDD	802.11ax HE40	159	5795	MCS0	Full	-
Mode 108	U-NII-3	5.725-5.85	CDD	802.11ax HE80	155	5775	MCS0	Full	-
Mode 109	U-NII-3	5.725-5.85	CDD	802.11ax HE20	149	5745	MCS0	Partial RU26/0	-
Mode 110	U-NII-3	5.725-5.85	CDD	802.11ax HE20	165	5825	MCS0	Partial RU26/8	-
Mode 111	U-NII-3	5.725-5.85	CDD	802.11ax HE20	149	5745	MCS0	Partial RU52/37	-
Mode 112	U-NII-3	5.725-5.85	CDD	802.11ax HE20	165	5825	MCS0	Partial RU52/40	-
Mode 113	U-NII-3	5.725-5.85	CDD	802.11ax HE20	149	5745	MCS0	Partial RU106/53	-
Mode 114	U-NII-3	5.725-5.85	CDD	802.11ax HE20	165	5825	MCS0	Partial RU106/54	-
Mode 115	U-NII-3	5.725-5.85	CDD	802.11be EHT20	149	5745	MCS0	Full	-
Mode 116	U-NII-3	5.725-5.85	CDD	802.11be EHT20	157	5785	MCS0	Full	-
Mode 117	U-NII-3	5.725-5.85	CDD	802.11be EHT20	165	5825	MCS0	Full	-
Mode 118	U-NII-3	5.725-5.85	CDD	802.11be EHT40	151	5755	MCS0	Full	-
Mode 119	U-NII-3	5.725-5.85	CDD	802.11be EHT40	159	5795	MCS0	Full	-
Mode 120	U-NII-3	5.725-5.85	CDD	802.11be EHT80	155	5775	MCS0	Full	-
Mode 121	UNII 2C-3	5.725-5.85	CDD	802.11a	144	5720	6Mbps	-	-
Mode 123	UNII 2C-3	5.725-5.85	CDD	802.11ac VHT20	144	5720	MCS0	-	-



Mode 124	UNII 2C-3	5.725-5.85	CDD	802.11ac VHT40	142	5710	MCS0	-	-
Mode 125	UNII 2C-3	5.725-5.85	CDD	802.11ac VHT80	138	5690	MCS0	-	-
Mode 126	UNII 2C-3	5.725-5.85	CDD	802.11ax HE20	144	5710	MCS0	Full	-
Mode 127	UNII 2C-3	5.725-5.85	CDD	802.11ax HE40	142	5690	MCS0	Full	-
Mode 128	UNII 2C-3	5.725-5.85	CDD	802.11ax HE80	138	5720	MCS0	Full	-
Mode 129	UNII 2C-3	5.725-5.85	CDD	802.11be EHT40	142	5710	MCS0	Full	-
Mode 130	UNII 2C-3	5.725-5.85	CDD	802.11be EHT80	138	5690	MCS0	Full	-
Mode 131	U-NII-1	5.15-5.25	CDD	802.11be EHT20	36	5180	MCS0	Single RU 106/53	-
Mode 132	U-NII-1	5.25-5.35	CDD	802.11be EHT20	64	5320	MCS0	Single RU 106/54	-
Mode 133	U-NII-2A	5.47-5.725	CDD	802.11be EHT20	100	5500	MCS0	Single RU 106/53	-
Mode 134	U-NII-2A	5.47-5.725	CDD	802.11be EHT20	140	5700	MCS0	Single RU 106/54	-
Mode 135	U-NII-3	5.725-5.85	CDD	802.11be EHT20	149	5745	MCS0	Single RU 106/53	-
Mode 136	U-NII-3	5.725-5.85	CDD	802.11be EHT20	165	5825	MCS0	Single RU 106/54	-
Mode 137	U-NII-1	5.15-5.25	CDD	802.11be EHT20	36	5180	MCS0	Small RU 53+4	-
Mode 138	U-NII-2A	5.25-5.35	CDD	802.11be EHT20	64	5320	MCS0	Small RU 40+6	-
Mode 139	U-NII-2C	5.47-5.725	CDD	802.11be EHT20	100	5500	MCS0	Small RU 37+2	-
Mode 140	U-NII-2C	5.47-5.725	CDD	802.11be EHT20	140	5700	MCS0	Small RU 54+4	-
Mode 141	U-NII-3	5.725-5.85	CDD	802.11be EHT20	149	5745	MCS0	Small RU 37+2	-
Mode 142	U-NII-3	5.725-5.85	CDD	802.11be EHT20	165	5825	MCS0	Small RU 54+4	-
Mode 143	U-NII-1	5.15-5.25	CDD	802.11be EHT80	42	5210	MCS0	Puncturing 20M④	-
Mode 144	U-NII-2A	5.25-5.35	CDD	802.11be EHT80	58	5290	MCS0	Puncturing 20M①	-
Mode 145	U-NII-2C	5.47-5.725	CDD	802.11be EHT80	106	5530	MCS0	Puncturing 20M④	-
Mode 146	U-NII-2C	5.47-5.725	CDD	802.11be EHT80	122	5610	MCS0	Puncturing 20M①	-
Mode 147	U-NII-2A	5.25-5.35	CDD	802.11be EHT160	50	5250	MCS0	Puncturing 40M④	-
Mode 148	U-NII-2A	5.25-5.35	CDD	802.11be EHT160	50	5250	MCS0	Puncturing 40M①	-
Mode 149	U-NII-2C	5.47-5.725	CDD	802.11be EHT160	114	5570	MCS0	Puncturing 40M④	-
Mode 150	U-NII-2C	5.47-5.725	CDD	802.11be EHT160	114	5570	MCS0	Puncturing 40M①	-
Mode 151	U-NII-2A	5.25-5.35	CDD	802.11be EHT160	50	5250	MCS0	Puncturing 20M①	-
Mode 152	U-NII-2A	5.25-5.35	CDD	802.11be EHT160	50	5250	MCS0	Puncturing 20M⑧	-
Mode 153	U-NII-2C	5.47-5.725	CDD	802.11be EHT160	114	5570	MCS0	Puncturing 20M①	-



Mode 154	U-NII-2C	5.47-5.725	CDD	802.11be EHT160	114	5570	MCS0	Puncturing 20M ⁸	-
Mode 155	U-NII-3	5.725-5.85	CDD	802.11be EHT80	155	5775	MCS0	Puncturing 20M ¹	-
Mode 156	U-NII-3	5.725-5.85	CDD	802.11be EHT80	155	5775	MCS0	Puncturing 20M ⁴	-
Mode 157	U-NII-3	5.47-5.725-3	CDD	802.11be EHT80	138	5690	MCS0	Puncturing 20M ¹	-
Mode 158	U-NII-1	5.15-5.25	CDD	802.11be EHT80	42	5210	MCS0	Large RU 484+242 ⁴	-
Mode 159	U-NII-2A	5.25-5.35	CDD	802.11be EHT80	58	5290	MCS0	Large RU 484+242 ¹	-
Mode 160	U-NII-2C	5.47-5.725	CDD	802.11be EHT80	106	5530	MCS0	Large RU 484+242 ⁴	-
Mode 161	U-NII-2C	5.47-5.725	CDD	802.11be EHT80	122	5610	MCS0	Large RU 484+242 ¹	-
Mode 162	U-NII-2A	5.25-5.35	CDD	802.11be EHT160	50	5250	MCS0	Large RU 996+484 ⁴	-
Mode 163	U-NII-2A	5.25-5.35	CDD	802.11be EHT160	50	5250	MCS0	Large RU 996+484 ¹	-
Mode 164	U-NII-2C	5.47-5.725	CDD	802.11be EHT160	114	5570	MCS0	Large RU 996+484 ⁴	-
Mode 165	U-NII-2C	5.47-5.725	CDD	802.11be EHT160	114	5570	MCS0	Large RU 996+484 ¹	-
Mode 166	U-NII-3	5.725-5.85	CDD	802.11be EHT80	155	5775	MCS0	Large RU 484+242 ⁴	-
Mode 167	U-NII-3	5.725-5.85	CDD	802.11be EHT80	155	5775	MCS0	Large RU 484+242 ¹	-
Mode 168	U-NII-2C	5.47-5.725	CDD	802.11ax HE80-LF	106	5530	MCS0	Full	-
Mode 169	U-NII-3	5.725-5.85	CDD	802.11a-LF	165	5825	6Mbps	Full	-
Mode 170	Co-location	5.47-5.725	CDD	802.11ax HE80	106	5530	MCS0	Full	-
		2400-2483.5	CDD	802.11ax HE40	9	2452	MCS0	Full	-
Mode 171	UNII 2C-3	5.47-5.85	CDD	802.11be EHT20	144	5710	MCS0	Full	



Summary of each worse mode

Mode	Modulation	Ch.	Freq. (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Pol.	Peak Avg.	Result	Remark
1	802.11a	36	5149.76	47.27	54.00	-6.73	H	AVERAGE	Pass	Band Edge
1	802.11a	36	10360.00	48.03	68.30	-20.27	H	Peak	Pass	Harmonic
2	802.11a	44	-	-	-	-	-	-	-	Band Edge
2	802.11a	44	10440.00	47.47	68.30	-20.83	H	Peak	Pass	Harmonic
3	802.11a	48	-	-	-	-	-	-	-	Band Edge
3	802.11a	48	10480.00	47.75	68.30	-20.55	V	Peak	Pass	Harmonic
4	802.11a	52	-	-	-	-	-	-	-	Band Edge
4	802.11a	52	10520.00	47.94	68.30	-20.36	H	Peak	Pass	Harmonic
5	802.11a	60	-	-	-	-	-	-	-	Band Edge
5	802.11a	60	15900.00	50.48	74.00	-23.52	V	Peak	Pass	Harmonic
6	802.11a	64	5351.78	53.87	54.00	-0.63	H	AVERAGE	Pass	Band Edge
6	802.11a	64	15960.00	50.65	74.00	-23.35	H	Peak	Pass	Harmonic
7	802.11a	100	5459.95	45.41	54.00	-8.59	H	AVERAGE	Pass	Band Edge
7	802.11a	100	16500.00	49.48	68.30	-18.82	V	Peak	Pass	Harmonic
8	802.11a	116	-	-	-	-	-	-	-	Band Edge
8	802.11a	116	16740.00	49.85	68.30	-18.45	V	Peak	Pass	Harmonic
9	802.11a	140	5725.35	58.37	68.30	-9.93	H	PEAK	Pass	Band Edge
9	802.11a	140	17100.00	50.07	68.30	-18.23	H	Peak	Pass	Harmonic
10	802.11ac VHT20	36	5149.76	47.05	54.00	-6.95	H	AVERAGE	Pass	Band Edge
10	802.11ac VHT20	36	10360.00	48.62	68.30	-19.68	H	Peak	Pass	Harmonic
11	802.11ac VHT20	44	-	-	-	-	-	-	-	Band Edge
11	802.11ac VHT20	44	10440.00	48.74	68.30	-19.56	V	Peak	Pass	Harmonic
12	802.11ac VHT20	48	-	-	-	-	-	-	-	Band Edge
12	802.11ac VHT20	48	10480.00	49.01	68.30	-19.29	V	Peak	Pass	Harmonic
13	802.11ac VHT20	52	-	-	-	-	-	-	-	Band Edge
13	802.11ac VHT20	52	10520.00	48.56	68.30	-19.74	V	Peak	Pass	Harmonic
14	802.11ac VHT20	60	-	-	-	-	-	-	-	Band Edge
14	802.11ac VHT20	60	15900.00	52.00	74.00	-22.00	H	Peak	Pass	Harmonic
15	802.11ac VHT20	64	5351.08	50.91	54.00	-3.09	H	AVERAGE	Pass	Band Edge
15	802.11ac VHT20	64	15960.00	50.81	74.00	-23.19	H	Peak	Pass	Harmonic
16	802.11ac VHT20	100	5459.65	45.06	54.00	-8.94	H	AVERAGE	Pass	Band Edge
16	802.11ac VHT20	100	16500.00	49.08	68.30	-19.22	H	Peak	Pass	Harmonic
17	802.11ac VHT20	116	-	-	-	-	-	-	-	Band Edge
17	802.11ac VHT20	116	16740.00	49.53	68.30	-18.77	V	Peak	Pass	Harmonic
18	802.11ac VHT20	140	5725.09	67.01	68.30	-1.29	V	PEAK	Pass	Band Edge
18	802.11ac VHT20	140	17100.00	50.80	68.30	-17.50	H	Peak	Pass	Harmonic
19	802.11ac VHT40	38	5130.53	51.33	54.00	-2.67	H	AVERAGE	Pass	Band Edge
19	802.11ac VHT40	38	10380.00	47.41	68.30	-20.89	V	Peak	Pass	Harmonic



20	802.11ac VHT40	46	5149.96	48.39	54.00	-5.61	H	AVERAGE	Pass	Band Edge
20	802.11ac VHT40	46	10460.00	48.98	68.30	-19.32	V	Peak	Pass	Harmonic
21	802.11ac VHT40	54	-	-	-	-	-	-	-	Band Edge
21	802.11ac VHT40	54	10540.00	48.45	68.30	-19.85	V	Peak	Pass	Harmonic
22	802.11ac VHT40	62	5350.29	53.51	54.00	-0.49	V	AVERAGE	Pass	Band Edge
22	802.11ac VHT40	62	15930.00	50.09	-	-	V	Peak	Pass	Harmonic
23	802.11ac VHT40	102	5467.52	59.80	68.30	-8.50	V	PEAK	Pass	Band Edge
23	802.11ac VHT40	102	16530.00	49.88	68.30	-18.42	V	Peak	Pass	Harmonic
24	802.11ac VHT40	110	-	-	-	-	-	-	-	Band Edge
24	802.11ac VHT40	110	16650.00	50.13	68.30	-18.17	V	Peak	Pass	Harmonic
25	802.11ac VHT40	134	5725.73	62.18	68.30	-6.12	V	PEAK	Pass	Band Edge
25	802.11ac VHT40	134	17010.00	51.82	68.30	-16.48	V	Peak	Pass	Harmonic
26	802.11ac VHT80	42	5146.69	51.16	54.00	-2.84	V	AVERAGE	Pass	Band Edge
26	802.11ac VHT80	42	10420.00	48.52	68.30	-19.78	V	Peak	Pass	Harmonic
27	802.11ac VHT80	58	5351.97	53.16	54.00	-0.84	V	AVERAGE	Pass	Band Edge
27	802.11ac VHT80	58	10580.00	49.24	68.30	-19.06	H	Peak	Pass	Harmonic
28	802.11ac VHT80	106	5432.55	44.95	54.00	-9.05	V	AVERAGE	Pass	Band Edge
28	802.11ac VHT80	106	16590.00	50.84	68.30	-17.46	V	Peak	Pass	Harmonic
29	802.11ac VHT80	122	5726.19	58.64	68.30	-9.66	V	PEAK	Pass	Band Edge
29	802.11ac VHT80	122	16830.00	50.09	68.30	-18.21	V	Peak	Pass	Harmonic
30	802.11ac VHT160	50	5123.75	48.34	54.00	-5.66	H	AVERAGE	Pass	Band Edge
30	802.11ac VHT160	50	10500.00	47.59	68.30	-20.71	V	Peak	Pass	Harmonic
31	802.11ac VHT160	114	5436.02	50.07	54.00	-3.93	H	AVERAGE	Pass	Band Edge
31	802.11ac VHT160	114	16710.00	50.93	68.30	-17.37	V	Peak	Pass	Harmonic
32	802.11ax HE20	36	5149.94	45.74	54.00	-8.26	H	AVERAGE	Pass	Band Edge
32	802.11ax HE20	36	10360.00	47.28	68.30	-21.02	H	Peak	Pass	Harmonic
33	802.11ax HE20	44	-	-	-	-	-	-	-	Band Edge
33	802.11ax HE20	44	10440.00	48.21	68.30	-20.09	V	Peak	Pass	Harmonic
34	802.11ax HE20	48	-	-	-	-	-	-	-	Band Edge
34	802.11ax HE20	48	10480.00	48.17	68.30	-20.13	V	Peak	Pass	Harmonic
35	802.11ax HE20	52	-	-	-	-	-	-	-	Band Edge
35	802.11ax HE20	52	10520.00	48.57	68.30	-19.73	V	Peak	Pass	Harmonic
36	802.11ax HE20	60	-	-	-	-	-	-	-	Band Edge
36	802.11ax HE20	60	15900.00	50.21	74.00	-23.79	H	Peak	Pass	Harmonic
37	802.11ax HE20	64	5350.10	50.57	54.00	-3.43	H	AVERAGE	Pass	Band Edge
37	802.11ax HE20	64	15960.00	50.90	74.00	-23.10	H	Peak	Pass	Harmonic
38	802.11ax HE20	100	5456.50	45.59	54.00	-8.41	H	AVERAGE	Pass	Band Edge
38	802.11ax HE20	100	16500.00	48.42	68.30	-19.88	H	Peak	Pass	Harmonic
39	802.11ax HE20	116	-	-	-	-	-	-	-	Band Edge
39	802.11ax HE20	116	16740.00	50.51	68.30	-17.79	V	Peak	Pass	Harmonic
40	802.11ax HE20	140	5725.29	64.47	68.30	-3.83	V	PEAK	Pass	Band Edge
40	802.11ax HE20	140	17100.00	52.28	68.30	-16.02	H	Peak	Pass	Harmonic



41	802.11ax HE20	36	5137.16	42.08	54.00	-11.92	H	AVERAGE	Pass	Band Edge
41	802.11ax HE20	36	-	-	-	-	-	-	-	Harmonic
44	802.11ax HE20	64	5352.48	42.66	54.00	-11.34	H	AVERAGE	Pass	Band Edge
44	802.11ax HE20	64	-	-	-	-	-	-	-	Harmonic
45	802.11ax HE20	100	5456.20	42.62	54.00	-11.38	V	AVERAGE	Pass	Band Edge
45	802.11ax HE20	100	-	-	-	-	-	-	-	Harmonic
46	802.11ax HE20	140	5739.65	53.60	68.30	-14.70	H	PEAK	Pass	Band Edge
46	802.11ax HE20	140	-	-	-	-	-	-	-	Harmonic
47	802.11ax HE20	36	5148.68	43.14	54.00	-10.86	H	AVERAGE	Pass	Band Edge
47	802.11ax HE20	36	-	-	-	-	-	-	-	Harmonic
50	802.11ax HE20	64	5353.88	42.43	54.00	-11.57	H	AVERAGE	Pass	Band Edge
50	802.11ax HE20	64	-	-	-	-	-	-	-	Harmonic
51	802.11ax HE20	100	5459.20	42.89	54.00	-11.11	H	AVERAGE	Pass	Band Edge
51	802.11ax HE20	100	-	-	-	-	-	-	-	Harmonic
52	802.11ax HE20	140	5757.92	53.51	68.30	-14.79	H	PEAK	Pass	Band Edge
52	802.11ax HE20	140	-	-	-	-	-	-	-	Harmonic
53	802.11ax HE20	36	5149.94	43.10	54.00	-10.90	H	AVERAGE	Pass	Band Edge
53	802.11ax HE20	36	-	-	-	-	-	-	-	Harmonic
56	802.11ax HE20	64	5350.24	45.27	54.00	-8.73	H	AVERAGE	Pass	Band Edge
56	802.11ax HE20	64	-	-	-	-	-	-	-	Harmonic
57	802.11ax HE20	100	5456.80	42.95	54.00	-11.05	H	AVERAGE	Pass	Band Edge
57	802.11ax HE20	100	-	-	-	-	-	-	-	Harmonic
58	802.11ax HE20	140	5726.20	53.35	68.30	-14.95	V	PEAK	Pass	Band Edge
58	802.11ax HE20	140	-	-	-	-	-	-	-	Harmonic
59	802.11ax HE40	38	5127.87	53.45	54.00	-0.55	H	AVERAGE	Pass	Band Edge
59	802.11ax HE40	38	10380.00	47.48	68.30	-20.82	V	Peak	Pass	Harmonic
60	802.11ax HE40	46	-	-	-	-	-	-	-	Band Edge
60	802.11ax HE40	46	10460.00	47.96	68.30	-20.34	H	Peak	Pass	Harmonic
61	802.11ax HE40	54	-	-	-	-	-	-	-	Band Edge
61	802.11ax HE40	54	10540.00	48.09	68.30	-20.21	H	Peak	Pass	Harmonic
62	802.11ax HE40	62	5351.85	50.58	54.00	-3.42	H	AVERAGE	Pass	Band Edge
62	802.11ax HE40	62	15930.00	50.46	74.00	-23.54	H	Peak	Pass	Harmonic
63	802.11ax HE40	102	5469.36	65.36	68.30	-2.94	H	PEAK	Pass	Band Edge
63	802.11ax HE40	102	16530.00	50.11	68.30	-18.19	V	Peak	Pass	Harmonic
64	802.11ax HE40	110	-	-	-	-	-	-	-	Band Edge
64	802.11ax HE40	110	16650.00	49.95	68.30	-18.35	H	Peak	Pass	Harmonic
65	802.11ax HE40	134	5746.29	66.26	68.30	-2.04	H	PEAK	Pass	Band Edge
65	802.11ax HE40	134	17010.00	50.12	68.30	-18.18	V	Peak	Pass	Harmonic
66	802.11ax HE80	42	5123.27	53.25	54.00	-0.75	H	AVERAGE	Pass	Band Edge
66	802.11ax HE80	42	10420.00	47.96	68.30	-20.34	V	Peak	Pass	Harmonic
67	802.11ax HE80	58	5350.01	53.05	54.00	-0.95	H	AVERAGE	Pass	Band Edge
67	802.11ax HE80	58	10580.00	48.45	68.30	-19.85	H	Peak	Pass	Harmonic



68	802.11ax HE80	106	5436.04	53.52	54.00	-0.48	V	AVERAGE	Pass	Band Edge
68	802.11ax HE80	106	16590.00	49.62	68.30	-18.68	V	Peak	Pass	Harmonic
69	802.11ax HE80	122	5728.58	66.96	68.30	-1.34	H	PEAK	Pass	Band Edge
69	802.11ax HE80	122	16830.00	49.63	68.30	-18.67	H	Peak	Pass	Harmonic
70	802.11ax HE160	50	5148.00	53.24	54.00	-0.76	H	AVERAGE	Pass	Band Edge
70	802.11ax HE160	50	10500.00	49.16	68.30	-19.14	V	Peak	Pass	Harmonic
71	802.11ax HE160	114	5726.39	66.21	68.30	-2.09	V	PEAK	Pass	Band Edge
71	802.11ax HE160	114	16710.00	50.30	68.30	-18.00	V	Peak	Pass	Harmonic
72	802.11be EHT20	36	5140.76	45.56	54.00	-8.44	H	AVERAGE	Pass	Band Edge
72	802.11be EHT20	36	10360.00	48.15	68.30	-20.15	H	Peak	Pass	Harmonic
73	802.11be EHT20	44	-	-	-	-	-	-	-	Band Edge
73	802.11be EHT20	44	10440.00	48.13	68.30	-20.17	V	Peak	Pass	Harmonic
74	802.11be EHT20	48	-	-	-	-	-	-	-	Band Edge
74	802.11be EHT20	48	10480.00	48.12	68.30	-20.18	V	Peak	Pass	Harmonic
75	802.11be EHT20	52	-	-	-	-	-	-	-	Band Edge
75	802.11be EHT20	52	10520.00	47.96	68.30	-20.34	H	Peak	Pass	Harmonic
76	802.11be EHT20	60	-	-	-	-	-	-	-	Band Edge
76	802.11be EHT20	60	15900.00	49.94	74.00	-24.06	H	Peak	Pass	Harmonic
77	802.11be EHT20	64	5350.24	50.99	54.00	-3.01	H	AVERAGE	Pass	Band Edge
77	802.11be EHT20	64	15960.00	50.27	74.00	-23.73	H	Peak	Pass	Harmonic
78	802.11be EHT20	100	5455.15	44.33	54.00	-9.67	H	AVERAGE	Pass	Band Edge
78	802.11be EHT20	100	16500.00	49.84	68.30	-18.46	V	Peak	Pass	Harmonic
79	802.11be EHT20	116	-	-	-	-	-	-	-	Band Edge
79	802.11be EHT20	116	16740.00	49.93	68.30	-18.37	V	Peak	Pass	Harmonic
80	802.11be EHT20	140	5725.81	58.13	68.30	-10.17	V	PEAK	Pass	Band Edge
80	802.11be EHT20	140	17100.00	49.83	68.30	-18.47	V	Peak	Pass	Harmonic
81	802.11be EHT40	38	5149.91	48.89	54.00	-5.11	H	AVERAGE	Pass	Band Edge
81	802.11be EHT40	38	10380.00	48.24	68.30	-20.06	V	Peak	Pass	Harmonic
82	802.11be EHT40	46	-	-	-	-	-	-	-	Band Edge
82	802.11be EHT40	46	10460.00	47.87	68.30	-20.43	H	Peak	Pass	Harmonic
83	802.11be EHT40	54	-	-	-	-	-	-	-	Band Edge
83	802.11be EHT40	54	10540.00	48.44	68.30	-19.86	V	Peak	Pass	Harmonic
84	802.11be EHT40	62	5351.10	53.30	54.00	-0.70	H	AVERAGE	Pass	Band Edge
84	802.11be EHT40	62	15930.00	49.37	74.00	-24.63	V	Peak	Pass	Harmonic
85	802.11be EHT40	102	5465.52	60.88	68.30	-7.42	H	PEAK	Pass	Band Edge
85	802.11be EHT40	102	16530.00	49.07	68.30	-19.23	H	Peak	Pass	Harmonic
86	802.11be EHT40	110	-	-	-	-	-	-	-	Band Edge
86	802.11be EHT40	110	16650.00	49.40	68.30	-18.90	V	Peak	Pass	Harmonic
87	802.11be EHT40	134	5747.43	58.97	68.30	-9.33	H	PEAK	Pass	Band Edge
87	802.11be EHT40	134	17010.00	49.82	68.30	-18.48	H	Peak	Pass	Harmonic
88	802.11be EHT80	42	5149.73	47.16	54.00	-6.84	H	AVERAGE	Pass	Band Edge
88	802.11be EHT80	42	10420.00	48.85	68.30	-19.45	H	Peak	Pass	Harmonic



89	802.11be EHT80	58	5369.73	52.86	54.00	-1.14	H	AVERAGE	Pass	Band Edge
89	802.11be EHT80	58	10580.00	48.42	68.30	-19.88	H	Peak	Pass	Harmonic
90	802.11be EHT80	106	5438.02	48.02	54.00	-5.98	V	AVERAGE	Pass	Band Edge
90	802.11be EHT80	106	16590.00	49.01	68.30	-19.29	V	Peak	Pass	Harmonic
91	802.11be EHT80	122	5458.16	44.85	54.00	-9.15	H	AVERAGE	Pass	Band Edge
91	802.11be EHT80	122	16830.00	50.49	68.30	-17.81	V	Peak	Pass	Harmonic
92	802.11be EHT160	50	5125.75	51.22	54.00	-2.78	H	AVERAGE	Pass	Band Edge
92	802.11be EHT160	50	10500.00	47.53	68.30	-20.77	H	Peak	Pass	Harmonic
93	802.11be EHT160	114	5726.39	66.07	68.30	-2.23	H	PEAK	Pass	Band Edge
93	802.11be EHT160	114	16710.00	49.95	68.30	-18.35	H	Peak	Pass	Harmonic
94	802.11a	149	5622.33	53.40	68.30	-14.90	V	PEAK	Pass	Band Edge
94	802.11a	149	11490.00	43.99	54.00	-10.01	V	Average	Pass	Harmonic
95	802.11a	157	-	-	-	-	-	-	-	Band Edge
95	802.11a	157	11570.00	44.58	54.00	-9.42	V	Average	Pass	Harmonic
96	802.11a	165	5931.00	53.90	68.30	-14.40	V	PEAK	Pass	Band Edge
96	802.11a	165	11650.00	44.80	54.00	-9.20	V	Average	Pass	Harmonic
97	802.11ac VHT20	149	5624.51	53.54	68.30	-14.76	V	PEAK	Pass	Band Edge
97	802.11ac VHT20	149	17235.00	50.08	68.30	-18.22	H	Peak	Pass	Harmonic
98	802.11ac VHT20	157	-	-	-	-	-	-	-	Band Edge
98	802.11ac VHT20	157	17355.00	50.31	68.30	-17.99	H	Peak	Pass	Harmonic
99	802.11ac VHT20	165	5932.63	54.48	68.30	-13.82	V	PEAK	Pass	Band Edge
99	802.11ac VHT20	165	17475.00	49.62	68.30	-18.68	H	Peak	Pass	Harmonic
100	802.11ac VHT40	151	5612.56	53.71	68.30	-14.59	V	PEAK	Pass	Band Edge
100	802.11ac VHT40	151	17265.00	50.12	68.30	-18.18	V	Peak	Pass	Harmonic
101	802.11ac VHT40	159	5609.36	54.11	68.30	-14.19	H	PEAK	Pass	Band Edge
101	802.11ac VHT40	159	17385.00	49.10	68.30	-19.20	V	Peak	Pass	Harmonic
102	802.11ac VHT80	155	5927.25	56.27	68.30	-12.03	V	PEAK	Pass	Band Edge
102	802.11ac VHT80	155	17325.00	50.53	68.30	-17.77	H	Peak	Pass	Harmonic
103	802.11ax HE20	149	5618.85	53.49	68.30	-14.81	V	PEAK	Pass	Band Edge
103	802.11ax HE20	149	17235.00	48.87	68.30	-19.43	V	Peak	Pass	Harmonic
104	802.11ax HE20	157	-	-	-	-	-	-	-	Band Edge
104	802.11ax HE20	157	17355.00	49.22	68.30	-19.08	H	Peak	Pass	Harmonic
105	802.11ax HE20	165	5948.75	53.58	68.30	-14.72	H	PEAK	Pass	Band Edge
105	802.11ax HE20	165	17475.00	50.46	68.30	-17.84	H	Peak	Pass	Harmonic
106	802.11ax HE40	151	5926.99	53.91	68.30	-14.39	H	PEAK	Pass	Band Edge
106	802.11ax HE40	151	17265.00	49.82	68.30	-18.48	V	Peak	Pass	Harmonic
107	802.11ax HE40	159	5924.89	55.06	68.38	-13.32	V	PEAK	Pass	Band Edge
107	802.11ax HE40	159	17385.00	50.44	68.30	-17.86	V	Peak	Pass	Harmonic
108	802.11ax HE80	155	5649.70	58.89	68.30	-9.41	V	PEAK	Pass	Band Edge
108	802.11ax HE80	155	17325.00	49.42	68.30	-18.88	V	Peak	Pass	Harmonic
109	802.11ax HE20	149	5648.43	52.96	68.30	-15.34	V	PEAK	Pass	Band Edge
109	802.11ax HE20	149	-	-	-	-	-	-	-	Harmonic



110	802.11ax HE20	165	5941.75	53.66	68.30	-14.64	H	PEAK	Pass	Band Edge
110	802.11ax HE20	165	-	-	-	-	-	-	-	Harmonic
111	802.11ax HE20	149	5634.37	52.69	68.30	-15.61	H	PEAK	Pass	Band Edge
111	802.11ax HE20	149	-	-	-	-	-	-	-	Harmonic
112	802.11ax HE20	165	5945.75	53.24	68.30	-15.06	H	PEAK	Pass	Band Edge
112	802.11ax HE20	165	-	-	-	-	-	-	-	Harmonic
113	802.11ax HE20	149	5643.94	53.34	68.30	-14.96	V	PEAK	Pass	Band Edge
113	802.11ax HE20	149	-	-	-	-	-	-	-	Harmonic
114	802.11ax HE20	165	5936.00	54.07	68.30	-14.23	H	PEAK	Pass	Band Edge
114	802.11ax HE20	165	-	-	-	-	-	-	-	Harmonic
115	802.11be EHT20	149	5615.81	52.96	68.30	-15.34	V	PEAK	Pass	Band Edge
115	802.11be EHT20	149	17235.00	50.27	68.30	-18.03	H	Peak	Pass	Harmonic
116	802.11be EHT20	157	-	-	-	-	-	-	-	Band Edge
116	802.11be EHT20	157	17355.00	50.74	68.30	-17.56	H	Peak	Pass	Harmonic
117	802.11be EHT20	165	5928.50	53.06	68.30	-15.24	V	PEAK	Pass	Band Edge
117	802.11be EHT20	165	17475.00	50.76	68.30	-17.54	V	Peak	Pass	Harmonic
118	802.11be EHT40	151	5925.04	53.42	68.30	-14.88	V	PEAK	Pass	Band Edge
118	802.11be EHT40	151	17265.00	49.00	68.30	-19.30	V	Peak	Pass	Harmonic
119	802.11be EHT40	159	5936.52	53.69	68.30	-14.61	V	PEAK	Pass	Band Edge
119	802.11be EHT40	159	17385.00	49.89	68.30	-18.41	V	Peak	Pass	Harmonic
120	802.11be EHT80	155	5931.45	56.24	68.30	-12.06	V	PEAK	Pass	Band Edge
120	802.11be EHT80	155	17325.00	50.19	68.30	-18.11	V	Peak	Pass	Harmonic
121	802.11a	144	-	-	-	-	-	-	-	Band Edge
121	802.11a	144	17160.00	50.57	68.30	-17.73	H	Peak	Pass	Harmonic
123	802.11ac VHT20	144	-	-	-	-	-	-	-	Band Edge
123	802.11ac VHT20	144	17160.00	49.17	68.30	-19.13	H	Peak	Pass	Harmonic
124	802.11ac VHT40	142	-	-	-	-	-	-	-	Band Edge
124	802.11ac VHT40	142	17130.00	49.20	68.30	-19.10	V	Peak	Pass	Harmonic
125	802.11ac VHT80	138	-	-	-	-	-	-	-	Band Edge
125	802.11ac VHT80	138	17070.00	50.87	68.30	-17.43	V	Peak	Pass	Harmonic
126	802.11ax HE20	144	-	-	-	-	-	-	-	Band Edge
126	802.11ax HE20	144	17160.00	49.08	68.30	-19.22	H	Peak	Pass	Harmonic
127	802.11ax HE40	142	-	-	-	-	-	-	-	Band Edge
127	802.11ax HE40	142	17130.00	49.35	68.30	-18.95	V	Peak	Pass	Harmonic
128	802.11ax HE80	138	-	-	-	-	-	-	-	Band Edge
128	802.11ax HE80	138	17070.00	49.95	68.30	-18.35	H	Peak	Pass	Harmonic
129	802.11be EHT40	142	-	-	-	-	-	-	-	Band Edge
129	802.11be EHT40	142	17130.00	49.22	68.30	-19.08	V	Peak	Pass	Harmonic
130	802.11be EHT80	138	-	-	-	-	-	-	-	Band Edge
130	802.11be EHT80	138	17070.00	49.73	68.30	-18.57	H	Peak	Pass	Harmonic
131	802.11be EHT20	36	5142.20	42.65	54.00	-11.35	H	AVERAGE	Pass	Band Edge
131	802.11be EHT20	36	-	-	-	-	-	-	-	Harmonic



132	802.11be EHT20	64	5352.34	43.20	54.00	-10.80	H	AVERAGE	Pass	Band Edge
132	802.11be EHT20	64	-	-	-	-	-	-	-	Harmonic
133	802.11be EHT20	100	5458.00	43.12	54.00	-10.88	V	AVERAGE	Pass	Band Edge
133	802.11be EHT20	100	-	-	-	-	-	-	-	Harmonic
134	802.11be EHT20	140	5747.91	52.58	68.30	-15.72	H	PEAK	Pass	Band Edge
134	802.11be EHT20	140	-	-	-	-	-	-	-	Harmonic
135	802.11be EHT20	149	5618.27	52.99	68.30	-15.31	H	PEAK	Pass	Band Edge
135	802.11be EHT20	149	-	-	-	-	-	-	-	Harmonic
136	802.11be EHT20	165	5927.75	53.45	68.30	-14.85	V	PEAK	Pass	Band Edge
136	802.11be EHT20	165	-	-	-	-	-	-	-	Harmonic
137	802.11be EHT20	36	5149.22	42.65	54.00	-11.35	H	AVERAGE	Pass	Band Edge
137	802.11be EHT20	36	-	-	-	-	-	-	-	Harmonic
138	802.11be EHT20	64	5352.34	43.53	54.00	-10.47	H	AVERAGE	Pass	Band Edge
138	802.11be EHT20	64	-	-	-	-	-	-	-	Harmonic
139	802.11be EHT20	100	5458.60	43.25	54.00	-10.75	V	AVERAGE	Pass	Band Edge
139	802.11be EHT20	100	-	-	-	-	-	-	-	Harmonic
140	802.11be EHT20	140	5730.29	53.36	68.30	-14.94	V	PEAK	Pass	Band Edge
140	802.11be EHT20	140	-	-	-	-	-	-	-	Harmonic
141	802.11be EHT20	149	5621.17	52.65	68.30	-15.65	H	PEAK	Pass	Band Edge
141	802.11be EHT20	149	-	-	-	-	-	-	-	Harmonic
142	802.11be EHT20	165	5931.00	53.17	68.30	-15.13	V	PEAK	Pass	Band Edge
142	802.11be EHT20	165	-	-	-	-	-	-	-	Harmonic
143	802.11be EHT80	42	5149.94	50.00	54.00	-4.00	H	AVERAGE	Pass	Band Edge
143	802.11be EHT80	42	-	-	-	-	-	-	-	Harmonic
144	802.11be EHT80	58	5350.01	51.43	54.00	-2.57	H	AVERAGE	Pass	Band Edge
144	802.11be EHT80	58	-	-	-	-	-	-	-	Harmonic
145	802.11be EHT80	106	5445.76	46.34	54.00	-7.66	H	AVERAGE	Pass	Band Edge
145	802.11be EHT80	106	-	-	-	-	-	-	-	Harmonic
146	802.11be EHT80	122	5726.87	59.51	68.30	-8.79	H	PEAK	Pass	Band Edge
146	802.11be EHT80	122	-	-	-	-	-	-	-	Harmonic
147	802.11be EHT160	50	5147.50	51.54	54.00	-2.46	H	AVERAGE	Pass	Band Edge
147	802.11be EHT160	50	-	-	-	-	-	-	-	Harmonic
148	802.11be EHT160	50	5147.50	50.18	54.00	-3.82	H	AVERAGE	Pass	Band Edge
148	802.11be EHT160	50	-	-	-	-	-	-	-	Harmonic
149	802.11be EHT160	114	5418.86	50.66	54.00	-3.34	H	AVERAGE	Pass	Band Edge
149	802.11be EHT160	114	-	-	-	-	-	-	-	Harmonic
150	802.11be EHT160	114	5725.42	66.95	68.30	-1.35	V	PEAK	Pass	Band Edge
150	802.11be EHT160	114	-	-	-	-	-	-	-	Harmonic
151	802.11be EHT160	50	5147.75	50.63	54.00	-3.37	V	AVERAGE	Pass	Band Edge
151	802.11be EHT160	50	-	-	-	-	-	-	-	Harmonic
152	802.11be EHT160	50	5148.50	53.42	54.00	-0.58	H	-	Pass	Band Edge
152	802.11be EHT160	50	-	-	-	-	-	-	-	Harmonic







153	802.11be EHT160	114	5441.30	53.47	54.00	-0.53	V	-	Pass	Band Edge
153	802.11be EHT160	114	-	-	-	-	-	-	-	Harmonic
154	802.11be EHT160	114	5458.68	53.17	54.00	-0.83	V	AVERAGE	Pass	Band Edge
154	802.11be EHT160	114	-	-	-	-	-	-	-	Harmonic
155	802.11be EHT80	155	5934.60	54.26	68.30	-14.04	V	PEAK	Pass	Band Edge
155	802.11be EHT80	155	-	-	-	-	-	-	-	Harmonic
156	802.11be EHT80	155	5930.93	54.49	68.30	-13.81	H	PEAK	Pass	Band Edge
156	802.11be EHT80	155	-	-	-	-	-	-	-	Harmonic
157	802.11be EHT80	138	5460.00	42.30	54.00	-11.70	V	AVERAGE	Pass	Band Edge
157	802.11be EHT80	138	-	-	-	-	-	-	-	Harmonic
158	802.11be EHT80	42	5149.10	49.38	54.00	-4.62	V	AVERAGE	Pass	Band Edge
158	802.11be EHT80	42	-	-	-	-	-	-	-	Harmonic
159	802.11be EHT80	58	5351.37	49.57	54.00	-4.43	H	AVERAGE	Pass	Band Edge
159	802.11be EHT80	58	-	-	-	-	-	-	-	Harmonic
160	802.11be EHT80	106	5449.00	46.20	54.00	-7.80	V	AVERAGE	Pass	Band Edge
160	802.11be EHT80	106	-	-	-	-	-	-	-	Harmonic
161	802.11be EHT80	122	5456.86	43.47	54.00	-10.53	H	AVERAGE	Pass	Band Edge
161	802.11be EHT80	122	-	-	-	-	-	-	-	Harmonic
162	802.11be EHT160	50	5354.16	49.01	54.00	-4.99	V	AVERAGE	Pass	Band Edge
162	802.11be EHT160	50	-	-	-	-	-	-	-	Harmonic
163	802.11be EHT160	50	5351.64	46.71	54.00	-7.29	H	AVERAGE	Pass	Band Edge
163	802.11be EHT160	50	-	-	-	-	-	-	-	Harmonic
164	802.11be EHT160	114	5443.72	51.15	54.00	-2.85	H	AVERAGE	Pass	Band Edge
164	802.11be EHT160	114	-	-	-	-	-	-	-	Harmonic
165	802.11be EHT160	114	5469.46	63.79	68.30	-4.51	H	PEAK	Pass	Band Edge
165	802.11be EHT160	114	-	-	-	-	-	-	-	Harmonic
166	802.11be EHT80	155	5650.58	58.86	68.73	-9.87	V	PEAK	Pass	Band Edge
166	802.11be EHT80	155	-	-	-	-	-	-	-	Harmonic
167	802.11be EHT80	155	5925.33	54.72	68.30	-13.58	V	PEAK	Pass	Band Edge
167	802.11be EHT80	155	-	-	-	-	-	-	-	Harmonic
168	802.11ax HE80-LF	106	30.00	28.52	40	-11.48	V	PEAK	Pass	LF
168	802.11ax HE80-LF	106	-	-	-	-	-	-	-	Harmonic
169	802.11a-LF	165	30.00	28.44	40	-11.56	V	PEAK	Pass	LF
169	802.11a-LF	165	-	-	-	-	-	-	-	Harmonic
170	Co-location		5434.42	53.25	54.00	-0.75	H	AVERAGE	Pass	Band Edge
			16590.00	49.87	68.30	-18.43	V	PEAK	Pass	Harmonic
171	802.11be HE20	144	-	-	-	-	-	-	-	Band Edge
171	802.11be HE20	144	17160.00	48.81	68.30	-19.49	V	PEAK	Pass	Harmonic



Mode	1																																																																																	
	Band Edge																																																																																	
	U-NII-1_5.15-5.25_802.11a_CH36_5180MHz																																																																																	
ANT	CDD																																																																																	
Pol.	Horizontal	Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2024-01-05 140 122.5 105.0 87.5 70.0 52.5 35.0 17.5 5000 5036. 5072. 5108. 5144. 5180 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5146.52</td><td>57.50</td><td>74.00</td><td>-16.50</td><td>45.35</td><td>36.11</td><td>8.53</td><td>32.49</td><td>348</td><td>260 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5146.52	57.50	74.00	-16.50	45.35	36.11	8.53	32.49	348	260 PEAK	Level (dBuV/m) Date: 2024-01-05 140 122.5 105.0 87.5 70.0 52.5 35.0 17.5 1000 2200. 3400. 4600. 5800. 7000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5180.00</td><td>111.34</td><td>-----</td><td>-----</td><td>99.12</td><td>36.09</td><td>8.58</td><td>32.45</td><td>348</td><td>260 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5180.00	111.34	-----	-----	99.12	36.09	8.58	32.45	348	260 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5146.52	57.50	74.00	-16.50	45.35	36.11	8.53	32.49	348	260 PEAK																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5180.00	111.34	-----	-----	99.12	36.09	8.58	32.45	348	260 PEAK																																																																									
Avg	Level (dBuV/m) Date: 2024-01-05 140 122.5 105.0 87.5 70.0 52.5 35.0 17.5 5000 5036. 5072. 5108. 5144. 5180 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5149.76</td><td>47.27</td><td>54.00</td><td>-6.73</td><td>35.11</td><td>36.11</td><td>8.54</td><td>32.49</td><td>348</td><td>260 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5149.76	47.27	54.00	-6.73	35.11	36.11	8.54	32.49	348	260 AVERAGE	Level (dBuV/m) Date: 2024-01-05 140 122.5 105.0 87.5 70.0 52.5 35.0 17.5 1000 2200. 3400. 4600. 5800. 7000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5180.00</td><td>105.47</td><td>-----</td><td>-----</td><td>93.25</td><td>36.09</td><td>8.58</td><td>32.45</td><td>348</td><td>260 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5180.00	105.47	-----	-----	93.25	36.09	8.58	32.45	348	260 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5149.76	47.27	54.00	-6.73	35.11	36.11	8.54	32.49	348	260 AVERAGE																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5180.00	105.47	-----	-----	93.25	36.09	8.58	32.45	348	260 AVERAGE																																																																									



Mode	1																																																																																
	Band Edge																																																																																
	U-NII-1_5.15-5.25_802.11a_CH36_5180MHz																																																																																
ANT	CDD																																																																																
Pol.	Vertical					Fundamental																																																																											
Peak																																																																																	
	<table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5145.26</td><td>53.46</td><td>74.00</td><td>-20.54</td><td>41.32</td><td>36.11</td><td>8.53</td><td>32.50</td><td>375</td><td>173</td><td>PEAK</td></tr></tbody></table>						Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	dB	cm	deg	1	5145.26	53.46	74.00	-20.54	41.32	36.11	8.53	32.50	375	173	PEAK	<table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5180.00</td><td>105.50</td><td>-----</td><td>-----</td><td>93.29</td><td>36.10</td><td>8.57</td><td>32.46</td><td>375</td><td>173</td><td>PEAK</td></tr></tbody></table>						Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	dB	cm	deg	1	5180.00	105.50	-----	-----	93.29	36.10	8.57	32.46	375	173
	Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																						
	MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	dB	cm	deg																																																																						
1	5145.26	53.46	74.00	-20.54	41.32	36.11	8.53	32.50	375	173	PEAK																																																																						
	Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																						
	MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	dB	cm	deg																																																																						
1	5180.00	105.50	-----	-----	93.29	36.10	8.57	32.46	375	173	PEAK																																																																						
Avg																																																																																	
	<table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5147.24</td><td>43.96</td><td>54.00</td><td>-10.04</td><td>31.81</td><td>36.11</td><td>8.53</td><td>32.49</td><td>375</td><td>173</td><td>AVERAGE</td></tr></tbody></table>						Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	dB	cm	deg	1	5147.24	43.96	54.00	-10.04	31.81	36.11	8.53	32.49	375	173	AVERAGE	<table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5180.00</td><td>99.28</td><td>-----</td><td>-----</td><td>87.07</td><td>36.10</td><td>8.57</td><td>32.46</td><td>375</td><td>173</td><td>AVERAGE</td></tr></tbody></table>						Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	dB	cm	deg	1	5180.00	99.28	-----	-----	87.07	36.10	8.57	32.46	375	173
	Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																						
	MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	dB	cm	deg																																																																						
1	5147.24	43.96	54.00	-10.04	31.81	36.11	8.53	32.49	375	173	AVERAGE																																																																						
	Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																						
	MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	dB	cm	deg																																																																						
1	5180.00	99.28	-----	-----	87.07	36.10	8.57	32.46	375	173	AVERAGE																																																																						





Mode	1																																																																																																					
	Harmonic																																																																																																					
	U-NII-1_5.15-5.25_802.11a_CH36_5180MHz																																																																																																					
ANT	CDD																																																																																																					
Pol.	Horizontal						Vertical																																																																																															
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)						Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)																																																																																															
	<table><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td></tr><tr><td>1</td><td>10360.00</td><td>48.03</td><td>68.30</td><td>-20.27</td><td>60.89</td><td>38.74</td><td>12.06</td><td>63.66</td><td>148</td><td>360</td><td>Peak</td></tr><tr><td>2</td><td>15540.00</td><td>50.61</td><td>74.00</td><td>-23.39</td><td>59.29</td><td>40.73</td><td>14.58</td><td>63.99</td><td>148</td><td>360</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	1	10360.00	48.03	68.30	-20.27	60.89	38.74	12.06	63.66	148	360	Peak	2	15540.00	50.61	74.00	-23.39	59.29	40.73	14.58	63.99	148	360	Peak	<table><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td></tr><tr><td>1</td><td>10360.00</td><td>46.90</td><td>68.30</td><td>-21.40</td><td>59.76</td><td>38.74</td><td>12.06</td><td>63.66</td><td>152</td><td>0</td><td>Peak</td></tr><tr><td>2</td><td>15540.00</td><td>49.05</td><td>74.00</td><td>-24.95</td><td>57.73</td><td>40.73</td><td>14.58</td><td>63.99</td><td>152</td><td>0</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	1	10360.00	46.90	68.30	-21.40	59.76	38.74	12.06	63.66	152	0	Peak	2	15540.00	49.05	74.00	-24.95	57.73	40.73	14.58	63.99	152	0	Peak
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																															
Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																																																
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB																																																																																																
1	10360.00	48.03	68.30	-20.27	60.89	38.74	12.06	63.66	148	360	Peak																																																																																											
2	15540.00	50.61	74.00	-23.39	59.29	40.73	14.58	63.99	148	360	Peak																																																																																											
Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																																																
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB																																																																																																
1	10360.00	46.90	68.30	-21.40	59.76	38.74	12.06	63.66	152	0	Peak																																																																																											
2	15540.00	49.05	74.00	-24.95	57.73	40.73	14.58	63.99	152	0	Peak																																																																																											



Mode	2																																																																																																																			
	Harmonic																																																																																																																			
	U-NII-1_5.15-5.25_802.11a_CH44_5220MHz																																																																																																																			
ANT	CDD																																																																																																																			
Pol.	Horizontal						Vertical																																																																																																													
Peak Avg	Level (dBuV/m) Date: 2024-01-09 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10440.00</td><td>47.47</td><td>68.30</td><td>-20.83</td><td>60.20</td><td>38.78</td><td>12.12</td><td>63.63</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15660.00</td><td>49.27</td><td>74.00</td><td>-24.73</td><td>57.83</td><td>40.83</td><td>14.64</td><td>64.03</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10440.00	47.47	68.30	-20.83	60.20	38.78	12.12	63.63	---	---	Peak	2	15660.00	49.27	74.00	-24.73	57.83	40.83	14.64	64.03	---	---	Peak	Level (dBuV/m) Date: 2024-01-09 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10440.00</td><td>46.68</td><td>68.30</td><td>-21.62</td><td>59.41</td><td>38.78</td><td>12.12</td><td>63.63</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15660.00</td><td>50.26</td><td>74.00</td><td>-23.74</td><td>58.82</td><td>40.83</td><td>14.64</td><td>64.03</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10440.00	46.68	68.30	-21.62	59.41	38.78	12.12	63.63	---	---	Peak	2	15660.00	50.26	74.00	-23.74	58.82	40.83	14.64	64.03	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																												
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																											
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10440.00	47.47	68.30	-20.83	60.20	38.78	12.12	63.63	---	---	Peak																																																																																																									
2	15660.00	49.27	74.00	-24.73	57.83	40.83	14.64	64.03	---	---	Peak																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10440.00	46.68	68.30	-21.62	59.41	38.78	12.12	63.63	---	---	Peak																																																																																																									
2	15660.00	50.26	74.00	-23.74	58.82	40.83	14.64	64.03	---	---	Peak																																																																																																									



Mode	3																																																																																																	
	Harmonic																																																																																																	
	U-NII-1_5.15-5.25_802.11a_CH48_5240MHz																																																																																																	
ANT	CDD																																																																																																	
Pol.	Horizontal	Vertical																																																																																																
Peak Avg	Level (dBuV/m) Date: 2024-01-12 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 10480.00</td><td>47.55</td><td>68.30</td><td>-20.75</td><td>60.22</td><td>38.79</td><td>12.15</td><td>63.61</td><td>---</td><td>Peak</td></tr><tr><td>2 15720.00</td><td>50.86</td><td>74.00</td><td>-23.14</td><td>59.37</td><td>40.88</td><td>14.66</td><td>64.05</td><td>---</td><td>Peak</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10480.00	47.55	68.30	-20.75	60.22	38.79	12.15	63.61	---	Peak	2 15720.00	50.86	74.00	-23.14	59.37	40.88	14.66	64.05	---	Peak	Level (dBuV/m) Date: 2024-01-12 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 10480.00</td><td>47.75</td><td>68.30</td><td>-20.55</td><td>60.42</td><td>38.79</td><td>12.15</td><td>63.61</td><td>---</td><td>Peak</td></tr><tr><td>2 15720.00</td><td>49.30</td><td>74.00</td><td>-24.70</td><td>57.81</td><td>40.88</td><td>14.66</td><td>64.05</td><td>---</td><td>Peak</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10480.00	47.75	68.30	-20.55	60.42	38.79	12.15	63.61	---	Peak	2 15720.00	49.30	74.00	-24.70	57.81	40.88	14.66	64.05	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																										
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																									
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																									
1 10480.00	47.55	68.30	-20.75	60.22	38.79	12.15	63.61	---	Peak																																																																																									
2 15720.00	50.86	74.00	-23.14	59.37	40.88	14.66	64.05	---	Peak																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																											
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																										
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																									
1 10480.00	47.75	68.30	-20.55	60.42	38.79	12.15	63.61	---	Peak																																																																																									
2 15720.00	49.30	74.00	-24.70	57.81	40.88	14.66	64.05	---	Peak																																																																																									







Mode	4																																																																																																					
	Harmonic																																																																																																					
	U-NII-2A_5.25-5.35_802.11a_CH52_5260MHz																																																																																																					
ANT	CDD																																																																																																					
Pol.	Horizontal	Vertical																																																																																																				
Peak Avg	Level (dBuV/m) Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 10520.00</td><td>47.94</td><td>68.30</td><td>-20.36</td><td>60.55</td><td>38.81</td><td>12.18</td><td>63.60</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2 15780.00</td><td>51.20</td><td>74.00</td><td>-22.80</td><td>59.66</td><td>40.92</td><td>14.69</td><td>64.07</td><td>---</td><td>---</td><td>Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10520.00	47.94	68.30	-20.36	60.55	38.81	12.18	63.60	---	---	Peak	2 15780.00	51.20	74.00	-22.80	59.66	40.92	14.69	64.07	---	---	Peak	Level (dBuV/m) Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 10520.00</td><td>47.83</td><td>68.30</td><td>-20.47</td><td>60.44</td><td>38.81</td><td>12.18</td><td>63.60</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2 15780.00</td><td>49.71</td><td>74.00</td><td>-24.29</td><td>58.17</td><td>40.92</td><td>14.69</td><td>64.07</td><td>---</td><td>---</td><td>Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10520.00	47.83	68.30	-20.47	60.44	38.81	12.18	63.60	---	---	Peak	2 15780.00	49.71	74.00	-24.29	58.17	40.92	14.69	64.07	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																														
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																													
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																													
1 10520.00	47.94	68.30	-20.36	60.55	38.81	12.18	63.60	---	---	Peak																																																																																												
2 15780.00	51.20	74.00	-22.80	59.66	40.92	14.69	64.07	---	---	Peak																																																																																												
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																														
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																													
1 10520.00	47.83	68.30	-20.47	60.44	38.81	12.18	63.60	---	---	Peak																																																																																												
2 15780.00	49.71	74.00	-24.29	58.17	40.92	14.69	64.07	---	---	Peak																																																																																												



Mode	5																																																																																																																																	
	Harmonic																																																																																																																																	
	U-NII-2A_5.25-5.35_802.11a_CH60_5300MHz																																																																																																																																	
ANT	CDD																																																																																																																																	
Pol.	Horizontal						Vertical																																																																																																																											
Peak Avg	Level (dBuV/m) Date: 2024-01-09 Frequency (MHz) <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>10600.00</td><td>46.32</td><td>74.00</td><td>-27.68</td><td>58.82</td><td>38.84</td><td>12.23</td><td>63.57</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15900.00</td><td>49.57</td><td>74.00</td><td>-24.43</td><td>57.91</td><td>41.02</td><td>14.75</td><td>64.11</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	10600.00	46.32	74.00	-27.68	58.82	38.84	12.23	63.57	---	---	Peak	2	15900.00	49.57	74.00	-24.43	57.91	41.02	14.75	64.11	---	---	Peak	Level (dBuV/m) Date: 2024-01-09 Frequency (MHz) <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>10600.00</td><td>47.57</td><td>74.00</td><td>-26.43</td><td>60.07</td><td>38.84</td><td>12.23</td><td>63.57</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15900.00</td><td>50.48</td><td>74.00</td><td>-23.52</td><td>58.82</td><td>41.02</td><td>14.75</td><td>64.11</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	10600.00	47.57	74.00	-26.43	60.07	38.84	12.23	63.57	---	---	Peak	2	15900.00	50.48	74.00	-23.52	58.82	41.02	14.75	64.11	---	---	Peak
			Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																						
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																										
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	10600.00	46.32	74.00	-27.68	58.82	38.84	12.23	63.57	---	---	Peak																																																																																																																							
2	15900.00	49.57	74.00	-24.43	57.91	41.02	14.75	64.11	---	---	Peak																																																																																																																							
		Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	10600.00	47.57	74.00	-26.43	60.07	38.84	12.23	63.57	---	---	Peak																																																																																																																							
2	15900.00	50.48	74.00	-23.52	58.82	41.02	14.75	64.11	---	---	Peak																																																																																																																							



		6																																																																																							
Mode		Band Edge																																																																																							
		U-NII-2A_5.25-5.35_802.11a_CH64_5320MHz																																																																																							
ANT		CDD																																																																																							
Pol.		Horizontal					Fundamental																																																																																		
Peak	Level (dBuV/m) Date: 2024-01-05  Frequency (MHz)					Level (dBuV/m) Date: 2024-01-05  Frequency (MHz)																																																																																			
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5353.18</td><td>64.32</td><td>74.00</td><td>-9.68</td><td>51.16</td><td>35.99</td><td>9.38</td><td>32.21</td><td>400</td><td>92 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5353.18	64.32	74.00	-9.68	51.16	35.99	9.38	32.21	400	92 PEAK	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5320.00</td><td>110.46</td><td>-----</td><td>-----</td><td>97.49</td><td>36.01</td><td>9.21</td><td>32.25</td><td>400</td><td>92 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5320.00	110.46	-----	-----	97.49	36.01	9.21	32.25	400
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5353.18	64.32	74.00	-9.68	51.16	35.99	9.38	32.21	400	92 PEAK																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5320.00	110.46	-----	-----	97.49	36.01	9.21	32.25	400	92 PEAK																																																																																
Avg	Level (dBuV/m) Date: 2024-01-05  Frequency (MHz)					Level (dBuV/m) Date: 2024-01-05  Frequency (MHz)																																																																																			
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5351.78</td><td>53.37</td><td>54.00</td><td>-0.63</td><td>40.22</td><td>35.99</td><td>9.37</td><td>32.21</td><td>400</td><td>92 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5351.78	53.37	54.00	-0.63	40.22	35.99	9.37	32.21	400	92 AVERAGE	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5320.00</td><td>104.12</td><td>-----</td><td>-----</td><td>91.12</td><td>36.00</td><td>9.24</td><td>32.24</td><td>400</td><td>92 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5320.00	104.12	-----	-----	91.12	36.00	9.24	32.24	400
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5351.78	53.37	54.00	-0.63	40.22	35.99	9.37	32.21	400	92 AVERAGE																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5320.00	104.12	-----	-----	91.12	36.00	9.24	32.24	400	92 AVERAGE																																																																																



Mode	6	
	Band Edge	
	U-NII-2A_5.25-5.35_802.11a_CH64_5320MHz	
ANT	CDD	
Pol.	Vertical	Fundamental
Peak	Level (dBuV/m) Date: 2024-01-05 1 5352.48 61.94 74.00 -12.06 48.78 35.99 9.38 32.21 323 184 PEAK	Level (dBuV/m) Date: 2024-01-05 1 5320.00 109.32 ----- 96.35 36.01 9.21 32.25 323 184 PEAK
	Level (dBuV/m) Date: 2024-01-05 1 5350.66 52.67 54.00 -1.33 39.52 35.99 9.37 32.21 323 184 AVERAGE	Level (dBuV/m) Date: 2024-01-05 1 5320.00 102.72 ----- 89.72 36.00 9.24 32.24 323 184 AVERAGE



Mode	6																																																																																																																			
	Harmonic																																																																																																																			
	U-NII-2A_5.25-5.35_802.11a_CH64_5320MHz																																																																																																																			
ANT	CDD																																																																																																																			
Pol.	Horizontal						Vertical																																																																																																													
Peak Avg	Level (dBuV/m) Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10640.00</td><td>47.68</td><td>74.00</td><td>-26.32</td><td>60.11</td><td>38.86</td><td>12.26</td><td>63.55</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15960.00</td><td>50.65</td><td>74.00</td><td>-23.35</td><td>58.94</td><td>41.07</td><td>14.77</td><td>64.13</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10640.00	47.68	74.00	-26.32	60.11	38.86	12.26	63.55	---	---	Peak	2	15960.00	50.65	74.00	-23.35	58.94	41.07	14.77	64.13	---	---	Peak	Level (dBuV/m) Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10640.00</td><td>47.47</td><td>74.00</td><td>-26.53</td><td>59.90</td><td>38.86</td><td>12.26</td><td>63.55</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15960.00</td><td>48.31</td><td>74.00</td><td>-25.69</td><td>56.60</td><td>41.07</td><td>14.77</td><td>64.13</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10640.00	47.47	74.00	-26.53	59.90	38.86	12.26	63.55	---	---	Peak	2	15960.00	48.31	74.00	-25.69	56.60	41.07	14.77	64.13	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																												
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																											
1	10640.00	47.68	74.00	-26.32	60.11	38.86	12.26	63.55	---	---	Peak																																																																																																									
2	15960.00	50.65	74.00	-23.35	58.94	41.07	14.77	64.13	---	---	Peak																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																											
1	10640.00	47.47	74.00	-26.53	59.90	38.86	12.26	63.55	---	---	Peak																																																																																																									
2	15960.00	48.31	74.00	-25.69	56.60	41.07	14.77	64.13	---	---	Peak																																																																																																									



		7																																																															
Mode		Band Edge																																																															
		U-NII-2C_5.47-5.725_802.11a_CH100_5500MHz																																																															
ANT		CDD																																																															
Pol.		Horizontal					Fundamental																																																										
Peak	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor dB cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5456.95</td><td>53.21</td><td>74.00</td><td>-20.79</td><td>39.65</td><td>35.93</td><td>9.69</td><td>32.06</td><td>100</td><td>212 PEAK</td></tr><tr><td>2</td><td>5469.40</td><td>55.76</td><td>68.30</td><td>-12.54</td><td>42.19</td><td>35.92</td><td>9.69</td><td>32.04</td><td>100</td><td>212 PEAK</td></tr></table>						MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5456.95	53.21	74.00	-20.79	39.65	35.93	9.69	32.06	100	212 PEAK	2	5469.40	55.76	68.30	-12.54	42.19	35.92	9.69	32.04	100	212 PEAK	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor dB cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5500.00</td><td>111.47</td><td>-----</td><td>-----</td><td>97.86</td><td>35.91</td><td>9.71</td><td>32.01</td><td>100</td><td>212 PEAK</td></tr></table>						MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5500.00	111.47	-----	-----	97.86	35.91	9.71	32.01	100	212 PEAK
		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																							
1	5456.95	53.21	74.00	-20.79	39.65	35.93	9.69	32.06	100	212 PEAK																																																							
2	5469.40	55.76	68.30	-12.54	42.19	35.92	9.69	32.04	100	212 PEAK																																																							
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																								
1	5500.00	111.47	-----	-----	97.86	35.91	9.71	32.01	100	212 PEAK																																																							
Avg	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor dB cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5459.95</td><td>45.41</td><td>54.00</td><td>-8.59</td><td>31.86</td><td>35.92</td><td>9.69</td><td>32.06</td><td>100</td><td>212 AVERAGE</td></tr></table>						MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5459.95	45.41	54.00	-8.59	31.86	35.92	9.69	32.06	100	212 AVERAGE	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor dB cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5500.00</td><td>104.10</td><td>-----</td><td>-----</td><td>90.49</td><td>35.91</td><td>9.71</td><td>32.01</td><td>100</td><td>212 AVERAGE</td></tr></table>						MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5500.00	104.10	-----	-----	90.49	35.91	9.71	32.01	100	212 AVERAGE											
		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																							
1	5459.95	45.41	54.00	-8.59	31.86	35.92	9.69	32.06	100	212 AVERAGE																																																							
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																								
1	5500.00	104.10	-----	-----	90.49	35.91	9.71	32.01	100	212 AVERAGE																																																							



		7																																																															
Mode		Band Edge																																																															
		U-NII-2C_5.47-5.725_802.11a_CH100_5500MHz																																																															
ANT		CDD																																																															
Pol.		Vertical					Fundamental																																																										
Peak	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5438.95</td><td>54.54</td><td>74.00</td><td>-19.46</td><td>41.01</td><td>35.94</td><td>9.68</td><td>32.09</td><td>312</td><td>194 PEAK</td></tr><tr><td>2</td><td>5466.40</td><td>54.72</td><td>68.30</td><td>-13.58</td><td>41.16</td><td>35.92</td><td>9.69</td><td>32.05</td><td>312</td><td>194 PEAK</td></tr></table> Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5500.00</td><td>107.81</td><td>-----</td><td>-----</td><td>94.20</td><td>35.91</td><td>9.71</td><td>32.01</td><td>312</td><td>194 PEAK</td></tr></table>											MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5438.95	54.54	74.00	-19.46	41.01	35.94	9.68	32.09	312	194 PEAK	2	5466.40	54.72	68.30	-13.58	41.16	35.92	9.69	32.05	312	194 PEAK		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5500.00	107.81	-----	-----	94.20	35.91	9.71	32.01	312	194 PEAK
		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																																						
1	5438.95	54.54	74.00	-19.46	41.01	35.94	9.68	32.09	312	194 PEAK																																																							
2	5466.40	54.72	68.30	-13.58	41.16	35.92	9.69	32.05	312	194 PEAK																																																							
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																																							
1	5500.00	107.81	-----	-----	94.20	35.91	9.71	32.01	312	194 PEAK																																																							
Avg	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5455.75</td><td>44.51</td><td>54.00</td><td>-9.49</td><td>30.95</td><td>35.93</td><td>9.69</td><td>32.06</td><td>312</td><td>194 AVERAGE</td></tr></table> Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5500.00</td><td>100.81</td><td>-----</td><td>-----</td><td>87.20</td><td>35.91</td><td>9.71</td><td>32.01</td><td>312</td><td>194 AVERAGE</td></tr></table>											MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5455.75	44.51	54.00	-9.49	30.95	35.93	9.69	32.06	312	194 AVERAGE		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5500.00	100.81	-----	-----	87.20	35.91	9.71	32.01	312	194 AVERAGE											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																																							
1	5455.75	44.51	54.00	-9.49	30.95	35.93	9.69	32.06	312	194 AVERAGE																																																							
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																																							
1	5500.00	100.81	-----	-----	87.20	35.91	9.71	32.01	312	194 AVERAGE																																																							



Mode	7																																																																																																					
	Harmonic																																																																																																					
	U-NII-2C_5.47-5.725_802.11a_CH100_5500MHz																																																																																																					
ANT	CDD																																																																																																					
Pol.	Horizontal	Vertical																																																																																																				
Peak Avg	Level (dBuV/m) Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11000.00</td><td>49.99</td><td>74.00</td><td>-24.01</td><td>61.89</td><td>39.00</td><td>12.52</td><td>63.42</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2 16500.00</td><td>48.24</td><td>68.30</td><td>-20.06</td><td>56.38</td><td>41.35</td><td>15.17</td><td>64.66</td><td>---</td><td>---</td><td>Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11000.00	49.99	74.00	-24.01	61.89	39.00	12.52	63.42	---	---	Peak	2 16500.00	48.24	68.30	-20.06	56.38	41.35	15.17	64.66	---	---	Peak	Level (dBuV/m) Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11000.00</td><td>49.81</td><td>74.00</td><td>-24.19</td><td>61.71</td><td>39.00</td><td>12.52</td><td>63.42</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2 16500.00</td><td>49.48</td><td>68.30</td><td>-18.82</td><td>57.62</td><td>41.35</td><td>15.17</td><td>64.66</td><td>---</td><td>---</td><td>Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11000.00	49.81	74.00	-24.19	61.71	39.00	12.52	63.42	---	---	Peak	2 16500.00	49.48	68.30	-18.82	57.62	41.35	15.17	64.66	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																														
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																													
1 11000.00	49.99	74.00	-24.01	61.89	39.00	12.52	63.42	---	---	Peak																																																																																												
2 16500.00	48.24	68.30	-20.06	56.38	41.35	15.17	64.66	---	---	Peak																																																																																												
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																														
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																													
1 11000.00	49.81	74.00	-24.19	61.71	39.00	12.52	63.42	---	---	Peak																																																																																												
2 16500.00	49.48	68.30	-18.82	57.62	41.35	15.17	64.66	---	---	Peak																																																																																												



Mode	8																																																																																																					
	Harmonic																																																																																																					
	U-NII-2C_5.47-5.725_802.11a_CH116_5580MHz																																																																																																					
ANT	CDD																																																																																																					
Pol.	Horizontal						Vertical																																																																																															
Peak Avg	Level (dBuV/m) Date: 2024-01-09 Frequency (MHz) <table><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td></tr><tr><td>1</td><td>11160.00</td><td>48.24</td><td>74.00</td><td>-25.76</td><td>59.97</td><td>39.06</td><td>12.64</td><td>63.43</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>16740.00</td><td>49.65</td><td>68.30</td><td>-18.65</td><td>57.74</td><td>41.47</td><td>15.35</td><td>64.91</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	1	11160.00	48.24	74.00	-25.76	59.97	39.06	12.64	63.43	---	---	Peak	2	16740.00	49.65	68.30	-18.65	57.74	41.47	15.35	64.91	---	---	Peak	Level (dBuV/m) Date: 2024-01-09 Frequency (MHz) <table><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td></tr><tr><td>1</td><td>11160.00</td><td>48.76</td><td>74.00</td><td>-25.24</td><td>60.49</td><td>39.06</td><td>12.64</td><td>63.43</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>16740.00</td><td>49.85</td><td>68.30</td><td>-18.45</td><td>57.94</td><td>41.47</td><td>15.35</td><td>64.91</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	1	11160.00	48.76	74.00	-25.24	60.49	39.06	12.64	63.43	---	---	Peak	2	16740.00	49.85	68.30	-18.45	57.94	41.47	15.35	64.91	---	---	Peak
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																															
	Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB																																																																																																
1	11160.00	48.24	74.00	-25.76	59.97	39.06	12.64	63.43	---	---	Peak																																																																																											
2	16740.00	49.65	68.30	-18.65	57.74	41.47	15.35	64.91	---	---	Peak																																																																																											
Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																																																
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB																																																																																																
1	11160.00	48.76	74.00	-25.24	60.49	39.06	12.64	63.43	---	---	Peak																																																																																											
2	16740.00	49.85	68.30	-18.45	57.94	41.47	15.35	64.91	---	---	Peak																																																																																											



Mode	9																																																																																		
	Band Edge																																																																																		
	U-NII-2C_5.47-5.725_802.11a_CH140_5700MHz																																																																																		
ANT	CDD																																																																																		
Pol.	Horizontal	Fundamental																																																																																	
Peak	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5725.35</td><td>58.37</td><td>68.30</td><td>-9.93</td><td>44.36</td><td>36.22</td><td>10.02</td><td>32.23</td><td>100</td><td>252 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5725.35	58.37	68.30	-9.93	44.36	36.22	10.02	32.23	100	252 PEAK	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5700.00</td><td>110.50</td><td>-----</td><td>96.54</td><td>36.19</td><td>9.97</td><td>32.20</td><td>100</td><td>252 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5700.00	110.50	-----	96.54	36.19	9.97	32.20	100	252 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																										
1	5725.35	58.37	68.30	-9.93	44.36	36.22	10.02	32.23	100	252 PEAK																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																										
1	5700.00	110.50	-----	96.54	36.19	9.97	32.20	100	252 PEAK																																																																										
Avg	Blank	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5700.00</td><td>103.74</td><td>-----</td><td>89.78</td><td>36.19</td><td>9.97</td><td>32.20</td><td>100</td><td>252 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5700.00	103.74	-----	89.78	36.19	9.97	32.20	100	252 AVERAGE																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																										
1	5700.00	103.74	-----	89.78	36.19	9.97	32.20	100	252 AVERAGE																																																																										



Mode	9																																																																																															
	Band Edge																																																																																															
	U-NII-2C_5.47-5.725_802.11a_CH140_5700MHz																																																																																															
ANT	CDD																																																																																															
Pol.	Vertical						Fundamental																																																																																									
Peak	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5726.13</td><td>57.35</td><td>68.30</td><td>-10.95</td><td>43.34</td><td>36.22</td><td>10.02</td><td>32.23</td><td>392</td><td>184</td><td>PEAK</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5726.13	57.35	68.30	-10.95	43.34	36.22	10.02	32.23	392	184	PEAK	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5700.00</td><td>108.80</td><td>-----</td><td>-----</td><td>94.84</td><td>36.19</td><td>9.97</td><td>32.20</td><td>392</td><td>184</td><td>PEAK</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5700.00	108.80	-----	-----	94.84	36.19	9.97	32.20	392	184	PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																							
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																							
1	5726.13	57.35	68.30	-10.95	43.34	36.22	10.02	32.23	392	184	PEAK																																																																																					
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																							
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																							
1	5700.00	108.80	-----	-----	94.84	36.19	9.97	32.20	392	184	PEAK																																																																																					
Avg	Blank						Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5700.00</td><td>101.23</td><td>-----</td><td>-----</td><td>87.27</td><td>36.19</td><td>9.97</td><td>32.20</td><td>392</td><td>184</td><td>AVERAGE</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5700.00	101.23	-----	-----	87.27	36.19	9.97	32.20	392	184	AVERAGE																																										
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																							
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																							
1	5700.00	101.23	-----	-----	87.27	36.19	9.97	32.20	392	184	AVERAGE																																																																																					



Mode	9																																																																																																					
	Harmonic																																																																																																					
	U-NII-2C_5.47-5.725_802.11a_CH140_5700MHz																																																																																																					
ANT	CDD																																																																																																					
Pol.	Horizontal						Vertical																																																																																															
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td></tr><tr><td>1</td><td>11400.00</td><td>48.56</td><td>74.00</td><td>-25.44</td><td>60.03</td><td>39.16</td><td>12.81</td><td>63.44</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>17100.00</td><td>50.07</td><td>68.30</td><td>-18.23</td><td>57.97</td><td>41.71</td><td>15.62</td><td>65.23</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	1	11400.00	48.56	74.00	-25.44	60.03	39.16	12.81	63.44	---	---	Peak	2	17100.00	50.07	68.30	-18.23	57.97	41.71	15.62	65.23	---	---	Peak	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td></tr><tr><td>1</td><td>11400.00</td><td>48.70</td><td>74.00</td><td>-25.30</td><td>60.17</td><td>39.16</td><td>12.81</td><td>63.44</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>17100.00</td><td>49.60</td><td>68.30</td><td>-18.70</td><td>57.50</td><td>41.71</td><td>15.62</td><td>65.23</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	1	11400.00	48.70	74.00	-25.30	60.17	39.16	12.81	63.44	---	---	Peak	2	17100.00	49.60	68.30	-18.70	57.50	41.71	15.62	65.23	---	---	Peak
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																															
	Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB																																																																																																
1	11400.00	48.56	74.00	-25.44	60.03	39.16	12.81	63.44	---	---	Peak																																																																																											
2	17100.00	50.07	68.30	-18.23	57.97	41.71	15.62	65.23	---	---	Peak																																																																																											
Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																																																
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB																																																																																																
1	11400.00	48.70	74.00	-25.30	60.17	39.16	12.81	63.44	---	---	Peak																																																																																											
2	17100.00	49.60	68.30	-18.70	57.50	41.71	15.62	65.23	---	---	Peak																																																																																											





Mode	10																																																																											
	Band Edge																																																																											
	U-NII-1_5.15-5.25_802.11ac VHT20_CH36_5180MHz																																																																											
ANT	CDD																																																																											
Pol.	Horizontal	Fundamental																																																																										
Peak	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5143.28</td><td>56.57</td><td>74.00</td><td>-17.43</td><td>44.44</td><td>36.11</td><td>8.52</td><td>32.50</td><td>378 107 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5143.28	56.57	74.00	-17.43	44.44	36.11	8.52	32.50	378 107 PEAK	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5180.00</td><td>111.96</td><td>-----</td><td>-----</td><td>99.74</td><td>36.09</td><td>8.58</td><td>32.45</td><td>378 107 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5180.00	111.96	-----	-----	99.74	36.09	8.58	32.45	378 107 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5143.28	56.57	74.00	-17.43	44.44	36.11	8.52	32.50	378 107 PEAK																																																																			
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5180.00	111.96	-----	-----	99.74	36.09	8.58	32.45	378 107 PEAK																																																																			
Avg	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5149.76</td><td>47.05</td><td>54.00</td><td>-6.95</td><td>34.89</td><td>36.11</td><td>8.54</td><td>32.49</td><td>378 107 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5149.76	47.05	54.00	-6.95	34.89	36.11	8.54	32.49	378 107 AVERAGE	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5180.00</td><td>104.31</td><td>-----</td><td>-----</td><td>92.09</td><td>36.09</td><td>8.58</td><td>32.45</td><td>378 107 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5180.00	104.31	-----	-----	92.09	36.09	8.58	32.45	378 107 AVERAGE
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5149.76	47.05	54.00	-6.95	34.89	36.11	8.54	32.49	378 107 AVERAGE																																																																			
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5180.00	104.31	-----	-----	92.09	36.09	8.58	32.45	378 107 AVERAGE																																																																			



Mode	10																																									
	Band Edge																																									
	U-NII-1_5.15-5.25_802.11ac VHT20_CH36_5180MHz																																									
ANT	CDD																																									
Pol.	Vertical	Fundamental																																								
Peak	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5149.94</td><td>54.19</td><td>74.00</td><td>-19.81</td><td>42.03</td><td>36.11</td><td>8.54</td><td>32.49</td><td>400</td><td>176 PEAK</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5149.94	54.19	74.00	-19.81	42.03	36.11	8.54	32.49	400	176 PEAK	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5180.00</td><td>106.11</td><td>-----</td><td>-----</td><td>93.85</td><td>36.09</td><td>8.61</td><td>32.44</td><td>400</td><td>176 PEAK</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5180.00	106.11	-----	-----	93.85	36.09	8.61	32.44	400	176 PEAK
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																
1 5149.94	54.19	74.00	-19.81	42.03	36.11	8.54	32.49	400	176 PEAK																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																	
1 5180.00	106.11	-----	-----	93.85	36.09	8.61	32.44	400	176 PEAK																																	
Avg	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5149.76</td><td>45.16</td><td>54.00</td><td>-8.84</td><td>33.00</td><td>36.11</td><td>8.54</td><td>32.49</td><td>400</td><td>176 AVERAGE</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5149.76	45.16	54.00	-8.84	33.00	36.11	8.54	32.49	400	176 AVERAGE	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5180.00</td><td>99.89</td><td>-----</td><td>-----</td><td>87.68</td><td>36.10</td><td>8.57</td><td>32.46</td><td>400</td><td>176 AVERAGE</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5180.00	99.89	-----	-----	87.68	36.10	8.57	32.46	400	176 AVERAGE
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																	
1 5149.76	45.16	54.00	-8.84	33.00	36.11	8.54	32.49	400	176 AVERAGE																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																	
1 5180.00	99.89	-----	-----	87.68	36.10	8.57	32.46	400	176 AVERAGE																																	



Mode	10																																																																																															
	Harmonic																																																																																															
	U-NII-1_5.15-5.25_802.11ac VHT20_CH36_5180MHz																																																																																															
ANT	CDD																																																																																															
Pol.	Horizontal						Vertical																																																																																									
Peak Avg																																																																																																
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr></thead><tbody><tr><td>1</td><td>10360.00</td><td>48.62</td><td>68.30</td><td>-19.68</td><td>61.48</td><td>38.74</td><td>12.06</td><td>63.66</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15540.00</td><td>50.96</td><td>74.00</td><td>-23.04</td><td>59.64</td><td>40.73</td><td>14.58</td><td>63.99</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	1	10360.00	48.62	68.30	-19.68	61.48	38.74	12.06	63.66	---	---	Peak	2	15540.00	50.96	74.00	-23.04	59.64	40.73	14.58	63.99	---	---	Peak	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr></thead><tbody><tr><td>1</td><td>10360.00</td><td>48.21</td><td>68.30</td><td>-20.09</td><td>61.07</td><td>38.74</td><td>12.06</td><td>63.66</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15540.00</td><td>50.06</td><td>74.00</td><td>-23.94</td><td>58.74</td><td>40.73</td><td>14.58</td><td>63.99</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	1	10360.00	48.21	68.30	-20.09	61.07	38.74	12.06	63.66	---	---	Peak	2	15540.00	50.06	74.00	-23.94	58.74	40.73	14.58	63.99	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																								
1	10360.00	48.62	68.30	-19.68	61.48	38.74	12.06	63.66	---	---	Peak																																																																																					
2	15540.00	50.96	74.00	-23.04	59.64	40.73	14.58	63.99	---	---	Peak																																																																																					
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																								
1	10360.00	48.21	68.30	-20.09	61.07	38.74	12.06	63.66	---	---	Peak																																																																																					
2	15540.00	50.06	74.00	-23.94	58.74	40.73	14.58	63.99	---	---	Peak																																																																																					
<table><thead><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>10360.00</td><td>48.62</td><td>68.30</td><td>-19.68</td><td>61.48</td><td>38.74</td><td>12.06</td><td>63.66</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15540.00</td><td>50.96</td><td>74.00</td><td>-23.04</td><td>59.64</td><td>40.73</td><td>14.58</td><td>63.99</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10360.00	48.62	68.30	-19.68	61.48	38.74	12.06	63.66	---	---	Peak	2	15540.00	50.96	74.00	-23.04	59.64	40.73	14.58	63.99	---	---	Peak	<table><thead><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>10360.00</td><td>48.21</td><td>68.30</td><td>-20.09</td><td>61.07</td><td>38.74</td><td>12.06</td><td>63.66</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15540.00</td><td>50.06</td><td>74.00</td><td>-23.94</td><td>58.74</td><td>40.73</td><td>14.58</td><td>63.99</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10360.00	48.21	68.30	-20.09	61.07	38.74	12.06	63.66	---	---	Peak	2	15540.00	50.06	74.00	-23.94	58.74	40.73	14.58	63.99	---	---	Peak																	
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																							
1	10360.00	48.62	68.30	-19.68	61.48	38.74	12.06	63.66	---	---	Peak																																																																																					
2	15540.00	50.96	74.00	-23.04	59.64	40.73	14.58	63.99	---	---	Peak																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																							
1	10360.00	48.21	68.30	-20.09	61.07	38.74	12.06	63.66	---	---	Peak																																																																																					
2	15540.00	50.06	74.00	-23.94	58.74	40.73	14.58	63.99	---	---	Peak																																																																																					





Mode	11																																																																																																																																	
	Harmonic																																																																																																																																	
	U-NII-1_5.15-5.25_802.11ac VHT20_CH44_5220MHz																																																																																																																																	
ANT	CDD																																																																																																																																	
Pol.	Horizontal						Vertical																																																																																																																											
Peak Avg	Level (dBuV/m) Date: 2024-01-12 <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>10440.00</td><td>48.16</td><td>68.30</td><td>-20.14</td><td>60.89</td><td>38.78</td><td>12.12</td><td>63.63</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15660.00</td><td>51.10</td><td>74.00</td><td>-22.90</td><td>59.66</td><td>40.83</td><td>14.64</td><td>64.03</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	10440.00	48.16	68.30	-20.14	60.89	38.78	12.12	63.63	---	---	Peak	2	15660.00	51.10	74.00	-22.90	59.66	40.83	14.64	64.03	---	---	Peak	Level (dBuV/m) Date: 2024-01-12 <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>10440.00</td><td>48.74</td><td>68.30</td><td>-19.56</td><td>61.47</td><td>38.78</td><td>12.12</td><td>63.63</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15660.00</td><td>48.89</td><td>74.00</td><td>-25.11</td><td>57.45</td><td>40.83</td><td>14.64</td><td>64.03</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	10440.00	48.74	68.30	-19.56	61.47	38.78	12.12	63.63	---	---	Peak	2	15660.00	48.89	74.00	-25.11	57.45	40.83	14.64	64.03	---	---	Peak
			Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																						
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																										
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	10440.00	48.16	68.30	-20.14	60.89	38.78	12.12	63.63	---	---	Peak																																																																																																																							
2	15660.00	51.10	74.00	-22.90	59.66	40.83	14.64	64.03	---	---	Peak																																																																																																																							
		Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	10440.00	48.74	68.30	-19.56	61.47	38.78	12.12	63.63	---	---	Peak																																																																																																																							
2	15660.00	48.89	74.00	-25.11	57.45	40.83	14.64	64.03	---	---	Peak																																																																																																																							



Mode	12																																																																																																															
	Harmonic																																																																																																															
	U-NII-1_5.15-5.25_802.11ac VHT20_CH48_5240MHz																																																																																																															
ANT	CDD																																																																																																															
Pol.	Horizontal					Vertical																																																																																																										
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th colspan="2"></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10480.00</td><td>47.83</td><td>68.30</td><td>-20.47</td><td>60.50</td><td>38.79</td><td>12.15</td><td>63.61</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15720.00</td><td>51.03</td><td>74.00</td><td>-22.97</td><td>59.54</td><td>40.88</td><td>14.66</td><td>64.05</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10480.00	47.83	68.30	-20.47	60.50	38.79	12.15	63.61	---	Peak	2	15720.00	51.03	74.00	-22.97	59.54	40.88	14.66	64.05	---	Peak	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th colspan="2"></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10480.00</td><td>49.01</td><td>68.30</td><td>-19.29</td><td>61.68</td><td>38.79</td><td>12.15</td><td>63.61</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15720.00</td><td>49.64</td><td>74.00</td><td>-24.36</td><td>58.15</td><td>40.88</td><td>14.66</td><td>64.05</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10480.00	49.01	68.30	-19.29	61.68	38.79	12.15	63.61	---	Peak	2	15720.00	49.64	74.00	-24.36	58.15	40.88	14.66	64.05	---	Peak
			Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																						
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																								
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																							
1	10480.00	47.83	68.30	-20.47	60.50	38.79	12.15	63.61	---	Peak																																																																																																						
2	15720.00	51.03	74.00	-22.97	59.54	40.88	14.66	64.05	---	Peak																																																																																																						
		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																									
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																							
1	10480.00	49.01	68.30	-19.29	61.68	38.79	12.15	63.61	---	Peak																																																																																																						
2	15720.00	49.64	74.00	-24.36	58.15	40.88	14.66	64.05	---	Peak																																																																																																						



Mode	13																																																																																																																			
	Harmonic																																																																																																																			
	U-NII-2A_5.25-5.35_802.11ac VHT20_CH52_5260MHz																																																																																																																			
ANT	CDD																																																																																																																			
Pol.	Horizontal						Vertical																																																																																																													
Peak Avg																																																																																																																				
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10520.00</td><td>47.94</td><td>68.30</td><td>-20.36</td><td>60.55</td><td>38.81</td><td>12.18</td><td>63.60</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15780.00</td><td>51.37</td><td>74.00</td><td>-22.63</td><td>59.83</td><td>40.92</td><td>14.69</td><td>64.07</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10520.00	47.94	68.30	-20.36	60.55	38.81	12.18	63.60	---	---	Peak	2	15780.00	51.37	74.00	-22.63	59.83	40.92	14.69	64.07	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10520.00</td><td>48.56</td><td>68.30</td><td>-19.74</td><td>61.17</td><td>38.81</td><td>12.18</td><td>63.60</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15780.00</td><td>49.48</td><td>74.00</td><td>-24.52</td><td>57.94</td><td>40.92</td><td>14.69</td><td>64.07</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10520.00	48.56	68.30	-19.74	61.17	38.81	12.18	63.60	---	---	Peak	2	15780.00	49.48	74.00	-24.52	57.94	40.92	14.69	64.07	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																												
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10520.00	47.94	68.30	-20.36	60.55	38.81	12.18	63.60	---	---	Peak																																																																																																									
2	15780.00	51.37	74.00	-22.63	59.83	40.92	14.69	64.07	---	---	Peak																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10520.00	48.56	68.30	-19.74	61.17	38.81	12.18	63.60	---	---	Peak																																																																																																									
2	15780.00	49.48	74.00	-24.52	57.94	40.92	14.69	64.07	---	---	Peak																																																																																																									



Mode	14																																																																																																											
	Harmonic																																																																																																											
	U-NII-2A_5.25-5.35_802.11ac VHT20_CH60_5300MHz																																																																																																											
ANT	CDD																																																																																																											
Pol.	Horizontal					Vertical																																																																																																						
Peak Avg	Level (dBuV/m) Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th></th><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10600.00</td><td>47.56</td><td>74.00</td><td>-26.44</td><td>60.06</td><td>38.84</td><td>12.23</td><td>63.57</td><td>--- Peak</td></tr><tr><td>2</td><td>15900.00</td><td>52.00</td><td>74.00</td><td>-22.00</td><td>60.34</td><td>41.02</td><td>14.75</td><td>64.11</td><td>--- Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10600.00	47.56	74.00	-26.44	60.06	38.84	12.23	63.57	--- Peak	2	15900.00	52.00	74.00	-22.00	60.34	41.02	14.75	64.11	--- Peak	Level (dBuV/m) Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th></th><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10600.00</td><td>47.67</td><td>74.00</td><td>-26.33</td><td>60.17</td><td>38.84</td><td>12.23</td><td>63.57</td><td>--- Peak</td></tr><tr><td>2</td><td>15900.00</td><td>50.24</td><td>74.00</td><td>-23.76</td><td>58.58</td><td>41.02</td><td>14.75</td><td>64.11</td><td>--- Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10600.00	47.67	74.00	-26.33	60.17	38.84	12.23	63.57	--- Peak	2	15900.00	50.24	74.00	-23.76	58.58	41.02	14.75	64.11	--- Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																				
		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																		
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																			
1	10600.00	47.56	74.00	-26.44	60.06	38.84	12.23	63.57	--- Peak																																																																																																			
2	15900.00	52.00	74.00	-22.00	60.34	41.02	14.75	64.11	--- Peak																																																																																																			
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																					
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																			
1	10600.00	47.67	74.00	-26.33	60.17	38.84	12.23	63.57	--- Peak																																																																																																			
2	15900.00	50.24	74.00	-23.76	58.58	41.02	14.75	64.11	--- Peak																																																																																																			



Mode	15																																																																																	
	Band Edge																																																																																	
	U-NII-2A_5.25-5.35_802.11ac VHT20_CH64_5320MHz																																																																																	
ANT	CDD																																																																																	
Pol.	Horizontal	Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5352.48</td><td>59.56</td><td>74.00</td><td>-14.44</td><td>46.40</td><td>35.99</td><td>9.38</td><td>32.21</td><td>400</td><td>95 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5352.48	59.56	74.00	-14.44	46.40	35.99	9.38	32.21	400	95 PEAK	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5320.00</td><td>110.41</td><td>-----</td><td>-----</td><td>97.48</td><td>36.01</td><td>9.18</td><td>32.26</td><td>400</td><td>95 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5320.00	110.41	-----	-----	97.48	36.01	9.18	32.26	400	95 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5352.48	59.56	74.00	-14.44	46.40	35.99	9.38	32.21	400	95 PEAK																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5320.00	110.41	-----	-----	97.48	36.01	9.18	32.26	400	95 PEAK																																																																									
Avg	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5351.08</td><td>50.91</td><td>54.00</td><td>-3.09</td><td>37.76</td><td>35.99</td><td>9.37</td><td>32.21</td><td>400</td><td>95 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5351.08	50.91	54.00	-3.09	37.76	35.99	9.37	32.21	400	95 AVERAGE	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5320.00</td><td>103.97</td><td>-----</td><td>-----</td><td>91.04</td><td>36.01</td><td>9.18</td><td>32.26</td><td>400</td><td>95 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5320.00	103.97	-----	-----	91.04	36.01	9.18	32.26	400	95 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5351.08	50.91	54.00	-3.09	37.76	35.99	9.37	32.21	400	95 AVERAGE																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5320.00	103.97	-----	-----	91.04	36.01	9.18	32.26	400	95 AVERAGE																																																																									







Mode	15	
	Band Edge	
	U-NII-2A_5.25-5.35_802.11ac VHT20_CH64_5320MHz	
ANT	CDD	
Pol.	Vertical	Fundamental
Peak	Level (dBuV/m) Date: 2024-01-05 1 5350.38 57.95 74.00 -16.05 44.80 35.99 9.37 32.21 323 180 PEAK	Level (dBuV/m) Date: 2024-01-05 1 5320.00 109.39 ----- 96.39 36.00 9.24 32.24 323 180 PEAK
	Level (dBuV/m) Date: 2024-01-05 1 5351.78 48.36 54.00 -5.64 35.21 35.99 9.37 32.21 323 180 AVERAGE	Level (dBuV/m) Date: 2024-01-05 1 5320.00 102.28 ----- 89.28 36.00 9.24 32.24 323 180 AVERAGE



Mode	15																																																																																																									
	Harmonic																																																																																																									
	U-NII-2A_5.25-5.35_802.11ac VHT20_CH64_5320MHz																																																																																																									
ANT	CDD																																																																																																									
Pol.	Horizontal					Vertical																																																																																																				
Peak Avg	Level (dBuV/m) Date: 2024-01-12 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 10640.00</td><td>47.22</td><td>74.00</td><td>-26.78</td><td>59.65</td><td>38.86</td><td>12.26</td><td>63.55</td><td>---</td><td>--- Peak</td></tr><tr><td>2 15960.00</td><td>50.81</td><td>74.00</td><td>-23.19</td><td>59.10</td><td>41.07</td><td>14.77</td><td>64.13</td><td>---</td><td>--- Peak</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10640.00	47.22	74.00	-26.78	59.65	38.86	12.26	63.55	---	--- Peak	2 15960.00	50.81	74.00	-23.19	59.10	41.07	14.77	64.13	---	--- Peak	Level (dBuV/m) Date: 2024-01-12 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 10640.00</td><td>47.94</td><td>74.00</td><td>-26.06</td><td>60.37</td><td>38.86</td><td>12.26</td><td>63.55</td><td>---</td><td>--- Peak</td></tr><tr><td>2 15960.00</td><td>49.12</td><td>74.00</td><td>-24.88</td><td>57.41</td><td>41.07</td><td>14.77</td><td>64.13</td><td>---</td><td>--- Peak</td></tr></tbody></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10640.00	47.94	74.00	-26.06	60.37	38.86	12.26	63.55	---	--- Peak	2 15960.00	49.12	74.00	-24.88	57.41	41.07	14.77	64.13	---	--- Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																		
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																	
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																	
1 10640.00	47.22	74.00	-26.78	59.65	38.86	12.26	63.55	---	--- Peak																																																																																																	
2 15960.00	50.81	74.00	-23.19	59.10	41.07	14.77	64.13	---	--- Peak																																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																		
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																	
1 10640.00	47.94	74.00	-26.06	60.37	38.86	12.26	63.55	---	--- Peak																																																																																																	
2 15960.00	49.12	74.00	-24.88	57.41	41.07	14.77	64.13	---	--- Peak																																																																																																	



		16																																																																																												
Mode		Band Edge																																																																																												
		U-NII-2C_5.47-5.725_802.11ac VHT20_CH100_5500MHz																																																																																												
ANT		CDD																																																																																												
Pol.		Horizontal					Fundamental																																																																																							
Peak	Level (dBuV/m) Date: 2024-01-05  535053805410544054705500 Frequency (MHz) <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5452.15</td><td>54.60</td><td>74.00</td><td>-19.40</td><td>41.06</td><td>35.93</td><td>9.68</td><td>32.07</td><td>100</td><td>208</td><td>PEAK</td></tr><tr><td>2</td><td>5460.25</td><td>54.12</td><td>68.30</td><td>-14.18</td><td>40.57</td><td>35.92</td><td>9.69</td><td>32.06</td><td>100</td><td>208</td><td>PEAK</td></tr></tbody></table>						Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		MHz	dBuV/m	dBuV/m	(dB)	dBuV	dB/m	dB	dB	cm	deg		1	5452.15	54.60	74.00	-19.40	41.06	35.93	9.68	32.07	100	208	PEAK	2	5460.25	54.12	68.30	-14.18	40.57	35.92	9.69	32.06	100	208	PEAK	Level (dBuV/m) Date: 2024-01-05  100022003400460058007000 Frequency (MHz) <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5500.00</td><td>109.64</td><td>-----</td><td>-----</td><td>96.03</td><td>35.90</td><td>9.71</td><td>32.00</td><td>100</td><td>208</td><td>PEAK</td></tr></tbody></table>						Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		MHz	dBuV/m	dBuV/m	(dB)	dBuV	dB/m	dB	dB	cm	deg		1	5500.00	109.64	-----	-----	96.03	35.90	9.71	32.00	100	208	PEAK
		Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
	MHz	dBuV/m	dBuV/m	(dB)	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5452.15	54.60	74.00	-19.40	41.06	35.93	9.68	32.07	100	208	PEAK																																																																																			
2	5460.25	54.12	68.30	-14.18	40.57	35.92	9.69	32.06	100	208	PEAK																																																																																			
	Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
	MHz	dBuV/m	dBuV/m	(dB)	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5500.00	109.64	-----	-----	96.03	35.90	9.71	32.00	100	208	PEAK																																																																																			
Avg	Level (dBuV/m) Date: 2024-01-05  535053805410544054705500 Frequency (MHz) <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5459.65</td><td>45.06</td><td>54.00</td><td>-8.94</td><td>31.51</td><td>35.92</td><td>9.69</td><td>32.06</td><td>100</td><td>208</td><td>AVERAGE</td></tr></tbody></table>						Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		MHz	dBuV/m	dBuV/m	(dB)	dBuV	dB/m	dB	dB	cm	deg		1	5459.65	45.06	54.00	-8.94	31.51	35.92	9.69	32.06	100	208	AVERAGE	Level (dBuV/m) Date: 2024-01-05  100022003400460058007000 Frequency (MHz) <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5500.00</td><td>102.20</td><td>-----</td><td>-----</td><td>88.59</td><td>35.90</td><td>9.71</td><td>32.00</td><td>100</td><td>208</td><td>AVERAGE</td></tr></tbody></table>						Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		MHz	dBuV/m	dBuV/m	(dB)	dBuV	dB/m	dB	dB	cm	deg		1	5500.00	102.20	-----	-----	88.59	35.90	9.71	32.00	100	208	AVERAGE												
	Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
	MHz	dBuV/m	dBuV/m	(dB)	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5459.65	45.06	54.00	-8.94	31.51	35.92	9.69	32.06	100	208	AVERAGE																																																																																			
	Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
	MHz	dBuV/m	dBuV/m	(dB)	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5500.00	102.20	-----	-----	88.59	35.90	9.71	32.00	100	208	AVERAGE																																																																																			



Mode	16																																																																																																					
	Band Edge																																																																																																					
	U-NII-2C_5.47-5.725_802.11ac VHT20_CH100_5500MHz																																																																																																					
ANT	CDD																																																																																																					
Pol.	Vertical						Fundamental																																																																																															
Peak	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5420.95</td><td>53.33</td><td>74.00</td><td>-20.67</td><td>39.82</td><td>35.95</td><td>9.67</td><td>32.11</td><td>311</td><td>198</td><td>PEAK</td></tr><tr><td>2</td><td>5470.00</td><td>54.44</td><td>68.30</td><td>-13.86</td><td>40.87</td><td>35.92</td><td>9.69</td><td>32.04</td><td>311</td><td>198</td><td>PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	cm	deg	1	5420.95	53.33	74.00	-20.67	39.82	35.95	9.67	32.11	311	198	PEAK	2	5470.00	54.44	68.30	-13.86	40.87	35.92	9.69	32.04	311	198	PEAK	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5500.00</td><td>108.63</td><td>-----</td><td>-----</td><td>95.02</td><td>35.91</td><td>9.71</td><td>32.01</td><td>311</td><td>198</td><td>PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	cm	deg	1	5500.00	108.63	-----	-----	95.02	35.91	9.71	32.01	311	198	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																													
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	cm	deg																																																																																														
1	5420.95	53.33	74.00	-20.67	39.82	35.95	9.67	32.11	311	198	PEAK																																																																																											
2	5470.00	54.44	68.30	-13.86	40.87	35.92	9.69	32.04	311	198	PEAK																																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																														
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	cm	deg																																																																																														
1	5500.00	108.63	-----	-----	95.02	35.91	9.71	32.01	311	198	PEAK																																																																																											
Avg	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5459.50</td><td>44.77</td><td>54.00</td><td>-9.23</td><td>31.22</td><td>35.92</td><td>9.69</td><td>32.06</td><td>311</td><td>198</td><td>AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	cm	deg	1	5459.50	44.77	54.00	-9.23	31.22	35.92	9.69	32.06	311	198	AVERAGE	Blank																																																								
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																														
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	cm	deg																																																																																														
1	5459.50	44.77	54.00	-9.23	31.22	35.92	9.69	32.06	311	198	AVERAGE																																																																																											



Mode	16																																																																																							
	Harmonic																																																																																							
	U-NII-2C_5.47-5.725_802.11ac VHT20_CH100_5500MHz																																																																																							
ANT	CDD																																																																																							
Pol.	Horizontal								Vertical																																																																															
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)								Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)																																																																															
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th>Remark</th></tr><tr><td>1</td><td>11000.00</td><td>49.45</td><td>74.00</td><td>-24.55</td><td>61.35</td><td>39.00</td><td>12.52</td><td>63.42 --- --- Peak</td></tr><tr><td>2</td><td>16500.00</td><td>49.08</td><td>68.30</td><td>-19.22</td><td>57.22</td><td>41.35</td><td>15.17</td><td>64.66 --- --- Peak</td></tr></table>									Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark	1	11000.00	49.45	74.00	-24.55	61.35	39.00	12.52	63.42 --- --- Peak	2	16500.00	49.08	68.30	-19.22	57.22	41.35	15.17	64.66 --- --- Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th>Remark</th></tr><tr><td>1</td><td>11000.00</td><td>49.61</td><td>74.00</td><td>-24.39</td><td>61.51</td><td>39.00</td><td>12.52</td><td>63.42 --- --- Peak</td></tr><tr><td>2</td><td>16500.00</td><td>48.59</td><td>68.30</td><td>-19.71</td><td>56.73</td><td>41.35</td><td>15.17</td><td>64.66 --- --- Peak</td></tr></table>									Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark	1	11000.00	49.61	74.00	-24.39	61.51	39.00	12.52	63.42 --- --- Peak	2	16500.00	48.59	68.30	-19.71	56.73	41.35	15.17	64.66 --- --- Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark																																																																																
1	11000.00	49.45	74.00	-24.55	61.35	39.00	12.52	63.42 --- --- Peak																																																																																
2	16500.00	49.08	68.30	-19.22	57.22	41.35	15.17	64.66 --- --- Peak																																																																																
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark																																																																																
1	11000.00	49.61	74.00	-24.39	61.51	39.00	12.52	63.42 --- --- Peak																																																																																
2	16500.00	48.59	68.30	-19.71	56.73	41.35	15.17	64.66 --- --- Peak																																																																																
<table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11000.00</td><td>49.45</td><td>74.00</td><td>-24.55</td><td>61.35</td><td>39.00</td><td>12.52</td><td>63.42</td><td>---</td><td>---</td></tr><tr><td>2</td><td>16500.00</td><td>49.08</td><td>68.30</td><td>-19.22</td><td>57.22</td><td>41.35</td><td>15.17</td><td>64.66</td><td>---</td><td>---</td></tr></table>									MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11000.00	49.45	74.00	-24.55	61.35	39.00	12.52	63.42	---	---	2	16500.00	49.08	68.30	-19.22	57.22	41.35	15.17	64.66	---	---	<table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11000.00</td><td>49.61</td><td>74.00</td><td>-24.39</td><td>61.51</td><td>39.00</td><td>12.52</td><td>63.42</td><td>---</td><td>---</td></tr><tr><td>2</td><td>16500.00</td><td>48.59</td><td>68.30</td><td>-19.71</td><td>56.73</td><td>41.35</td><td>15.17</td><td>64.66</td><td>---</td><td>---</td></tr></table>									MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11000.00	49.61	74.00	-24.39	61.51	39.00	12.52	63.42	---	---	2	16500.00	48.59	68.30	-19.71	56.73	41.35	15.17	64.66	---	---							
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																														
1	11000.00	49.45	74.00	-24.55	61.35	39.00	12.52	63.42	---	---																																																																														
2	16500.00	49.08	68.30	-19.22	57.22	41.35	15.17	64.66	---	---																																																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																														
1	11000.00	49.61	74.00	-24.39	61.51	39.00	12.52	63.42	---	---																																																																														
2	16500.00	48.59	68.30	-19.71	56.73	41.35	15.17	64.66	---	---																																																																														



Mode	17																																																																																																																																	
	Harmonic																																																																																																																																	
	U-NII-2C_5.47-5.725_802.11ac VHT20_CH116_5580MHz																																																																																																																																	
ANT	CDD																																																																																																																																	
Pol.	Horizontal						Vertical																																																																																																																											
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)						Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)																																																																																																																											
	<table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1 11160.00</td><td>49.43</td><td>74.00</td><td>-24.57</td><td>61.16</td><td>39.06</td><td>12.64</td><td>63.43</td><td>---</td><td>---</td><td>Peak</td><td></td></tr><tr><td>2 16740.00</td><td>49.42</td><td>68.30</td><td>-18.88</td><td>57.51</td><td>41.47</td><td>15.35</td><td>64.91</td><td>---</td><td>---</td><td>Peak</td><td></td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1 11160.00	49.43	74.00	-24.57	61.16	39.06	12.64	63.43	---	---	Peak		2 16740.00	49.42	68.30	-18.88	57.51	41.47	15.35	64.91	---	---	Peak		<table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1 11160.00</td><td>49.43</td><td>74.00</td><td>-24.57</td><td>61.16</td><td>39.06</td><td>12.64</td><td>63.43</td><td>---</td><td>---</td><td>Peak</td><td></td></tr><tr><td>2 16740.00</td><td>49.53</td><td>68.30</td><td>-18.77</td><td>57.62</td><td>41.47</td><td>15.35</td><td>64.91</td><td>---</td><td>---</td><td>Peak</td><td></td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1 11160.00	49.43	74.00	-24.57	61.16	39.06	12.64	63.43	---	---	Peak		2 16740.00	49.53	68.30	-18.77	57.62	41.47	15.35	64.91	---	---	Peak	
			Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																						
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1 11160.00	49.43	74.00	-24.57	61.16	39.06	12.64	63.43	---	---	Peak																																																																																																																								
2 16740.00	49.42	68.30	-18.88	57.51	41.47	15.35	64.91	---	---	Peak																																																																																																																								
		Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1 11160.00	49.43	74.00	-24.57	61.16	39.06	12.64	63.43	---	---	Peak																																																																																																																								
2 16740.00	49.53	68.30	-18.77	57.62	41.47	15.35	64.91	---	---	Peak																																																																																																																								



Mode	18																																																																																		
	Band Edge																																																																																		
	U-NII-2C_5.47-5.725_802.11ac VHT20_CH140_5700MHz																																																																																		
ANT	CDD																																																																																		
Pol.	Horizontal	Fundamental																																																																																	
Peak	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5725.03</td><td>64.55</td><td>68.30</td><td>-3.75</td><td>50.54</td><td>36.22</td><td>10.02</td><td>32.23</td><td>134</td><td>147 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5725.03	64.55	68.30	-3.75	50.54	36.22	10.02	32.23	134	147 PEAK	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5700.00</td><td>108.50</td><td>-----</td><td>94.54</td><td>36.19</td><td>9.97</td><td>32.20</td><td>134</td><td>147 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5700.00	108.50	-----	94.54	36.19	9.97	32.20	134	147 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																										
1	5725.03	64.55	68.30	-3.75	50.54	36.22	10.02	32.23	134	147 PEAK																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																										
1	5700.00	108.50	-----	94.54	36.19	9.97	32.20	134	147 PEAK																																																																										
Avg	Blank	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5700.00</td><td>101.74</td><td>-----</td><td>87.77</td><td>36.19</td><td>9.99</td><td>32.21</td><td>134</td><td>147 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5700.00	101.74	-----	87.77	36.19	9.99	32.21	134	147 AVERAGE																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																										
1	5700.00	101.74	-----	87.77	36.19	9.99	32.21	134	147 AVERAGE																																																																										



Mode	18																																																																																									
	Band Edge																																																																																									
	U-NII-2C_5.47-5.725_802.11ac VHT20_CH140_5700MHz																																																																																									
ANT	CDD																																																																																									
Pol.	Vertical					Fundamental																																																																																				
Peak	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5725.09</td><td>67.01</td><td>68.30</td><td>-1.29</td><td>53.00</td><td>36.22</td><td>10.02</td><td>32.23</td><td>369 178 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5725.09	67.01	68.30	-1.29	53.00	36.22	10.02	32.23	369 178 PEAK	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5700.00</td><td>109.45</td><td>-----</td><td>-----</td><td>95.49</td><td>36.19</td><td>9.97</td><td>32.20</td><td>369 178 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5700.00	109.45	-----	-----	95.49	36.19	9.97	32.20	369 178 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5725.09	67.01	68.30	-1.29	53.00	36.22	10.02	32.23	369 178 PEAK																																																																																	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5700.00	109.45	-----	-----	95.49	36.19	9.97	32.20	369 178 PEAK																																																																																	
Avg	Blank					Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5700.00</td><td>101.99</td><td>-----</td><td>-----</td><td>88.03</td><td>36.19</td><td>9.97</td><td>32.20</td><td>369 178 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5700.00	101.99	-----	-----	88.03	36.19	9.97	32.20	369 178 AVERAGE																																								
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5700.00	101.99	-----	-----	88.03	36.19	9.97	32.20	369 178 AVERAGE																																																																																	



Mode	18																																																																																																					
	Harmonic																																																																																																					
	U-NII-2C_5.47-5.725_802.11ac VHT20_CH140_5700MHz																																																																																																					
ANT	CDD																																																																																																					
Pol.	Horizontal						Vertical																																																																																															
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td></tr><tr><td>1</td><td>11400.00</td><td>50.25</td><td>74.00</td><td>-23.75</td><td>61.72</td><td>39.16</td><td>12.81</td><td>63.44</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>17100.00</td><td>50.80</td><td>68.30</td><td>-17.50</td><td>58.70</td><td>41.71</td><td>15.62</td><td>65.23</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	1	11400.00	50.25	74.00	-23.75	61.72	39.16	12.81	63.44	---	---	Peak	2	17100.00	50.80	68.30	-17.50	58.70	41.71	15.62	65.23	---	---	Peak	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td></tr><tr><td>1</td><td>11400.00</td><td>49.55</td><td>74.00</td><td>-24.45</td><td>61.02</td><td>39.16</td><td>12.81</td><td>63.44</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>17100.00</td><td>50.15</td><td>68.30</td><td>-18.15</td><td>58.05</td><td>41.71</td><td>15.62</td><td>65.23</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	1	11400.00	49.55	74.00	-24.45	61.02	39.16	12.81	63.44	---	---	Peak	2	17100.00	50.15	68.30	-18.15	58.05	41.71	15.62	65.23	---	---	Peak
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																															
	Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB																																																																																																
1	11400.00	50.25	74.00	-23.75	61.72	39.16	12.81	63.44	---	---	Peak																																																																																											
2	17100.00	50.80	68.30	-17.50	58.70	41.71	15.62	65.23	---	---	Peak																																																																																											
Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																																																
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB																																																																																																
1	11400.00	49.55	74.00	-24.45	61.02	39.16	12.81	63.44	---	---	Peak																																																																																											
2	17100.00	50.15	68.30	-18.15	58.05	41.71	15.62	65.23	---	---	Peak																																																																																											



		19																																																																																		
Mode		Band Edge - L																																																																																		
		U-NII-1_5.15-5.25_802.11ac VHT40_CH38_5190MHz																																																																																		
ANT		CDD																																																																																		
Pol.		Horizontal					Fundamental																																																																													
Peak	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5131.48</td><td>61.21</td><td>74.00</td><td>-12.79</td><td>49.11</td><td>36.12</td><td>8.50</td><td>32.52</td><td>333 259 PEAK</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5131.48	61.21	74.00	-12.79	49.11	36.12	8.50	32.52	333 259 PEAK	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5190.00</td><td>104.67</td><td>-----</td><td>-----</td><td>92.36</td><td>36.08</td><td>8.64</td><td>32.41</td><td>333 259 PEAK</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5190.00	104.67	-----	-----	92.36	36.08	8.64	32.41	333 259 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5131.48	61.21	74.00	-12.79	49.11	36.12	8.50	32.52	333 259 PEAK																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5190.00	104.67	-----	-----	92.36	36.08	8.64	32.41	333 259 PEAK																																																																											
Avg	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5130.53</td><td>51.33</td><td>54.00</td><td>-2.67</td><td>39.23</td><td>36.12</td><td>8.50</td><td>32.52</td><td>333 259 AVERAGE</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5130.53	51.33	54.00	-2.67	39.23	36.12	8.50	32.52	333 259 AVERAGE	Level (dBuV/m) Date: 2024-01-05 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5190.00</td><td>98.63</td><td>-----</td><td>-----</td><td>86.32</td><td>36.08</td><td>8.64</td><td>32.41</td><td>333 259 AVERAGE</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5190.00	98.63	-----	-----	86.32	36.08	8.64	32.41	333 259 AVERAGE
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5130.53	51.33	54.00	-2.67	39.23	36.12	8.50	32.52	333 259 AVERAGE																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5190.00	98.63	-----	-----	86.32	36.08	8.64	32.41	333 259 AVERAGE																																																																											



Mode	19																																		
	Band Edge - R																																		
	U-NII-1_5.15-5.25_802.11ac VHT40_CH38_5190MHz																																		
ANT	CDD																																		
Pol.	Horizontal	Fundamental																																	
Peak	Date: 2024-01-05 <table><tr><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1 5455.95</td><td>52.00</td><td>74.00</td><td>-22.00</td><td>38.44</td><td>35.93</td><td>9.69</td><td>32.06</td><td>333</td><td>259</td><td>PEAK</td></tr></table>	Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	cm	deg		1 5455.95	52.00	74.00	-22.00	38.44	35.93	9.69	32.06	333	259	PEAK	Blank
Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																									
MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	cm	deg																										
1 5455.95	52.00	74.00	-22.00	38.44	35.93	9.69	32.06	333	259	PEAK																									
Avg	Date: 2024-01-05 <table><tr><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1 5459.46</td><td>42.24</td><td>54.00</td><td>-11.76</td><td>28.69</td><td>35.92</td><td>9.69</td><td>32.06</td><td>333</td><td>259</td><td>AVERAGE</td></tr></table>	Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	cm	deg		1 5459.46	42.24	54.00	-11.76	28.69	35.92	9.69	32.06	333	259	AVERAGE	Blank
Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																									
MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	cm	deg																										
1 5459.46	42.24	54.00	-11.76	28.69	35.92	9.69	32.06	333	259	AVERAGE																									



Mode	19																																									
	Band Edge - L																																									
	U-NII-1_5.15-5.25_802.11ac VHT40_CH38_5190MHz																																									
ANT	CDD																																									
Pol.	Vertical	Fundamental																																								
Peak	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5137.37</td><td>55.82</td><td>74.00</td><td>-18.18</td><td>43.70</td><td>36.12</td><td>8.51</td><td>32.51</td><td>400</td><td>174 PEAK</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5137.37	55.82	74.00	-18.18	43.70	36.12	8.51	32.51	400	174 PEAK	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5190.00</td><td>102.56</td><td>-----</td><td>-----</td><td>90.34</td><td>36.09</td><td>8.58</td><td>32.45</td><td>400</td><td>174 PEAK</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5190.00	102.56	-----	-----	90.34	36.09	8.58	32.45	400	174 PEAK
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																
1 5137.37	55.82	74.00	-18.18	43.70	36.12	8.51	32.51	400	174 PEAK																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																	
1 5190.00	102.56	-----	-----	90.34	36.09	8.58	32.45	400	174 PEAK																																	
Avg	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5140.03</td><td>46.19</td><td>54.00</td><td>-7.81</td><td>34.05</td><td>36.12</td><td>8.52</td><td>32.50</td><td>400</td><td>174 AVERAGE</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5140.03	46.19	54.00	-7.81	34.05	36.12	8.52	32.50	400	174 AVERAGE	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5190.00</td><td>96.20</td><td>-----</td><td>-----</td><td>83.98</td><td>36.09</td><td>8.58</td><td>32.45</td><td>400</td><td>174 AVERAGE</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5190.00	96.20	-----	-----	83.98	36.09	8.58	32.45	400	174 AVERAGE
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																	
1 5140.03	46.19	54.00	-7.81	34.05	36.12	8.52	32.50	400	174 AVERAGE																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																	
1 5190.00	96.20	-----	-----	83.98	36.09	8.58	32.45	400	174 AVERAGE																																	







Mode	19																																										
	Band Edge - R																																										
	U-NII-1_5.15-5.25_802.11ac VHT40_CH38_5190MHz																																										
ANT	CDD																																										
Pol.	Vertical	Fundamental																																									
Peak	Date: 2024-01-05 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5384.13</td><td>51.74</td><td>74.00</td><td>-22.26</td><td>38.39</td><td>35.97</td><td>9.54</td><td>32.16</td><td>400</td><td>174 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5384.13	51.74	74.00	-22.26	38.39	35.97	9.54	32.16	400	174 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5384.13	51.74	74.00	-22.26	38.39	35.97	9.54	32.16	400	174 PEAK																																	
Avg	Date: 2024-01-05 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5437.86</td><td>42.29</td><td>54.00</td><td>-11.71</td><td>28.76</td><td>35.94</td><td>9.68</td><td>32.09</td><td>400</td><td>174 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5437.86	42.29	54.00	-11.71	28.76	35.94	9.68	32.09	400	174 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5437.86	42.29	54.00	-11.71	28.76	35.94	9.68	32.09	400	174 AVERAGE																																	



Mode	19																																																																																																	
	Harmonic																																																																																																	
	U-NII-1_5.15-5.25_802.11ac VHT40_CH38_5190MHz																																																																																																	
ANT	CDD																																																																																																	
Pol.	Horizontal	Vertical																																																																																																
Peak Avg	Level (dBuV/m) Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10380.00</td><td>46.86</td><td>68.30</td><td>-21.44</td><td>59.68</td><td>38.75</td><td>12.08</td><td>63.65</td><td>--- Peak</td></tr><tr><td>2</td><td>15570.00</td><td>49.97</td><td>74.00</td><td>-24.03</td><td>58.61</td><td>40.76</td><td>14.60</td><td>64.00</td><td>--- Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10380.00	46.86	68.30	-21.44	59.68	38.75	12.08	63.65	--- Peak	2	15570.00	49.97	74.00	-24.03	58.61	40.76	14.60	64.00	--- Peak	Level (dBuV/m) Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10380.00</td><td>47.41</td><td>68.30</td><td>-20.89</td><td>60.23</td><td>38.75</td><td>12.08</td><td>63.65</td><td>--- Peak</td></tr><tr><td>2</td><td>15570.00</td><td>50.15</td><td>74.00</td><td>-23.85</td><td>58.79</td><td>40.76</td><td>14.60</td><td>64.00</td><td>--- Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10380.00	47.41	68.30	-20.89	60.23	38.75	12.08	63.65	--- Peak	2	15570.00	50.15	74.00	-23.85	58.79	40.76	14.60	64.00	--- Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																										
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																									
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																									
1	10380.00	46.86	68.30	-21.44	59.68	38.75	12.08	63.65	--- Peak																																																																																									
2	15570.00	49.97	74.00	-24.03	58.61	40.76	14.60	64.00	--- Peak																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																											
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																									
1	10380.00	47.41	68.30	-20.89	60.23	38.75	12.08	63.65	--- Peak																																																																																									
2	15570.00	50.15	74.00	-23.85	58.79	40.76	14.60	64.00	--- Peak																																																																																									



		20																																																																																							
Mode		Band Edge - L																																																																																							
		U-NII-1_5.15-5.25_802.11ac VHT40_CH46_5230MHz																																																																																							
ANT		CDD																																																																																							
Pol.		Horizontal					Fundamental																																																																																		
Peak																																																																																									
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5149.50</td><td>56.62</td><td>74.00</td><td>-17.38</td><td>44.47</td><td>36.11</td><td>8.53</td><td>32.49</td><td>289</td><td>102 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5149.50	56.62	74.00	-17.38	44.47	36.11	8.53	32.49	289	102 PEAK	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5230.00</td><td>107.31</td><td>-----</td><td>-----</td><td>94.85</td><td>36.06</td><td>8.77</td><td>32.37</td><td>289</td><td>102 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5230.00	107.31	-----	-----	94.85	36.06	8.77	32.37	289
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5149.50	56.62	74.00	-17.38	44.47	36.11	8.53	32.49	289	102 PEAK																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5230.00	107.31	-----	-----	94.85	36.06	8.77	32.37	289	102 PEAK																																																																																
Avg																																																																																									
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5149.96</td><td>48.39</td><td>54.00</td><td>-5.61</td><td>36.23</td><td>36.11</td><td>8.54</td><td>32.49</td><td>289</td><td>102 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5149.96	48.39	54.00	-5.61	36.23	36.11	8.54	32.49	289	102 AVERAGE	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5230.00</td><td>100.66</td><td>-----</td><td>-----</td><td>88.30</td><td>36.07</td><td>8.68</td><td>32.39</td><td>289</td><td>102 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5230.00	100.66	-----	-----	88.30	36.07	8.68	32.39	289
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5149.96	48.39	54.00	-5.61	36.23	36.11	8.54	32.49	289	102 AVERAGE																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5230.00	100.66	-----	-----	88.30	36.07	8.68	32.39	289	102 AVERAGE																																																																																



Mode	20																																	
	Band Edge - R																																	
	U-NII-1_5.15-5.25_802.11ac VHT40_CH46_5230MHz																																	
ANT	CDD																																	
Pol.	Horizontal	Fundamental																																
Peak	Date: 2024-01-12 <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th></tr></thead><tbody><tr><td>1 5453.56</td><td>51.74</td><td>74.00</td><td>-22.26</td><td>38.20</td><td>35.93</td><td>9.68</td><td>32.07</td></tr></tbody></table> Remark: 102 PEAK	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	1 5453.56	51.74	74.00	-22.26	38.20	35.93	9.68	32.07	Blank
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																											
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm																											
1 5453.56	51.74	74.00	-22.26	38.20	35.93	9.68	32.07																											
Avg	Date: 2024-01-12 <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th></tr></thead><tbody><tr><td>1 5353.05</td><td>42.55</td><td>54.00</td><td>-11.45</td><td>29.39</td><td>35.99</td><td>9.38</td><td>32.21</td></tr></tbody></table> Remark: 102 AVERAGE	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	1 5353.05	42.55	54.00	-11.45	29.39	35.99	9.38	32.21	Blank
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																											
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm																											
1 5353.05	42.55	54.00	-11.45	29.39	35.99	9.38	32.21																											



Mode	20																																								
	Band Edge - L																																								
	U-NII-1_5.15-5.25_802.11ac VHT40_CH46_5230MHz																																								
ANT	CDD																																								
Pol.	Vertical	Fundamental																																							
Peak	Level (dBuV/m) Date: 2024-01-12 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5149.50</td><td>55.90</td><td>74.00</td><td>-18.10</td><td>43.75</td><td>36.11</td><td>8.53</td><td>32.49</td><td>400</td><td>201 PEAK</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5149.50	55.90	74.00	-18.10	43.75	36.11	8.53	32.49	400	201 PEAK	Level (dBuV/m) Date: 2024-01-12 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5230.00</td><td>103.10</td><td>-----</td><td>90.64</td><td>36.06</td><td>8.77</td><td>32.37</td><td>400</td><td>201 PEAK</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5230.00	103.10	-----	90.64	36.06	8.77	32.37	400	201 PEAK
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																															
1 5149.50	55.90	74.00	-18.10	43.75	36.11	8.53	32.49	400	201 PEAK																																
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																
1 5230.00	103.10	-----	90.64	36.06	8.77	32.37	400	201 PEAK																																	
Avg	Level (dBuV/m) Date: 2024-01-12 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5149.27</td><td>45.21</td><td>54.00</td><td>-8.79</td><td>33.06</td><td>36.11</td><td>8.53</td><td>32.49</td><td>400</td><td>201 AVERAGE</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5149.27	45.21	54.00	-8.79	33.06	36.11	8.53	32.49	400	201 AVERAGE	Level (dBuV/m) Date: 2024-01-12 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5230.00</td><td>96.85</td><td>-----</td><td>84.39</td><td>36.06</td><td>8.77</td><td>32.37</td><td>400</td><td>201 AVERAGE</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5230.00	96.85	-----	84.39	36.06	8.77	32.37	400	201 AVERAGE
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																
1 5149.27	45.21	54.00	-8.79	33.06	36.11	8.53	32.49	400	201 AVERAGE																																
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																
1 5230.00	96.85	-----	84.39	36.06	8.77	32.37	400	201 AVERAGE																																	



Mode	20																																										
	Band Edge - R																																										
	U-NII-1_5.15-5.25_802.11ac VHT40_CH46_5230MHz																																										
ANT	CDD																																										
Pol.	Vertical	Fundamental																																									
Peak	Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5451.72</td><td>51.97</td><td>74.00</td><td>-22.03</td><td>38.43</td><td>35.93</td><td>9.68</td><td>32.07</td><td>400</td><td>201 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5451.72	51.97	74.00	-22.03	38.43	35.93	9.68	32.07	400	201 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5451.72	51.97	74.00	-22.03	38.43	35.93	9.68	32.07	400	201 PEAK																																	
Avg	Date: 2024-01-12 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5354.43</td><td>42.49</td><td>54.00</td><td>-11.51</td><td>29.31</td><td>35.99</td><td>9.39</td><td>32.20</td><td>400</td><td>201 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5354.43	42.49	54.00	-11.51	29.31	35.99	9.39	32.20	400	201 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5354.43	42.49	54.00	-11.51	29.31	35.99	9.39	32.20	400	201 AVERAGE																																	







Mode	20																																																																																	
	Harmonic																																																																																	
	U-NII-1_5.15-5.25_802.11ac VHT40_CH46_5230MHz																																																																																	
ANT	CDD																																																																																	
Pol.	Horizontal					Vertical																																																																												
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)					Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)																																																																												
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><td>1</td><td>10460.00</td><td>47.81</td><td>68.30</td><td>-20.49</td><td>60.52</td><td>38.78</td><td>12.13</td><td>63.62 --- Peak</td></tr><tr><td>2</td><td>15690.00</td><td>49.73</td><td>74.00</td><td>-24.27</td><td>58.27</td><td>40.85</td><td>14.65</td><td>64.04 --- Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	1	10460.00	47.81	68.30	-20.49	60.52	38.78	12.13	63.62 --- Peak	2	15690.00	49.73	74.00	-24.27	58.27	40.85	14.65	64.04 --- Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><td>1</td><td>10460.00</td><td>48.98</td><td>68.30</td><td>-19.32</td><td>61.69</td><td>38.78</td><td>12.13</td><td>63.62 --- Peak</td></tr><tr><td>2</td><td>15690.00</td><td>50.49</td><td>74.00</td><td>-23.51</td><td>59.03</td><td>40.85</td><td>14.65</td><td>64.04 --- Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	1	10460.00	48.98	68.30	-19.32	61.69	38.78	12.13	63.62 --- Peak	2	15690.00	50.49	74.00	-23.51	59.03	40.85	14.65	64.04 --- Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																										
1	10460.00	47.81	68.30	-20.49	60.52	38.78	12.13	63.62 --- Peak																																																																										
2	15690.00	49.73	74.00	-24.27	58.27	40.85	14.65	64.04 --- Peak																																																																										
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																											
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																										
1	10460.00	48.98	68.30	-19.32	61.69	38.78	12.13	63.62 --- Peak																																																																										
2	15690.00	50.49	74.00	-23.51	59.03	40.85	14.65	64.04 --- Peak																																																																										
<table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10460.00</td><td>47.81</td><td>68.30</td><td>-20.49</td><td>60.52</td><td>38.78</td><td>12.13</td><td>63.62</td><td>---</td><td>---</td></tr><tr><td>2</td><td>15690.00</td><td>49.73</td><td>74.00</td><td>-24.27</td><td>58.27</td><td>40.85</td><td>14.65</td><td>64.04</td><td>---</td><td>---</td></tr></table>						MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10460.00	47.81	68.30	-20.49	60.52	38.78	12.13	63.62	---	---	2	15690.00	49.73	74.00	-24.27	58.27	40.85	14.65	64.04	---	---	<table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10460.00</td><td>48.98</td><td>68.30</td><td>-19.32</td><td>61.69</td><td>38.78</td><td>12.13</td><td>63.62</td><td>---</td><td>---</td></tr><tr><td>2</td><td>15690.00</td><td>50.49</td><td>74.00</td><td>-23.51</td><td>59.03</td><td>40.85</td><td>14.65</td><td>64.04</td><td>---</td><td>---</td></tr></table>						MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10460.00	48.98	68.30	-19.32	61.69	38.78	12.13	63.62	---	---	2	15690.00	50.49	74.00	-23.51	59.03	40.85	14.65	64.04	---	---							
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																								
1	10460.00	47.81	68.30	-20.49	60.52	38.78	12.13	63.62	---	---																																																																								
2	15690.00	49.73	74.00	-24.27	58.27	40.85	14.65	64.04	---	---																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																								
1	10460.00	48.98	68.30	-19.32	61.69	38.78	12.13	63.62	---	---																																																																								
2	15690.00	50.49	74.00	-23.51	59.03	40.85	14.65	64.04	---	---																																																																								







Mode	21																																																																									
	Harmonic																																																																									
	U-NII-2A_5.25-5.35_802.11ac VHT40_CH54_5270MHz																																																																									
ANT	CDD																																																																									
Pol.	Horizontal	Vertical																																																																								
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><td>1</td><td>10540.00</td><td>47.51</td><td>68.30</td><td>-20.79</td><td>60.09</td><td>38.82</td><td>12.19</td><td>63.59 --- Peak</td></tr><tr><td>2</td><td>15810.00</td><td>48.71</td><td>74.00</td><td>-25.29</td><td>57.13</td><td>40.95</td><td>14.71</td><td>64.08 --- Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	1	10540.00	47.51	68.30	-20.79	60.09	38.82	12.19	63.59 --- Peak	2	15810.00	48.71	74.00	-25.29	57.13	40.95	14.71	64.08 --- Peak	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><td>1</td><td>10540.00</td><td>48.45</td><td>68.30</td><td>-19.85</td><td>61.03</td><td>38.82</td><td>12.19</td><td>63.59 --- Peak</td></tr><tr><td>2</td><td>15810.00</td><td>50.08</td><td>74.00</td><td>-23.92</td><td>58.50</td><td>40.95</td><td>14.71</td><td>64.08 --- Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	1	10540.00	48.45	68.30	-19.85	61.03	38.82	12.19	63.59 --- Peak	2	15810.00	50.08	74.00	-23.92	58.50	40.95	14.71	64.08 --- Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																		
1	10540.00	47.51	68.30	-20.79	60.09	38.82	12.19	63.59 --- Peak																																																																		
2	15810.00	48.71	74.00	-25.29	57.13	40.95	14.71	64.08 --- Peak																																																																		
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																		
1	10540.00	48.45	68.30	-19.85	61.03	38.82	12.19	63.59 --- Peak																																																																		
2	15810.00	50.08	74.00	-23.92	58.50	40.95	14.71	64.08 --- Peak																																																																		



Mode	22	
	Band Edge - L	
	U-NII-2A_5.25-5.35_802.11ac VHT40_CH62_5310MHz	
ANT	CDD	
Pol.	Horizontal	Fundamental
Peak	Level (dBuV/m) Date: 2024-01-04  1 5045.14 52.87 74.00 -21.13 38.49 34.89 11.14 31.65 332 73 PEAK	Level (dBuV/m) Date: 2024-01-04  1 5310.00 97.55 ----- 83.70 34.84 10.98 31.97 332 73 PEAK
	Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg	Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg
Avg	Level (dBuV/m) Date: 2024-01-04  1 5101.22 42.84 54.00 -11.16 28.57 34.88 11.11 31.72 332 73 AVERAGE	Level (dBuV/m) Date: 2024-01-04  1 5310.00 90.29 ----- 76.44 34.84 10.98 31.97 332 73 AVERAGE
	Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg	Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg



		22																																																																																		
Mode		Band Edge - L																																																																																		
		U-NII-2A_5.25-5.35_802.11ac VHT40_CH62_5310MHz																																																																																		
ANT		CDD																																																																																		
Pol.		Vertical					Fundamental																																																																													
Peak																																																																																				
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5126.02	52.96	74.00	-21.04	38.74	34.87	11.10	31.75	200	188 PEAK		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5310.00	104.63	-----	-----	90.78	34.84	10.98	31.97	200	188 PEAK				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																											
1 5126.02	52.96	74.00	-21.04	38.74	34.87	11.10	31.75	200	188 PEAK																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																											
1 5310.00	104.63	-----	-----	90.78	34.84	10.98	31.97	200	188 PEAK																																																																											
Avg																																																																																				
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5134.39	42.97	54.00	-11.03	28.77	34.87	11.09	31.76	200	188 AVERAGE		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5310.00	97.19	-----	-----	83.34	34.84	10.98	31.97	200	188 AVERAGE				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																											
1 5134.39	42.97	54.00	-11.03	28.77	34.87	11.09	31.76	200	188 AVERAGE																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																											
1 5310.00	97.19	-----	-----	83.34	34.84	10.98	31.97	200	188 AVERAGE																																																																											



Mode	22																																										
	Band Edge - R																																										
	U-NII-2A_5.25-5.35_802.11ac VHT40_CH62_5310MHz																																										
ANT	CDD																																										
Pol.	Vertical	Fundamental																																									
Peak	Date: 2024-01-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5353.89</td><td>64.73</td><td>74.00</td><td>-9.27</td><td>50.99</td><td>34.83</td><td>10.94</td><td>32.03</td><td>200</td><td>188 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5353.89	64.73	74.00	-9.27	50.99	34.83	10.94	32.03	200	188 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5353.89	64.73	74.00	-9.27	50.99	34.83	10.94	32.03	200	188 PEAK																																	
Avg	Date: 2024-01-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5350.29</td><td>53.51</td><td>54.00</td><td>-0.49</td><td>39.77</td><td>34.83</td><td>10.94</td><td>32.03</td><td>200</td><td>188 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5350.29	53.51	54.00	-0.49	39.77	34.83	10.94	32.03	200	188 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5350.29	53.51	54.00	-0.49	39.77	34.83	10.94	32.03	200	188 AVERAGE																																	



Mode	22																																																																																																																							
	Harmonic																																																																																																																							
	U-NII-2A_5.25-5.35_802.11ac VHT40_CH62_5310MHz																																																																																																																							
ANT	CDD																																																																																																																							
Pol.	Horizontal						Vertical																																																																																																																	
Peak Avg	Data: 1 Level (dBuV/m) Date: 2024-01-15 Frequency (MHz) <table><tr><th></th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Limit</th><th>Line</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>10620.00</td><td>48.20</td><td>-25.80</td><td>74.00</td><td>60.65</td><td>38.85</td><td>12.26</td><td>63.56</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2 *</td><td>15930.00</td><td>49.62</td><td>-24.38</td><td>74.00</td><td>57.94</td><td>41.04</td><td>14.76</td><td>64.12</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos		Freq	Level	Limit	Line	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	10620.00	48.20	-25.80	74.00	60.65	38.85	12.26	63.56	---	---	Peak	2 *	15930.00	49.62	-24.38	74.00	57.94	41.04	14.76	64.12	---	---	Peak	Data: 2 Level (dBuV/m) Date: 2024-01-15 Frequency (MHz) <table><tr><th></th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Limit</th><th>Line</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>10620.00</td><td>47.62</td><td>-26.38</td><td>74.00</td><td>60.07</td><td>38.85</td><td>12.26</td><td>63.56</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2 *</td><td>15930.00</td><td>50.09</td><td>-23.91</td><td>74.00</td><td>58.41</td><td>41.04</td><td>14.76</td><td>64.12</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos		Freq	Level	Limit	Line	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	10620.00	47.62	-26.38	74.00	60.07	38.85	12.26	63.56	---	---	Peak	2 *	15930.00	50.09	-23.91	74.00	58.41	41.04	14.76	64.12	---	---	Peak
		Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos																																																																																																																
	Freq	Level	Limit	Line	Level	Factor	Loss	Factor	Remark																																																																																																															
		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																																													
1	10620.00	48.20	-25.80	74.00	60.65	38.85	12.26	63.56	---	---	Peak																																																																																																													
2 *	15930.00	49.62	-24.38	74.00	57.94	41.04	14.76	64.12	---	---	Peak																																																																																																													
	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos																																																																																																																	
Freq	Level	Limit	Line	Level	Factor	Loss	Factor	Remark																																																																																																																
	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																																														
1	10620.00	47.62	-26.38	74.00	60.07	38.85	12.26	63.56	---	---	Peak																																																																																																													
2 *	15930.00	50.09	-23.91	74.00	58.41	41.04	14.76	64.12	---	---	Peak																																																																																																													



Mode	23																																																								
	Band Edge - L																																																								
	U-NII-2C_5.47-5.725_802.11ac VHT40_CH102_5510MHz																																																								
ANT	CDD																																																								
Pol.	Horizontal	Fundamental																																																							
Peak	Level (dBuV/m) Date: 2024-01-04 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5458.72</td><td>52.31</td><td>74.00</td><td>-21.69</td><td>38.55</td><td>34.81</td><td>11.11</td><td>32.16</td><td>331</td><td>73 PEAK</td></tr><tr><td>2</td><td>5462.72</td><td>52.65</td><td>68.30</td><td>-15.65</td><td>38.88</td><td>34.81</td><td>11.13</td><td>32.17</td><td>331</td><td>73 PEAK</td></tr></table>		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5458.72	52.31	74.00	-21.69	38.55	34.81	11.11	32.16	331	73 PEAK	2	5462.72	52.65	68.30	-15.65	38.88	34.81	11.13	32.17	331	73 PEAK	Level (dBuV/m) Date: 2024-01-04 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5510.00</td><td>96.51</td><td>-----</td><td>-----</td><td>82.56</td><td>34.82</td><td>11.35</td><td>32.22</td><td>331</td><td>73 PEAK</td></tr></table>		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5510.00	96.51	-----	-----	82.56	34.82	11.35	32.22	331	73 PEAK
		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																														
1	5458.72	52.31	74.00	-21.69	38.55	34.81	11.11	32.16	331	73 PEAK																																															
2	5462.72	52.65	68.30	-15.65	38.88	34.81	11.13	32.17	331	73 PEAK																																															
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																															
1	5510.00	96.51	-----	-----	82.56	34.82	11.35	32.22	331	73 PEAK																																															
Avg	Level (dBuV/m) Date: 2024-01-04 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5458.26</td><td>42.72</td><td>54.00</td><td>-11.28</td><td>28.96</td><td>34.81</td><td>11.11</td><td>32.16</td><td>331</td><td>73 AVERAGE</td></tr></table>		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5458.26	42.72	54.00	-11.28	28.96	34.81	11.11	32.16	331	73 AVERAGE	Level (dBuV/m) Date: 2024-01-04 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5510.00</td><td>88.10</td><td>-----</td><td>-----</td><td>74.15</td><td>34.82</td><td>11.35</td><td>32.22</td><td>331</td><td>73 AVERAGE</td></tr></table>		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5510.00	88.10	-----	-----	74.15	34.82	11.35	32.22	331	73 AVERAGE											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																															
1	5458.26	42.72	54.00	-11.28	28.96	34.81	11.11	32.16	331	73 AVERAGE																																															
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																															
1	5510.00	88.10	-----	-----	74.15	34.82	11.35	32.22	331	73 AVERAGE																																															



Mode	23																																									
	Band Edge - R																																									
	U-NII-2C_5.47-5.725_802.11ac VHT40_CH102_5510MHz																																									
ANT	CDD																																									
Pol.	Horizontal	Fundamental																																								
Peak	Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5734.53</td><td>53.47</td><td>68.30</td><td>-14.83</td><td>39.08</td><td>35.13</td><td>11.65</td><td>32.39</td><td>331</td><td>73</td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5734.53	53.47	68.30	-14.83	39.08	35.13	11.65	32.39	331	73	PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5734.53	53.47	68.30	-14.83	39.08	35.13	11.65	32.39	331	73	PEAK																															



		23									
Mode		Band Edge - L									
		U-NII-2C_5.47-5.725_802.11ac VHT40_CH102_5510MHz									
ANT		CDD									
Pol.		Vertical					Fundamental				
Peak	Level (dBuV/m) Date: 2024-01-04 <										



Mode	23																																								
	Band Edge - R																																								
	U-NII-2C_5.47-5.725_802.11ac VHT40_CH102_5510MHz																																								
ANT	CDD																																								
Pol.	Vertical	Fundamental																																							
Peak	Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5751.87</td><td>52.42</td><td>68.30</td><td>-15.88</td><td>38.04</td><td>35.15</td><td>11.64</td><td>32.41</td><td>176</td><td>207 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5751.87	52.42	68.30	-15.88	38.04	35.15	11.64	32.41	176	207 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																
1	5751.87	52.42	68.30	-15.88	38.04	35.15	11.64	32.41	176	207 PEAK																															



Mode	23																																																																									
	Harmonic																																																																									
	U-NII-2C_5.47-5.725_802.11ac VHT40_CH102_5510MHz																																																																									
ANT	CDD																																																																									
Pol.	Horizontal	Vertical																																																																								
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><td>1</td><td>11020.00</td><td>49.14</td><td>74.00</td><td>-24.86</td><td>61.01</td><td>39.01</td><td>12.54</td><td>63.42 --- Peak</td></tr><tr><td>2</td><td>16530.00</td><td>48.75</td><td>68.30</td><td>-19.55</td><td>56.89</td><td>41.36</td><td>15.19</td><td>64.69 --- Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	1	11020.00	49.14	74.00	-24.86	61.01	39.01	12.54	63.42 --- Peak	2	16530.00	48.75	68.30	-19.55	56.89	41.36	15.19	64.69 --- Peak	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><td>1</td><td>11020.00</td><td>49.53</td><td>74.00</td><td>-24.47</td><td>61.40</td><td>39.01</td><td>12.54</td><td>63.42 --- Peak</td></tr><tr><td>2</td><td>16530.00</td><td>49.88</td><td>68.30</td><td>-18.42</td><td>58.02</td><td>41.36</td><td>15.19</td><td>64.69 --- Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	1	11020.00	49.53	74.00	-24.47	61.40	39.01	12.54	63.42 --- Peak	2	16530.00	49.88	68.30	-18.42	58.02	41.36	15.19	64.69 --- Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																		
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																	
1	11020.00	49.14	74.00	-24.86	61.01	39.01	12.54	63.42 --- Peak																																																																		
2	16530.00	48.75	68.30	-19.55	56.89	41.36	15.19	64.69 --- Peak																																																																		
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																		
1	11020.00	49.53	74.00	-24.47	61.40	39.01	12.54	63.42 --- Peak																																																																		
2	16530.00	49.88	68.30	-18.42	58.02	41.36	15.19	64.69 --- Peak																																																																		



Mode	24																																																																																											
	Harmonic																																																																																											
	U-NII-2C_5.47-5.725_802.11ac VHT40_CH110_5550MHz																																																																																											
ANT	CDD																																																																																											
Pol.	Horizontal						Vertical																																																																																					
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)						Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)																																																																																					
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th>Remark</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td></tr><tr><td>1</td><td>11100.00</td><td>48.84</td><td>74.00</td><td>-25.16</td><td>60.63</td><td>39.04</td><td>12.59 63.42 --- --- Peak</td></tr><tr><td>2</td><td>16650.00</td><td>49.17</td><td>68.30</td><td>-19.13</td><td>57.29</td><td>41.42</td><td>15.28 64.82 --- --- Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	1	11100.00	48.84	74.00	-25.16	60.63	39.04	12.59 63.42 --- --- Peak	2	16650.00	49.17	68.30	-19.13	57.29	41.42	15.28 64.82 --- --- Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th>Remark</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td></tr><tr><td>1</td><td>11100.00</td><td>48.88</td><td>74.00</td><td>-25.12</td><td>60.67</td><td>39.04</td><td>12.59 63.42 --- --- Peak</td></tr><tr><td>2</td><td>16650.00</td><td>50.13</td><td>68.30</td><td>-18.17</td><td>58.25</td><td>41.42</td><td>15.28 64.82 --- --- Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	1	11100.00	48.88	74.00	-25.12	60.67	39.04	12.59 63.42 --- --- Peak	2	16650.00	50.13	68.30	-18.17	58.25	41.42	15.28 64.82 --- --- Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss Factor	Remark																																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																					
1	11100.00	48.84	74.00	-25.16	60.63	39.04	12.59 63.42 --- --- Peak																																																																																					
2	16650.00	49.17	68.30	-19.13	57.29	41.42	15.28 64.82 --- --- Peak																																																																																					
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss Factor	Remark																																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																					
1	11100.00	48.88	74.00	-25.12	60.67	39.04	12.59 63.42 --- --- Peak																																																																																					
2	16650.00	50.13	68.30	-18.17	58.25	41.42	15.28 64.82 --- --- Peak																																																																																					



Mode	25																																																																																										
	Band Edge - L																																																																																										
	U-NII-2C_5.47-5.725_802.11ac VHT40_CH134_5670MHz																																																																																										
ANT	CDD																																																																																										
Pol.	Horizontal	Fundamental																																																																																									
Peak	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5376.72</td><td>51.75</td><td>74.00</td><td>-22.25</td><td>38.07</td><td>34.82</td><td>10.92</td><td>32.06</td><td>321</td><td>72 PEAK</td></tr><tr><td>2</td><td>5466.03</td><td>51.16</td><td>68.30</td><td>-17.14</td><td>37.37</td><td>34.81</td><td>11.15</td><td>32.17</td><td>321</td><td>72 PEAK</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5376.72	51.75	74.00	-22.25	38.07	34.82	10.92	32.06	321	72 PEAK	2	5466.03	51.16	68.30	-17.14	37.37	34.81	11.15	32.17	321	72 PEAK	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5670.00</td><td>93.44</td><td>-----</td><td>-----</td><td>79.06</td><td>35.05</td><td>11.68</td><td>32.35</td><td>321</td><td>72 PEAK</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5670.00	93.44	-----	-----	79.06	35.05	11.68	32.35	321	72 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	5376.72	51.75	74.00	-22.25	38.07	34.82	10.92	32.06	321	72 PEAK																																																																																	
2	5466.03	51.16	68.30	-17.14	37.37	34.81	11.15	32.17	321	72 PEAK																																																																																	
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	5670.00	93.44	-----	-----	79.06	35.05	11.68	32.35	321	72 PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5458.96</td><td>41.95</td><td>54.00</td><td>-12.05</td><td>28.18</td><td>34.81</td><td>11.12</td><td>32.16</td><td>321</td><td>72 AVERAGE</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5458.96	41.95	54.00	-12.05	28.18	34.81	11.12	32.16	321	72 AVERAGE	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5670.00</td><td>86.91</td><td>-----</td><td>-----</td><td>72.53</td><td>35.04</td><td>11.68</td><td>32.34</td><td>321</td><td>72 AVERAGE</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5670.00	86.91	-----	-----	72.53	35.04	11.68	32.34	321	72 AVERAGE											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	5458.96	41.95	54.00	-12.05	28.18	34.81	11.12	32.16	321	72 AVERAGE																																																																																	
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	5670.00	86.91	-----	-----	72.53	35.04	11.68	32.34	321	72 AVERAGE																																																																																	



Mode	25																																									
	Band Edge - R																																									
	U-NII-2C_5.47-5.725_802.11ac VHT40_CH134_5670MHz																																									
ANT	CDD																																									
Pol.	Horizontal	Fundamental																																								
Peak	Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5728.77</td><td>57.28</td><td>68.30</td><td>-11.02</td><td>42.90</td><td>35.12</td><td>11.65</td><td>32.39</td><td>321</td><td>72</td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5728.77	57.28	68.30	-11.02	42.90	35.12	11.65	32.39	321	72	PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5728.77	57.28	68.30	-11.02	42.90	35.12	11.65	32.39	321	72	PEAK																															



Mode	25																																																																																																			
	Band Edge - L																																																																																																			
	U-NII-2C_5.47-5.725_802.11ac VHT40_CH134_5670MHz																																																																																																			
ANT	CDD																																																																																																			
Pol.	Vertical					Fundamental																																																																																														
Peak	Level (dBuV/m) Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5458.35</td><td>52.26</td><td>74.00</td><td>-21.74</td><td>38.50</td><td>34.81</td><td>11.11</td><td>32.16</td><td>255 0 PEAK</td></tr><tr><td>2</td><td>5466.03</td><td>51.50</td><td>68.30</td><td>-16.80</td><td>37.71</td><td>34.81</td><td>11.15</td><td>32.17</td><td>255 0 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5458.35	52.26	74.00	-21.74	38.50	34.81	11.11	32.16	255 0 PEAK	2	5466.03	51.50	68.30	-16.80	37.71	34.81	11.15	32.17	255 0 PEAK	Level (dBuV/m) Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5670.00</td><td>104.52</td><td>-----</td><td>-----</td><td>90.15</td><td>35.01</td><td>11.69</td><td>32.33</td><td>255 0 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5670.00	104.52	-----	-----	90.15	35.01	11.69	32.33	255 0 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	5458.35	52.26	74.00	-21.74	38.50	34.81	11.11	32.16	255 0 PEAK																																																																																											
2	5466.03	51.50	68.30	-16.80	37.71	34.81	11.15	32.17	255 0 PEAK																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	5670.00	104.52	-----	-----	90.15	35.01	11.69	32.33	255 0 PEAK																																																																																											
Avg	Level (dBuV/m) Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5457.39</td><td>42.10</td><td>54.00</td><td>-11.90</td><td>28.34</td><td>34.81</td><td>11.11</td><td>32.16</td><td>255 0 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5457.39	42.10	54.00	-11.90	28.34	34.81	11.11	32.16	255 0 AVERAGE	Level (dBuV/m) Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5670.00</td><td>97.31</td><td>-----</td><td>-----</td><td>82.94</td><td>35.01</td><td>11.69</td><td>32.33</td><td>255 0 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5670.00	97.31	-----	-----	82.94	35.01	11.69	32.33	255 0 AVERAGE										
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	5457.39	42.10	54.00	-11.90	28.34	34.81	11.11	32.16	255 0 AVERAGE																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	5670.00	97.31	-----	-----	82.94	35.01	11.69	32.33	255 0 AVERAGE																																																																																											







Mode	25																																									
	Band Edge - R																																									
	U-NII-2C_5.47-5.725_802.11ac VHT40_CH134_5670MHz																																									
ANT	CDD																																									
Pol.	Vertical	Fundamental																																								
Peak	Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5725.73</td><td>62.18</td><td>68.30</td><td>-6.12</td><td>47.80</td><td>35.12</td><td>11.65</td><td>32.39</td><td>255</td><td>0</td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5725.73	62.18	68.30	-6.12	47.80	35.12	11.65	32.39	255	0	PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5725.73	62.18	68.30	-6.12	47.80	35.12	11.65	32.39	255	0	PEAK																															



Mode	25																																																																																											
	Harmonic																																																																																											
	U-NII-2C_5.47-5.725_802.11ac VHT40_CH134_5670MHz																																																																																											
ANT	CDD																																																																																											
Pol.	Horizontal						Vertical																																																																																					
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)						Level (dBuV/m) Date: 2024-01-12 Frequency (MHz)																																																																																					
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th>Remark</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td></tr><tr><td>1</td><td>11340.00</td><td>49.09</td><td>74.00</td><td>-24.91</td><td>60.62</td><td>39.14</td><td>12.77 63.44 --- --- Peak</td></tr><tr><td>2</td><td>17010.00</td><td>50.30</td><td>68.30</td><td>-18.00</td><td>58.33</td><td>41.61</td><td>15.55 65.19 --- --- Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	1	11340.00	49.09	74.00	-24.91	60.62	39.14	12.77 63.44 --- --- Peak	2	17010.00	50.30	68.30	-18.00	58.33	41.61	15.55 65.19 --- --- Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th>Remark</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td></tr><tr><td>1</td><td>11340.00</td><td>49.22</td><td>74.00</td><td>-24.78</td><td>60.75</td><td>39.14</td><td>12.77 63.44 --- --- Peak</td></tr><tr><td>2</td><td>17010.00</td><td>51.82</td><td>68.30</td><td>-16.48</td><td>59.85</td><td>41.61</td><td>15.55 65.19 --- --- Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	1	11340.00	49.22	74.00	-24.78	60.75	39.14	12.77 63.44 --- --- Peak	2	17010.00	51.82	68.30	-16.48	59.85	41.61	15.55 65.19 --- --- Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss Factor	Remark																																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																					
1	11340.00	49.09	74.00	-24.91	60.62	39.14	12.77 63.44 --- --- Peak																																																																																					
2	17010.00	50.30	68.30	-18.00	58.33	41.61	15.55 65.19 --- --- Peak																																																																																					
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss Factor	Remark																																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																					
1	11340.00	49.22	74.00	-24.78	60.75	39.14	12.77 63.44 --- --- Peak																																																																																					
2	17010.00	51.82	68.30	-16.48	59.85	41.61	15.55 65.19 --- --- Peak																																																																																					







Mode	26																																																																																									
	Band Edge - L																																																																																									
	U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz																																																																																									
ANT	CDD																																																																																									
Pol.	Horizontal					Fundamental																																																																																				
Peak																																																																																										
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5142.30</td><td>55.86</td><td>74.00</td><td>-18.14</td><td>41.67</td><td>34.87</td><td>11.09</td><td>31.77</td><td>400</td><td>72 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5142.30	55.86	74.00	-18.14	41.67	34.87	11.09	31.77	400	72 PEAK	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5210.00</td><td>96.57</td><td>-----</td><td>82.58</td><td>34.85</td><td>11.03</td><td>31.89</td><td>400</td><td>72 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5210.00	96.57	-----	82.58	34.85	11.03	31.89	400
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5142.30	55.86	74.00	-18.14	41.67	34.87	11.09	31.77	400	72 PEAK																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5210.00	96.57	-----	82.58	34.85	11.03	31.89	400	72 PEAK																																																																																	
Avg																																																																																										
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5145.01</td><td>46.47</td><td>54.00</td><td>-7.53</td><td>32.29</td><td>34.87</td><td>11.09</td><td>31.78</td><td>400</td><td>72 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5145.01	46.47	54.00	-7.53	32.29	34.87	11.09	31.78	400	72 AVERAGE	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5210.00</td><td>89.53</td><td>-----</td><td>75.54</td><td>34.85</td><td>11.03</td><td>31.89</td><td>400</td><td>72 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5210.00	89.53	-----	75.54	34.85	11.03	31.89	400
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5145.01	46.47	54.00	-7.53	32.29	34.87	11.09	31.78	400	72 AVERAGE																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5210.00	89.53	-----	75.54	34.85	11.03	31.89	400	72 AVERAGE																																																																																	



Mode	26																																										
	Band Edge - R																																										
	U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz																																										
ANT	CDD																																										
Pol.	Horizontal	Fundamental																																									
Peak	Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5436.65</td><td>52.28</td><td>74.00</td><td>-21.72</td><td>38.59</td><td>34.81</td><td>11.02</td><td>32.14</td><td>400</td><td>72 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5436.65	52.28	74.00	-21.72	38.59	34.81	11.02	32.14	400	72 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5436.65	52.28	74.00	-21.72	38.59	34.81	11.02	32.14	400	72 PEAK																																	
Avg	Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5454.38</td><td>42.08</td><td>54.00</td><td>-11.92</td><td>28.33</td><td>34.81</td><td>11.10</td><td>32.16</td><td>400</td><td>72 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5454.38	42.08	54.00	-11.92	28.33	34.81	11.10	32.16	400	72 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5454.38	42.08	54.00	-11.92	28.33	34.81	11.10	32.16	400	72 AVERAGE																																	



Mode	26																																																																																			
	Band Edge - L																																																																																			
	U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz																																																																																			
ANT	CDD																																																																																			
Pol.	Vertical	Fundamental																																																																																		
Peak	Level (dBuV/m) Date: 2024-01-04  5000 5042. 5084. 5126. 5168. 5210 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5148.39</td><td>60.80</td><td>74.00</td><td>-13.20</td><td>46.62</td><td>34.87</td><td>11.09</td><td>31.78</td><td>200</td><td>132 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5148.39	60.80	74.00	-13.20	46.62	34.87	11.09	31.78	200	132 PEAK	Level (dBuV/m) Date: 2024-01-04  1000 2200. 3400. 4600. 5800. 7000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5210.00</td><td>101.80</td><td>-----</td><td>-----</td><td>87.77</td><td>34.86</td><td>11.04</td><td>31.87</td><td>200</td><td>132 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5210.00	101.80	-----	-----	87.77	34.86	11.04	31.87	200	132 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																														
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																											
1	5148.39	60.80	74.00	-13.20	46.62	34.87	11.09	31.78	200	132 PEAK																																																																										
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																														
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																											
1	5210.00	101.80	-----	-----	87.77	34.86	11.04	31.87	200	132 PEAK																																																																										
Avg	Level (dBuV/m) Date: 2024-01-04  5000 5042. 5084. 5126. 5168. 5210 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5146.69</td><td>51.16</td><td>54.00</td><td>-2.84</td><td>36.98</td><td>34.87</td><td>11.09</td><td>31.78</td><td>200</td><td>132 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5146.69	51.16	54.00	-2.84	36.98	34.87	11.09	31.78	200	132 AVERAGE	Level (dBuV/m) Date: 2024-01-04  1000 2200. 3400. 4600. 5800. 7000 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5210.00</td><td>94.99</td><td>-----</td><td>-----</td><td>81.00</td><td>34.85</td><td>11.03</td><td>31.89</td><td>200</td><td>132 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5210.00	94.99	-----	-----	81.00	34.85	11.03	31.89	200	132 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																														
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																											
1	5146.69	51.16	54.00	-2.84	36.98	34.87	11.09	31.78	200	132 AVERAGE																																																																										
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																														
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																											
1	5210.00	94.99	-----	-----	81.00	34.85	11.03	31.89	200	132 AVERAGE																																																																										







Mode	26																																										
	Band Edge - R																																										
	U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz																																										
ANT	CDD																																										
Pol.	Vertical	Fundamental																																									
Peak	Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5350.65</td><td>51.53</td><td>74.00</td><td>-22.47</td><td>37.79</td><td>34.83</td><td>10.94</td><td>32.03</td><td>200</td><td>132 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5350.65	51.53	74.00	-22.47	37.79	34.83	10.94	32.03	200	132 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5350.65	51.53	74.00	-22.47	37.79	34.83	10.94	32.03	200	132 PEAK																																	
Avg	Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5350.88</td><td>42.18</td><td>54.00</td><td>-11.82</td><td>28.44</td><td>34.83</td><td>10.94</td><td>32.03</td><td>200</td><td>132 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5350.88	42.18	54.00	-11.82	28.44	34.83	10.94	32.03	200	132 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5350.88	42.18	54.00	-11.82	28.44	34.83	10.94	32.03	200	132 AVERAGE																																	







Mode	26																																																																																																																																	
	Harmonic																																																																																																																																	
	U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz																																																																																																																																	
ANT	CDD																																																																																																																																	
Pol.	Horizontal						Vertical																																																																																																																											
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>10420.00</td><td>48.12</td><td>68.30</td><td>-20.18</td><td>60.87</td><td>38.77</td><td>12.11</td><td>63.63</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15630.00</td><td>50.06</td><td>74.00</td><td>-23.94</td><td>58.66</td><td>40.80</td><td>14.62</td><td>64.02</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	10420.00	48.12	68.30	-20.18	60.87	38.77	12.11	63.63	---	---	Peak	2	15630.00	50.06	74.00	-23.94	58.66	40.80	14.62	64.02	---	---	Peak	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>10420.00</td><td>48.52</td><td>68.30</td><td>-19.78</td><td>61.27</td><td>38.77</td><td>12.11</td><td>63.63</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15630.00</td><td>49.59</td><td>74.00</td><td>-24.41</td><td>58.19</td><td>40.80</td><td>14.62</td><td>64.02</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	10420.00	48.52	68.30	-19.78	61.27	38.77	12.11	63.63	---	---	Peak	2	15630.00	49.59	74.00	-24.41	58.19	40.80	14.62	64.02	---	---	Peak
			Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																						
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																										
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	10420.00	48.12	68.30	-20.18	60.87	38.77	12.11	63.63	---	---	Peak																																																																																																																							
2	15630.00	50.06	74.00	-23.94	58.66	40.80	14.62	64.02	---	---	Peak																																																																																																																							
		Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	10420.00	48.52	68.30	-19.78	61.27	38.77	12.11	63.63	---	---	Peak																																																																																																																							
2	15630.00	49.59	74.00	-24.41	58.19	40.80	14.62	64.02	---	---	Peak																																																																																																																							



		27																																																																																								
Mode		Band Edge - L																																																																																								
		U-NII-2A_5.25-5.35_802.11ac VHT80_CH58_5290MHz																																																																																								
ANT		CDD																																																																																								
Pol.		Horizontal					Fundamental																																																																																			
Peak																																																																																										
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5146.02</td><td>53.96</td><td>74.00</td><td>-20.04</td><td>39.78</td><td>34.87</td><td>11.09</td><td>31.78</td><td>324</td><td>71 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5146.02	53.96	74.00	-20.04	39.78	34.87	11.09	31.78	324	71 PEAK	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5290.00</td><td>97.99</td><td>-----</td><td>84.03</td><td>34.85</td><td>11.02</td><td>31.91</td><td>324</td><td>71 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5290.00	97.99	-----	84.03	34.85	11.02	31.91	324
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5146.02	53.96	74.00	-20.04	39.78	34.87	11.09	31.78	324	71 PEAK																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5290.00	97.99	-----	84.03	34.85	11.02	31.91	324	71 PEAK																																																																																	
Avg																																																																																										
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5149.99</td><td>44.03</td><td>54.00</td><td>-9.97</td><td>29.86</td><td>34.87</td><td>11.08</td><td>31.78</td><td>324</td><td>71 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5149.99	44.03	54.00	-9.97	29.86	34.87	11.08	31.78	324	71 AVERAGE	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5290.00</td><td>90.67</td><td>-----</td><td>76.71</td><td>34.85</td><td>11.02</td><td>31.91</td><td>324</td><td>71 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5290.00	90.67	-----	76.71	34.85	11.02	31.91	324
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5149.99	44.03	54.00	-9.97	29.86	34.87	11.08	31.78	324	71 AVERAGE																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5290.00	90.67	-----	76.71	34.85	11.02	31.91	324	71 AVERAGE																																																																																	



		27																																																																																								
Mode		Band Edge - L																																																																																								
		U-NII-2A_5.25-5.35_802.11ac VHT80_CH58_5290MHz																																																																																								
ANT		CDD																																																																																								
Pol.		Vertical					Fundamental																																																																																			
Peak	 Date: 2024-01-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5147.44</td><td>56.62</td><td>74.00</td><td>-17.38</td><td>42.44</td><td>34.87</td><td>11.09</td><td>31.78</td><td>193 209 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5147.44	56.62	74.00	-17.38	42.44	34.87	11.09	31.78	193 209 PEAK	 Date: 2024-01-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5290.00</td><td>101.75</td><td>-----</td><td>-----</td><td>87.82</td><td>34.85</td><td>11.01</td><td>31.93</td><td>193 209 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5290.00	101.75	-----	-----	87.82	34.85	11.01	31.93	193 209 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5147.44	56.62	74.00	-17.38	42.44	34.87	11.09	31.78	193 209 PEAK																																																																																	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5290.00	101.75	-----	-----	87.82	34.85	11.01	31.93	193 209 PEAK																																																																																	
Avg	 Date: 2024-01-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5148.94</td><td>47.27</td><td>54.00</td><td>-6.73</td><td>33.09</td><td>34.87</td><td>11.09</td><td>31.78</td><td>193 209 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5148.94	47.27	54.00	-6.73	33.09	34.87	11.09	31.78	193 209 AVERAGE	 Date: 2024-01-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5290.00</td><td>94.52</td><td>-----</td><td>-----</td><td>80.58</td><td>34.85</td><td>11.01</td><td>31.92</td><td>193 209 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5290.00	94.52	-----	-----	80.58	34.85	11.01	31.92	193 209 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5148.94	47.27	54.00	-6.73	33.09	34.87	11.09	31.78	193 209 AVERAGE																																																																																	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5290.00	94.52	-----	-----	80.58	34.85	11.01	31.92	193 209 AVERAGE																																																																																	



Mode	27																																																																																																																																	
	Harmonic																																																																																																																																	
	U-NII-2A_5.25-5.35_802.11ac VHT80_CH58_5290MHz																																																																																																																																	
ANT	CDD																																																																																																																																	
Pol.	Horizontal						Vertical																																																																																																																											
Peak Avg	Level (dBuV/m) Date: 2024-01-12 <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>10580.00</td><td>49.24</td><td>68.30</td><td>-19.06</td><td>61.77</td><td>38.83</td><td>12.22</td><td>63.58</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15870.00</td><td>50.32</td><td>74.00</td><td>-23.68</td><td>58.69</td><td>41.00</td><td>14.73</td><td>64.10</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	10580.00	49.24	68.30	-19.06	61.77	38.83	12.22	63.58	---	---	Peak	2	15870.00	50.32	74.00	-23.68	58.69	41.00	14.73	64.10	---	---	Peak	Level (dBuV/m) Date: 2024-01-12 <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>10580.00</td><td>48.46</td><td>68.30</td><td>-19.84</td><td>60.99</td><td>38.83</td><td>12.22</td><td>63.58</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15870.00</td><td>50.09</td><td>74.00</td><td>-23.91</td><td>58.46</td><td>41.00</td><td>14.73</td><td>64.10</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	10580.00	48.46	68.30	-19.84	60.99	38.83	12.22	63.58	---	---	Peak	2	15870.00	50.09	74.00	-23.91	58.46	41.00	14.73	64.10	---	---	Peak
			Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																						
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																										
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	10580.00	49.24	68.30	-19.06	61.77	38.83	12.22	63.58	---	---	Peak																																																																																																																							
2	15870.00	50.32	74.00	-23.68	58.69	41.00	14.73	64.10	---	---	Peak																																																																																																																							
		Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	10580.00	48.46	68.30	-19.84	60.99	38.83	12.22	63.58	---	---	Peak																																																																																																																							
2	15870.00	50.09	74.00	-23.91	58.46	41.00	14.73	64.10	---	---	Peak																																																																																																																							



Mode	28																																																																																											
	Band Edge - L																																																																																											
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH106_5530MHz																																																																																											
ANT	CDD																																																																																											
Pol.	Horizontal	Fundamental																																																																																										
Peak	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5421.21</td><td>52.61</td><td>74.00</td><td>-21.39</td><td>38.95</td><td>34.82</td><td>10.96</td><td>32.12</td><td>345</td><td>70</td><td>PEAK</td></tr><tr><td>2</td><td>5466.01</td><td>53.06</td><td>68.30</td><td>-15.24</td><td>39.27</td><td>34.81</td><td>11.15</td><td>32.17</td><td>345</td><td>70</td><td>PEAK</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5421.21	52.61	74.00	-21.39	38.95	34.82	10.96	32.12	345	70	PEAK	2	5466.01	53.06	68.30	-15.24	39.27	34.81	11.15	32.17	345	70	PEAK	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5530.00</td><td>93.78</td><td>-----</td><td>-----</td><td>79.83</td><td>34.82</td><td>11.35</td><td>32.22</td><td>345</td><td>70</td><td>PEAK</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5530.00	93.78	-----	-----	79.83	34.82	11.35	32.22	345	70	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5421.21	52.61	74.00	-21.39	38.95	34.82	10.96	32.12	345	70	PEAK																																																																																	
2	5466.01	53.06	68.30	-15.24	39.27	34.81	11.15	32.17	345	70	PEAK																																																																																	
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5530.00	93.78	-----	-----	79.83	34.82	11.35	32.22	345	70	PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5458.63</td><td>43.03</td><td>54.00</td><td>-10.97</td><td>29.27</td><td>34.81</td><td>11.11</td><td>32.16</td><td>345</td><td>70</td><td>AVERAGE</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5458.63	43.03	54.00	-10.97	29.27	34.81	11.11	32.16	345	70	AVERAGE	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5530.00</td><td>86.27</td><td>-----</td><td>-----</td><td>72.32</td><td>34.82</td><td>11.35</td><td>32.22</td><td>345</td><td>70</td><td>AVERAGE</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5530.00	86.27	-----	-----	72.32	34.82	11.35	32.22	345	70	AVERAGE												
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5458.63	43.03	54.00	-10.97	29.27	34.81	11.11	32.16	345	70	AVERAGE																																																																																	
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5530.00	86.27	-----	-----	72.32	34.82	11.35	32.22	345	70	AVERAGE																																																																																	



Mode	28																																																																																											
	Band Edge - L																																																																																											
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH106_5530MHz																																																																																											
ANT	CDD																																																																																											
Pol.	Vertical	Fundamental																																																																																										
Peak	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5453.77</td><td>55.13</td><td>74.00</td><td>-18.87</td><td>41.39</td><td>34.81</td><td>11.09</td><td>32.16</td><td>300 226 PEAK</td></tr><tr><td>2</td><td>5469.99</td><td>56.64</td><td>68.30</td><td>-11.66</td><td>42.85</td><td>34.81</td><td>11.16</td><td>32.18</td><td>300 226 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5453.77	55.13	74.00	-18.87	41.39	34.81	11.09	32.16	300 226 PEAK	2	5469.99	56.64	68.30	-11.66	42.85	34.81	11.16	32.18	300 226 PEAK	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5530.00</td><td>99.31</td><td>-----</td><td>-----</td><td>85.28</td><td>34.85</td><td>11.42</td><td>32.24</td><td>300 226 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5530.00	99.31	-----	-----	85.28	34.85	11.42	32.24	300 226 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5453.77	55.13	74.00	-18.87	41.39	34.81	11.09	32.16	300 226 PEAK																																																																																			
2	5469.99	56.64	68.30	-11.66	42.85	34.81	11.16	32.18	300 226 PEAK																																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5530.00	99.31	-----	-----	85.28	34.85	11.42	32.24	300 226 PEAK																																																																																			
Avg	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5432.55</td><td>44.95</td><td>54.00</td><td>-9.05</td><td>31.26</td><td>34.81</td><td>11.01</td><td>32.13</td><td>300 226 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5432.55	44.95	54.00	-9.05	31.26	34.81	11.01	32.13	300 226 AVERAGE	Level (dBuV/m) Date: 2024-01-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5530.00</td><td>91.92</td><td>-----</td><td>-----</td><td>77.89</td><td>34.85</td><td>11.42</td><td>32.24</td><td>300 226 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5530.00	91.92	-----	-----	77.89	34.85	11.42	32.24	300 226 AVERAGE										
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5432.55	44.95	54.00	-9.05	31.26	34.81	11.01	32.13	300 226 AVERAGE																																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5530.00	91.92	-----	-----	77.89	34.85	11.42	32.24	300 226 AVERAGE																																																																																			



Mode	28																																									
	Band Edge - R																																									
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH106_5530MHz																																									
ANT	CDD																																									
Pol.	Vertical	Fundamental																																								
Peak	Date: 2024-01-04 Level (dBuV/m) Frequency (MHz) PART 15.407 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5752.45</td><td>53.06</td><td>68.30</td><td>-15.24</td><td>38.68</td><td>35.15</td><td>11.64</td><td>32.41</td><td>300</td><td>226</td><td>PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5752.45	53.06	68.30	-15.24	38.68	35.15	11.64	32.41	300	226	PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5752.45	53.06	68.30	-15.24	38.68	35.15	11.64	32.41	300	226	PEAK																															



Mode	28																																																																																																																																	
	Harmonic																																																																																																																																	
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH106_5530MHz																																																																																																																																	
ANT	CDD																																																																																																																																	
Pol.	Horizontal						Vertical																																																																																																																											
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>11060.00</td><td>48.48</td><td>74.00</td><td>-25.52</td><td>60.31</td><td>39.02</td><td>12.57</td><td>63.42</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>16590.00</td><td>49.82</td><td>68.30</td><td>-18.48</td><td>57.95</td><td>41.39</td><td>15.23</td><td>64.75</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	11060.00	48.48	74.00	-25.52	60.31	39.02	12.57	63.42	---	---	Peak	2	16590.00	49.82	68.30	-18.48	57.95	41.39	15.23	64.75	---	---	Peak	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr><tr><td>1</td><td>11060.00</td><td>49.67</td><td>74.00</td><td>-24.33</td><td>61.50</td><td>39.02</td><td>12.57</td><td>63.42</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>16590.00</td><td>50.84</td><td>68.30</td><td>-17.46</td><td>58.97</td><td>41.39</td><td>15.23</td><td>64.75</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	11060.00	49.67	74.00	-24.33	61.50	39.02	12.57	63.42	---	---	Peak	2	16590.00	50.84	68.30	-17.46	58.97	41.39	15.23	64.75	---	---	Peak
			Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																						
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	11060.00	48.48	74.00	-25.52	60.31	39.02	12.57	63.42	---	---	Peak																																																																																																																							
2	16590.00	49.82	68.30	-18.48	57.95	41.39	15.23	64.75	---	---	Peak																																																																																																																							
		Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	11060.00	49.67	74.00	-24.33	61.50	39.02	12.57	63.42	---	---	Peak																																																																																																																							
2	16590.00	50.84	68.30	-17.46	58.97	41.39	15.23	64.75	---	---	Peak																																																																																																																							



Mode	29																																																								
	Band Edge - L																																																								
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH122_5610MHz																																																								
ANT	CDD																																																								
Pol.	Horizontal	Fundamental																																																							
Peak	Level (dBuV/m) Date: 2024-01-04 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor dB cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5429.17</td><td>51.82</td><td>74.00</td><td>-22.18</td><td>38.15</td><td>34.81</td><td>10.99</td><td>32.13</td><td>336</td><td>71 PEAK</td></tr><tr><td>2</td><td>5463.75</td><td>51.30</td><td>68.30</td><td>-17.00</td><td>37.52</td><td>34.81</td><td>11.14</td><td>32.17</td><td>336</td><td>71 PEAK</td></tr></table>		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5429.17	51.82	74.00	-22.18	38.15	34.81	10.99	32.13	336	71 PEAK	2	5463.75	51.30	68.30	-17.00	37.52	34.81	11.14	32.17	336	71 PEAK	Level (dBuV/m) Date: 2024-01-04 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor dB cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5610.00</td><td>91.55</td><td>-----</td><td>-----</td><td>77.23</td><td>34.93</td><td>11.67</td><td>32.28</td><td>336</td><td>71 PEAK</td></tr></table>		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5610.00	91.55	-----	-----	77.23	34.93	11.67	32.28	336	71 PEAK
		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																														
1	5429.17	51.82	74.00	-22.18	38.15	34.81	10.99	32.13	336	71 PEAK																																															
2	5463.75	51.30	68.30	-17.00	37.52	34.81	11.14	32.17	336	71 PEAK																																															
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																															
1	5610.00	91.55	-----	-----	77.23	34.93	11.67	32.28	336	71 PEAK																																															
Avg	Level (dBuV/m) Date: 2024-01-04 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor dB cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5455.17</td><td>42.19</td><td>54.00</td><td>-11.81</td><td>28.44</td><td>34.81</td><td>11.10</td><td>32.16</td><td>336</td><td>71 AVERAGE</td></tr></table>		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5455.17	42.19	54.00	-11.81	28.44	34.81	11.10	32.16	336	71 AVERAGE	Level (dBuV/m) Date: 2024-01-04 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor dB cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5610.00</td><td>84.17</td><td>-----</td><td>-----</td><td>69.82</td><td>34.94</td><td>11.70</td><td>32.29</td><td>336</td><td>71 AVERAGE</td></tr></table>		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1	5610.00	84.17	-----	-----	69.82	34.94	11.70	32.29	336	71 AVERAGE											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																															
1	5455.17	42.19	54.00	-11.81	28.44	34.81	11.10	32.16	336	71 AVERAGE																																															
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																															
1	5610.00	84.17	-----	-----	69.82	34.94	11.70	32.29	336	71 AVERAGE																																															





Mode	29																																																																
	Band Edge - R																																																																
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH122_5610MHz																																																																
ANT	CDD																																																																
Pol.	Horizontal	Fundamental																																																															
Peak	Date: 2024-01-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th></tr><tr><td>1</td><td>5734.87</td><td>53.24</td><td>68.30</td><td>-15.06</td><td>38.85</td><td>35.13</td><td>11.65</td><td>32.39</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>336</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>71</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	1	5734.87	53.24	68.30	-15.06	38.85	35.13	11.65	32.39									336									71									PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark																																																									
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm																																																									
1	5734.87	53.24	68.30	-15.06	38.85	35.13	11.65	32.39																																																									
								336																																																									
								71																																																									
								PEAK																																																									



Mode	29																																																																																											
	Band Edge - L																																																																																											
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH122_5610MHz																																																																																											
ANT	CDD																																																																																											
Pol.	Vertical	Fundamental																																																																																										
Peak	Level (dBuV/m) Date: 2024-01-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5452.60</td><td>51.99</td><td>74.00</td><td>-22.01</td><td>38.25</td><td>34.81</td><td>11.09</td><td>32.16</td><td>200 10 PEAK</td></tr><tr><td>2</td><td>5465.31</td><td>53.50</td><td>68.30</td><td>-14.80</td><td>39.72</td><td>34.81</td><td>11.14</td><td>32.17</td><td>200 10 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5452.60	51.99	74.00	-22.01	38.25	34.81	11.09	32.16	200 10 PEAK	2	5465.31	53.50	68.30	-14.80	39.72	34.81	11.14	32.17	200 10 PEAK	Level (dBuV/m) Date: 2024-01-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5610.00</td><td>99.19</td><td>-----</td><td>-----</td><td>84.82</td><td>34.98</td><td>11.70</td><td>32.31</td><td>200 10 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5610.00	99.19	-----	-----	84.82	34.98	11.70	32.31	200 10 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5452.60	51.99	74.00	-22.01	38.25	34.81	11.09	32.16	200 10 PEAK																																																																																			
2	5465.31	53.50	68.30	-14.80	39.72	34.81	11.14	32.17	200 10 PEAK																																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5610.00	99.19	-----	-----	84.82	34.98	11.70	32.31	200 10 PEAK																																																																																			
Avg	Level (dBuV/m) Date: 2024-01-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5458.81</td><td>42.80</td><td>54.00</td><td>-11.20</td><td>29.03</td><td>34.81</td><td>11.12</td><td>32.16</td><td>200 10 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5458.81	42.80	54.00	-11.20	29.03	34.81	11.12	32.16	200 10 AVERAGE	Level (dBuV/m) Date: 2024-01-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5610.00</td><td>92.15</td><td>-----</td><td>-----</td><td>77.78</td><td>34.98</td><td>11.70</td><td>32.31</td><td>200 10 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5610.00	92.15	-----	-----	77.78	34.98	11.70	32.31	200 10 AVERAGE										
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5458.81	42.80	54.00	-11.20	29.03	34.81	11.12	32.16	200 10 AVERAGE																																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5610.00	92.15	-----	-----	77.78	34.98	11.70	32.31	200 10 AVERAGE																																																																																			

Mode	29																																										
	Band Edge - R																																										
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH122_5610MHz																																										
ANT	CDD																																										
Pol.	Vertical					Fundamental																																					
Peak	Date: 2024-01-04 <table><tr><th>Freq</th><th>Level</th><th>Limit Line</th><th>Margin (dB)</th><th>Read Level</th><th>Ant Factor</th><th>Cable Loss</th><th>Preamplifier</th><th>Apos</th><th>TPos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1 5726.19</td><td>58.64</td><td>68.30</td><td>-9.66</td><td>44.26</td><td>35.12</td><td>11.65</td><td>32.39</td><td>200</td><td>10</td><td>PEAK</td></tr></table>					Freq	Level	Limit Line	Margin (dB)	Read Level	Ant Factor	Cable Loss	Preamplifier	Apos	TPos	Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg		1 5726.19	58.64	68.30	-9.66	44.26	35.12	11.65	32.39	200	10	PEAK	Blank				
Freq	Level	Limit Line	Margin (dB)	Read Level	Ant Factor	Cable Loss	Preamplifier	Apos	TPos	Remark																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																		
1 5726.19	58.64	68.30	-9.66	44.26	35.12	11.65	32.39	200	10	PEAK																																	



Mode	29																																																																																																																			
	Harmonic																																																																																																																			
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH122_5610MHz																																																																																																																			
ANT	CDD																																																																																																																			
Pol.	Horizontal						Vertical																																																																																																													
Peak Avg	Level (dBuV/m) Date: 2024-01-12 						Level (dBuV/m) Date: 2024-01-12 																																																																																																													
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11220.00</td><td>49.12</td><td>74.00</td><td>-24.88</td><td>60.78</td><td>39.09</td><td>12.68</td><td>63.43</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>16830.00</td><td>49.11</td><td>68.30</td><td>-19.19</td><td>57.19</td><td>41.51</td><td>15.41</td><td>65.00</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11220.00	49.12	74.00	-24.88	60.78	39.09	12.68	63.43	---	---	Peak	2	16830.00	49.11	68.30	-19.19	57.19	41.51	15.41	65.00	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11220.00</td><td>48.59</td><td>74.00</td><td>-25.41</td><td>60.25</td><td>39.09</td><td>12.68</td><td>63.43</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>16830.00</td><td>50.09</td><td>68.30</td><td>-18.21</td><td>58.17</td><td>41.51</td><td>15.41</td><td>65.00</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11220.00	48.59	74.00	-25.41	60.25	39.09	12.68	63.43	---	---	Peak	2	16830.00	50.09	68.30	-18.21	58.17	41.51	15.41	65.00	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																												
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																											
1	11220.00	49.12	74.00	-24.88	60.78	39.09	12.68	63.43	---	---	Peak																																																																																																									
2	16830.00	49.11	68.30	-19.19	57.19	41.51	15.41	65.00	---	---	Peak																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																											
1	11220.00	48.59	74.00	-25.41	60.25	39.09	12.68	63.43	---	---	Peak																																																																																																									
2	16830.00	50.09	68.30	-18.21	58.17	41.51	15.41	65.00	---	---	Peak																																																																																																									



Mode	30																																																																									
	Band Edge - L																																																																									
	U-NII-2A_5.25-5.35_802.11ac VHT160_CH50_5250MHz																																																																									
ANT	CDD																																																																									
Pol.	Horizontal	Fundamental																																																																								
Peak	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5133.75</td><td>60.52</td><td>74.00</td><td>-13.48</td><td>48.40</td><td>36.12</td><td>8.51</td><td>32.51</td><td>400 263 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5133.75	60.52	74.00	-13.48	48.40	36.12	8.51	32.51	400 263 PEAK	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5250.00</td><td>99.80</td><td>-----</td><td>-----</td><td>87.26</td><td>36.05</td><td>8.84</td><td>32.35</td><td>400 263 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5250.00	99.80	-----	-----	87.26	36.05	8.84	32.35	400 263 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																			
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5133.75	60.52	74.00	-13.48	48.40	36.12	8.51	32.51	400 263 PEAK																																																																		
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																			
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5250.00	99.80	-----	-----	87.26	36.05	8.84	32.35	400 263 PEAK																																																																		
Avg	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5123.75</td><td>48.34</td><td>54.00</td><td>-5.66</td><td>36.25</td><td>36.13</td><td>8.49</td><td>32.53</td><td>400 263 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5123.75	48.34	54.00	-5.66	36.25	36.13	8.49	32.53	400 263 AVERAGE	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5250.00</td><td>93.07</td><td>-----</td><td>-----</td><td>80.53</td><td>36.05</td><td>8.84</td><td>32.35</td><td>400 263 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5250.00	93.07	-----	-----	80.53	36.05	8.84	32.35	400 263 AVERAGE
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																			
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5123.75	48.34	54.00	-5.66	36.25	36.13	8.49	32.53	400 263 AVERAGE																																																																		
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																			
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5250.00	93.07	-----	-----	80.53	36.05	8.84	32.35	400 263 AVERAGE																																																																		





Mode	30																																																		
	Band Edge - R																																																		
	U-NII-2A_5.25-5.35_802.11ac VHT160_CH50_5250MHz																																																		
ANT	CDD																																																		
Pol.	Horizontal					Fundamental																																													
Peak	Date: 2024-01-08 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5359.62</td><td>51.43</td><td>74.00</td><td>-22.57</td><td>38.24</td><td>35.98</td><td>9.41</td><td>32.20</td><td>400</td><td>263 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5359.62	51.43	74.00	-22.57	38.24	35.98	9.41	32.20	400	263 PEAK	Blank				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																										
1	5359.62	51.43	74.00	-22.57	38.24	35.98	9.41	32.20	400	263 PEAK																																									
Avg	Date: 2024-01-08 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5377.89</td><td>42.84</td><td>54.00</td><td>-11.16</td><td>29.53</td><td>35.97</td><td>9.51</td><td>32.17</td><td>400</td><td>263 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5377.89	42.84	54.00	-11.16	29.53	35.97	9.51	32.17	400	263 AVERAGE	Blank				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																										
1	5377.89	42.84	54.00	-11.16	29.53	35.97	9.51	32.17	400	263 AVERAGE																																									



Mode	30																																																																																	
	Band Edge - L																																																																																	
	U-NII-2A_5.25-5.35_802.11ac VHT160_CH50_5250MHz																																																																																	
ANT	CDD																																																																																	
Pol.	Vertical	Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5149.00</td><td>61.48</td><td>74.00</td><td>-12.52</td><td>49.33</td><td>36.11</td><td>8.53</td><td>32.49</td><td>358 156 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5149.00	61.48	74.00	-12.52	49.33	36.11	8.53	32.49	358 156 PEAK	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5250.00</td><td>95.83</td><td>-----</td><td>-----</td><td>83.19</td><td>36.04</td><td>8.93</td><td>32.33</td><td>358 156 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5250.00	95.83	-----	-----	83.19	36.04	8.93	32.33	358 156 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5149.00	61.48	74.00	-12.52	49.33	36.11	8.53	32.49	358 156 PEAK																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5250.00	95.83	-----	-----	83.19	36.04	8.93	32.33	358 156 PEAK																																																																									
Avg	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5144.25</td><td>45.12</td><td>54.00</td><td>-8.88</td><td>32.99</td><td>36.11</td><td>8.52</td><td>32.50</td><td>358 156 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5144.25	45.12	54.00	-8.88	32.99	36.11	8.52	32.50	358 156 AVERAGE	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5250.00</td><td>87.23</td><td>-----</td><td>-----</td><td>74.59</td><td>36.04</td><td>8.93</td><td>32.33</td><td>358 156 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5250.00	87.23	-----	-----	74.59	36.04	8.93	32.33	358 156 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5144.25	45.12	54.00	-8.88	32.99	36.11	8.52	32.50	358 156 AVERAGE																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5250.00	87.23	-----	-----	74.59	36.04	8.93	32.33	358 156 AVERAGE																																																																									







Mode	30																																										
	Band Edge - R																																										
	U-NII-2A_5.25-5.35_802.11ac VHT160_CH50_5250MHz																																										
ANT	CDD																																										
Pol.	Vertical	Fundamental																																									
Peak	Date: 2024-01-08 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5370.12</td><td>52.68</td><td>74.00</td><td>-21.32</td><td>39.41</td><td>35.98</td><td>9.47</td><td>32.18</td><td>358</td><td>156 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5370.12	52.68	74.00	-21.32	39.41	35.98	9.47	32.18	358	156 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5370.12	52.68	74.00	-21.32	39.41	35.98	9.47	32.18	358	156 PEAK																																	
Avg	Date: 2024-01-08 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5456.64</td><td>41.99</td><td>54.00</td><td>-12.01</td><td>28.43</td><td>35.93</td><td>9.69</td><td>32.06</td><td>358</td><td>156 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5456.64	41.99	54.00	-12.01	28.43	35.93	9.69	32.06	358	156 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5456.64	41.99	54.00	-12.01	28.43	35.93	9.69	32.06	358	156 AVERAGE																																	



Mode	30																																																																																																	
	Harmonic																																																																																																	
	U-NII-2A_5.25-5.35_802.11ac VHT160_CH50_5250MHz																																																																																																	
ANT	CDD																																																																																																	
Pol.	Horizontal	Vertical																																																																																																
Peak Avg	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 10500.00</td><td>47.52</td><td>68.30</td><td>-20.78</td><td>60.16</td><td>38.80</td><td>12.16</td><td>63.60</td><td>---</td><td>--- Peak</td></tr><tr><td>2 15750.00</td><td>48.44</td><td>74.00</td><td>-25.56</td><td>56.92</td><td>40.90</td><td>14.68</td><td>64.06</td><td>---</td><td>--- Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10500.00	47.52	68.30	-20.78	60.16	38.80	12.16	63.60	---	--- Peak	2 15750.00	48.44	74.00	-25.56	56.92	40.90	14.68	64.06	---	--- Peak	Level (dBuV/m) Date: 2024-01-12 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 10500.00</td><td>47.59</td><td>68.30</td><td>-20.71</td><td>60.23</td><td>38.80</td><td>12.16</td><td>63.60</td><td>---</td><td>--- Peak</td></tr><tr><td>2 15750.00</td><td>50.36</td><td>74.00</td><td>-23.64</td><td>58.84</td><td>40.90</td><td>14.68</td><td>64.06</td><td>---</td><td>--- Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10500.00	47.59	68.30	-20.71	60.23	38.80	12.16	63.60	---	--- Peak	2 15750.00	50.36	74.00	-23.64	58.84	40.90	14.68	64.06	---	--- Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																										
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																									
1 10500.00	47.52	68.30	-20.78	60.16	38.80	12.16	63.60	---	--- Peak																																																																																									
2 15750.00	48.44	74.00	-25.56	56.92	40.90	14.68	64.06	---	--- Peak																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																											
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																										
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																									
1 10500.00	47.59	68.30	-20.71	60.23	38.80	12.16	63.60	---	--- Peak																																																																																									
2 15750.00	50.36	74.00	-23.64	58.84	40.90	14.68	64.06	---	--- Peak																																																																																									



Mode	31																																																																																																						
	Band Edge - L																																																																																																						
	U-NII-2C_5.47-5.725_802.11ac VHT160_CH114_5570MHz																																																																																																						
ANT	CDD																																																																																																						
Pol.	Horizontal					Fundamental																																																																																																	
Peak	 Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) PART 15.407					 Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) PART 15.407																																																																																																	
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5454.72</td><td>57.65</td><td>74.00</td><td>-16.35</td><td>44.10</td><td>35.93</td><td>9.68</td><td>32.06</td><td>100</td><td>247 PEAK</td></tr><tr><td>2</td><td>5460.66</td><td>62.48</td><td>68.30</td><td>-5.82</td><td>48.93</td><td>35.92</td><td>9.69</td><td>32.06</td><td>100</td><td>247 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5454.72	57.65	74.00	-16.35	44.10	35.93	9.68	32.06	100	247 PEAK	2	5460.66	62.48	68.30	-5.82	48.93	35.92	9.69	32.06	100	247 PEAK	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5570.00</td><td>99.82</td><td>-----</td><td>-----</td><td>86.16</td><td>35.98</td><td>9.74</td><td>32.06</td><td>100</td><td>247 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5570.00	99.82	-----	-----	86.16	35.98	9.74	32.06	100	247 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																													
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																														
1	5454.72	57.65	74.00	-16.35	44.10	35.93	9.68	32.06	100	247 PEAK																																																																																													
2	5460.66	62.48	68.30	-5.82	48.93	35.92	9.69	32.06	100	247 PEAK																																																																																													
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																														
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																														
1	5570.00	99.82	-----	-----	86.16	35.98	9.74	32.06	100	247 PEAK																																																																																													
Avg	 Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) PART 15.407 AVG					 Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) PART 15.407 AVG																																																																																																	
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5436.02</td><td>50.07</td><td>54.00</td><td>-3.93</td><td>36.55</td><td>35.94</td><td>9.67</td><td>32.09</td><td>100</td><td>247 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5436.02	50.07	54.00	-3.93	36.55	35.94	9.67	32.09	100	247 AVERAGE	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5570.00</td><td>93.20</td><td>-----</td><td>-----</td><td>79.53</td><td>35.98</td><td>9.74</td><td>32.05</td><td>100</td><td>247 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5570.00	93.20	-----	-----	79.53	35.98	9.74	32.05	100	247 AVERAGE											
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																													
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																														
1	5436.02	50.07	54.00	-3.93	36.55	35.94	9.67	32.09	100	247 AVERAGE																																																																																													
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																														
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																														
1	5570.00	93.20	-----	-----	79.53	35.98	9.74	32.05	100	247 AVERAGE																																																																																													





Mode	31																																									
	Band Edge - R																																									
	U-NII-2C_5.47-5.725_802.11ac VHT160_CH114_5570MHz																																									
ANT	CDD																																									
Pol.	Horizontal	Fundamental																																								
Peak	Date: 2024-01-08 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5737.12</td><td>59.25</td><td>68.30</td><td>-9.05</td><td>45.22</td><td>36.23</td><td>10.04</td><td>32.24</td><td>100</td><td>247</td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5737.12	59.25	68.30	-9.05	45.22	36.23	10.04	32.24	100	247	PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5737.12	59.25	68.30	-9.05	45.22	36.23	10.04	32.24	100	247	PEAK																															







		31																																																																																																		
Mode		Band Edge - L																																																																																																		
		U-NII-2C_5.47-5.725_802.11ac VHT160_CH114_5570MHz																																																																																																		
ANT		CDD																																																																																																		
Pol.		Vertical					Fundamental																																																																																													
Peak	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5452.74</td><td>57.31</td><td>74.00</td><td>-16.69</td><td>43.77</td><td>35.93</td><td>9.68</td><td>32.07</td><td>400 190 PEAK</td></tr><tr><td>2</td><td>5468.58</td><td>58.56</td><td>68.30</td><td>-9.74</td><td>44.99</td><td>35.92</td><td>9.69</td><td>32.04</td><td>400 190 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5452.74	57.31	74.00	-16.69	43.77	35.93	9.68	32.07	400 190 PEAK	2	5468.58	58.56	68.30	-9.74	44.99	35.92	9.69	32.04	400 190 PEAK	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5570.00</td><td>98.80</td><td>-----</td><td>-----</td><td>85.13</td><td>36.00</td><td>9.74</td><td>32.07</td><td>400 190 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5570.00	98.80	-----	-----	85.13	36.00	9.74	32.07	400 190 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	5452.74	57.31	74.00	-16.69	43.77	35.93	9.68	32.07	400 190 PEAK																																																																																											
2	5468.58	58.56	68.30	-9.74	44.99	35.92	9.69	32.04	400 190 PEAK																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	5570.00	98.80	-----	-----	85.13	36.00	9.74	32.07	400 190 PEAK																																																																																											
Avg	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5444.82</td><td>47.06</td><td>54.00</td><td>-6.94</td><td>33.53</td><td>35.93</td><td>9.68</td><td>32.08</td><td>400 190 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5444.82	47.06	54.00	-6.94	33.53	35.93	9.68	32.08	400 190 AVERAGE	Level (dBuV/m) Date: 2024-01-08 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5570.00</td><td>92.17</td><td>-----</td><td>-----</td><td>78.50</td><td>36.00</td><td>9.74</td><td>32.07</td><td>400 190 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5570.00	92.17	-----	-----	78.50	36.00	9.74	32.07	400 190 AVERAGE										
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	5444.82	47.06	54.00	-6.94	33.53	35.93	9.68	32.08	400 190 AVERAGE																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	5570.00	92.17	-----	-----	78.50	36.00	9.74	32.07	400 190 AVERAGE																																																																																											



Mode		31																																																																																																																				
		Harmonic																																																																																																																				
		U-NII-2C_5.47-5.725_802.11ac VHT160_CH114_5570MHz																																																																																																																				
ANT		CDD																																																																																																																				
Pol.		Horizontal						Vertical																																																																																																														
Peak Avg																																																																																																																						
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>11140.00</td><td>48.62</td><td>74.00</td><td>-25.38</td><td>60.37</td><td>39.06</td><td>12.62</td><td>63.43</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>16710.00</td><td>50.05</td><td>68.30</td><td>-18.25</td><td>58.16</td><td>41.45</td><td>15.32</td><td>64.88</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	11140.00	48.62	74.00	-25.38	60.37	39.06	12.62	63.43	---	---	Peak	2	16710.00	50.05	68.30	-18.25	58.16	41.45	15.32	64.88	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>11140.00</td><td>47.53</td><td>74.00</td><td>-26.47</td><td>59.28</td><td>39.06</td><td>12.62</td><td>63.43</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>16710.00</td><td>50.93</td><td>68.30</td><td>-17.37</td><td>59.04</td><td>41.45</td><td>15.32</td><td>64.88</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	11140.00	47.53	74.00	-26.47	59.28	39.06	12.62	63.43	---	---	Peak	2	16710.00	50.93	68.30	-17.37	59.04	41.45	15.32	64.88	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																														
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																													
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																													
1	11140.00	48.62	74.00	-25.38	60.37	39.06	12.62	63.43	---	---	Peak																																																																																																											
2	16710.00	50.05	68.30	-18.25	58.16	41.45	15.32	64.88	---	---	Peak																																																																																																											
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																														
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																													
1	11140.00	47.53	74.00	-26.47	59.28	39.06	12.62	63.43	---	---	Peak																																																																																																											
2	16710.00	50.93	68.30	-17.37	59.04	41.45	15.32	64.88	---	---	Peak																																																																																																											





Mode	32																																																																																								
	Band Edge																																																																																								
	U-NII-1_5.15-5.25_802.11ax HE20_CH36_Full_5180MHz																																																																																								
ANT	CDD																																																																																								
Pol.	Horizontal					Fundamental																																																																																			
Peak	Level (dBuV/m) Date: 2024-01-05  Frequency (MHz)					Level (dBuV/m) Date: 2024-01-05  Frequency (MHz)																																																																																			
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5134.64</td><td>54.41</td><td>74.00</td><td>-19.59</td><td>42.29</td><td>36.12</td><td>8.51</td><td>32.51</td><td>400</td><td>112 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5134.64	54.41	74.00	-19.59	42.29	36.12	8.51	32.51	400	112 PEAK	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5180.00</td><td>110.11</td><td>-----</td><td>-----</td><td>97.89</td><td>36.09</td><td>8.58</td><td>32.45</td><td>400</td><td>112 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5180.00	110.11	-----	-----	97.89	36.09	8.58	32.45	400
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5134.64	54.41	74.00	-19.59	42.29	36.12	8.51	32.51	400	112 PEAK																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5180.00	110.11	-----	-----	97.89	36.09	8.58	32.45	400	112 PEAK																																																																																
Avg	Level (dBuV/m) Date: 2024-01-05  Frequency (MHz)					Level (dBuV/m) Date: 2024-01-05  Frequency (MHz)																																																																																			
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5149.94</td><td>45.74</td><td>54.00</td><td>-8.26</td><td>33.58</td><td>36.11</td><td>8.54</td><td>32.49</td><td>400</td><td>112 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5149.94	45.74	54.00	-8.26	33.58	36.11	8.54	32.49	400	112 AVERAGE	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5180.00</td><td>102.25</td><td>-----</td><td>-----</td><td>90.03</td><td>36.09</td><td>8.58</td><td>32.45</td><td>400</td><td>112 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5180.00	102.25	-----	-----	90.03	36.09	8.58	32.45	400
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5149.94	45.74	54.00	-8.26	33.58	36.11	8.54	32.49	400	112 AVERAGE																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5180.00	102.25	-----	-----	90.03	36.09	8.58	32.45	400	112 AVERAGE																																																																																



Mode	32																																									
	Band Edge																																									
	U-NII-1_5.15-5.25_802.11ax HE20_CH36_Full_5180MHz																																									
ANT	CDD																																									
Pol.	Vertical	Fundamental																																								
Peak	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5139.86</td><td>52.70</td><td>74.00</td><td>-21.30</td><td>40.56</td><td>36.12</td><td>8.52</td><td>32.50</td><td>400</td><td>186 PEAK</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5139.86	52.70	74.00	-21.30	40.56	36.12	8.52	32.50	400	186 PEAK	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5180.00</td><td>108.51</td><td>-----</td><td>-----</td><td>96.25</td><td>36.09</td><td>8.61</td><td>32.44</td><td>400</td><td>186 PEAK</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5180.00	108.51	-----	-----	96.25	36.09	8.61	32.44	400	186 PEAK
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																
1 5139.86	52.70	74.00	-21.30	40.56	36.12	8.52	32.50	400	186 PEAK																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																	
1 5180.00	108.51	-----	-----	96.25	36.09	8.61	32.44	400	186 PEAK																																	
Avg	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5149.40</td><td>44.55</td><td>54.00</td><td>-9.45</td><td>32.40</td><td>36.11</td><td>8.53</td><td>32.49</td><td>400</td><td>186 AVERAGE</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5149.40	44.55	54.00	-9.45	32.40	36.11	8.53	32.49	400	186 AVERAGE	Level (dBuV/m) Date: 2024-01-05 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1 5180.00</td><td>99.14</td><td>-----</td><td>-----</td><td>86.88</td><td>36.09</td><td>8.61</td><td>32.44</td><td>400</td><td>186 AVERAGE</td></tr></table>	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark	1 5180.00	99.14	-----	-----	86.88	36.09	8.61	32.44	400	186 AVERAGE
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																	
1 5149.40	44.55	54.00	-9.45	32.40	36.11	8.53	32.49	400	186 AVERAGE																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	Remark																																	
1 5180.00	99.14	-----	-----	86.88	36.09	8.61	32.44	400	186 AVERAGE																																	



Mode	32																																																																																																																			
	Harmonic																																																																																																																			
	U-NII-1_5.15-5.25_802.11ax HE20_CH36_Full_5180MHz																																																																																																																			
ANT	CDD																																																																																																																			
Pol.	Horizontal						Vertical																																																																																																													
Peak Avg																																																																																																																				
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr></thead><tbody><tr><td></td><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>cm</td><td>deg</td></tr><tr><td>1</td><td>10360.00</td><td>47.28</td><td>68.30</td><td>-21.02</td><td>60.14</td><td>38.74</td><td>12.06</td><td>63.66</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15540.00</td><td>51.04</td><td>74.00</td><td>-22.96</td><td>59.72</td><td>40.73</td><td>14.58</td><td>63.99</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10360.00	47.28	68.30	-21.02	60.14	38.74	12.06	63.66	---	---	Peak	2	15540.00	51.04	74.00	-22.96	59.72	40.73	14.58	63.99	---	---	Peak	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr></thead><tbody><tr><td></td><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>cm</td><td>deg</td></tr><tr><td>1</td><td>10360.00</td><td>47.22</td><td>68.30</td><td>-21.08</td><td>60.08</td><td>38.74</td><td>12.06</td><td>63.66</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>15540.00</td><td>51.07</td><td>74.00</td><td>-22.93</td><td>59.75</td><td>40.73</td><td>14.58</td><td>63.99</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10360.00	47.22	68.30	-21.08	60.08	38.74	12.06	63.66	---	---	Peak	2	15540.00	51.07	74.00	-22.93	59.75	40.73	14.58	63.99	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																												
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10360.00	47.28	68.30	-21.02	60.14	38.74	12.06	63.66	---	---	Peak																																																																																																									
2	15540.00	51.04	74.00	-22.96	59.72	40.73	14.58	63.99	---	---	Peak																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10360.00	47.22	68.30	-21.08	60.08	38.74	12.06	63.66	---	---	Peak																																																																																																									
2	15540.00	51.07	74.00	-22.93	59.75	40.73	14.58	63.99	---	---	Peak																																																																																																									