FCC §15.247 (i), §2.1091 – RF Exposure

FCC ID: 2AO2SWLC-T05-HWC

Applied procedures / limit
According to FCC §15.247(i) and §1.1307(b)(1), systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy level in excess of the Commission's guidelines.

Limits for Occupational / Controlled Exposure

Frequency Range (MHz)	Electric Field Strength (E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/ cm^2)	Averaging Time $|E|^2$,$|H|^2$ or S (minutes)
0.3-3.0	614	1.63	(100)*	6
3.0-30	1842 / f	4.89 / f	(900 / f)*	6
30-300	61.4	0.163	1.0	6
300-1500			F/300	6
1500-100,000			5	6

Note: ƒ is frequency in MHz
   * = Power density limit is applicable at frequencies greater than 100 MHz

Limits for General Population / Uncontrolled Exposure

Frequency Range (MHz)	Electric Field Strength (E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/ cm^2)	Averaging Time $|E|^2$,$|H|^2$ or S (minutes)
0.3-1.34	614	1.63	(100)*	30
1.34-30	824/f	2.19/f	(180/f)*	30
30-300	27.5	0.073	0.2	30
300-1500			F/1500	30
1500-100,000			1.0	30

Note: f = frequency in MHz
   * = Plane-wave equivalent power density

MPE PREDICTION

Predication of MPE limit at a given distance, Equation from OET Bulletin 65, Edition 97-01

$$S = PG/4\pi R^2$$

Where: S = power density
P = power input to antenna
G = power gain of the antenna in the direction of interest relative to an isotropic radiator
R = distance to the center of radiation of the antenna,R=20cm

Test Result of RF Exposure Evaluation

	Modes& Channel Freq. (MHz)	Tune up Produce power	Maximum peak output power (dBm)	Output power to antenna (mW)	Antenna Gain (numeric)	Power Density (S) (mW/ cm2)	Limit (mW / cm2)	Result
EDR	8DPSK& LCH	5±1	6	3.9811	0.8551 (-0.68dBi)	0.0007	1	Pass
BLE	GFSK& HCH	0±1	1	1.2589	0.8551 (-0.68dBi)	0.0002	1	Pass
Zigbee	O-QPSK& HCH	3±1	4	2.5119	2.1878 (3.4dBi)	0.0011	1	Pass
2.4G WIFI	802.11b&2 412	14±1	15	31.6228	0.8551 (-0.68dBi)	0.0054	1	Pass

S=0.0011/1+0.0054/1=0.0065 < 1，The result is pass