

RF Exposure Requirements: **§90.1217, §1.1307(b)(1) and §1.1307(b)(2):** Systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess of the Commission's guidelines.

RF Radiation Exposure Limit: **§1.1310:** As specified in this section, the Maximum Permissible Exposure (MPE) Limit shall be used to evaluate the environmental impact of human exposure to radiofrequency (RF) radiation as specified in Sec. 1.1307(b), except in the case of portable devices which shall be evaluated according to the provisions of Sec. 2.1093 of this chapter.

MPE Limit Calculation: EUT's operating frequencies @ 4940-4990 MHz; highest conducted power = 24.28 dBm (peak) therefore, **Limit for Uncontrolled exposure: 1 mW/cm² or 10 W/m²**

Equation from page 18 of OET 65, Edition 97-01

EUT with 9 dBi Omni Antenna

$$S = PG / 4\pi R^2 \quad \text{or} \quad R = \sqrt{PG / 4\pi S}$$

where, S = Power Density (1 mW/cm²)

P = Power Input to antenna (267.92 mW)

G = Antenna Gain (7.94 numeric)

$$R = (267.92 * 7.94 / 4 * 3.14)^{1/2} = (2128.14 / 12.56)^{1/2} = 13.02 \text{ cm} \text{ in order to comply with } 1 \text{ mW/cm}^2$$

$$S = (267.92 * 7.94 / 4 * 3.14 * 20.0^2) = (2128.14 / 5024) = 0.43 \text{ mW/cm}^2 \text{ @ 20cm separation}$$

EUT with 16 dBi Sector Antenna

$$S = PG / 4\pi R^2 \quad \text{or} \quad R = \sqrt{PG / 4\pi S}$$

where, S = Power Density (1 mW/cm²)

P = Power Input to antenna (267.92 mW)

G = Antenna Gain (39.81 numeric)

$$R = (267.92 * 39.81 / 4 * 3.14)^{1/2} = (10665.96 / 12.56)^{1/2} = 29.14 \text{ cm} \text{ in order to comply with } 1 \text{ mW/cm}^2$$

$$S = (267.92 * 39.81 / 4 * 3.14 * 20.0^2) = (10665.96 / 5024) = 2.12 \text{ mW/cm}^2 \text{ @ 20cm separation}$$

EUT with 19 dBi Panel Antenna

$$S = PG / 4\pi R^2 \quad \text{or} \quad R = \sqrt{PG / 4\pi S}$$

where, S = Power Density (1 mW/cm²)

P = Power Input to antenna (267.92 mW)

G = Antenna Gain (79.43 numeric)

$$R = (267.92 * 79.43 / 4 * 3.14)^{1/2} = (21281.39 / 12.56)^{1/2} = 41.16 \text{ cm} \text{ in order to comply with } 1 \text{ mW/cm}^2$$

$$S = (267.92 * 79.43 / 4 * 3.14 * 20.0^2) = (21281.39 / 5024) = 4.23 \text{ mW/cm}^2 \text{ @ 20cm separation}$$