Amedia Networks Inc.
Digital Media Adaptor DMA3.1L

## **Electromagnetic Compatibility Criteria for Intentional Radiators**

**RF Exposure Requirements:** 

§1.1307(b)(1) and §1.1307(b)(2): Systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess of the Commission's guidelines.

**RF Radiation Exposure Limit:** 

**§1.1310:** As specified in this section, the Maximum Permissible Exposure (MPE) Limit shall be used to evaluate the environmental impact of human exposure to radiofrequency (RF) radiation as specified in Sec. 1.1307(b), except in the case of portable devices which shall be evaluated according to the provisions of Sec. 2.1093 of this chapter.

Limit for Uncontrolled exposure: 1 mW/cm<sup>2</sup> or 10 W/m<sup>2</sup>

EUT maximum antenna gain = 0 dBi.

Equation from page 18 of OET 65, Edition 97-01

$$S = PG / 4\pi R^2$$
 or  $R = \int PG / 4\pi S$ 

where,  $S = Power Density (1 mW/cm^2)$ 

P = Power Input to antenna (mW)

G = Antenna Gain (63.1 numeric)

## Low Band

Power Input to Antenna in dBm	15.53
Power Input to Antenna in W	0.035727284
Antenna Gain in dBi	2
Numeric Antenna Gain	1.584893192
S (W/m2)	0.112706865

R=2.12 cm

## **High Band**

Power Input to Antenna in dBm	23.92
Power Input to Antenna in W	0.246603934
Antenna Gain in dBi	2
Numeric Antenna Gain	1.584893192
S (W/m2)	0.777947643

R=5.57cm