

Bluetooth Stereo Headset

- 1) Boot pairing: Turned off, press the multifunctional key for about 3 seconds long boot blue lights flash in pairing mode after five times, or take off from the launch tower automatic startup blue lights flash in pairing mode after 5 times (base on 5 v and was on), will see the red light blue light flashing, indicates that the bluetooth hands-free in matching the search state, operating mobile phone or TVX59 launch can make matching. After the device is powered on, it is automatically connected to the paired device.
- 2) Shutdown: In power-on state, long press the multi-function button for about 3 seconds to shut down, and the red light flashes 5 times with a prompt tone.
- 3) Answering function: When there is an external call on a connected mobile phone, press the multi-function button to answer the call. There is a prompt tone.
- 4) Hang up function: During a call, you can hang up the phone by pressing the multi-function key.
- 5) Reject calls: Connect the mobile phone. When there is an external call, long press the multi-function button for about 2 seconds to reject the call.
- 6) Volume adjustment: During a call or music playback, press the + key to turn up the volume, and press the - key to turn down the volume. There is an announcement for the maximum and minimum volume.
- 7) Start SIRI: in standby state, long press the multi-function for about 1.5 seconds to release, you can start the phone SIRI (need bluetooth support of the phone), there is a prompt sound.
- 8) Voice transfer: During the conversation, long press the volume "+" button for about 2 seconds, you will hear a beep, and then the sound will be transferred from the headset to the phone. The same operation transfers sound from the phone back to the headphones.
- 9) Call mute: During a call, long press the volume "-" button for about 2 seconds to turn off the microphone, and perform the same operation to turn on the microphone, and there will be a prompt tone.
- 10) Play pause music: short press the multifunction button to play pause music.
- 11) Music up and down: long press the volume "-" button for about 2 seconds to play the last song, long press the volume "+" button for about 2 seconds to play the next song.
- 12) Double connection:
A is connected with the first mobile phone A;

SHENZHEN SURE THING INDUSTRY AND COMMERCE DEVELOPMENT CO.,LTD
Bluetooth Stereo Headset

B turns off the bluetooth of mobile phone A, and TVX59 automatically enters the pairing mode;

C searches and connects with the second mobile phone B;

D manually connects to the first mobile phone A, so that bluetooth connects to two mobile phones.

13) Call Transfer:

A When mobile phone A is talking and there is an incoming call from mobile phone B, double-click the multi-function button to answer the call from mobile phone B. When answering the call from mobile phone B, the call from mobile phone A is automatically hanging up.

B When mobile phone A is talking and there is an incoming call from mobile phone B, hold down the multi-function button for about 2 seconds to reject the call from mobile phone B and hold the call from mobile phone A.

14) Support display of battery quantity when connected to IPHONE.

15) Clear pairing: In standby state, hold down the volume "+/-" key for about 5 seconds to clear pairing. After clearing pairing, you can enter pairing state again with a prompt tone.

16) Redial of last number: in standby state, double click the multi-function key will dial the last group of dialed numbers, with a prompt tone.

17)Line input: Line songs can be played on or off the headset.

A Bluetooth headset connection status When Line song is entered: The Line song is played preferentially. In this case, the Line Line must be unplugged to answer an incoming call.

B The Line song can be normally played when the Bluetooth headset is off. At this time, long press the multi-function button of the headset to start the phone and connect it to the Bluetooth.

Indicator status :(requirement)

Power on:blue light flashes 5 times

Shutdown: red light flashes 5 times

SHENZHEN SURE THING INDUSTRY AND COMMERCE DEVELOPMENT CO.,LTD
Bluetooth Stereo Headset

No connection Standby:the blue indicator blinks every 8 seconds

Connection Standby:the blue indicator blinks every 8 seconds

Pairing status: the red and blue indicator blinks alternately

Call:the blue light flashes every 2 seconds

During a call:the blue light flashes once every 7 seconds

Playing music:the blue light blinks once every 8 seconds

Charging process: red light on

Charge completed:red light off

Low power warning: red light flashes twice every 7 seconds

Exit pairing mode:

1. There is no connection in the pairing mode. After 10 minutes, exit the pairing mode and enter the standby mode.
2. The paired phone enters the pairing mode after the Bluetooth is disconnected. After 10 minutes, the paired phone exits the pairing mode and enters the standby mode.
3. Switch off bluetooth from a distance and enter the pairing mode. Exit the pairing mode after 10 minutes and enter the standby mode

Automatic reconnection (including two cases) :

1. When the headset is turned on, it can automatically connect to the last paired mobile phone.
2. When the communication distance between the headset and the mobile phone exceeds the normal distance (generally more than 10 meters, namely link loss), and the headset returns to the normal communication distance within about 5 minutes, the headset will automatically connect to the newly paired mobile phone.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

SHENZHEN SURE THING INDUSTRY AND COMMERCE DEVELOPMENT CO.,LTD

Bluetooth Stereo Headset

-Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.