



| SH1 Notice Before Using | |
|--|--|
| 01 01. Notice Before Using Thank you for purchasing the Bluetooth® Headset SH1. Please read this User's Manual completely before you use the headset. SH1 is designed for listening to high-quality music wirelessly, based on the latest Bluetooth® wireless technology. SH1 can be easily connected to a mobile phone for calls, conversation, and music listening. It is also capable of connecting to other Bluetooth®-enabled devices like notebooks, iPods, etc. SH1 is compliant with Bluetooth V3.0 specification, supports HSP, HFP, A2DP, and AVRCP profiles. Please make sure your phone or other device supports these profiles. | |


| SH1 Specification | |
|---|--|
| 02 02. Specification Bluetooth® specification: V3.0 Supported profile: HSP, HFP, A2DP, AVRCP Operation range: Up to 10 meters Talk time: 6 hours Play time: 5 hours Standby time: 200 hours Charge time: 1 hour | |

| SH1 Package Contents List | |
|---|--|
| 03 03. Package Contents List Please inspect this package and refer to the package contents list below to verify all items were included in this package: 1. SH1 Bluetooth® headset(1) 2. USB Charging Cable(1) 3. User's Manual(1) 4. Ear Cap (2) | |

| SH1 Bluetooth® Headset Overview | |
|---|--|
| 04 04. SH1 Bluetooth® Headset Overview  The device is equipped with an integrated lithium-polymer battery. Before you use your headset for the first time, you must pair the unit with a Bluetooth®-enabled mobile phone. Pairing is a one-time process and is required only for the first connection with the mobile phone. The SH1 can be connected with two mobile phones simultaneously. 1. Keep the SH1 within 1 meter range of a Bluetooth®-enabled mobile phone. 2. Press and hold the Power/Play button for about 5s, the indicator light will flash red and blue intermittently, the device is now in pairing mode. 3. Find the Bluetooth® setting of your mobile phone and start the search for Bluetooth® devices. (For further details, please refer to the operating instructions of your mobile phone.) | |

| SH1 Battery information | |
|---|--|
| 05 05. Battery information 4) When the battery is fully charged, the red indicator light turns blue. Disconnect the charger from the headset and the outlet. The headset is ready to use.  NOTE: For first time use, please charge the headset fully. - The fully charged battery has power for up to 5 hours of talk-time and 4.5 hours of music playing, and up to 300 hours of standby time. However, the talk and standby times may vary when used with different mobile phones or other compatible Bluetooth® devices, usage settings, usage styles, and environments. When the battery power is low, the headset will remind you by voice prompt "Battery low" every 20 seconds, and the red indicator light starts to flash. Important: Ensure that the battery is fully charged if you do not use the device for a long period of time. To avoid a complete discharge of the battery, the SH1 should be charged at least every 3 months. | |

| SH1 Charging the battery | |
|---|--|
| 06 06. Charging the battery The device is equipped with an integrated lithium-polymer battery. Before you use your headset for the first time, you must pair the unit with a Bluetooth®-enabled mobile phone. Pairing is a one-time process and is required only for the first connection with the mobile phone. The SH1 can be connected with two mobile phones simultaneously. 1. Connect USB cable to a general USB power supplier. 2. Connect the charger to the correct outlet. 3. When the charger is connected to the headset, the red indicator light will turn on. Charging the battery fully may take up to 1 hour.  NOTE: If pairing is not completed within 5 minutes, the headset will automatically disconnect from the mobile phone. The SH1 supports multi-connection, so for simultaneous use of the SH1 with two mobile phones. After pairing successfully with 2 mobile phones, switch off the headset and switch on again. The headset will connect to both mobile phones automatically. Otherwise, you can connect the headset on the phone manually. NOTE: To conserve power, if the headset is not connected to a power source for approximately 10 minutes, the headset will turn off automatically. | |

| SH1 Pair to your Bluetooth® phone | |
|--|--|
| 07 07. Pair to your Bluetooth® phone 4. On the list of devices found, select the "SH1". 5. If required, enter the PIN code "0000" and confirm the entry. Once the pairing process is successful, the SH1 will connect to the mobile phone automatically. Then switch to standby mode, the indicator will flash blue every 5 seconds.  Turn on your headset Long press the Power/Play button for 3 seconds to turn on your headset. If your headset has completed the pairing process successfully, when the headset turns on, it will connect to the phone you last connected automatically. Please ensure your phone's Bluetooth® function is active. Turn off the headset Long press the power button for 3 seconds to turn off the headset. The red indicator will flash red. NOTE: To conserve power, if the headset is not connected to a power source for approximately 10 minutes, the headset will turn off automatically. | |

| SH1 Turning headset on/off | |
|--|--|
| 08 08. Turning the headset on/off Turn on your headset Long press the Power/Play button for 3 seconds to turn on your headset. If your headset has completed the pairing process successfully, when the headset turns on, it will connect to the phone you last connected automatically. Please ensure your phone's Bluetooth® function is active. Turn off the headset Long press the power button for 3 seconds to turn off the headset. The red indicator will flash red. NOTE: To conserve power, if the headset is not connected to a power source for approximately 10 minutes, the headset will turn off automatically. | |

| SH1 Bluetooth Earbuds | |
|---|--|
| Bluetooth Earbuds Quick start manual Model:SH1 | |

| SH1 Using for music play | |
|---|--|
| 09 09. Using for music play Play/Pause Press Power/Play button to get the music play or pause. Next/Previous song Press and hold Next button to skip to next song or chapter, press and hold Previous button to go back previous song or chapter. Answering a call Press Answer shortly to answer the incoming call. Reject an incoming call Press and hold Answer for 2 seconds to reject the incoming call. Increase/Decrease volume Press Volume Up button to increase volume, press Volume Down button to decrease volume. Transferring a call Press and hold Volume Up for 2 seconds to transfer the call between the phone and headset. Ending a call Press the Answer shortly to end a call. | |

| SH1 Using for phone call | |
|---|--|
| 10 10. Using for phone call Last number re-dialing At standby status, double press the Answer, the last number you dialed will be re-dialed. Note: The last number re-dialing is available only for the first device if two mobile phones are connected. The connection sequence can be determined by reconnect manually. Answering a call Press Answer shortly to answer the incoming call. Reject an incoming call Press and hold Answer for 2 seconds to reject the incoming call. Volume adjusting Press the Volume Up and Volume Down button to adjust the volume. Mute While a call is in progress, press and hold Volume Down button for 2s to mute the headset, a reminder tone would be heard every 10 seconds. Repeat the operation to un-mute. | |

| SH1 Safety and general information | |
|---|--|
| 11 11. Safety and general information Call-waiting - If there is an incoming call while a call is in progress, press Answer shortly to accept the waiting call and end current calling. - If there is an incoming call while a call is in progress, press and hold Answer for 3 seconds to accept the incoming call and place the current call on hold. Note: The same operation could be performed in case of multi-connection. Volume adjusting Press the Volume Up and Volume Down button to adjust the volume. Mute While a call is in progress, press and hold Volume Down button for 2s to mute the headset, a reminder tone would be heard every 10 seconds. Repeat the operation to un-mute. | |

| SH1 FCC & IC Statement | |
|--|--|
| 12 12. FCC & IC Statement Product uses radio frequency bands not harmonized within EU. Supplier's responsibility will be limited to the repair or replacement of the product if its sole discretion. Specifically exempt from any warranty are limited-life consumable components subject to normal wear and tear such as batteries, decorates and other accessories. Supplier is not responsible for repair or replacement from accident, abuse, misuse or any unauthorized repair or modification. Modification and repair of the unit should be done by authorized and qualified service centers or returned to the manufacturer. Such modifications could void the user's authority to operate the equipment. This product is CE certified according to the provision of the R&TTE Directive (99/5/EC). This declares that this product is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. Please note that this model is not yet type-approval if the product has been subjected to physical abuse, improper installation, | |

| SH1 EC Declaration of Conformity | |
|---|--|
| 13 13. EC Declaration of Conformity Operation is subject to the following two conditions: (1) This device may not cause harmful interference. (2) This device must accept any interference received, including interference that may cause undesired operation. Note: The manufacturer is not responsible for ANY interference, for example RADIO or TV interference, caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment. Operation is subject to the following two conditions: (1) This device may not cause harmful interference. (2) This device must accept any interference received, including interference that may cause undesired operation. Note: The manufacturer is not responsible for ANY interference, for example RADIO or TV interference, caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment. 14. Warranty The conditions of the warranty and supplier's responsibilities under this warranty are as follows: Warranty is non-transferable and is limited to the original purchaser only. - You must be able to prove the date of original purchase of the unit with a dated receipt. - The warranty is not applicable if the product has been subjected to physical abuse, improper installation, | |

| SH1 Warranty | |
|--|--|
| 14 14. Bluetooth Earbuds Quick start manual Model:SH1 | |

Federal Communications Commission (FCC) Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

RF exposure warning

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.

The equipment must not be co-located or operating in conjunction with any other antenna or transmitter.