

MIXER / RECORDER

The MixPre-D sets a new standard for compact, high-performance portable audio mixers. Powered by only two-AA batteries or 10-18 VDC, the MixPre-D is designed specifically for audio professional needing the most flexible connectivity in production applications where capturing great sound is important, but size and weight are a concern. The MixPre-D is also a class compliant USB portable audio hardware interface for Mac OS, Windows or Linux computers.



BACK PANEL

LEFT PANE:

Copyright information: The MoPro-3 provides unintruding operation and interface; aiding videographers in achieving professional-level audio. Lorem ipsum dolor sit amet, consectetur adipiscing elit.



- AA 4-pack
- AA 8-pack
- L-mount pack
- USB 'C'

- 5 Rec Tracks (3 iso + mix)
- Sample Rates: 44.1k, 48k, 96k
- Bit Depth: 16, 24
- SD Card: 1
- USB Drive Thumb: Mix Only, Copy from SD
- Audio File Formats bwav (mono, poly), mp3
- LTC 3.5mm input
- HDMI input

- 5.68" x 4.35" x 1.40" (144mm x 110mm x 36mm)
[Length x Depth x Height]
- 1 lb 1oz (490g)

- USB2.0 File Transfer (micro)
- USB2.0 High Speed Audio Interface (micro) 2 in / 2 out

- A connector, 2 in / 2 out

- 3 (XLR only) Mic/Line XLR/TRS comb

- Mic
- Line

- 3.5mm 2ch
- Unbalanced L,R out
- Adjustable output level (0 to -40)

Headphone Out

- 3.5mm

Quick Start Guide
USB C to USB A cable included
Battery holder (x4) x1 included



Available on the AppStore

MixPre3



Track and output metering on touchscreen dolor sit amet, consectetur adipiscing elit. Lorem ipsum, consectetur adipiscing elit. Lorem ipsum dolor sit amet, consectetur adipiscing elit. Lorem ipsum dolor sit amet, consectetur adipiscing elit. Lorem ipsum dolor sit amet, consectetur adipiscing elit. Lorem ipsum dolor sit amet, consectetur adipiscing elit. Lorem ipsum dolor sit amet.



FC

FCC ID: 2AKLX-739M3
IC: 22225-739M3
HVIN: MIXPRE3

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.



© 2016 SOUND DEVICES, LLC

SOUND **DEVICES**

Sound Devices, LLC
P.O. Box 576
E7556 State Road 23 & 33
Reedsburg, Wisconsin 53959
support@sounddevices.com

support@sounddevices.com
www.sounddevices.com
www.videodevices.com



MIXER / RECORDER

MixPre3



MIXER / RECORDER

MixPre/3