

(M171) User's Manual

Dear customer:

Thank you for choosing this mobile phone. This mobile phone incorporates the latest world advanced functions, enabling simple and convenient operation, satisfying your special requirements.

The mobile phone supports T-FLASH (memory) card and Dual SIM standby. It integrates the following available functions: SMS, MP3, MP4, Camera, FM radio, Video recorder and Calendar, enabling you arranging your work, study and life freely; with long standby duration, as well as Alarm and Calculator, your communication will be easier and smoother; powerful File manager allows you managing the files conveniently. In addition, the chord ringtone allows you selecting music to set as ringtone; the personalized appearance also can satisfy your selection.

Note: *User's Manual is just to guide the user about the functionality of the phone. Some functions may vary due to modifications and up gradations of software or due to print mistake.*

Contents

Keys functions.....	2
Call	4
Phonebook.....	4
Call center	4
Messaging	5
Camera	5
Multimedia	5
Organizer.....	7
Settings.....	8
Services	9
RF Exposure Information (SAR)	11

Keys functions

Keys	Functions
Left soft key	Press this button to enter standby mode shortcuts; Press this key to confirm the function you choose; Press this key to answer a call.

Right soft key	<p>Press this key to enter phonebook list under standby mode;</p> <p>Press this key to go back to previous menu;</p> <p>Press this key to reject a call.</p>
Call key	<p>Press this key to call out;</p> <p>Press to pick up phone when there is an incoming call;</p> <p>Press to enter call logs under standby mode.</p>
End key	<p>Power Off: Long press to power off under standby mode;</p> <p>Power On: Long press to power on if the phone is power off;</p> <p>Press this key to go back to standby screen.</p>
Navigation keys	<p>Press them to scroll the options when browsing a function list. In edit state, press direction keys to navigate. Under standby mode, press a direction key to enter the specified function page. You can also customize direction keys to match the desired functions.</p>
OK key	<p>Press this key to confirm the function you choose. Enter the dial interface</p>
Number keys	<p>Dial numbers under standby mode and enter numbers and characters in editing mode.</p>
* key	<p>Under standby mode, press * key twice to display “+” to call international numbers;”P” and “W” to call extension numbers. Help to lock the keypad with pressing left soft key first. Under players and FM mode, press * key to decrease volume. Long press * key lock screen</p>
# key	<p>Under standby mode, press and hold this key to switch between general mode and meeting mode. Under players and FM mode, press # key to increase volume.</p>

Call

Under standby interface, input a phone number and press the Call key to make a call by SIM1/SIM2. To end or reject a receiving call, press the End key.

Phonebook

Phone Can store up to 50 phone number of phone calls, While SIM cards contact capacity depends on the network operator, please consult the local operator. press Options, you can View: View, Send text message, Call, Edit, Delete, Copy, Add to Blacklist, Mark several , Phonebook Settings.

Call center

- ◆ In the main menu, you can view Missed calls/Dialed calls/Received calls /All calls/Delete call logs .You can also press call key to enter call logs. Go to the advanced settings in the call settings and you can view: Blacklist, Auto redial, Call time reminder and Answer mode.

Messaging

Enter this menu, you can view: Write message, Inbox, Drafts, Outbox, Sent messages and SMS settings. The capacity of messages is due to maximum storage capacity built in mobile phone and external SIM cards. And you can check the memory status of the SIM cards or mobile phone.

Camera

Camera supports photographing function .you can take pictures with the embedded camera and adjust the camera settings. The camera lens is in the rear side of the mobile phone and the screen is the viewfinder window. The pictures are taken in JPG format. After downloading to PC, please view with appropriate software. If the mobile phone memory is insufficient, please delete certain pictures or other files in “File manager”.

Multimedia

◆ Video recorder

Press OK key to start video recording. The recording time depends on the time limit and the capacity of the memory card. Enter options to perform the following settings: Switch to camera, Camcorder setting, Video settings and Storage.

◆ **Image viewer**

With this function, you can select any picture and press left soft key to perform the following operations: View, Send, Use as, Rename, Delete, Storage.

◆ **Video player**

Enter Video player. Press left soft key to enter options: Play, Send, Rename, Delete and Storage.

◆ **Audio player**

Enter Audio player. Press left soft key to enter options: Play, Refresh list and Settings.

◆ **Sound recorder**

Enter Sound recorder. press left soft key and you can do: New record, List.

◆ **FM radio**

To use the FM Radio, please insert the earphone first and then listen to it. You can perform the followings operations as your need: Channel list, Manual input, Auto search, Settings.

◆ **File manager**

File Manager explores the files in phone and external memory card. In this menu, you can manage the pictures, MP3 files and other folders etc in this menu.

Organizer

Enter this Organizer, you can view: Calendar, Alarm, Calculator. It is convenient and good for you to arrange your life orderly every day and make your life become lively and beautiful.

Settings

- ◆ Dual SIM settings: Due to dual SIM cards phone design, user can set SIM card by 'Dual SIM settings', Such as Dual SIM open, Only SIM1 open, Only SIM2 open and Flight Mode.
- ◆ User profiles: This mobile phone is provided with several profiles. You can customize the ringtone according to events and environment. You can customize a profile and activate it. Available options are:
 - ❖ General
 - ❖ Silent
 - ❖ Meeting
 - ❖ Outdoor
- ◆ Phone settings: The phone has 5 languages, English, Spanish, Italian, Portuguese and German. The default language is English, In this menu, you can perform: Time and date; Language; Pref.input method; Display and Dedicated keys.
- ◆ Security settings: To protect personal privacy, you can set SIM security, Phone security.
- ◆ Connectivity: In this menu, You can choose and change your network parameters. You can transfer files via Bluetooth.

- ◆ Restore settings: To reset the factory setting, please input the password '0000'.

Services

Go to this menu and you can view: Internet service, SIM toolkit. You can go online in this menu and check the information you need.

FCC Regulations:

This mobile phone complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This mobile phone has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiated radio frequency energy and, if not installed and used in accordance with the

instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC Note:

Caution: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

RF Exposure Information (SAR)

This phone is designed and manufactured not to exceed the emission limits for exposure to radio frequency (RF) energy set by the Federal Communications Commission of the United States.

During SAR testing, this device was set to transmit at its highest certified power level in all tested frequency bands, and placed in positions that simulate RF exposure in usage against the head with no separation, and near the body with the separation of 15 mm. Although the SAR is determined at the highest certified power level, the actual SAR level of the device while operating can be well below the maximum value. This is because the phone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the power output.

The exposure standard for wireless devices employing a unit of measurement is known as the Specific Absorption Rate, or SAR.

The SAR limit set by the FCC is 1.6W/kg.

This device is complied with SAR for general population /uncontrolled exposure limits in ANSI/IEEE C95.1-1992 and had been tested in accordance with the measurement methods and procedures specified in IEEE1528.

The FCC has granted an Equipment Authorization for this model phone with all reported SAR levels evaluated as in compliance with the FCC RF exposure guidelines. SAR information on this model phone is on file with the FCC and can be found under the Display Grant section of www.fcc.gov/oet/ea/fccid after searching on FCC ID: 2ALTAM171X.

For this device, the highest reported SAR value for usage against the head is 0.98 W/kg, for usage near the body is 0.32 W/kg.

While there may be differences between the SAR levels of various phones and at various positions, they all meet the government requirements.

SAR compliance for body-worn operation is based on a separation distance of 15 mm between the unit and the human body. Carry this device at least 15 mm away from your body to ensure RF exposure level compliant or lower to the reported level. To support body-worn operation, choose the belt clips or holsters, which do not contain metallic components, to maintain a separation of 15 mm between this device and your body.

RF exposure compliance with any body-worn accessory, which contains metal, was not tested and certified, and use such body-worn accessory should be avoided.