

Table of Contents

Introduction	2
ATA Bluetooth Headset BT25	2
Usage Requirement	2
Appearance	3
Changing the Battery	4
Putting on the Headset	5
Turning on/off the Headset	6
Adjusting the Listening Volume	7
Pairing	8
Bluetooth Passkey	8
Pairing the headset with device using Headset profile	9
Pairing the headset with device using Handsfree profile	10
Making and Receiving Calls	11
Call transfer	12
Enhance Handsfree Profile Features	13
Headset Battery Level	14
Troubleshooting	15
Important Information	16
Warranty	17

This User's Guide is published by ATO without any warranty. Improvements and changes to this User's Guide necessitated by typographical errors, inaccuracies of current information, or improvements to programs and/or equipment, may be made by ATO at any time and without notice.

User's Manual



Turning on the Headset

Press and hold the ON/OFF button (for about 3 seconds) until the headset indicator light flashes green or until you hear one short tone. Then release the button. The headset is now ready to use (in standby mode).

Note: If the battery is "LOW", the indicator light flashes "ORANGE".



3 seconds

Turning off the Headset


Press and hold the ON/OFF button (for about 3 seconds) until the headset indicator light goes off or until you hear two short tones.



3 seconds

Adjusting the Listening Volume

During a call, you can adjust the headset listening volume using the VOLUME (+) (-) control button.



(+) volume up

(-) volume down

Introduction

ATA Bluetooth Headset BT25

The ATA Bluetooth Headset BT25 is a portable handsfree communication device built on Bluetooth wireless technology. This Headset is designed and manufactured in accordance with Bluetooth specification v1.1.

Bluetooth wireless technology is a global specification for personal area wireless connectivity to ensure communication compatibility worldwide. It connects any portable and stationary communication devices easily without a single inch of cable.

You can connect your wireless Headset to your mobile phone, computer or any Bluetooth-enabled products that support the Headset/ Handsfree Profile, so as to free your hands for other valuable tasks.

This User's Guide shows you how to use the Headset with other Bluetooth devices such as mobile phone or PC.

You can handle incoming and outgoing calls, call transfer, call waiting, call reject, voice dialing, last number redial, and adjust the listening volume by using the "On/Off", "+", "-", or "*" buttons on the Headset.

Usage Requirement


You can use the Bluetooth Headset with any device that is compatible with Bluetooth wireless technology and supports the Headset/ Handsfree Profile.

To use the headset together with a mobile phone, you need to have a Bluetooth-enabled phone or a phone with a Bluetooth adapter connected to it.

Headset / Handsfree Profile-Defined by the Bluetooth Special Interest Group (SIG). It describes how manufacture should implement the various features supported by a Bluetooth Headset.

Appearance

Main body



Earphone

On/off, call pick-up/end call button



Changing the Battery

The BT25 is designed to use one "AAA" size battery. Normal disposable or rechargeable battery (NiMH or NiCD) can be used.

When the indicator light of the BT25 body unit starts flashing ORANGE, it indicates that the battery is going to be exhausted soon and needs to be replaced.

To change the battery,

1. Make sure the headset is in off mode.
2. Open the battery chamber.
3. Replace the exhausted battery with a new one.
4. Close the battery chamber cover.



Back View

Putting on the Headset

1. Put the headset over the shoulder, adjust the headset until it place on the shoulder evenly.
2. When making or receiving a call, place the ear-phone on either left or right side ear.
3. When the earphone is not in use, it can be placed on the magnetic earphone platform.



Place either in left or right ear

Turning on the Headset

Press and hold the ON/OFF button (for about 3 seconds) until the headset indicator light flashes green or until you hear one short tone. Then release the button. The headset is now ready to use (in standby mode).

Note: If the battery is "LOW", the indicator light flashes "ORANGE".



3 seconds

Turning off the Headset


Press and hold the ON/OFF button (for about 3 seconds) until the headset indicator light goes off or until you hear two short tones.



3 seconds

Adjusting the Listening Volume

During a call, you can adjust the headset listening volume using the VOLUME (+) (-) control button.



(+) volume up

(-) volume down

Pairing

Bluetooth Passkey

The Bluetooth passkey (or PIN) is used to validate two Bluetooth devices to each other and create a trusted relationship between them.

It is to prevent unauthorized use of a Bluetooth device. The process of creating a trusted relationship between two Bluetooth devices is called "Pairing" (see next section).

Each ATA Bluetooth headset has a default passkey "0000", which is stored in its internal memory. Whether you need to input the Passkey during pairing depends on the kind of Bluetooth device that the headset will be connected to.

If you want to use the headset with a Bluetooth mobile phone or other devices with built-in Bluetooth capability, you are usually required to enter the passkey on that device during pairing. Please refer to the user's manual of the device for the specific operation procedures.

Pairing the Headset

To use the headset with a Bluetooth-enabled device for the first time, you must pair the headset with that device such as mobile phone or PC.

Different device may require different pairing procedure, please refer to the user manual of the other device(s) for specific pairing method.

To complete pairing, you need to enter the correct passkey when required by the other device during pairing.

BT25 supports both handsfree and headset profile one of which must selected during pairing. The default one when entering pair mode is headset profile.

To pair the headset with device using Headset profile,

1. Activate the Bluetooth function in the other device if necessary.
2. Turn the headset off first. Press and hold the VOLUME (+) button of the headset for six seconds until the indicator light on the headset flashes green and orange alternatively. The headset is now ready for pairing. Make sure the headset and the other device are not too far apart. (i.e. Within 10 meters)



6 seconds

3. Initiate Bluetooth pairing in the other device to pair it with the headset. Please refer to the user manual of the device for specific operation.

4. When asked by the device, enter the headset passkey and then confirm if necessary. If pairing is successful, the headset indicator light flashes green and the headset is now ready to use.

5. If no pairing is possible for a period of time (approx two minutes), the headset will automatically turn off. Previous pairing (if any) is revoked. You may need to repeat steps 2 to 4 until pairing succeeded. (Note: for pairing with Bluetooth mobile phone, it is recommended to reset the phone by turning it off first).

6. You can abort pairing mode any time by pressing and holding the VOLUME (+) button for about three seconds until the green and orange light goes off and the headset is now turned off. Previous pairing (if any) is revoked.

To pair the headset with device using Handsfree profile

When the headset is on off mode, press and hold the volume (+) button for six seconds until the indicator light flashes, then press the volume (+) button once, the flash should go faster. Now the headset is ready for pairing in handsfree profile mode.

Making and Receiving Calls

With a Bluetooth enabled Mobile Phone

After the headset successfully paired with your mobile phone, you can make and receive calls using the headset within a 10 meters. The headset light indicator flashes more quickly during a call.

To make a call using a Bluetooth enabled mobile phone:

1. Make sure the phone and the headset are on and within the range of each other.
2. If the mobile phone supports voice dialing, press the ON/OFF button of the headset once, after hearing a beep sound from the headset, you can voice dial as you normally do. (Note: activate the voice dialing function in the mobile phone first)
3. If the mobile phone does not support voice dialing enter the number using the phone's keypad or recall it from the phone book as you normally do.
4. After the call has been set up, the call should be transferred to the headset automatically.
5. You can end the call by pressing ON/OFF button of the earphone once.

To answer a call,

1. With the headset rings, press the ON/OFF button of the earphone once.
2. If the phone rings first, wait until the earphone rings, then press the ON/OFF button of the earphone once.
3. You can end the call by pressing ON/OFF button of the earphone once or pressing the NO key (or any key with equivalent function) on the phone.

Call transfer


From a Bluetooth enabled Mobile Phone to Headset

During a call you can transfer the call to the headset anytime. Make sure that your headset has been paired with the phone. To transfer the call from the phone to the headset press the ON/OFF button the earphone once.

Note: Make sure the Bluetooth function in the mobile phone is activated.

From Headset to a Bluetooth Mobile Phone

To transfer your call from the headset to the phone, please refer to the user manual of the phone for specific operation.



Enhanced Handsfree Profile Features

Call reject

When there is an incoming call, press and hold the On/Off button to reject the call.

Call waiting

When BT25 is in talk mode, and a 3rd party is calling, double clicking the On/Off button will accept the 3rd party call and hold the original. Double clicking the On/Off button again will change conversation back to original party.

Last number redial

When BT25 is in ready mode, double clicking the On/Off button will start last number redial.

Voice dialing

When BT25 is in ready mode, press and hold the On/Off button for 1 second and release, Voice dial will be activated.

Headset Battery Level

Press and hold both ON/OFF and VOLUME button (+) when the headset is in standby mode. The light indicator will turn "ORANGE". The battery level is indicated by the flash pattern of the "ORANGE" indicator.

Flash once - LOW

Flash twice - MEDIUM

Flash three times - HIGH

Troubleshooting

This section lists some problems that you might encounter while using your headset

No sound contact between headset and other device

The headset and the device you are using with it have to be paired to recognize each other. They also have to be within the range of each other. Make sure the headset and the device you are using are no more than 10m/30ft apart.

The headset indicator light flashes orange

This indicates that the headset has only very limited operation time left. Replace the 'AAA' battery with a new one, or a fresh fully-charged one if using a rechargeable 'AAA' size battery.

Pairing Unsuccessful

If pairing has not been succeeded for a few times, you may have to reset first before pairing.

To Reset the headset

With the headset turned off, press and hold the volume button for about six seconds until the indicator light flashes orange and green, and then press and hold the ON/OFF button until the indicator light goes off. The headset is now reset.

Some Headset Functions Do Not Work

If you notice you can't make use of all features in the headset. Please check if your mobile phone has the right software version.

Important Information

(Note: Please read all this information before using the Bluetooth headset)

1. Check for any exceptions or rules, due to national/local requirements or limitations, in usage of this Bluetooth headset or any other Bluetooth devices.
2. Check also the laws and regulations on the use of mobile phones and handsfree equipment in the areas where you drive.
3. Please note that only the ATA authorized dealer or service partner should remove and/or replace the headset components.
4. Please use ATA original accessories only. Use of non-ATA original accessories may result in damage, loss of performance to the product, injury, electric shock or even fire.
5. Please do not expose the product to extreme high or low temperatures, moisture or fluid.
6. Please do not drop, throw or bend the product as rough treatment will damage it.
7. If the headset will not be used for a while, please store it in a place that is dry, free from moisture, dust, and extremes temperature.
8. RF frequency and energy may affect some electronic systems in a motor vehicle. Please check with the manufacturer to ensure that the headset will not affect the electronic systems in the motor vehicle.
9. Some medical electronic equipment may not be shielded from RF energy. Therefore, please do not use the headset near medical equipment without permission.
10. Please turn off the headset before boarding any aircraft. To prevent any interference with communication systems, please do not use the headset while the plane is in the air.
11. Please turn off the headset in the blasting areas or any area with a potentially explosive atmosphere.
12. Please do not allow children to play with the headset since it contains small parts.

Note: Important-the headset connected to the mobile phone or any electronic device using radio frequency signals, which cannot guarantee connection under all conditions or circumstances. Therefore, please never rely solely upon the headset for essential or emergency communications.



Thank you for purchasing the ATA Bluetooth headset. Within the warranty period, if the product fails to operate under normal use and service, due to improper workmanship or materials, the authorized dealers will, at their option, either replace or repair the product in accordance with the following terms and conditions:

1. The warranty is valid only if the original receipt issued to the original purchase by ATA authorized dealer is presented with the product to be replaced or repaired. The date of purchase and serial number shall be specified in receipt. For the replacement and repair policies and procedures in the countries / provinces which the product is purchased, please refer to the local ATA authorized dealer.

2. The warranty does not cover any failure of product due to normal tear and wear, or misuses, including but not limit to use in other than the manner according to the instructions for operation and maintenance of the product. The warranty also does not cover any failure of the product due to modification, adjustment, accident, acts of God, or any improper use or storage.

3. The warranty does not cover product failure due to improper repair, modification, adjustment, installation, or service by a non authorized ATA services partner.

4. The warranty does not cover product failures caused by the use of non ATA original accessories.

5. ATA shall not be liable for any losses, damages whatsoever, including but not limit to any lost of profits, damage to property, personal injury and death, arising under or related to the use of the product and/or the accompanying software, written material or from errors, deficiencies or fault, whether such loss or damage is caused by negligence or otherwise.

6. The warranty terms and conditions will be subject to change without prior notice.

Declaration of Conformity

We, Antonio Precise Products Manufactory Ltd. of

3/F, Photonics Centre, No. 2 Science Park East Avenue, Hong Kong Science Park, Shatin, Hong Kong

declare under our sole responsibility that our product **ATA type BT25** to which this declaration relates is in conformity with the appropriate standards *ETS 300 328-2, EN 301 489-17* and *EN 60950* following the provisions of Radio Equipment and Telecommunication Equipment directive **1999/5/EC** with requirements covering EMC directive **89/336/EEC** and Low voltage directive **73/23/EEC**.

Hong Kong, Dec 2003

Place and date of issue



Wong Wing Cheong, Anthony, Director



FCC Statement

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected!
- Consult the dealer or an experienced radio TV technician for help.

Warning: You are cautioned that any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions : (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Static electricity may cause the headset to turn off. If happen, please turn on the headset again by press and hold the ON/OFF button.

