

## Call transfer


### From a Bluetooth enabled Mobile Phone to Headset

During a call you can transfer the call to the headset anytime. Make sure that your headset has been paired with the phone. To transfer the call from the phone to the headset press the ON/OFF button the earphone once.

Note: Make sure the Bluetooth function in the mobile phone is activated.

### From Headset to a Bluetooth Mobile Phone

To transfer your call from the headset to the phone, please refer to the user manual of the phone for specific operation.



12

## Enhanced Handsfree Profile Features

### Call reject

When there is an incoming call, press and hold the On/Off button to reject the call.

### Call waiting

When BT25 is in talk mode, and a 3rd party is calling, double clicking the On/Off button will accept the 3rd party call and hold the original. Double clicking the On/Off button again will change conversation back to original party.

### Last number redial

When BT25 is in ready mode, double clicking the On/Off button will start last number redial.

### Voice dialing

When BT25 is in ready mode, press and hold the On/Off button for 1 second and release. Voice dial will be activated.

## Headset Battery Level

Press and hold both ON/OFF and VOLUME button (+) when the headset is in standby mode. The light indicator will turn "ORANGE". The battery level is indicated by the flash pattern of the "ORANGE" indicator.

### Flash once - LOW

### Flash twice - MEDIUM

### Flash three times - HIGH

## Troubleshooting

This section lists some problems that you might encounter while using your headset.

### No sound contact between headset and other device

The headset and the device you are using with it have to be paired to recognize each other.

They also have to be within the range of each other. Make sure the headset and the device you are using are no more than 10m/30ft.apart.

### The headset indicator light flashes orange

This indicates that the headset has only very limited operation time left. Replace the 'AAA' battery with a new one, or a fresh fully-charged one if using a rechargeable 'AAA' size battery.

### Pairing Unsuccessful

If pairing has not been succeeded for a few times, you may have to reset first before pairing.

### To Reset the headset

With the headset turned off, press and hold the volume button for about six seconds until the indicator light flashes orange and green, and then press and hold the ON/OFF button until the indicator light goes off. The headset is now reset.

### Some Headset Functions Do Not Work

If you notice you can't make use of all features in the headset. Please check if your mobile phone has the right software version.

## Important Information

(Note: Please read all this information before using the Bluetooth headset)

1. Check for any exceptions or rules, due to national/local requirements or limitations, in usage of this Bluetooth headset or any other Bluetooth devices.

2. Check also the laws and regulations on the use of mobile phones and handsfree equipment in the areas where you drive.

3. Please note that only the ATA authorized dealer or service partner should remove and/or replace the headset components.

4. Please use ATA original accessories only. Use of non-ATA original accessories may result in damage, loss of performance to the product, injury, electric shock or even fire.

5. Please do not expose the product to extreme high or low temperatures, moisture or fluid.

6. Please do not drop, throw or bend the product as rough treatment will damage it.

7. If the headset will not be used for a while, please store it in a place that is dry, free from moisture, dust, and extremes temperature.

8. RF frequency and energy may affect some electronic systems in a motor vehicle. Please check with the manufacturer to ensure that the headset will not affect the electronic systems in the motor vehicle.

9. Some medical electronic equipment may not be shielded from RF energy. Therefore, please so not use the headset near medical equipment without permission.

10. Please turn off the headset before boarding any aircraft. To prevent any interference with communication systems, please do not use the headset while the plane is in the air.

11. Please turn off the headset in the blasting areas or any area with a potentially explosive atmosphere.

12. Please do not allow children to play with the headset since it contains small parts.

Note: Important-the headset connected to the mobile phone or any electronic device using radio frequency signals, which cannot guarantee connection under all conditions or circumstances. Therefore, please never rely solely upon the headset for essential or emergency communications.

**Bluetooth®**  
WIRELESS HEADSET  
BT25

**ATA**  
WIRELESS HEADSET

## Warranty

Thank you for purchasing the ATA Bluetooth headset. Within the warranty period, if the product fails to operate under normal use and service, due to improper workmanship or materials, the authorized dealers will, at their option, either replace or repair the product in accordance with the following terms and conditions:

1. The warranty is valid only if the original receipt issued to the original purchase by ATA authorized dealer is presented with the product to be replaced or repaired. The date of purchase and serial number shall be specified in receipt. For the replacement and repair policies and procedures in the countries / provinces which the product is purchased, please refer to the local ATA authorized dealer.

2. The warranty does not cover any failure of product due to normal tear and wear, or misuses, including but not limit to use in other than the manner according to the instructions for operation and maintenance of the product. The warranty also does not cover any failure of the product due to modification, adjustment, accident, acts of God, or any improper use or storage.

3. The warranty does not cover product failure due to improper repair, modification, adjustment, installation, or service by a non authorized ATA services partner.

4. The warranty does not cover product failures caused by the use of non ATA original accessories.

5. ATA shall not be liable for any losses, damages whatsoever, including but not limit to any lost of profits, damage to property, personal injury and death, arising under or related to the use of the product and/or the accompanying software, written material or from errors, deficiencies or fault, whether such loss or damage is caused by negligence or otherwise.

6. The warranty terms and conditions will be subject to change without prior notice.

17

## Declaration of Conformity

### We, Antonio Precise Products Manufactory Ltd. of

3/F, Photonics Centre, No. 2 Science Park  
East Avenue, Hong Kong Science Park,  
Shatin, Hong Kong

declare under our sole responsibility that our product **ATA type BT25** to which this declaration relates is in conformity with the appropriate standards **ETS 300 328-2, EN 301 489-17 and EN 60950** following the provisions of Radio Equipment and Telecommunication Equipment directive **1999/5/EC** with requirements covering EMC directive **89/336/EEC** and Low voltage directive **73/23/EEC**.

Hong Kong, Dec 2003

Place and date of issue

CE<sup>①</sup>



Wong Wing Cheong, Anthony, Director

**ATA**<sup>®</sup>

### FCC Statement

**Note:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected!
- Consult the dealer or an experienced radio TV technician for help.

**Warning:** You are cautioned that any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions : (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

"Static electricity may cause the headset to turn off. If happen, please turn on the headset again by press and hold the ON/OFF button."

