

User's Guide

[BHF1800]

11th Mar. 2011

REVISION HISTORY

Version	Date	Name	Revision History
00.10	7 th Feb. 2011	OJ Sim	Initial release
01.00	10 th Feb. 2011	OJ Sim	<ol style="list-style-type: none">1. Subsequent pairing key change2. Deleting pairing list key correction3. Key description correction4. Other wording corrections
01.10	11 th Mar. 2011	OJ Sim	<ol style="list-style-type: none">1. MMI change2. Waiting for Multi point MMI

Contents

1.	Get familiar	4
2.	How to	5
	2.1 Power on and off	6
	2.2 Charging	6
	2.3 Pairing.....	7
3.	Others	8
	3.1 Voice alerts	8
	3.2 Multi point	8
	3.3 Multi pairing	8
	3.4 3 way call	8
	3.5 Streaming audio	8
4.	Specifications	9
5.	For more help	10
6.	Safety and General Information	11
7.	Certification and Safety approvals	12
8.	Warranty	13

1. Get familiar

MFB (Multi Function Button):

- Answer a call or end it: Tap
- Reject a call: Press when incoming call
- Last number redial: Double tap
- Transfer audio to or from phone during call: Long press during call
- Reconnect lost connection: Tap
- Voice dial: Press
- Manual pairing: Press very long until you hear 'Pair mode'

Power switch:

- Power on: Slide up
- Power off: Slide down

Microphone



Volume buttons:

- Increase volume: Tap the volume up button
- Decrease volume: Tap the volume down button
- Mute or un-mute: Press the volume down button

Status LED:

- Pairing mode: Red/blue flashes
- When connected: Blue flashes
- Low battery: Red flashes and voice alert

Micro USB charging port

- With micro USB or car charger: 2.5hours (100% charge)

* Key description

Instruction	Duration of press
Tap	Press briefly (0~0.75 sec)
Double Tap	2 quickly repeated taps (max 0.5 sec interval between taps)
Press	Press and release for approx. 0.75~2.0 seconds (after 1 beep)
Long Press	Press and release for approx. 2~4 seconds (after 2 beeps)
Very long Press	Press and release for more than 5.0 seconds

2. How to

Your product should be placed on the sun visor using its wire clip. For optimal sound quality, place it right in front of you and speak directly to it.



2.1 Power on and off



When disconnected from your phone, your product will automatically go to sleep mode after 10 minutes or you can turn off the power manually by switching it off when not in use.

2.2 Charging

Connect your product to the car charger using USB cable and plug the charger jack into your car's power outlet. A red LED icon will light up while charging. When fully charged the green LED icon will appear. Make sure to fully charge the unit for best performance.

2.3 Pairing

1. BHF1800 preparation:

1.1 First pairing

- 1) Turn your product off
- 2) When you turn it back on, you will hear 'Pair mode' and the red/blue begin to flash.
- 3) Your product is now ready. When it is paired with your phone, 'BHF1800' will display on the screen.

1.2 Subsequent pairing

- 1) Turn on the Bluetooth feature on your phone.
- 2) Press and hold the MFB until you hear 'Pair mode' and the red/blue begin to flash.
- 3) Your product is now in pairing mode.

2. Phone preparation

2.1 Activate Bluetooth feature on your phone, then use the phone's setting to add/search/discover new Bluetooth devices.

2.2 Select 'BHF1800' from the list of Bluetooth devices shown on your phone.

2.3 If necessary, enter the PIN code (default is '0000'). You may see **** on screen.

3. Others

3.1 Voice alerts

What you'll hear	Product status
Power on sound	After sliding the Power switch to 'On' position
Power off sound	After sliding the Power switch to 'Off' position
'Battery level low'	When you have approximately 30 minutes left before
'Pair mode'	While the product and phone are trying to pair/connect
'Connected'	After the product and phone are successfully paired/connected

3.2 Multi point

TBD

3.3 Multi pairing

BHF1800 supports multi pairing feature up to 8 phones. To delete the phone connection list, press and hold the MFB for 5 seconds during pair mode. When deleted, pairing is activated automatically.

3.4 3 way call

First call on hold, second call answer

Press the MFB to accept the second incoming call, then the first call will be automatically put on hold. If you want to switch back the first call, press the MFB again.

First call end, second call answer

Tap the MFB, then you can answer the second call. The first call will be terminated.

Second call rejects

Long press the MFB, then you can reject the second call and keep the first call.

3.5 Streaming audio

If your phone supports the Bluetooth A2DP profile, you can also hear streaming audio like music and GPS instructions through your product. Music streaming can be controlled from your phone only.

4. Specifications

Product name	BHF1800
Dimension	61.9mm(W) x 111.9mm(L) x 19.6mm(T)
Weight	75g
Bluetooth	V 3.0
RF Power	Class 2
Profile	HFP, HSP, A2DP
Acoustic Quality	Full duplex / Noise reduction / Echo cancellation
Voice prompts	✓
Multi point	✓
Talk Time	25 hrs
Stand by Time	50 days
Etc.	Status LED, Micro USB I/O

5. For more help

Customer care

If you are having trouble getting your product to work, please visit our website www.driventalks.com for help and support. Please contact us before returning your product to a store and we will help you through any difficulty you may have.

6. Safety and General Information

For the efficient and safe operation of your product, observe these manual-lines.

Pair your product with the phone and adjust the settings before driving to ensure your attention and focus remain on driving safely.

All air bag inflates with great force. Do not place your product in the area over the air bag area. If your product is improperly placed and the air bag inflates, serious injury could result.

Keep your product away from small children and pets. Small parts may cause choking or serious injury if swallowed.

Observe all signs and instructions regarding the use of an electrical device or RF radio product in designated areas, such as gas stations, hospitals, potentially explosive atmospheres or aircraft.

Use only provided chargers specifically designed for your product. Do not use the chargers for any other purpose.

Never place your product on or in heating devices, such as microwave ovens, stoves, or radiators. Battery may explode when overheated.

Do not allow your product to get wet. Liquid and moisture can cause serious damage to electric devices.

Do not separate, repair nor remodel your product arbitrarily. If repair is needed, please contact us or your dealer.

Do not use any chemical solvents or detergent. The use of chemicals on your product may cause damage to it. Turn your product off and use a soft dry cloth to clean the phone.

If you use any other medical devices, please consult a physician or the manufacturer of the medical devices to determine if they are adequately shielded from external RF energy. Your physician may be able to assist you in obtaining this information. Always check the regulations of the healthcare facilities, which generally request that all mobiles are switched off on entry.

7. Certification and Safety approvals

This product is CE marked according to the provisions of the R&TTE Directive (99/5/EC). We declare that this product is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. For further information, please refer to website.

FCC Information to User

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution

Modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

FCC Compliance Information : This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation

Note on environmental protection:

After the implementation of the European Directive 2002/96/EU in the national legal system, the following applies: Electrical and electronic devices may not be disposed of with domestic waste. Consumers are obliged by law to return electrical and electronic devices at the end of their service lives to the public collecting points set up for this purpose or point of sale. Details to this are defined by the national law of the respective country. This symbol on the product, the instruction manual or the package indicates that a product is subject to these regulations. By recycling, reusing the materials or other forms of utilizing old devices, you are making an important contribution to protecting our environment.

8. Warranty

Limited One (1) Year Warranty

DriveNTalk ("DNT") warrants this product to be free from defects in materials and workmanship (subject to the terms set forth below) for a period of one (1) year from the date of purchase ("Warranty Period").

During the Warranty Period, DNT will repair or replace (at DNT's sole discretion) this product or any defective parts ("Warranty Service").

If repair or replacement is not commercially practicable or cannot be timely made, DNT may choose to refund to you the purchase price paid for the affected product. Repair or replacement under the terms of this Warranty does not give right to any extension or a new beginning of the period of warranty.

Claims under the Warranty

To obtain Warranty Service, please contact the DNT's dealer from which you purchased this product. You will need to return the product to the dealer in either its original packaging or packaging affording an equal degree of protection.

The following information must be presented to obtain Warranty Service: (a) the product, (b) proof of purchase, which clearly indicates the name and address of the dealer, the date of purchase and the product type, and (c) reason for return.

As part of DNT's efforts to reduce environmental waste you understand that the product may consist of reconditioned equipment that contains used components, some of which have been reworked. The used components all live up to DNT's high quality standards and comply with DNT's product performance and reliability specifications.

You understand that replaced parts or components will become the property of DNT.

Limitation of Warranty

This Warranty is only valid for the original purchaser and will automatically terminate prior to expiration, if this product is sold or otherwise transferred to another party. The warranty provided by DNT in this statement applies only to products purchased for use, and not for resale. It does not apply to open box purchases, which are sold "as is" and without any warranty.

Specifically exempt from warranty are limited-life consumable components subject to normal wear and tear, such as cables, mount, clip, tapes, cushions, modular plugs, decorative finishes, batteries, and other accessories.

This Warranty is invalid if the factory-applied serial number, date code label, or product label has been altered or removed from the product.

This Warranty does not cover defects or damages that result from: (a) improper storage, misuse or abuse, accident or neglect, such as physical damage (cracks, scratches, etc.) to the surface of the product resulting from misuse; (b) contact with water, extreme humidity, sand, dirt or the like or extreme heat; (c) use of the product or accessories for commercial purposes or subjecting the product or accessories to abnormal usage or conditions; or (d) other acts which are not the fault of DNT.

Furthermore, this Warranty does not cover damage due to improper operation, maintenance or installation, or attempted repair by anyone other than DNT or a DNT's dealer which is authorized to do DNT warranty work. Any unauthorized repairs will void this Warranty. Neither does this Warranty cover defects or damages that result from the use of non-DNT branded or certified products, accessories, or other peripheral equipment, nor does this Warranty apply to products which have not been charged for six (6) months.

DNT does not offer any warranty for such performance.

REPAIRS OR REPLACEMENTS AS PROVIDED UNDER THIS WARRANTY ARE THE EXCLUSIVE REMEDY OF THE BUYER. DNT SHALL NOT BE LIABLE FOR ANY INCIDENTAL OR CONSEQUENTIAL DAMAGES FOR BREACH OF ANY EXPRESS OR IMPLIED WARRANTY ON THIS PRODUCT.

EXCEPT TO THE EXTENT PROHIBITED BY LAW, THIS WARRANTY IS EXCLUSIVE AND IN LIEU OF ALL OTHER EXPRESS AND IMPLIED WARRANTIES WHATSOEVER, INCLUDING BUT NOT LIMITED TO THE WARRANTY OF MERCHANTABILITY AND FITNESS FOR A PRACTICAL PURPOSE.

! NOTE

This Warranty gives you specific legal rights. You may have other rights which vary from location to location. Some jurisdictions do not allow the exclusion or limitation of incidental or consequential damages or implied warranties, so the above exclusions may not apply to you.

This Warranty does not affect your legal statutory rights under your applicable national or local laws.

© 2010 Enustech Inc. The driventalk is a registered trademark of Enustech Inc. All rights reserved.

9. CERTIFICATION and SAFETY APPROVALS